CONTROL DATA

CYBER 180


810 and 830 Computer Systems


Logic Diagrams
Volume 2 of 3
IOU and MEM

810 Computer System
810A Computer System
830 Computer System
830A Computer System


60469004

IOU PANEL



5 CHANNEL 5
4 CHANNEL 4
3 CHANNEL 3
2 CHANNEL 2
1 CHANNEL 1
0 CHANNEL 0
28 ACF "LOGIC ZERO"
3 AAE BYTE ADDRESS
3 AAF ENABLE PAR. REGEN. REG.
MUX 10164 K08
2K 10160 K06
AAC 3
CC6BAL 34 FLAG STATUS
CC5BAL 33
CC4BAL 32
CC3BAL 31
CC2BAL 30
CC1BAL 29
MUX 10164 K14
CC6BAK 34 ACTIVE STATUS
CC5BAK 33
CC4BAK 32
CC3BAK 31
CC2BAK 30
CC1BAK 29
MUX 10164 K10
CC6BAM 34 ERROR STATUS
CC5BAM 33
CC4BAM 32
CC3BAM 31
CC2BAM 30
CC1BAM 29
MUX 10164 K16
CC6BAJ 34 FULL STATUS
CC5BAJ 33
CC4BAJ 32
CC3BAJ 31
CC2BAJ 30
CC1BAJ 29
MUX 10164 K12
AAD 3
CONTROL DATA CANADA LTD
STATUS MUX TO MAC INTERFACE
210 PAK ASSEMBLY
TYPE: 1CH0
C
A
08-MAR-84
SHEET 02
LOC. D10




CONTROL DATA CANADA LTD	MAC INTERFACE MODULE ASSY: 210 PAK TYPE: 1CH0		C	D
		04-MAR-86	SHEET 03	



CONTROL DATA CANADA LTD	BBL 0,BBL 1 CHANNEL CODE MODULE ASSY: 210 PAK TYPE: 1CH0		C	A
		08-MAR-84	SHEET 04	LOC D10




CONTROL DATA CANADA LTD	CHANNEL SELECTS BBL 0, BBL 1 210 PAK ASSEMBLY TYPE: 1CH0		C	A
		08-MAR-84	SHEET 05	LOC. D10




** SHORT LINES


CONTROL DATA CANADA LTD	CHANNEL STATUS BBL 0 MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		14-MAR-84	SHEET 06	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL STATUS BBL 1 MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		14-MAR-84	SHEET 07	LOC. D10




CONTROL DATA CANADA LTD	1CC0 TO 1CD0 CONTROL MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 08	LOC. D10



CONTROL DATA CANADA LTD	BBL 0 DATA BUS MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		08-MAR-84	SHEET 09	LOC. D10




CONTROL DATA CANADA LTD	BBL 1 DATA BUS 210 PAK ASSEMBLY TYPE: 1CH0	C	A
		08-MAR-84	SHEET 10 LOC. D10




* NOTE :
TERMINATE THESE LINES
NEAR THE 10110 CHIPS

CONTROL DATA CANADA LTD	CHANNEL 00 CONTROL TO EXTERNAL EQUIPMENT 210 PAK ASSEMBLY TYPE: 1CH0		C	A
		09-MAR-84	SHEET 11	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 00 EXTERNAL DATA INTERFACE MODULE ASSY:210 PAK TYPE: 1CH0	C	A
		09-MAR-84	SHEET 12 / LOC. D10

ALL PINS HAVE AC SIGNALS




CONTROL DATA CANADA LTD	CHANNEL 01 EXTERNAL RECEIVERS MODULE ASSY:210 PAK TYPE: 1CH0		C		C
		21-MAR-85	SHEET 013	LOC. D10	

ALL PINS HAVE AC SIGNALS




CONTROL DATA CANADA LTD	CHANNEL 03 EXTERNAL RECEIVERS MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 14	LOC. D10


ALL PINS HAVE AC SIGNALS.




CONTROL DATA CANADA LTD	CHANNEL 04 EXTERNAL RECEIVERS MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 15.	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 01 EXTERNAL TRANSMITTERS MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 16	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 01 EXTERNAL TRANSMITTERS MODULE ASSY:210 PAK TYPE:1CH0		C	A
		09-MAR-84	SHEET 17	LOC. D10



CONTROL DATA CANADA LTD	CHANNEL 03 EXTERNAL TRANSMITTERS MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 18	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 03 EXTERNAL TRANMITTERS MODULE ASSY:210 PAK TYPE: 1CH0		C		A
		09-MAR-84	SHEET 19	LOC. D10	




CONTROL DATA CANADA LTD	CHANNEL 04 EXTERNAL TRANSMITTERS MODULE ASSY: 210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 20	LOC. D10


ALL PINS HAVE AC SIGNALS




CONTROL DATA CANADA LTD	CHANNEL 04 EXTERNAL TRANSMITTERS 210 PAK ASSEMBLY TYPE: 1CH0		C	A
		09-MAR-84	SHEET 21	LOC. D10




CONTROL DATA CANADA LTD	PARITY GENERATION FOR EXTERNAL DATA IN 210 PAK ASSEMBLY TYPE: 1CH0	C	A
		09-MAR-84	SHEET 22 LOC. D10




CONTROL DATA CANADA LTD	PARITY CHECKERS (CHANNELS 3-5) 210 PAK ASSEMBLY TYPE: 1CH0		C	A
		09-MAR-84	SHEET 23	LOC. D10




CONTROL DATA CANADA LTD	PARITY CHECKERS (CHANNELS 0-2) 210 PAK ASSEMBLY TYPE: 1CH0		C	A
		09-MAR-84	SHEET 24	LOC. D10





CONTROL DATA CANADA LTD	CHANNEL 00-05 ERROR REPORTING MODULE ASSY:210 PAK TYPE: 1CH0		C		C
		21-MAR-85	SHEET 025	LOC. D10	


* SHORT LINES
28 ACB -T1
28 ABZ -T2
28 ABW -T30 TIME
28 ABX -T40 TIME
1 10104 C20
S 10131 E40
-TXX
& 10110 H16
AAX 19
AAY 18,19
AAZ 18
ABA 18
ABB 19,27
ABC 17
& 10110 H28
ABD 20
ABE 21
ABF 21,27
ABG 20
ABH 20,21
ABI 17,27
& 10110 H10
ABJ 16
ABK 16,17
ABL 16
28 ACA -MC
28 ABU -T1
& 10105 H42
S 10131 G36
-M.C. ABM 27
C1MHZA A064 1 MHZ
S 10131 F38
1 10104 G24
-1 MHZ ABN 27
& 10105 F40
28 ABY -T20 TIME
-10 MHZ ABO 27
28 ACD -T2
S 10131 E42
-TXX FOR 10 MHZ ABP 27
CONTROL DATA CANADA LTD
100 NSEC CLOCKS
MODULE ASSY:210 PAK
TYPE: 1CH0
C
A
09-MAR-84
SHEET 26
LOC. D10




CONTROL DATA CANADA LTD	CLOCK TRANSMITTERS MODULE ASSY:210 PAK TYPE: 1CH0		C		A
		09-MAR-84	SHEET 27	LOC. D10	



[CLOCK] CH1TAG 37,38
[CLOCK] CH1TAH 39,40
[CLOCK] CH1TAJ 41,42
[CLOCK] CH1TAD 29-31
[CLOCK] CH1TAE 32-34
[CLOCK] CH1TAF 35,36
[CLOCK] ABT 3,25
[CLOCK] ABU 12,26
[CLOCK] ACC 5
ACB 26
DDB 25
-T30 TIME ABW 26
[CLOCK] CH1TAP 32-34
[CLOCK] CH1TAK 35-42
[CLOCK] CH1TAN 29-31
CH1TAR 29
-T40 TIME ABY 25,26
-T20 TIME ABX 26
ACD 26
ABZ 26
+MC A116
CH1TAA 29-31
ACA 22,26
ACE 12
CH1TAM 32-34
CH1TAL 35-42
+CH 00-05 INSTALLED B060 CH1TAB
"LOGIC ZERO" ACF 2,3,22
CH1TAC 28-34,37,38,41,42
T1P3E B062 -T1 [CLOCK]
CK1MAA A061 * +MC
B064 ** +CHANNEL 0 LOCATION
T2P4A B061 -T2 [CLOCK]
* DO NOT TERMINATE
** SOURCE TERMINATED THIS PIN.
30
& 10110 E24
& 10110 F24
& 10110 E24
1 10104 C10
1 10104 C10
S 10131 F38
S 10131 E42
G1 10101 D18
& D18
G42
C RGTR 10176 J12
CD
G1 10101 J16
& J16
G1 10101 J08
J08
& 10105 H12
CONTROL DATA CANADA LTD
CLOCKS
MODULE ASSY:210 PAK
TYPE: 1CH0
C
A
09-MAR-84
SHEET 28
LOC D10




CONTROL DATA CANADA LTD	CHANNEL 00 CONTROL CHIP MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 29	LOC. D10




CONTROL DATA CANADA LTD	CNANNEL 01 CONTROL CHIP MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 30	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 02 CONTROL CHIP MODULE ASSY: 210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 31	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 03 CONTROL CHIP MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 32	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 04 CONTROL CHIP MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 33	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 05 CONTROL CHIP MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 34	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 00,01,02 DATA CHIP BITS 59-63 MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 35	LOC. D10




CONTROL DATA CANADA LTD	CHANNELS 00,01,02 DATA CHIP BITS 54-58 MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 36	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 00,01,02 DATA CHIP BITS 49-53 MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 37	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 00,01,02 DATA CHIP PARITY BIT,BIT 48 MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 38	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 03,04,05 DATA CHIP BITS 59-63 MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		09-MAR-84	SHEET 39	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 03,04,05 DATA CHIP BITS 54-58 MODULE ASSY: 210 PAK TYPE: 1CH0		C	A
		08-MAR-84	SHEET 40	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 03,04,05 DATA CHIP BITS 49-53 MODULE ASSY:210 PAK TYPE: 1CH0		C		A
		08-MAR-84		SHEET 41	LOC. D10



CONTROL DATA CANADA LTD	CHANNEL 03,04,05 DATA CHIP PARITY BIT,BIT 48 MODULE ASSY:210 PAK TYPE: 1CH0		C	A
		08-MAR-84	SHEET 42	LOC. D10




CONTROL DATA CANADA LTD	CHANNEL 15 AND 17 INPUT MUX CONTROLS MODULE ASSY:210 PAK TYPE: 1CJ0		C	
		22-JAN-84	SHEET 02	LOC. D08




3	BARREL 3 BUS BITS 48-54, PARITY
2	BARREL 2 BUS BITS 48-54, PARITY
1	BARREL 1 BUS BITS 48-54, PARITY
0	BARREL 0 BUS BITS 48-54, PARITY


CONTROL DATA CANADA LTD	CHANNEL 17 INPUT MUX BITS 48-54,P MODULE ASSY:210 PAK TYPE: 1CJ0	C	/1
		22-JAN-84	SHEET 03 LOC. D08




CONTROL DATA CANADA LTD	CHANNEL 17 MUX DATA BITS 55-63 MODULE ASSY:210 PAK TYPE: 1CJ0	C	A
		22-JAN-84	SHEET 04 / LOC. D08




CONTROL DATA CANADA LTD	CHANNEL 17 DATA REG. AND CHAN. 17 PARITY MODULE ASSY:210 PAK TYPE: 1CJ0		C		
		22-JAN-84	SHEET 05	LOC. D08	




CONTROL DATA CANADA LTD	CHANNEL 15 INPUT MUX MODULE ASSY:210 PAK TYPE: 1CJ0		C	
		22-JAN-84	SHEET 06	LOC. D08




CONTROL DATA CANADA LTD	CHANNEL 15 INPUT MUX MODULE ASSY:210 PAK TYPE: 1CJ0		C		
		22-JAN-84	SHEET 07	LOC. D08	




CONTROL DATA CANADA LTD	CHANNEL 15 INPUT DATA REG. MODULE ASSY:210 PAK TYPE: 1CJ0		C	
		22-JAN-84	SHEET 08	LOC. D08




CONTROL DATA CANADA LTD	CHANNEL 14 REAL TIME CLOCK MODULE ASSY:210 PAK TYPE: 1CJ0		C		
		22-JAN-84	SHEET 09	LOC. D08	




CONTROL DATA CANADA LTD	BARREL 0 OUTPUT MUX AND DRIVERS MODULE ASSY:210 PAK TYPE: 1CJ0		C	
		22-JAN-84	SHEET 10	LOC. D08




CONTROL DATA CANADA LTD	BARREL 1 OUTPUT MUX AND DRIVERS MODULE ASSY:210 PAK TYPE: 1CJ0		C	A
		22-JAN-84	SHEET 11	LOC. D08




CONTROL DATA CANADA LTD	BARREL 2 OUTPUT MUX AND DRIVERS MODULE ASSY:210 PAK TYPE: 1CJ0		C	
		22-JAN-84	SHEET 12	LOC. D08




CONTROL DATA CANADA LTD	BARREL 3 OUTPUT MUX AND DRIVERS MODULE ASSY:210 PAK TYPE: 1CJ0		C	1
		22-JAN-84	SHEET 13	LOC. D08




CONTROL DATA CANADA LTD	BARRELS 0 AND 1 STATUS BUS MODULE ASSY:210 PAK TYPE: 1CJ0		C	
		22-JAN-84	SHEET 14	LOC. D08





CONTROL DATA CANADA LTD	MCH FLAG CONFLICT RESOLUTION MODULE ASSY:210 PAK TYPE: 1CJ0		C	A
		22-JAN-84	SHEET 15	LOC. D08


CP1U61 B110 BARREL 0 FUNCTION CODE 2
CP1U62 A111 BARREL 0 FUNCTION CODE 1
CP1U63 B122 BARREL 0 FUNCTION CODE 0
CP2U61 A114 BARREL 1 FUNCTION CODE 2
CP2U62 B111 BARREL 1 FUNCTION CODE 1
CP2U63 B115 BARREL 1 FUNCTION CODE 0
A121 BARREL 2 FUNCTION CODE 2
A120 BARREL 2 FUNCTION CODE 1
A112 BARREL 2 FUNCTION CODE 0
B118 BARREL 3 FUNCTION CODE 2
A118 BARREL 3 FUNCTION CODE 1
B119 BARREL 3 FUNCTION CODE 0
CM15AP B091 SELECT CH.15 BARREL 0
CM25AP A091 SELECT CH.15 BARREL 1
B089 SELECT CH.15 BARREL 2
A090 SELECT CH.15 BARREL 3
50
52
46
47
ABJ 18
ABK 18
CK1QAA B092 +FULL IN
CK1GAA A092 +ERROR IN
CK1QAE B109 +EMPTY IN
CK1QAB A109 +INACTIVE IN
ABL 34
C RGTR 10176 E34
CD
CJ1FAA
CJ1FAB
CJ1FAD
CJ1FAC
CJ1FAE
+FUNCTION B086 CJ1FAA
+FULL B088 CJ1FAB
+EMPTY A085 CJ1FAD
+ACTIVATE A086 CJ1FAC
+INACTIVATE B085 CJ1FAE
& 10105 H38
S 10135 GJ G GK R G24
ABM 33
ABN 33
G1 10101 F18
CK1MAA A055* +M/C
CJ1EAF
CJ1EAG
ABO 25,34
ABP 17,28,32
ABQ 9
ABR 25,26
T1P3D B052 -T1 [CLOCK]
& 10110 F22
CJ1EAE 19,20
ABT 2,9
ABU 14,18,32
ABV 5,15,18,32,34
ABW 25,28,36
ABX 17
* DO NOT TERMINATE
CONTROL DATA CANADA LTD
T1 AND M/C FANOUT CHANNEL CONTROLS
MODULE ASSY:210 PAK
TYPE: 1CJ0
C
22-JAN-84
SHEET 16
LOC. D08




CONTROL DATA CANADA LTD	TIMEOUT CCT MODULE ASSY:210 PAK TYPE: 1CJ0		C	
		22-JAN-84	SHEET 17	LOC. D08



16 ABV -T1 [CLOCK]
16 ABJ SEL. CH.15 BARREL 2
16 ABK SEL. CH.15 BARREL 3
15 ABH SEL. CH.17 BARREL 2
15 ABI SEL. CH.17 BARREL 3
A082 SELECT CH.14 BARREL 2
A081 SELECT CH.14 BARREL 3
15 ABF +FAKE BARREL 2 FLAG SET
CCFBAL 20 +FLAG CH.17
15 ABG +FAKE BARREL 3 FLAG SET
16 ABU -T1 [CLOCK]
CCEBAJ 19 +FULL CH.15
CCFBAJ 20 +FULL CH.17
CCEBAK 19 +ACTIVE CH.15
CCFBAK 20 +ACTIVE CH.17
CCEBAL 19 +FLAG CH.15
CCEBAM 19 +ERROR FLAG CH.15
CCFBAM 20 +ERROR FLAG CH.15
9 AAQ LOGIC "0"
-CH.17 ACTIVE ACA 17
CH.15 FULL B082 CJ1DAA
CH.15 ACTIVE A083 CJ1DAB
+FULL B104
+ACTIVE A103
+SELECT CH.14 BARREL 2 ACB 8
+SELECT CH.14 BARREL 3 ACC 8
+FLAG A108
+ERROR FLAG B105
+CH.15 FULL ACD 34
+FULL A104
+ACTIVE B103
+CH.17 FULL ACE 5
+FLAG B108
+ERROR FLAG A105
* EXTRA SHORT
CONTROL DATA CANADA LTD
BARREL 2 AND 3 STATUS BUS
MODULE ASSY:210 PAK
TYPE: 1CJ0
C
22-JAN-84
SHEET 18
LOC. D08




CONTROL DATA CANADA LTD	CHANNEL 15 CONTROL MACROCELL MODULE ASSY 210 PAK TYPE: 1CJ0		C	A
		22-JAN-84	SHEET 19	LOC D08



CONTROL DATA CANADA LTD	CHANNEL 17 CONTROL MACROCELL MODULE ASSY 210 PAK TYPE: 1CJ0		C	.
		22-JAN-84	SHEET 20	LOC D08




CONTROL DATA CANADA LTD	RADIAL INTERFACE 2 RECIEVERS MODULE ASSY:210 PAK TYPE: 1CJ0		C		A
		22-JAN-84	SHEET 21	loc. d08	




RESISTORS CONNECTED TO GROUND ARE 51ohms.

RESISTORS CONNECTED TO -5.2v ARE 2.4K ohms.


CONTROL DATA CANADA LTD	RADIAL INTERFACE 3 RECIEVERS MODULE ASSY:210 PAK TYPE: 1CJ0		C	
		22-JAN-84	SHEET 22	LOC. D08




CONTROL DATA CANADA LTD	SELECT RADIAL INTERFACE MUX MODULE ASSY 210 PAK TYPE 1CJ0		C	
		22-JAN-84	SHEET 23	LOC D08




CONTROL DATA CANADA LTD	RI DATA TO CHANNEL RI DATA TO <up> MODULE ASSY 210 PAK TYPE: 1CJ0		C	
		22-JAN-84	SHEET 24	LOC D08




CONTROL DATA CANADA LTD	CONNECT CODE REGISTER MODULE ASSY 210 PAK TYPE 1CJ0		C		
		22-JAN-84		SHEET 25	LOC D08




CONTROL DATA CANADA LTD	RI DATA MUX MODULE ASSY 210 PAK TYPE 1CJ0		C	
		22-JAN-84	SHEET 26	LOC D08


25 ACP SELECT Z80
25 ACN +FUNCTION
CCF7AB 20 +FULL
32 ADN INACT RESP
9 AAQ LOGIC "0"
32 ADM RDY RESP
CCF7AD 20 EMPTY
CCF7AC 20 ACTIVE
CCF7AE 20 INACTIVATE
CK1CAG B056 U INACTIVE
17 ABY +TIMEOUT
CK1CAF A047 +U ACTIVATE
CK1QAA A059 +U EMPTY
25 ACS
CK1CAC B076 U NEXT FULL
IS FUNC
25 ACR U CONNECT
C G2 G1 RGTR 10173 J14
C G2 G1 J20 RGTR 10173
2CD 1CD
FUNC
FULL
EMP
ACT
INACT
ADG 28
ADH 28
ADI 28
ADJ 28
ADK 28
& 10105 H14
& 10105 H06
& 10105 F28
& 10105 H06
& 10104 H08
G1 10101 J30
G1 10101 F30
CONTROL DATA CANADA LTD
RI CONTROL MUX
MODULE ASSY 210 PAK
TYPE: 1CJ0
C
22-JAN-84
SHEET 27
LOC D08




CONTROL DATA CANADA LTD	Z80 RESPONSE FLOPS MODULE ASSY 210 PAK TYPE 1CJ0		C	A
		22-JAN-84	SHEET 28	LOC D08




* THESE FOILS MUST BE EXTRA SHORT AND TERMINATE AT THE END FARTHEST FROM THE PIN.


CONTROL DATA CANADA LTD	MAC BUS DRIVERS MODULE ASSY 210 PAK TYPE 1CJ0		C	
		22-JAN-84	SHEET 29	LOC D08




CONTROL DATA CANADA LTD	RADIAL INTERFACE 2 DRIVERS MODULE ASSY 210 PAK TYPE 1CJ0		C	
		22-JAN-84	SHEET 30	LOC D08



CONTROL DATA CANADA LTD	RADIAL INTERFACE 3 DRIVERS MODULE ASSY 210 PAK TYPE 1CJ0		C		
		22-JAN-84	SHEET 31	LOC D08	




CONTROL DATA CANADA LTD	RI CONTROL RESYNCH AND MUX MODULE ASSY 210 PAK TYPE 1CJ0		C	
		22-JAN-84	SHEET 32	LOC D08




* THESE FOILS ARE AS SHORT AS POSSIBLE AND TERMINATED AT THE END FARTHEST FROM THE PIN


CONTROL DATA CANADA LTD	CHANNEL 15 BUS DRIVERS MODULE ASSY 210 PAK TYPE 1CJ0		C	
		22-JAN-84	SHEET 33	LOC D08




CONTROL DATA CANADA LTD	CH 15 PARITY CHECKER R BITS 59 TO 63 MODULE ASSY 210 PAK TYPE 1CJ0		C	
		22-JAN-84	SHEET 34	LOC D08




CONTROL DATA CANADA LTD	MAC MUX MODULE ASSY 210 PAK TYPE 1CJ0		C	
		22-JAN-84	SHEET 35	LOC D08



CONTROL DATA CANADA LTD	MAC INTERFACE MODULE ASSY:210 PAK TYPE: 1CJ0		C	E
		04-MAR-86	SHEET 36	




CONTROL DATA CANADA LTD	Z80 CPU & BUS DRIVERS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 02	





NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.

CONTROL DATA CANADA LTD	Z80 CPU & BUS DRIVERS 210 PAK ASSEMBLY TYPE: ICK0		C	A
		19-APR-85	SHEET 02A	





CONTROL DATA CANADA LTD	PROMS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 03	


2 ACX ADDRESS BUS
14 ADK CONTROLS
2 ACY CONTROLS
X->Y
2048
1024
512
256
128
64
32
16
8
4
2
1
A4095
A0000
M1
M3
M4
M0
M2
RD
&
F
MEM
2732
H02
F02
D02
K02
G02
AF
-DATA BUS
ADL 2,5-9,23
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.
CONTROL DATA CANADA LTD
PROMS
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
19-APR-85
SHEET 03A




CONTROL DATA CANADA LTD	RAMS & PROM BUS DRIVERS BATTERY CIRCUIT 210 ASSEMBLY PAK TYPE: 1CK0		C	A
		19-APR-85	SHEET 04	



2 ACX -ADDRESS BUS
2 ACY -CONTROLS
14 AYZ -CONTROLS
+5V
+5V
+4.7V
G03 4.7K
4.7 K K05
4.7 K J13
N/$ 339 B04 X>Y
1 4025 C04
.68K
D43
R001
C074
R003
CR05
1 7404 A04
A008 POWER GOOD
13 ADQ CLR BATT FAILED FLOP
& 7408 C06
R015
A020 -DEADSTART BUTTON
B015 +5 VOLTS
A015 +5 VOLTS
B022 +5 VOLTS
A022 +5 VOLTS
A006 +5 VOLTS
B006 +5 VOLTS
A009
+4.7V
R004
R002
CR06
CR04
B06
15 AEW TTL LOGIC ONE
B009
AA4
LITHIUM BATTERY K02 3.6V
PIN CONFIG
J09 4.7K
+5V
X->Y 512 256 128 64 32 16 8 4 2 1
A1023 A0000
WR
&
C
F
MEM 6514 E04
AF
MEM 6514 F04
DATA BUS DAB 2,5-9,2
-RESET AER 2,6,13
+RESET AET 5,6
+RESET AES 10,12,2
47
B12
S 74279 C02
+BATTERY FAILED AEP 8
-WAIT WAT 2
4013 C08
CLK
AGG 14
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.
CONTROL DATA CANADA LTD
RAMS & PROM BUS DRIVERS
BATTERY CIRCUIT
210 ASSEMBLY PAK
TYPE: 1CK0
C
A
19-APR-85
SHEET 04A




CONTROL DATA CANADA LTD	PORT 0 UART &RS-232 DRIVERS & RECEIVERS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 05	




CONTROL DATA CANADA LTD	PORT 0 UART &RS-232 DRIVERS & RECEIVERS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 05A	



A032 -12 VOLTS
B032 -12 VOLTS
-12V
-12V
LSI
ASYNCHRONOUS
COMMUNICATIONS
ELEMENT
INS8250
J14
2 ACY CONTROLS
CLK
RD
WR
2 ACX ADDRESS BUS
4 AET +RESET
14 ADK CONTROLS
14 DAA DATA BUS
4 DAB DATA BUS
3 ADL DATA BUS
I05
+5V
+5V
(G19)
R007
1K
+12V
DTL/232
1488
H14
DATA OUT A043
+RTS B042
+DTR A042
NC
-12V
C059 (G15)
C060 (G13)
C061 (F13)
+INTERUPT PORT 1 AFD 5
X/Y
10124
F14
A045 +CARRIER ON
B043 +CLR TO SEND
B041 +RING IND
A041 +DATA SET READY
1489
G14
C01
RI1
DS1
RS-232 STATUS AFE 27
C062 (J15)
C063 (K15)
B033 DATA IN
1489
G18
C064 (K13)
C065 (J13)
C066 (K19)
NC
CAPACITORS: C059 TO C072 ARE ALL 470 PFD.
13 ADR +ENABLE RS-366 INTERFACE
9 ACR Z80 DATA OUT-TTL
7400
G24
13 ATA
4 AER -RESET
RGTR
74174
G16
CD
R
DTL/232
1488
G10
+CALL REQUEST B023
C067 (G11)
+DIGIT PRESENT A023
C068 (G09)
NB8 B021
C069 (G07)
DTL/232
1488
H16
NB4 B051
C070 (G17)
NB2 A050
C071 (H15)
NB1 A051
C072 (H19)
A029 +12 VOLTS
B029 +12 VOLTS
+12V
+12V
CONTROL
DATA
CANADA
LTD
PORT, UART & RS-232 DRIVERS &
RECEIVERS RS-366 DRIVERS
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
19-APR-85
SHEET 06



CONTROL DATA CANADA LTD	PORT, UART & RS-232 DRIVERS & RECEIVERS RS-366 DRIVERS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 06A	





CONTROL DATA CANADA LTD	STATUS INPUT PORTS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 07	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.


CONTROL DATA CANADA LTD	STATUS INPUT PORTS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 07A	


9 AAD TTL LOGIC 1''
14 ADK CONTROLS
2 ACX ADRS BUS
2 ZDA MI
2 ACY CONTROLS
14 DAA DATA BUS
3 ADL DATA BUS
4 DAB DATA BUS
LSI
PRGM PORT
Z80A PIO
J20
PORT B/A SEL
CONT/DATA SEL
CHIP SEL
MEM CYC 1
I/O REQ
READ CYC STATUS
CLK
INTRPT ENBL IN
PORT A STROBE
PORT B STROBE
DATA
PORT A
PORT B
INTRPT ENBL OUT
INTRPT REQ
PORT A RDY
PORT B RDY
+5V
F20
+READ PIO
READ PIO
AFF 26
AFI 13
RS-366A DATA BITS (59-63)
MUXED DATA BITS (56-63)
PORT 1 FIFO DATA BITS (56-63)
PORT 0 FIFO DATA BITS (56-63)
9 ACS FUNCTION DATA
15 AEI PORT 0 FIFO DATA
15 AEL PORT 1 FIFO DATA
16 AAV MUXED DATA
5 AFH RS366A DATA
MUX 74153 H18
MUX 74153 H20
MUX 74153 H22
MUX 74153 H24
X->Y
4 AEP +BATT. FAILED
R019 1K
A056 (A06)
C073 60UF
(A06)
7404 C08
CONTROL DATA CANADA LTD
DATA INPUT PORT
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
19-APR-85
SHEET 08


TTL LOGIC 1
CONTROLS
ADRS BUS
CONTROLS
DATA BUS
DATA BUS
DATA BUS
+5V
LSI
PRGM PORT
Z80A PIO
J20
PORT B/A SEL
CONT/DATA SEL
CHIP SEL
MEM CYC 1
I/O REQ
READ CYC STATUS
CLK
INTRPT ENBL IN
PORT A STROBE
PORT B STROBE
DATA
PORT A
PORT B
INTRPT ENBL OUT
INTRPT REQ
PORT A RDY
PORT B RDY
+READ PIO
READ PIO
RS-366A DATA BITS (59-63)
MUXED DATA BITS (56-63)
PORT 1 FIFO DATA BITS (56-63)
PORT 0 FIFO DATA BITS (56-63)
FUNCTION DATA
PORT 0 FIFO DATA
PORT 1 FIFO DATA
MUXED DATA
RS366A DATA
+BATT. FAILED
MUX 74153 H18
MUX 74153 H22
MUX 74153 H20
MUX 74153 H24
X->Y
+5V
1K
G08
A056
7404 A04
B43
60UF
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.
CONTROL DATA CANADA LTD
DATA INPUT PORT
210 PAK ASSEMBLY
TYPE: 1CK0
C
19-APR-85
SHEET 08A
A




CONTROL DATA CANADA LTD	OUTPUT PORTS (FUNCTION,DATA) 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		23-APR-85	SHEET 09	





NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.

CONTROL DATA CANADA LTD	OUTPUT PORTS (FUNCTION,DATA) 210 PAK ASSEMBLY TYPE: 1CK0	C		A
		19-APR-85	SHEET 09A	





CONTROL DATA CANADA LTD	HOLDING REGISTERS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		24-APR-85	SHEET 10	



9 ACT Z80 DATA OUT
16 AAW HLDG RGTR STBS
PORT 1 HLDG RGTR
CALENDAR CLOCK HOLDING REGISTER
C RGTR 10176 E26
C RGTR 10176 F28
C RGTR 10176 F26
C RGTR 10176 E28
C RGTR 10176 D26
CD
12 G1 10101 F36
10 & 1 F36 11 14
T
CAL CLOCK DATA AAI 27
12 LHR LD HLDG RGTRS
& 10105 D32
ENBL STB DCDR AAT 16
PORT 1 DATA AAL 11
SEL CAL CLK RGTR AAU 27
11 AEA LOGIC "0"
24 AEX INACTIVATE
22 ABH +M/C
9 ACO FULL PULSE
S 10131 B34
1 C
R
NC S 10135 GJ G34 G GK R
34 2ND PARCEL AAH 16
9 ACN -FCTN & FULL PAUSE
4 AES +RESET
PORT 0 HLDG RGTR
C RGTR 10176 C28
C RGTR 10176 D28
C RGTR 10176 C26
& 10105 D36
S 10131 D30
04 PORT 1 HLDG RGTR FULL AAJ 7, 11
15 AEN +M/C PORT 1
T1 AAP 9, 12, 13, 16, 19, 21, 22, 24, 26
NC 12 G1 10101 G32
& 1 G32
07 PORT 0 HLDG RGTR FULL AAK 7, 11
17 ACF EMPTY PORT 0
17 ACE EMP PORT 1
15 AEM +M/C PORT 0
PORT 0 DATA AAM 11, 27
AAN 12, 18, 27
AAO 12, 16, 22
T1P3L B089 T1[CLOCK]
& 10110 E32
37
NC
T1 AAR 17, 24
T1 AAS 12, 23
T1 AAQ 19, 22
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.
CONTROL DATA CANADA LTD
HOLDING REGISTERS
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
23-APR-85
SHEET 10A





CONTROL DATA CANADA LTD	TWO PORT MUX/ STATUS/DATA MUX MODULE ASSY:210 PAK TYPE: 1CK0		C	A
		23-APR-85	SHEET 11	


27 DAF -TWO PORT MUX SEL
27 DAG
10 AAL -PORT 1 DATA
27 DAE RS-232 STATUS REG. BITS
27 DAC
27 DAD
5 AFL PHONE ANSWERED
15 AEG +PORT 0 FULL FULL
15 AEJ +PORT 1 FIFO FULL
10 AAM -REG. PORT 0 DATA
10 AAK -PORT 0 HLDG RGTR FULL
10 AAJ -PORT 1 HLDG RGTR FULL
X->Y
G3
G0
MUX 10174 K30
MUX 10174 G30
MUX 10174 J30
MUX 10174 F30
MUX 10174 H30
MUX 10174 E30
NC
D0
D1
C0
C1
R0
R1
-DATA TO CH 15 ADP 18
CR02
LOGIC "0" AEA 10,18, 19,22,24
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.
CONTROL DATA CANADA LTD
TWO PORT MUX/ STATUS/DATA MUX
MODULE ASSY:210 PAK
TYPE: 1CK0
C
A
23-APR-85
SHEET 11A


13 ADW FCTN RGTR
10 AAN -T1
4 AES +RESET
10 AAO -T1
9 ACP FCTN PULSE DLYD'
10 AAP -T1
10 AAS -T1
13 ADU 2ND FCTN WORD
13 ADX FUNCTION DATA
CONNECT TO RI A110 CK1CAB
B095
LOAD HLDG RGTRS LHR 10
NEXT FULL IS A FUNCTION B128 CK1CAC
+HOLD FUNCTION ON CH10 A126 CK1CAL
DS SEQ IN PROG AAE 22
B096 CK1CAM
+DS SEQ IN PROG AAF 22
LDS IN PROGRESS B093 CK1CAD
LDS STATUS BIT A109 CK1CAN
-DISCONN RI A127 CK1CAE
SEND ACT A128 CK1CAF
SEND INACT B127 CK1CAG
-ENBL UNCOND IDLE A100 CK1CAJ
Z80 INACT. INA 17
Z80 REPLYS AAG 24
MED CHAR A098 CK1CAH
+SELECT 545 A096 CK1CAJ
SELECT 545 AEU 25
KEYBOARD SEL. B079 CK1CAK
R-BIT 59 AAB 19
R-BIT 60 AAC 19
B067 CK1A60
B075 CK1A62
B072 CK1A63
A055 CK1A59
A075 CK1A61
S 10131 H36
S 10131 K36
S 10131 J36
S 10135 H34
1 10104 H32
& 10105 C24
& K34
X->Y CODER 10161 K26
X->Y CODER 10161 J26
X->Y CODER 10162 K32
X->Y CODER 10161 J32
X->Y CODER 10161 H26
C RGTR 10176 F34
C RGTR 10176 E24
CONTROL DATA CANADA LTD
Z80 FUNCTION DECODER
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
23-APR-85
SHEET 12



13 ADW
10 AAN -T1
4 AES +RESET
10 AAO -T1
9 ACP FCTN PULSE DLY'D
10 AAP -T1
10 AAS
13 ADU 2ND FCTN WORD
13 ADX FUNCTION DATA
X->Y CODER 10161 K26
X->Y CODER 10161 J26
X->Y CODER 10161 H26
S 10131 H36
S 10131 K36
S 10131 J36
10104 H32
10101 K34
& K34
10105 C24
S 10135 H34
RGTR 10176 F34
RGTR 10176 E24
X->Y CODER 10162 K32
X->Y CODER 10161 J32
CONNECT TO RI
+HOLD FCTN ON CH 10
LOAD HLDG RGTRS
NEXT FULL IS A FUNCTION
+HOLD FUNCTION ON CH10
DS SEQ IN PROG
+DS SEQ IN PROG
LDS IN PROGRESS
LDS STATUS BIT
-DISCONN RI
SEND ACT
SEND INACT
-ENBL UNCOND IDLE
Z80 INACT.
Z80 REPLYS
MED CHAR
+SELECT 545
SELECT 545
KEYBOARD SEL.
R-BIT 59
R-BIT 60
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.
CONTROL DATA CANADA LTD
Z80 FUNCTION DECODER
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
23-APR-85
SHEET 12A


CLEAR BATTERY FAILED FLOP ADQ 4
9 ACS FUNCTION DATA
9 ACW +FCTN PULSE-TTL
CA3083 E02
(D02) R010
X--->Y 74138 F10
B08
74279
A04
+5V
D03
CR06
(D05) CR07
COIL
A019
B019
A011
B011
ATA 6
1 7404 K06
X--->Y 74138 G12
& 7432 G20
+ENABLE RS-366 INTERFACE ADR 6
4 AER RESET
7474 H10
& 7432 G20
1 7427 G22
+SHIFT OUT-PORT 0 ADS 15
8 AFI READ PIO
+SHIFT OUT-PORT 1 ADT 15
1 7404 K06
NC NC NC
+5V
(F17) R009 1K
10 AAP T1
9 ACQ FCTN PULSE
& 10105 G26
T
X/Y 10124 F18
2ND FUNCTION WORD ADU 12
C RGTR 10176 E22
NC
G1 10101 K34
14 60N
X/Y 10124 F16
FCTN RGTR ADW 12, 16
FUNCTION DATA ADX 12
CONTROL DATA CANADA LTD
Z80 FUNCTION CONVERSION & TTL DECODING
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
23-APR-85
SHEET 13




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.

CONTROL DATA CANADA LTD	Z80 FUNCTION CONVERSION & TTL DECODING 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		26-APR-85	SHEET 13A	





CONTROL DATA CANADA LTD	ADDRESS DECODER SWITCH DRIVERS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 14	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.


CONTROL DATA CANADA LTD	ADDRESS DECODER SWITCH DRIVERS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		23-APR-85	SHEET 14A	


16 AAV DATA TO PIO & FIFOS
13 ADS SHIFT OUT PORT 0
16 AAX LOAD FIFO
17 ACC SEL PORT 0
25 AEF +545 OR SEL RI
17 ACH 07XX FUNC.
13 ADT SHF OUT PORT 1
17 ACB SEL PORT 1
64X4 FIFO LSI 3341 C10
64X4 FIFO LSI 3341 A08
64X4 FIFO LSI 3341 B10
64X4 FIFO LSI 3341 A10
INP CLK
OUT CLK
RESET
DATA IN
INP RDY
OUT RDY
DATA OUT
-12V
+5V
(J04)
R011 1K
& 7408 A02
& 10105 D34
& 10105 E34
& 10105 C14
X/Y 10125 E20
X/Y 10124 B12
B12
TTL LOGIC "1" AEW 2,4,14
PORT 0 FIFO DATA RDY AEH 7
+PORT 0 BUFFER FULL AEG 11,24
PORT 0 FIFO DATA AEI 8
+M/C PORT 0 AEM 10
+PORT 1 BFR FULL AEJ 11,24
PORT 1 FIFO DATA RDY AEK 7
PORT 1 FIFO DATA AEL 8
+M/C PORT 1 AEN 10
-L25VR
CONTROL DATA CANADA LTD
TWO PORT MUX FIFO BUFFERS
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
23-APR-85
SHEET 15


16 AAV DATA TO PIO & FIFOS
13 ADS SHIFT OUT PORT 0
16 AAX LOAD FIFO
17 ACC SEL PORT 0
25 AEF +545 OR SEL RI
17 ACH 07XX FCTN
13 ADT SHF OUT PORT 1
17 ACB SEL PORT 1
+5V
K07
R011
64X4 FIFO LSI 3341 D10
64X4 FIFO LSI 3341 A10
64X4 FIFO LSI 3341 C10
64X4 FIFO LSI 3341 B10
INP CLK
OUT CLK
RESET
DATA IN
INP RDY
OUT RDY
DATA OUT
-12V
& 7408 B08
& 10105 D34
& 10105 E34
& 10105 C14
& B12
X/Y 10125 E20
X/Y 10124 B12
TTL LOGIC "1" AEW 2,4,14
PORT 0 FIFO DATA RDY AEH 7
+PORT 0 BUFFER FULL AEG 11,24
PORT 0 FIFO DATA AEI 8
+M/C PORT 0 AEM 10
+PORT 1 BUFFER FULL AEJ 11,24
PORT 1 FIFO DATA RDY AEK 7
PORT 1 FIFO DATA AEL 8
+M/C PORT 1 AEN 10
-1.25VR
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.
CONTROL DATA CANADA LTD
TWO PORT MUX FIFO BUFFERS
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
23-APR-85
SHEET 15A




CONTROL DATA CANADA LTD	CH15 BUS PARITY CHECKER INPUT DATA, ECL/TTL/ CONVERSION 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 16	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.

CONTROL DATA CANADA LTD	CH15 BUS PARITY CHECKER INPUT DATA, ECL/TTL/ CONVERSION 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		23-APR-85	SHEET 16A	




CONTROL DATA CANADA LTD	TWO PORT MUX FUNCTION DECODER 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 17	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.


CONTROL DATA CANADA LTD	TWO PORT MUX FUNCTION DECODER 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		23-APR-85	SHEET 17A	




CONTROL DATA CANADA LTD	CHANNEL 15 BUS DRIVERS 210 PAK ASSEMBLY TYPE 1CK0		C	A
		19-APR-85	SHEET 18	



CONTROL DATA CANADA LTD	CHANNEL 15 BUS DRIVERS 210 PAK ASSEMBLY TYPE 1CK0		C	A
		23-APR-85	SHEET 18A	




CONTROL DATA CANADA LTD	PP & DEADSTART NUMBER COUNTERS & PARITY GENERATORS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 19	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.

CONTROL DATA CANADA LTD	PP & DEADSTART NUMBER COUNTERS & PARITY GENERATORS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		23-APR-85	SHEET 19A	




CONTROL DATA CANADA LTD	DEADSTART CHANNEL NUMBER MUX 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 20	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.

CONTROL DATA CANADA LTD	DEADSTART CHANNEL NUMBER MUX 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		23-APR-85	SHEET 20A	




3	COUNTER BITS (60E-63E, 600-620)
2	COUNTER BITS (600-630, 60E-63E)
1	DS CHANNEL NUMBER FROM MRS BITS 60-63
0	DS CHANNEL NUMBER FROM MRS BITS 60-63

CONTROL DATA CANADA LTD	DEADSTART CHANNEL NUMBER MUX 10 PAK ASSEMBLY TYPE: 1CK0	C	A
		19-APR-85	SHEET 21




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.


CONTROL DATA CANADA LTD	DEADSTART CHANNEL NUMBER MUX 10 PAK ASSEMBLY TYPE: 1CK0		C	A
		23-APR-85	SHEET 21A	




CONTROL DATA CANADA LTD	MASTER CLEAR GENERATOR BRANCH TEST TIMEOUT COUNTER 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		24-APR-85	SHEET 22	




CONTROL DATA CANADA LTD	MASTER CLEAR GENERATOR BRANCH TEST TIMEOUT COUNTER 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		23-APR-85	SHEET 22A	



CONTROL DATA CANADA LTD	DEADSTART CONTROLS FANOUT 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 23	







3	P MATCH BBL 3
2	P MATCH BBL 2 OR 1/2X
1	P MATCH BBL 1/4X
0	P MATCH BBL 0

NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.


CONTROL DATA CANADA LTD	DEADSTART CONTROLS FANOUT 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		23-APR-85	SHEET 23A	





CONTROL DATA CANADA LTD	TWO PORT MUX OUTPUT CONTROLS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 24	




CONTROL DATA CANADA LTD	TWO PORT MUX OUTPUT CONTROLS 210 PAK ASSEMBLY TYPE: 1CK0		C		A
		23-APR-85	SHEET 24A		


26 AEB +READ MOST SIGNIFICANT CH 15 DATA
12 AEU SEL CC545
NC 12 G1 10101 D40
B099 * SEL RI 13 & 1 D40 9 15 12
13 1 10104 C34 15 9
T
6 7 NC 9 4 5 & 1 10117 B32 2 3 T
AEF 15
16 AFG +LOAD FIFO PULSE
4 5 & 10105 D36 2 3 T
13 12 & 10105 D36 15 14 T
3 DATA FROM CC545
2 RI BUS DRIVER DATA
1 CH.15 BUS DATA
0 CH.15 BUS DATA
A125 DATA FR CC545 56
B120 57
A119 58
B113 59
A111 60
A106 61
B103 62
A102 63
26 ADY -RI BUS DRIVER DATA
18 ABD CH15 BUS
X->Y
G3 G0
NC 14 V
MUX 10174 A42
MUX 10174 A38
MUX 10174 A40
MUX 10174 A36
MUXED DATA ACL 16
* SHORT AND DO NOT TERMINATE.
CONTROL DATA CANADA LTD
DISPLAY CONTROLLER
RADIAL INTERFACE, INTERFACES
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
19-APR-85
SHEET 25



26 AEB +READ MOST SIGNIFICANT CH 15 DATA
12 AEU SEL CC545
B099 * SEL RI
16 AFG +LOAD FIFO PULSE
* SHORT AND DO NOT TERMINATE.
AEF 15
A125 DATA FR CC545 56
B120 57
A119 58
B113 59
A111 60
A106 61
B103 62
A102 63
26 ADY -RI BUS DRIVER DATA
18 ABD CH15 BUS
3 DATA FROM CC545
2 RI BUS DRIVER DATA
1 CH.15 BUS DATA
0 CH.15 BUS DATA
MUX 10174 A42
MUX 10174 A38
MUX 10174 A40
MUX 10174 A36
X->Y
MUXED DATA ACL 16
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268184 ONLY.
CONTROL DATA CANADA LTD
DISPLAY CONTROLLER
RADIAL INTERFACE, INTERFACES
210 PAK ASSEMBLY
TYPE: 1CK0
C
A
23-APR-85
SHEET 25A




CONTROL DATA CANADA LTD	RADIAL INTERFACE BUS DRIVERS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		19-APR-85	SHEET 26	




CONTROL DATA CANADA LTD	RADIAL INTERFACE BUS DRIVERS 210 PAK ASSEMBLY TYPE: 1CK0		C	A
		23-APR-85	SHEET 26A	




CONTROL DATA CANADA LTD	MODULE ASSY:210 PAK TYPE: 1CK0		C	A
		23-APR-85	SHEET 27	




CONTROL DATA CANADA LTD	MODULE ASSY:210 PAK TYPE: 1CK0		C	A
		23-APR-85	SHEET 27A	




CONTROL DATA CANADA LTD	A BARREL SELECTION 210 PAK ASSEMBLY TYPE: 1CL0		C	A
		11-APR-85	SHEET 02	



21 ALC T1
22 ACK SELECT BARREL 1-RNK 8
RGTR 10173 A24
RGTR 10173 A22
RGTR 10173 A20
2CD A24
2CD A22
2CD A20
1CD
CR2H36 B103
CR1H36 B086
CR2H37 B094
CR1H37 A094
CR2H38 B093
CR1H38 A093
CR2H39 B084
CR1H39 A084
CR2H40 B083
CR1H40 A083
CR2H41 B092
CR1H41 A092
CR2H42 A081
CR1H42 B080
CR2H43 B090
CR1H43 A090
CR2H44 B091
CR1H44 A091
CR2H45 A082
CR1H45 B082
CR2HP1 B095
CR1HP1 A095
CR2HP2 B104
CR1HP2 A104
RGTR 10176 B24
RGTR 10176 B22
RGTR 10176 B20
RGTR 10176 C20
CD
PU
PL
R-RNK 0 AAK
R-RNK9 TO R+A ADDER AAJ
0 SELECT BAR 0
1 SELECT BAR 1
CONTROL DATA CANADA LTD
R BARREL SELECTION
BITS 36-45
210 PAK ASSEMBLY
TYPE: 1CL0
C
A
14-JAN-85
SHEET 03
LOC. D06




CONTROL DATA CANADA LTD	R BARREL SELECTION BITS 46-57 210 PAK ASSEMBLY TYPE: 1CL0		C	A
		14-JAN-85	SHEET 04	LOC. D06




CONTROL DATA CANADA LTD	R+A ADDER BITS 36-45 210 PAK ASSEMBLY TYPE: 1CL0		C	A
		14-JAN-85	SHEET 05	LOC. D06




CONTROL DATA CANADA LTD	R+A ADDER BITS 46-57 210 PAK ASSEMBLY TYPE: 1CL0		C	A
		14-JAN-85	SHEET 06	LOC. D06





CONTROL DATA CANADA LTD	CM ADDRESS PARITY GENERATOR 210 PAK ASSEMBLY TYPE: 1CL0		C	A
		11-APR-85	SHEET 07	LOC. D06




CONTROL DATA CANADA LTD	OS BOUNDS CHECKER 210 PAK ASSEMBLY TYPE: 1CL0		C		A
		14-JAN-85	SHEET 08	LOC. D06	


DATA TO Y MUX
25 AGE +DISABLE R MUX
5 AAQ -CM ADDRESS RK 0
3 AAK -R BARREL RK 0
27 ADE ENABLE R+A TO MEMORY
4 AAM -R BARREL RK 0
25 AGF +DISABLE R MUX
8 ABC LOGIC "0"
22 ACJ SELECT BAR 1 -RNK 9
NC 7
9
RGTR 10173 C22
CP27AD A085 R-UPPER-1 3
CP17AD B085 R UPPER-0 4
2CD
1CD
2
04
21 AFE T1
RGTR 10176 B08
CD
4
25 AGC MAC WRITE
1 10104 E10
6
7
3
X->Y
G3
G0
MUX 10174 E24
MUX 10174 E22
MUX 10174 E20
MUX 10174 E18
MUX 10174 E16
MUX 10174 E14
MUX 10174 E12
2 52
15 53
2 54
15 55
2 56
15 57
2 58
15 59
2 60
15 61
2 62
15 63
NC
PU
PL
=1 10107 D12
=1 10107
14 AFA REGENERATED PARITY BIT
CN1KAD A046 +INV PARITY
+DATA TOO Y MUX PAR ERR AAS 15
33
ABF 14
MUX SELECTS
0 R LOWER
1 R UPPER
2 R+A LOWER
3 R+A UPPER
CONTROL DATA CANADA LTD
Y MUX
210 PAK ASSEMBLY
TYPE: 1CL0
C
A
14-JAN-85
SHEET 09
LOC. D06



DQ1JAA B112 * -LOAD
28 ADG SELECTED PP @ RNK 9
21 ACH -T1 [CLOCK]
21 ACG +MC
21 ACB
DQ1JAE B109 * READ
21 ACI -RAW T1
15 ADA MUXED DATA TO MAC
21 ACG -T1 [CLOCK]
15 AGK -PARITY BIT
* SHORT & DO NOT TERMINATE
** SHORT. TERMINATE AT POINT FARTHEST FROM THE CONNECTOR PIN.
DATA B101 DQ1KAA
+PAUSE B111 CL1AAA
-ENABLE WRITE AGM 25
BYTE CODE ABI 25
MUX SELECT CODE AAY 13,30
MAC DATA AAV 11,12,14,16,25
AFP 16
AFQ 16
CONTROL DATA CANADA LTD
MAC INTERFACE
210 PAK ASSEMBLY
TYPE: 1CL0
C
A
19-APR-85
SHEET 10




CONTROL DATA CANADA LTD	OSB MAINTENANCE REGISTER BYTES 0-3 210 PAK ASSEMBLY TYPE: 1CL0		C	A
		14-JAN-85	SHEET 11	LOC. D06



CONTROL DATA CANADA LTD	OSB MAINTENANCE REGISTER BYTES 5-7 210 PAK ASSEMBLY TYPE: 1CL0		C	A
		14-JAN-85	SHEET12	LOC D06



CONTROL DATA CANADA LTD	MAC MUX 210 PAK ASSEMBLY TYPE: 1CL0		C	A
		14-JAN-85	SHEET 13	LOC. D06



CONTROL DATA CANADA LTD

MAC REGISTERS TO WRITE

PP MEMORY


MODULE ASSEMBLY-210 PAK

TYPE: 1CL0


C

A


11-APR-85 SHEET 14 LOC. D06




CONTROL DATA CANADA LTD	STATUS MUX MODULE ASSEMBLY-210 PAK TYPE: 1CL0		C	A
		14-JAN-85	SHEET 15	LOC. D06




CONTROL DATA CANADA LTD	SELECT CODE GENERATOR FOR A,P,K,Q, PPM MUX MODULE ASSY:210 PAK TYPE: 1CL0		C	A
		14-JAN-85	SHEET 16	LOC. D06



21 ALB T1
X->Y CODER 10162 F10
CP1J61 A021 * BIT 73
CP1J62 B020 * BIT 74
CP1J63 A027 * BIT 75
CP1FAA A031 BIT 76
NC
C RGTR 10176 G10
CD
RD
&
21 AFE -T1
C RGTR 10176 B04
C RGTR 10176 G12
R5R
R5
+READ 3RD PARCEL ACV 31
CLA
180
170
G1 10101 E06
& 1 E06
CP1BAC A016 16 BIT MODE
C RGTR 10176 G08
X->Y CODER 10162 F08
1 10104 E10
X
R1
CP1FAB B026 BIT 77
32 AFR EXCH BUSY
C RGTR 10176 H08
W5L
W5R
CLB
W1
ADU FUNC ABT 18,24
& 10105 H10
T
3 ADU WRITE ENABLE BBL 0 ABV 18
X->Y CODER 10162 E08
NC
C RGTR 10173 C22
2CD C22
1CD
180
-SEL 16 BIT MODE B072 CL1HAA
* SHORT
22 ACJ -SEL. BAR.1 RNK 9
19 ABY -16 BIT MODE BAR. 1
1 16 BIT MODE BAR.1
0 ADU FUNCTION 180
CONTROL DATA CANADA LTD
BARREL 0
ADU FUNCTION DECODER
MODULE ASSEMBLY - 210 PAK
TYPE: 1CL0
C
A
11-APR-85
SHEET 17




CONTROL DATA CANADA LTD	ADU CONTROLS BARREL SELECTION MODULE ASSY: 210 PAK TYPE: 1CL0		C	A
		14-JAN-85	SHEET 18	




CONTROL DATA CANADA LTD	BARREL 1 ADU FUNCTION DECODER MODULE ASSEMBLY - 210 PAK TYPE: 1CL0		C	A
		11-APR-85	SHEET 19	




CONTROL DATA CANADA LTD	ADU PAK ADDRESS GENERATOR MODULE ASSY: 210 PAK TYPE: 1CL0		C	A
		11-APR-85	SHEET 20	





CONTROL DATA CANADA LTD	CLOCK @ MC FANOUT MODULE ASSY:210 PAK TYPE:1CL0		C		A
		11-APR-85	SHEET 21	LOC. D06	


21 ACF -T1 [CLOCK]
REQUEST IN PROGRESS BARREL
*-----LONG FOIL
24 AFK
23 AXX
32 BXX
NC
10H117 F34
-REQUEST IN PROGRESS ACN 23
-NO REQUEST IN PROGRESS ACM 23
8 ABD LOGIC "0"
21 ADD +M/C ADU
10H121 J38
46
24 AFJ -START CM REQUEST BAR 0
19 CFL -START CM REQUEST BAR 1
23 ACO -SEL BAR 1 RNK 9
-SEL BAR 1 RNK 0 AFB 11
+SEL BAR 1 RNK 1 AGP 15 AGQ 15
-SELECT BAR 0 B102 CL1MAB
-SELECT BAR 1 A101 CL1MAC
-SEL BAR 1 RNK 9 ACJ 9,17,18,23,24
-TAG 3 B100 CL1MAA
BAR 0 SELECTED-RNK 9 AFU 23
-SEL BAR 1 RNK 8 ACK 3,4
-SEL BAR 1 RNK 8 ACL 2
03
SELECTED BARREL BARREL
CONTROL DATA CANADA LTD
REQUEST IN PROGRESS & SELECTED BARREL
MODULE ASSY:210 PAK
TYPE: 1CL0
C
A
17-APR-85
SHEET 22




CONTROL DATA CANADA LTD	PRIORITY STATUS BARREL MODULE ASSY:210 PAK TYPE: 1CL0		C		A
		19-APR-85	SHEET 23		



32 BGL +CM REQ COMPLETED BAR 1
17 ABT -ADU FUNC BAR 0
23 AFG -ADU BUSY BAR 0
DC1RSJ B098 -IOU PORT BUSY
+CM REQ COMPLETED AFM 23
CM REQ COMPLETED BAR 0 AFK 22,23
-IOU PORT BUSY BGE 32
+CM REQ. A056 CL1OAC
+CLEAR EXCH BUSY & RESP BGF 32
32 BGQ
32 BGP
32 BGN
27 B0B
22 ACJ
CP2IAA B057
CP1IAA B045
32 BGO
21 ACG
19 ABY ADU FUNC BAR 1
8 AFO OSB ERROR RNK 9
+OSB ERROR RNK 0 AAR 15
+START CM REQ BAR 0 AFI 23
-START CM REQ BAR 0 AFJ 22,23
BGI 32
BGJ 32
10H104 G14
10H104 E10
10H104 G16
10H104 K04
10H104 G38
10H105 H16
10H105 J12
10109 J04
10H105 J16
RGTR 10173 C22
RGTR 10176 C36
2CD C22
1CD
CONTROL DATA CANADA LTD
ADU CONTROLS
MODULE ASSY:210 PAK
TYPE: 1CL0
C
A
19-APR-85
SHEET 24




CONTROL DATA CANADA LTD	EC REGISTER STROBE DECODER MODULE ASSEMBLY-210 PAK TYPE: 1CL0		C	A
		14-JAN-85	SHEET 25	LOC D06



CONTROL DATA CANADA LTD	EC REGISTER BYTES 4 & 5 MODULE ASSY:210 PAK TYPE: 1CL0		C		A
		14-JAN-85	SHEET 26	LOC. D06	




CONTROL DATA CANADA LTD	EC REGISTER BYTES 6 & 7 MODULE ASSEMBLY- 210 PAK TYPE: 1CL0		C	A
		19-APR-85	SHEET 27	




* SHORT & NO TERMINATOR


CONTROL DATA CANADA LTD	MODULE ASSEMBLY - 210 PAK TYPE: 1CL0		C	A
		11-APR-85	SHEET 28	




CONTROL DATA CANADA LTD	MODULE ASSEMBLY - 210 PAK TYPE: 1CL0		C	A
		11-APR-85	SHEET 29	




CONTROL DATA CANADA LTD	ENVIRONMENT CONTROL READ MUX MODULE ASSEMBLY-210 PAK TYPE: 1CL0		C	A
		14-JAN-85	SHEET 30	LOC D06



CONTROL DATA CANADA LTD	DATA READY RAMS MODULE ASSEMBLY-210 PAK TYPE: 1CL0		C	A
		30-APR-85	SHEET 31	




CONTROL DATA CANADA LTD	ADU CONTROLS MODULE ASSY:210 PAK TYPE: 1CL0		C	A
		19-APR-85	SHEET 32	




* NOTE: NO TERM


CONTROL DATA CANADA LTD	PPM COUNTER MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		17-APR-85	SHEET 02	




CONTROL DATA CANADA LTD	BANK ACTIVE DECODE MODULE ASSY:210 PAK TYPE: 1CMO		C	A
		16-APR-85	SHEET 03	LOC D18




CONTROL DATA CANADA LTD	BANK WRITE ENABLE MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		15-APR-85	SHEET 04	LOC D18




CONTROL DATA CANADA LTD	Y MUX CONTROL CHANNEL SELECT DECODE MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 05	LOC D18


Y MUX
5 ACV +ADU TO Y MUX
5 ACY -Y MUX CNTRL 1
5 ADB -Y MUX CNTRL 2
41 ACS -LOGIC "0"
X->Y
G7
GO
MUX 10164 C14
MUX 10164 B14
MUX 10164 A14
MUX 10164 A24
CP1N48 A031 -CHANNEL DATA
CL1B48 A047 -R DATA (OR MAC)
CR1F48 B031 -A DATA
DDID48 B045 48
DDID60 A045 60
DDID56 B043 56
DDID52 A043 52
CP1N49 A032
CL1B49 B046
CR1F49 B032
DDID49 B042 49
DDID61 A042 61
DDID57 B041 57
DDID53 B021 53
CP1N50 A033
CL1B50 A046
CR1F50 B033
DDID50 A041 50
DDID62 B039 62
DDID58 A040 58
DDID54 B040 54
CP1N51 B060
CL1B51 A068
CR1F51 A003
DDID51 B063 51
DDID63 A064 63
DDID59 B064 59
DDID55 A063 55
15 48
15 49
15 50
15 51
-Y MUX DATA BITS 48-51 ADJ 10
ADI 7-9
7 LOGIC "0"
6 CHANNEL DATA BITS (48-51)
5 R REG BITS (48-51)
4 A REG BITS (48-51)
3 ADU DATA BITS (48-51)
2 ADU DATA BITS (60-63)
1 ADU DATA BITS (56-59)
0 ADU DATA BITS (52-55)
* NOTE: NO TERM AND SHORT
CONTROL DATA CANADA LTD
Y MUX BITS 48-51
MODULE ASSY:210 PAK
TYPE: 1CM0
C
A
15-APR-85
SHEET 06
LOC. D18




7	P DATA BITS (52-55)
6	CHANNEL DATA BITS (52-55)
5	R REG BITS (52-55)
4	A REG BITS (52-55)
3	ADU DATA BITS (52-55)
2	ADU DATA BITS (48-51)
1	ADU DATA BITS (60-63)
0	ADU DATA BITS (56-59)

CONTROL DATA CANADA LTD	Y MUX BITS 52-55 MODULE ASSY:210 PAK TYPE: 1CM0	C	A
		16-APR-85	SHEET 07 LOC. D18




CONTROL DATA CANADA LTD	Y MUX BITS 56-59 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		15-APR-85	SHEET 08	LOC. D18




7	P DATA BITS (60-63)
6	CHANNEL DATA BITS (60-63)
5	R REG BITS (60-63)
4	A REG BITS (60-63)
3	ADU DATA BITS (60-63)
2	ADU DATA BITS (56-59)
1	ADU DATA BITS (52-55)
0	ADU DATA BITS (48-51)


CONTROL DATA CANADA LTD	Y MUX BITS 60-63 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		15-APR-85	SHEET 09	LOC. D18




CONTROL DATA CANADA LTD	PPM DATA IN PARITY REGENERATOR/CHECKER MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		15-APR-85	SHEET 10	LOC. D18




CONTROL DATA CANADA LTD	BANK 0 ADDRESS REG DATA LATCH/TRANSLATION MODULE ASSEMBLY-210 PAK TYPE: 1CM0		C	A
		23-APR-85	SHEET 11	




CONTROL DATA CANADA LTD	BANK 0 ADDRESS TRANSLATION MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		15-APR-85	SHEET 12	LOC. D18




CONTROL DATA CANADA LTD	BANK 1 ADDRESS REG. DATA LATCH/TRANSLATION MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		15-APR-85	SHEET 13	




CONTROL DATA CANADA LTD	BANK 1 ADDRESS TRANSLATION MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 14	







CONTROL DATA CANADA LTD	BANK 2 ADDRESS REG. DATA LATCH/TRANSLATION MODULE ASSY:210 PAK TYPE: 1CM0		C		A
		17-APR-85		SHEET 15	




CONTROL DATA CANADA LTD	BANK 2 ADDRESS TRANSLATION MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		17-APR-85	SHEET 16	




CONTROL DATA CANADA LTD	BANK 0 BITS 48-50 MODULE ASSY 210 PAK TYPE: 1CM0		C		A
		16-APR-85	SHEET 17		




CONTROL DATA CANADA LTD	BANK 0 BITS 51-53 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 18	




CONTROL DATA CANADA LTD	BANK 0 BITS 54-56 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 19	




CONTROL DATA CANADA LTD	BANK 0 BITS 57-59 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 20	




CONTROL DATA CANADA LTD	BANK 0 BITS 60-62 MODULE ASSY:210 PAK TYPE: 1CM0		C		A
		16-APR-85		SHEET 21	




CONTROL DATA CANADA LTD	BANK 0 BIT 63,P0 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 22	




CONTROL DATA CANADA LTD	BANK 1 BITS 48-50 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		23-APR-85	SHEET 23	




CONTROL DATA CANADA LTD	BANK 1 BITS 51-53 MODULE ASSY: 210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 24	




CONTROL DATA CANADA LTD	BANK 1 BITS 54-56		C		A
	MODULE ASSY:210 PAK	16-APR-85	SHEET 25		
	TYPE: 1CM0				




CONTROL DATA CANADA LTD	BANK 1 BITS 57-59 MODULE ASSY:210 PAK TYPE: 1CM0	C		A
		16-APR-85	SHEET 26	




CONTROL DATA CANADA LTD	BANK 1 BITS 60-62 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 27	




CONTROL DATA CANADA LTD	BANK 1 BITS 63,P0 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 28	




CONTROL DATA CANADA LTD	BANK 2 BITS 48-50		C		A
	MODULE ASSY:210 PAK	16-APR-85	SHEET 29		
	TYPE: 1CM0				




CONTROL DATA CANADA LTD	BANK 2 BITS 51-53 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 30	




CONTROL DATA CANADA LTD	BANK 2 BITS 54-56 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 31	




CONTROL DATA CANADA LTD	BANK 2 BITS 57-59 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 32	




CONTROL DATA CANADA LTD	BANK 2 BITS 60-63 MODULE ASSY:210 PAK TYPE: 1CM0		C		A
		16-APR-85	SHEET 33		




CONTROL DATA CANADA LTD	BANK 2 BITS 63,P0 MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 34	




CONTROL DATA CANADA LTD	BANK 0 DATA OUT LATCH/TRANSLATION MODULE ASSY:210 PAK TYPE: 1CM0		C	A
		15-APR-85	SHEET 35	LOC D18



CONTROL DATA CANADA LTD	BANK 1 DATA OUT LATCH/TRANSLATION MODULE ASSY:210 PAK TYPE: 1CM0		C		A
		17-APR-85	SHEET 36	LOC D18	




CONTROL DATA CANADA LTD	BANK 2 DATA OUT LATCH/TRANSLATION MODULE ASSY:210 PAK TYPE: 1CM0		C		A
		15-APR-85	SHEET 37	LOC D18	




* SHORT


CONTROL DATA CANADA LTD	BANK DATA MERGE MODULE ASSEMBLY-210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 38	LOC. D18




CONTROL DATA CANADA LTD	PPM DATA HOLDING REG.		C		A
	MODULE ASSEMBLY-210 PAK	16-APR-85		SHEET 39	LOC. D18
	TYPE: 1CM0				



CONTROL DATA CANADA LTD	PPM DATA HOLDING REG MODULE ASSEMBLY-210 PAK TYPE: 1CM0		C	A
		16-APR-85	SHEET 40	LOC. D18




CONTROL DATA CANADA LTD	CONVERSION WORD COUNT MODULE ASSEMBLY-210 PAK TYPE: ICM0		C	A
		04-NOV-85	SHEET 41	



NOTE: THIS DRAWING IS APPLICABLE ONLY TO PWB 19268136


CONTROL DATA CANADA LTD	CONVERSION WORD COUNT MODULE ASSEMBLY-210 PAK TYPE: 1CM0		C	A
		04-NOV-85	SHEET 41A	




3	PPM DATA BITS (60-63)
2	PPM DATA BITS (56-63)
1	PPM DATA BITS (52-59)
0	PPM DATA BITS (48-55)

* SHORT


CONTROL DATA CANADA LTD	ADU MUX BITS 48-55		C	A
	MODULE ASSEMBLY-210 PAK TYPE: 1CM0	15-APR-85	SHEET 42	LOC D18




CONTROL DATA CANADA LTD	ADU MUX BITS 56-63 MODULE ASSEMBLY-210 PAK TYPE: 1CM0		C	A
		15-APR-85	SHEET 43	LOC D18




CONTROL DATA CANADA LTD	PPM PARITY GEN/CHECKER		C		A
	MODULE ASSEMBLY-210 PAK TYPE: 1CM0	15-APR-85	SHEET 44	LOC D18	




CONTROL DATA CANADA LTD	MASK + GROUP ERRORS BARRELS 0 +1/4X MODULE ASSEMBLY- 210 PAK TYPE: 1CN0	C	A
		02-MAY-84	SHEET 02 LOC. D07




CONTROL DATA CANADA LTD	MASK + GROUP ERRORS BARRELS 1/2X,2,3 MODULE ASSEMBLY- 210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 03	LOC. D07




CONTROL DATA CANADA LTD	DECODE TIMED ERROR TO APP MODULE ASSEMBLY- 210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 04	LOC. D07




CONTROL DATA CANADA LTD	ENCODE CM ERROR TO PPU MODULE ASSEMBLY-210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 05	LOC. D07




CONTROL DATA CANADA LTD	FS1 BYTES 0,1 MODULE ASSEMBLY-210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 06	LOC. D07




CONTROL DATA CANADA LTD	FS1 BYTES 2,3 MODULE ASSEMBLY-210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 07	LOC. D07





CONTROL DATA CANADA LTD	FS1 BYTE 4 MODULE ASSEMBLY-210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 08	LOC. D07




CONTROL DATA CANADA LTD	FS1 BYTE 5 MODULE ASSEMBLY-210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 09	LOC. D07


11 ABA FS1 BYTES 6,7 DATA
32 ACU T1
+CM DATA OUT BYTE ERRORS
C RGTR 10176 B12
C RGTR 10176 B14
B039
A039
B040
B032
B042
B041
B059
A042
CD
& 10109 B16
& 10109 B18
1 10104 D34
2K 10160 A14
DCRCIP A045 RESP. CODE P
20 ADG +INV PARITY
DCRCI2 B045 RESP. CODE 1
DCRCI1 A043 RESP CODE 4
DCRCI0 B043 RESP CODE 4
GI 10101 G38
X->Y CODER 10162 A12
RJ
UNR
UNW
C RGTR 10176 C14
DC1FRB B035 RESPONSE
5 AAL +TAG P.E.
+ADU ERROR AAT 5
DATA TO FS1 BYTES 6,7 AAU 11
CONTROL DATA CANADA LTD
ERROR REPORTING FOR BYTES 6,7
MODULE ASSEMBLY-210 PAK
TYPE: 1CN0
C
A
02-MAY-84
SHEET 10(A) LOC. D07



32 ACU T1
31 ACP +SELECT MAC DATA
30 ACD +MAC DATA
10 AAU DATA TO BYTES 6,7
2 AAD +BARREL 0 ERRORS
2 AAC +BARREL 1 ERRORS
3 AAG +BARREL 2 ERRORS
3 AAH +BARREL 3 ERRORS
A036 +CM DATA IN ERROR
RGTR 10173 C12
RGTR 10173 C16
RGTR 10173 D14
RGTR 10173 D16
RGTR 10176 B12
10105 F04
FS1 BYTES 6,7 DATA ABA 10,13, 21-28
CONTROL DATA CANADA LTD
FS1 BYTES 6,7
MODULE ASSEMBLY-210 PAK
TYPE: 1CN0
C
A
02-MAY-84
SHEET 11 (B)
LOC D07




CONTROL DATA CANADA LTD	PP ERROR STOP GENERATOR 210 PAK ASSEMBLY TYPE: 1CN0		C	A
		02-MAY-84	SHEET 12 OF LOC. D07	




CONTROL DATA CANADA LTD	UNCORRECTABLE ERROR GENERATOR MODULE ASSEMBLY-210 PAK TYPE: 1CN0	C		A
		02-MAY-84	SHEET 13<D>	LOC. D07




CONTROL DATA CANADA LTD	FS2 - BYTE 4 MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		01-MAY-84	SHEET 14(E)	LOC. D07




CONTROL DATA CANADA LTD	FS2 - BYTES 5&1/2 OF 6 MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		01-MAY-84	SHEET 15	



32 ACY -T1 [CLOCK]
31 ACO +SELECT MAC DATA
30 ACD +MAC DATA
17 ABE -CHANNEL MASK
CH3PAD A067 +CH 23 ERROR
CH3PAC A068 +CH 22 ERROR
CH3PAB A064 +CH 21 ERROR
CH3PAA B061 +CH 20 ERROR
A063
A062
A060 +RI 2/3 ERROR
CH4PAF A061 +CH 33 ERROR
CH4PAE B060 +CH 32 ERROR
CH4PAD B058 +CH 51 ERROR
CH4PAC A059 +CH 30 ERROR
10104 A16
10104
10104 F20
10104 E20
RGTR 10173 C20
RGTR 10173 F22
RGTR 10173 E22
2CD ICD
FS2 BYTE 6,7 DATA ABD 13,21-27
CONTROL DATA CANADA LTD
FS2 1/2 OF BYTE 6 & BYTE 7
MODULE ASSY:210 PAK
TYPE:1CN0
C
A
01-MAY-84
SHEET 16




CONTROL DATA CANADA LTD	MASK REGISTER MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		01-MAY-84	SHEET 17	




CONTROL DATA CANADA LTD	PP MASK GENERATOR MODULE ASSY:210 PAK TYPE:1CN0		C	A
		01-MAY-84	SHEET 18	




CONTROL DATA CANADA LTD	TESTMODE DECODERS MODULE ASSY:210 PAK TYPE: 1CN0		C		A
		01-MAY-84	SHEET 19(I)	LOC. D07	




CONTROL DATA CANADA LTD	TESTMODE DECODERS MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 20	




CONTROL DATA CANADA LTD	READ MUX - BIT 7 MODULE ASSEMBLY- 210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 21 CL LOC. D07	




CONTROL DATA CANADA LTD	READ MUX - BIT 6 MODULE ASSEMBLY- 210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 22(M)	LOC.D07




CONTROL DATA CANADA LTD	READ MUX - BIT 5 MODULE ASSEMBLY- 210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 23 CN3	LOC. D07




CONTROL DATA CANADA LTD	READ MUX - BIT 4 MODULE ASSEMBLY- 210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 24(03)	LOC. D07




CONTROL DATA CANADA LTD	READ MUX - BIT 3 MODULE ASSEMBLY- 210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 25CP1	LOC. D07




CONTROL DATA CANADA LTD	READ MUX - BIT 2 MODULE ASSEMBLY- 210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 26<02>	LOC. D07




CONTROL DATA CANADA LTD	READ MUX - BIT 1 MODULE ASSEMBLY-210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 27(R)	LOC. D07




CONTROL DATA CANADA LTD	READ MUX - BIT 0 MODULE ASSEMBLY-210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 28(S)	LOC D07




CONTROL DATA CANADA LTD	MAC INTERFACE MODULE ASSY:210 PAK TYPE: 1CN0		C	C
		04-MAR-86	SHEET 29	




CONTROL DATA CANADA LTD	MAC DATA FANNOUT MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 30(J)	LOC. D07




CONTROL DATA CANADA LTD	BYTE STROBE ENABLE DECODES FOR FS1,FS2,PPM ADDRESS MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 31<V> LOC. D07	




CONTROL DATA CANADA LTD	MASK REGISTER WRITE STROBE DECODES MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 32<W>	LOC. D07




CONTROL DATA CANADA LTD	TEST MODE REGISTER MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 33	




CONTROL DATA CANADA LTD	MASK REGISTER WRITE STROBE DECODES MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 32(W)	LOC. D07




CONTROL DATA CANADA LTD	TEST MODE REGISTER MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 33	




CONTROL DATA CANADA LTD	PP MEMORY ADDRESS REGISTER MODULE ASSY:210 PAK TYPE: 1CN0		C		A
		02-MAY-84		SHEET 34	




CONTROL DATA CANADA LTD	SELECTED PP TO TIMED PULSE MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 35(Z)	LOC. D07




CONTROL DATA CANADA LTD	PP COUNTERS MODULE ASSY:210 PAK TYPE: 1CN0		C	A
		02-MAY-84	SHEET 36 LOC. D07	



CTHE48 41 -NEW FUNCTION
CTIE48 42 -NEW FUNCTION
04
-RNK 7 AAC 3
3 AAF
22 ACU
23 ACZ
CTHD55 41
CTID55 42
CTHD56 41
CTID56 42
CTHD57 41
CTID57 42
CTHD58 41
CTID58 42
CTHD59 41
CTID59 42
CTHD60 41
CTID60 42
CTHD61 41
CTID61 42
CTHD62 41
CTID62 42
CTHD63 41
CTID63 42
CTHDPB 41
CTIDPB 42
RGTR 10173 D08
RGTR 10173 D06
RGTR 10173 D04
2CD
ICD
-I BARREL RNK 7 AAA 4
3 AAG
CTHE49 41 OUTSTANDING IDLE
CTIE49 42 OUTSTANDING IDLE
OUTSTANDING IDLE AAB 7
CTHE50 41 -CHANNEL SELECT
CTIE50 42 -CHANNEL SELECT
-CHANNEL SELECT A049 CP11AA
D24
I BARREL MUX
0 I BARREL RNK 7
1 PP MEM DATA RNK 7
CONTROL DATA CANADA LTD
NEW FUNCTION SELECT
MODULE ASSY: 210 PAK
TYPE: 1CP0
C
A
10-JAN-85
SHEET 02




CONTROL DATA CANADA LTD	I RNK 7 PARITY MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		15-JAN-85		SHEET 03	LOC. D11




CONTROL DATA CANADA LTD	MICROCODE ADDRESS MODULE ASSY: 210 PAK TYPE: 1CP0		C		A
		10-JAN-85		SHEET 04	LOC. D11




CONTROL DATA CANADA LTD	BARREL CHIP ADDRESS GENERATOR MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		10-JAN-85	SHEET 05	LOC. D11	




CONTROL DATA CANADA LTD	T1 CLOCK FANOUTS MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		10-JAN-85		SHEET 06	LOC. D11




CONTROL DATA CANADA LTD	MICROCODE ADDRESS FANOUT MODULE ASSY: 210 PAK TYPE: 1CP0		C		A
		10-JAN-85	SHEET 07	LOC. D11	




CONTROL DATA CANADA LTD	I BARREL-RNK 8,9 MODULE ASSY:210 PAK TYPE: ICP0		C	A
		10-JAN-85	SHEET 08	LOC. D11




CONTROL DATA CANADA LTD	BRANCH 1 ROMS MICROCODE BITS 49-56 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 09	LOC. D11



36 AEI +MAC WRITE
36 AEF -MAC WRITE
6 AAQ -T1 [CLOCK]
8 ABO I BARREL-RNK 9
8 ABP I BARREL-RNK 9
X-->Y
A255
A000
MEM
10149
J22
MEM
10149
J24
MEM
10149
J30
MEM
10149
J26
MEM
10149
J28
& 10105 H14
1 10104 C12
C RGTR 10176 H20
Y MUX SELECT BIT 62
A057 CP17AA
Y MUX SELECT BIT 63
B058 CP17AB
BRANCH 1 ABR 11
+CHANNEL DATA TO A
A015 CP17AC
R UPPER TO Y
B013 CP17AD
UCODE BITS 59, 60,71,72
ABS 21
BRANCH 2 ABT 11
CONTROL DATA CANADA LTD
BRANCH 2 ROMS
MICROCODE BITS 59-72
MODULE ASSY:210 PAK
TYPE: 1CP0
C
A
10-JAN-85
SHEET 10
LOC. D11




CONTROL DATA CANADA LTD	BRANCH SELECT MUX MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 11	LOC. D11




CONTROL DATA CANADA LTD	MICROCODE BITS 0-11 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 12	LOC. D11




CONTROL DATA CANADA LTD	MICROCODE BITS 12-19 MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		10-JAN-85	SHEET 13	LOC. D11	




CONTROL DATA CANADA LTD	MICROCODE BITS 20-27 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 14	LOC. D11




CONTROL DATA CANADA LTD	MICROCODE BITS 28-35 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 15	LOC. D11




CONTROL DATA CANADA LTD	MICROCODE BITS 36-43 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 16	LOC. D11




CONTROL DATA CANADA LTD	MICROCODE BITS 44-47,72-75 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 17	LOC D11




CONTROL DATA CANADA LTD	MICROCODE ROMS MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 18	LOC D11




CONTROL DATA CANADA LTD	MICROCODE PARITY CHECKER MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		11-JAN-85	SHEET 19	LOC. D11	




CONTROL DATA CANADA LTD	MICROCODE BITS 76,77,79 TO 83 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 20	LOC. D11




CONTROL DATA CANADA LTD	MICROCODE P.E. RNK 1 CM FUNCTION BITS MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 21	LOC, D11




CONTROL DATA CANADA LTD	PPM DATA BITS 48-55,P RNKS 0,7,8,9 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 22	LOC. D11




CONTROL DATA CANADA LTD	PPM DATA BITS 56-63 RNKS 0,7,8,9 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 23	LOC. D11




CONTROL DATA CANADA LTD	CHANNEL INPUT MUX MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 24	LOC. D11




CONTROL DATA CANADA LTD	CHANNEL DAT TO Y MUX K BARREL ENABLES MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		11-JAN-85		SHEET 25	LOC. D11




CONTROL DATA CANADA LTD	C BARREL BITS 52-57 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 26	LOC. D11




CONTROL DATA CANADA LTD	C BARREL BITS 58-63 MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		11-JAN-85	SHEET 27	LOC. D11	




CONTROL DATA CANADA LTD	C BARREL PARITY MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 28	LOC. D11




CONTROL DATA CANADA LTD	MAC MUX SELECTS MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		11-JAN-85		SHEET 29	LOC. D11




CONTROL DATA CANADA LTD	C BARREL INPUT MUX MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 30	LOC. D11




CONTROL DATA CANADA LTD	CP MAC MUX BITS 56-63 MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		11-JAN-85	SHEET 31	LOC. D11	




CONTROL DATA CANADA LTD	K BARREL MUX REGISTERS MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 32	LOC. D11




CONTROL DATA CANADA LTD	K BARREL INPUT MUX MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 33	LOC. D11




CONTROL DATA CANADA LTD	OUTSTANDING IDLE RNK 0 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 34	LOC. D11




CONTROL DATA CANADA LTD	NEW FUNCTION MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		10-JAN-85	SHEET 35	




CONTROL DATA CANADA LTD	MAC WRITE MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 36	




CONTROL DATA CANADA LTD	DATA CHANNEL BITS PB, 48-50 MODULE ASSY: 210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 37	LOC. D11



CONTROL DATA CANADA LTD	CHANNEL DATA BITS 51-54 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 38	LOC. D11




CONTROL DATA CANADA LTD	CHANNEL DATA BITS 55-58 MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		11-JAN-85	SHEET 39	LOC. D11	




* THESE FOILS MUST BE SHORT AND TERMINATED AT THE END FARTHEST FROM THE PINS.


CONTROL DATA CANADA LTD	CHANNEL DATA BITS 59-63 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 40	LOC. D11




CONTROL DATA CANADA LTD	I BARREL RNK 0-3 K BARREL RNK 1-4 MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		11-JAN-85	SHEET 41	LOC. D11	




CONTROL DATA CANADA LTD	I BARREL RNK 4-7 K BARREL RNK 5-8 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 42	LOC. D11




CONTROL DATA CANADA LTD	C BARREL RNK 0-3 C BARREL PARITY RNK 1-4 MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		11-JAN-85	SHEET 43	LOC. D11	




CONTROL DATA CANADA LTD	C BARREL RNK 4-7 C BARREL PARITY RNK 5-8 MODULE ASSY:210 PAK TYPE: 1CP0		C	A
		11-JAN-85	SHEET 44	LOC. D11



CP1C61 14
CP1C62 14
CP1C63 14
CP1D61 14
CP1D62 15
CP1D63 15
CP1E60 15
CP1E61 15
CP1E62 15
CP1E63 15
CP1F60 15
CP1F61 15
CP1F62 16
CP1F63 16
CP1H61 16
CP1H62 16
CP1H63 16
CP1G61 16
CP1G62 16
CP1G63 16
CP1I59 18
CP1I60 18
CP1I61 18
CP1I62 18
CP1I63 17
CR15AA 33
CR1CAB 33
CR1CAC 33
CP1PAD 35
CR14AJ 36
CR14AG 33
CN1CAA 34
CP1QAF 36
CP1BAB 14
CP1PAE 18
CP1QAC 36
CP1PAF 35
CP1PAG 35
CP1PAH 34
CP1PAI 35
CL1VAA 33
CL1NAC 35
CL1QAA 33
CL1NAA 35
CL1QAB 36
CP1QAE 36
CK1CAD 35
CP1PAB 35
CL1NAC 35
63
12
64
AC
56
53
54
QC
14
36
22
35
PC
17
19
8
16
GC
57
5
58
WC
27
37
28
EC
51
65
4
61
50
BC
44
45
47
25
62
49
48
33
31
29
30
32
34
40
24
46
42
41
38
39
21
59
52
6
23
13
55
A < 0
A = 1
A = 0
Q(58)
Q < 3
Q = 0
PP ERR
D = 0
EXIT
D.S. SEQ.
D.S. FULL
CHAN ACT
CHAN FULL
CHAN FLAG
CHAN ERR
DATA RDY
CM BUSY + ADU BUSY
EXCH BUSY
ADU BUSY
EXCH RESP
OUTSTANDING REQ
LDS
EXCH BUSY (CM + ADU) BUSY
CM BUSY + ADU BUSY
G NU
P NU
Q NU
ICE0
AN37
C40
ALL FOILS CONNECTED TO THIS CHIP (EXCEPT AC, QC, PC, GC, WC, EC, BC) MUST BE SHORT
A TO A
Q TO Q
P TO P
EXIT
PPM WRITE
G CONTROL
B.C. B
B.C. A
2
1
10
18
7
11
67
68
CP1XAA 33
CP1XAB 33
CP1XAC 33
CE17AB 35
CP1XAE 36
CP1XAF 33
CE1AAA 11
CE1BAA 11
CONTROL DATA CANADA LTD
MODULE ASSY:210 PAK
TYPE: 1CP0
C
A
20-APR-85
SHEET 45
LOC. D11




CONTROL DATA CANADA LTD.	OUTPUT CONVERSION CHIP (0)		C	A
	MODULE ASSY:210 PAK	11-JAN-85	SHEET 46	LOC. D11
	TYPE: 1CP0			




CONTROL DATA CANADA LTD.	INPUT CONVERSION CHIP MODULE ASSY:210 PAK TYPE: 1CP0		C		A
		11-JAN-85	SHEET 47	LOC. D11	




CONTROL DATA CANADA LTD	ASCII TO DISPLAY CODE CONVERSION & ADDRESS FANOUT 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C		D
		01-APR-85	SHEET 02		




CONTROL DATA CANADA LTD	UNBLANK ROM AND ROM ENABLE DECODER 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C		D
		23-APR-85		SHEET 03	




CONTROL DATA CANADA LTD	UNBLANK ROM AND ROM ENABLE DECODER 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	D
		01-APR-85	SHEET 03A	




CONTROL DATA CANADA LTD	BEAM MOVEMENT ROMS FOR DISPLAY CODE 20-57 CHARACTERS 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	D
		23-APR-85	SHEET 04	



CONTROL DATA CANADA LTD	BEAM MOVEMENT ROMS FOR DISPLAY CODE 0-17 CHARACTERS 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	D
		01-APR-85	SHEET 05	




CONTROL DATA CANADA LTD	CHARACTER PAINTER- HORIZONTAL MOVEMENT GENERATOR		C	D
	210 PAK ASSEMBLY TYPE: 1CQ0	01-APR-85	SHEET 06	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268188 ONLY.

CONTROL DATA CANADA LTD	CHARACTER PAINTER- HORIZONTAL MOVEMENT GENERATOR		C	D
	210 PAK ASSEMBLY TYPE: 1CQ0	02-APR-85	SHEET 06A	




CONTROL DATA CANADA LTD	CHARACTER PAINTER- VERTICAL MOVEMENT GENERATOR		C	D
	210 PAK ASSEMBLY TYPE: 1CQ0	29-MAR-85	SHEET 07	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268188 ONLY.


CONTROL DATA CANADA LTD	CHARACTER PAINTER- VERTICAL MOVEMENT GENERATOR		C	D
	210 PAK ASSEMBLY TYPE: 1CQ0	29-MAR-85	SHEET 07A	




CONTROL DATA CANADA LTD	KEYBOARD BUFFER 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	D
		29-MAR-85	SHEET 08	




CONTROL DATA CANADA LTD	DISPLAY CODE TO ASCII CONVERSION 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	P
		29-MAR-85	SHEET 09	




CONTROL DATA CANADA LTD	CH10 CONTROL MACROCELL 210 PAK ASSEMBLY TYPE: 1CQ0		C	D
		29-MAR-85	SHEET 10	



12 ABM
9 AAS +SELECT Z80
19 AAX CH10 DATA
Z80 DATA
CK1C56 B029 BIT 56
CK1C57 B023 BIT 57
CK1C58 A023 BIT 58
CK1C59 A029 BIT 59
CK1C60 B059 BIT 60
CK1C61 A059 BIT 61
CK1C62 B058 BIT 62
CK1C63 A058 BIT 63
12 ABF STB FCTN RGTR
22 AEE +CH 10 FULL
8 AAW T1
12 SFR -STB FCTN RGTR
CCD7AE 10 +INACTIVATE
CCD7AC 10 +ACTIVATE
RGTR 10173 B08
RGTR 10173 B20
RGTR 10173 F04
RGTR 10176 D20
RGTR 10176 F02
X->Y CODER 10161 E08
X->Y CODER 10161 E10
S 10131 E02
10101 C34
10101 G06
10101 E12
10104 E24
10104 C02
10105 D02
10107 A08
10160 C08
10160 C10
DATA TO S REGISTER ABB 13
Y COORD AAY 13
X COORD AAZ 13
7XXX ABE 12
BOTH
RIGHT
DOT
ASCII
LARGE
MED
FUNCTION REGISTER ABD 12
KYBD INP PULSE ABA 12
CH10 PARITY ERROR CQ1BAA 10
B013 CQ1BAB
CONTROL DATA CANADA LTD
CH10 PARITY CHECKER
DISPLAY CONTROLLER INPUT MUX
210 PAK
MODULE ASSEMBLY TYPE: 1CQ0
C
01-APR-85
SHEET 11
P



CONTROL DATA CANADA LTD	DISPLAY CONTROLLER FUNCTION MUX 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	D
		01-APR-85	SHEET 12	




CONTROL DATA CANADA LTD	S REGISTER AND CHARACTER CODE SELECTION MUX 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	D
		01-APR-85	SHEET 13	




ALL RESISTORS ARE
68 OHMS.


CONTROL DATA CANADA LTD	Y REGISTER 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	D
		01-APR-85	SHEET 14	



CONTROL DATA CANADA LTD	X REGISTER & INCREMENTER 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	D
		01-APR-85	SHEET 15	




CONTROL DATA CANADA LTD	DISPLAY CONTROLLER STATUS FLIP FLOPS 210 PAK MODULE ASSEMBLY TYPE: 1CQ0	C	D
		02-APR-85	SHEET 16




NOTE: THIS DRAWING IS ONLY
APPLICABLE TO PWB 19268188.

CONTROL DATA CANADA LTD	DISPLAY CONTROLLER STATUS FLIP FLOPS 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	D
		02-APR-85	SHEET 16A	




CONTROL DATA CANADA LTD	TIMING CHAIN COUNTERS 210 PAK MODULE ASSEMBLY TYPE: 1CQ0	C	D
		01-APR-85	SHEET 17




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268188.


CONTROL DATA CANADA LTD	TIMING CHAIN COUNTERS 210 PAK MODULE ASSEMBLY TYPE: 1CQ0		C	D
		02-APR-85	SHEET 17A	




CONTROL DATA CANADA LTD	CHANNEL 10 INPUT MUX AND CONTROLS 210 PAK ASSEMBLY TYPE: 1CQ0		C	D
		01-APR-85	SHEET 18	




CONTROL DATA CANADA LTD	CHANNEL 10 INPUT MUX AND DATA REGISTER 210 PAK ASSEMBLY TYPE: 1CQ0		C	D
		01-APR-85	SHEET 19	




CONTROL DATA CANADA LTD	BARREL 0 & 1 BUS DRIVERS 210 PAK ASSEMBLY TYPE: 1CQ0		C	D
		01-APR-85	SHEET 20	




CONTROL DATA CANADA LTD	BARREL 2 &3 BUS DRIVERS 210 PAK ASSEMBLY TYPE: 1CQ0		C	D
		01-APR-85	SHEET 21	




CONTROL DATA CANADA LTD	CHANNEL CONTROLS 210 PAK ASSEMBLY TYPE: 1CQ0		C	D
		02-APR-85	SHEET 22	






CONTROL DATA CANADA LTD	CHANNEL CONTROLS 210 PAK ASSEMBLY TYPE: 1CQ0		C	D
		02-APR-85	SHEET 23	




NOTE 1

FOIL LENGTHS FROM CONNECTOR PINS TO PINS 6 AND 4 OF 10117 SHOULD BE ABOUT 8 INCHES ±3 .
FOIL LENGTHS FROM PINS 6 AND 13 TO PINS 4 AND 11 MUST BE 28 INCHES, ±1 .
NOTE 2
N.T.=NO TERMINATION
- FOIL LENGTHS FOR INPUTS AND OUTPUTS OF DL10S AND OUTPUTS OF JUMPER BOXES MUST BE AS SHORT AS POSSIBLE.
- PATHS FROM 10101 THROUGH DL17S TO 10121 MUST ALL BE THE SAME LENGTH, WITHIN ONE INCH.
- DO NOT USE PADS 1, 8 AND 16 IN JUMPER BOX.

CONTROL DATA CANADA LTD	IOU CLOCK TUNING TYPE: 1CQ0		C	F
		12-JUN-86	SHEET 24	



3 AAK LOGIC"0"
NOTE 2
NC 12 G1 10101 F42
DP1INM A109 -SEL NARROW
DP1IWM B109
38 2 7 CR06 F41
10 14
4 5 N
6 W
3 11
4 5 M
1 10121 K32
NS DL10 K34
K36
10 IOU N.T. MT1 25
MASTER T1
SHORT
K35 3 510 OHM 1
-5.2V
1,16
T1B2J B047 -FIRST STAGE T1
NOTE 1
1 10117 E28
NS DL10 K26
K28
1 10121 K42
NS DL10 J40
J38
10 IOU MT2 25
MASTER T2
SHORT
N.T.
B048 -FIRST STAGE T2
NS DL10 K38
K40
NOTE 1
FOIL LENGTHS FROM CONNECTOR PINS TO PINS 6 AND 13 OF 10117 SHOULD BE ABOUT 8 INCHES ±3.
FOIL LENGTHS FROM PINS 6 AND 13 TO PINS 4 AND 11 MUST BE 28 INCHES ±1
NOTE 2
N.T. = NO TERMINATION
NOTE: THIS DRAWING IS APPLICABLE ONLY TO PWB 19268188.
CONTROL DATA CANADA LTD
IOU CLOCK TUNING
TYPE 1CQO
C
29-MAR-85
SHEET 24A
D



NOTE 1:
FOIL LENGTHS MUST BE ARRANGED SO THAT THE TOTAL LENGTH OF FOIL FROM ANY OUTPUT OF THIS 10110 TO ANY SECTION OF ANOTHER 10110 PLUS THE LENGTH FROM AN OUTPUT OF THAT SECTION TO A CONNECTOR PIN MUST BE THE SAME (WITHIN 1 INCH) FOR ALL PATHS.

NOTE 2:
FOIL LENGTHS MUST BE THE LENGTH OF THE OTHER CLOCK LINES PLUS 20 INCHES.

CONTROL DATA CANADA LTD	IOU CLOCKS 2ND STAGE FAN OUT TYPE: 1CQ0		C	D
		02-APR-85	SHEET 25	




NOTE 1:
FOIL LENGTHS MUST BE ARRANGED SO THAT THE TOTAL LENGTH OF FOIL FROM ANY OUTPUT OF THIS 10110 TO ANY SECTION OF ANOTHER 10110 PLUS THE LENGTH FROM AN OUTPUT OF THAT SECTION TO A CONNECTOR PIN MUST BE THE SAME (WITHIN 1 INCH) FOR ALL PATHS.

NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268188.

NOTE 2:
FOIL LENGTHS MUST BE THE LENGTH OF THE OTHER CLOCK LINES PLUS 20 INCHES.

CONTROL DATA CANADA LTD	IOU CLOCKS 2ND STAGE FAN OUT TYPE: 1CQ0		C	D
		02-APR-85	SHEET 25A	





NOTE 1
FOIL LENGTHS FROM CONNECTOR PINS TO PINS 11 AND 13 OF 10117 SHOULD BE ABOUT 8 INCHES ±3.
FOIL LENGTHS FROM PINS 6 AND 13 TO PINS 4 AND 11 MUST BE 28 INCHES ±1.

NOTE 2
N.T.= NO TERMINATION.
- FOIL LENGTHS FOR INPUTS AND OUTPUTS OF DL10S AND OUTPUTS OF JUMPER BOXES MUST BE AS SHORT AS POSSIBLE.
- PATS FROM 10101 THROUGH DL10S TO 10121 MUST ALL BE THE SAME LENGTH, WITHIN ONE INCH.
- DO NOT USE PADS 1,8 AND 16 IN JUMPER BOX.


NOTE: THIS DRAWING IS APPLICABLE ONLY TO PWB 19268888

CONTROL DATA CANADA LTD	IOU CLOCK TUNING TYPE: 1CQ0	C	D
		02-APR-85	SHEET 26



CR1P52 38 -P DATA
CR1P53 38
CR1P54 38
CR1P55 38
CR1P56 39
CR1P57 39
CR1P58 39
CR1P59 39
CR1P60 40
CR1P61 40
CR1P62 40
CR1P63 40
B094 CR1P52
A093 CR1P53
A102 CR1P54
A098 CR1P55
B083 CR1P56
A096 CR1P57
B101 CR1P58
A101 CR1P59
B102 CR1P60
A103 CR1P61
B099 CR1P62
A094 CR1P63
31 ACI
A015 CR1PP0
-PAK TEST ADL 12
NC 12 G1 10101 A06
A016 -PAK TEST 4 & 5 2
6 7 9 4 NC 5 & 1 10117 C20 2 3 NC 23
12 G1 10H101 C36
NC 4 & 5 CNTR BIT 0 CR12AA 35,36
2 NCR12AA 17,37
NC 7 6 CR12AB 17,36
3 NCR12AB 19,35
NC 10 11 CR12AC 17,35,37
14 NCR12AC 18,35,36
NC 13 9 CR12AD 18,19
15 NCR12AD 18,20
NC 12 G1 10H101 B20
4 & 5 CR12AT 19,20
2 NCR12AT 20,37
34
X->Y 1 V 15 1,4 0 2,4 4 NC
5 C3,5D 3 NC
6 C3,5D 2
11 C3,5D 15
12 C3,5D 14
22
B016 -2X 7 A06 6 NC 3
12 G1 10H101 A22
4 & 5 CNTR BIT 1 CR12AE 35,36
2 NC 6 CR12AF 17,36,37
7 3 11 NC CR12AG 18,19,37
10 14 NC 9 CR12AH 17-20
13 15 NC
32 ACK -CT1> [CLOCK]
(13) 16CNTR 10136 B22 C5 2,4-1 1,4+1
NC 10 G4
X->Y 9 2 3 V/C3 7 NC 1 2 G2 1 G1
27
12 G1 10H101 C26
4 & 5 CNTR BIT 2 CR12AJ 35,36
2 NC 6 CR12AK 17,36,37
7 3 11 NC CR12AL 18,19,37
10 14 NC 9 CR12AM 17-20
13 15 NC
B01 CR01
LOGIC ZERO AAA 3,8-10, 22,27,28
CR12AZ 38-40
CONTROL DATA CANADA LTD
BARREL COUNTER
MODULE ASSEMBLY - 210 PAK
TYPE: 1CR0
C
A
09-NOV-84
SHEET 02
LOC. D12




CONTROL DATA CANADA LTD	Q ADDER LOOKAHEAD MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		09-NOV-84	SHEET 03	LOC D12




CONTROL DATA CANADA LTD	P MUX LSB Q = 0, P MATCH MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET 04	LOC. D12




CONTROL DATA CANADA LTD	A REGISTER MODULE ASSEBLY -210 PAK TYPE: 1CRO		C		A
		19-JAN-84	SHEET 05	LOC D12	



CONTROL DATA CANADA LTD	A = 0,1 DECODE A REGISTER PARITY CHECK/GEN MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET 06	LOC D12



CONTROL DATA CANADA LTD	A ADDER CONTROL A ADDER B OPERAND INPUT DATA MODULE ASSEMBLY -210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET 07	LOC D12



E	BITS 46-47
0	LOGIC 0
1	Q9 <58-59>


E	D	ITS 48-51
0	0	LOGIC 0
0	1	PPM <48-51>
1	0	Q9 <60-63>
1	1	NOT USED


C	BITS 52-57
0	LOGIC 0
1	PPM <52-57>

A	BITS 58-62
0	LOGIC 0
1	PPM <58-62>


B	BIT 63
0	PPM <63>
1	LOGIC 0

CONTROL DATA CANADA LTD	A ADDER B OPERAND MUX MODULE ASSEMBLY - 210 PAK TYPE: 1CR0	C	A
		19-JAN-84	SHEET 08 LOC D12



7 AAI -A ADDER CODE
5 AAL -A DATA RK 9
8 AAM -B OPERAND
10 AAW -CARRY IN
2 AAA -LOGIC ZERO
& 10105 cd96 A42
ALU 10181 AG62
ALU 10181 AG63
ALU 10181 AG64
ALU 10181 AG65
ALU 10181 AG66
X->Y
G31 G00
F(A,B,C)
B42
D42
E42
G42
J42
F(A,B)>15
F(A,B)=15
C4
C3
C2
C0
-A ADDER RESULT AAQ 10
-A ADDER GENERATES AND PROPAGATES AAR 10
CONTROL DATA CANADA LTD
A ADDER
MODULE ASSEMBLY - 210 PAK
TYPE: 1CR0
C
19-JAN-84
SHEET 09
LOC D12
A




CONTROL DATA CANADA LTD	A ADDER LOOK AHEAD A ADDER OUTPUT REGISTER MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET 10	LOC D12




CONTROL DATA CANADA LTD	A BYPASS REGISTER A MUX MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET 11	LOC D12




CONTROL DATA CANADA LTD	SHIFTER ROMS MODULE ASSEMBLY TYPE: 1CR0		C	A
		20-JAN-84	SHEET 12	LOC D12




CONTROL DATA CANADA LTD	PPM NIBBLE PARITY GEN MODULE ASSEMBLY-210 PAK TYPE: 1CR0		C		A
		19-JAN-84		SHEET 13	LOC D12



CONTROL DATA CANADA LTD	PPM NIBBLE PARITY MUX MODULE ASSEMBLY-210 PAK TYPE: 1CR0		C		A
		19-JAN-84		SHEET 14	LOC D12




CONTROL DATA CANADA LTD	A REG PARITY 16/12 BIT PARITY MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET 15	LOC D12




VEE - 9,43
VCC - 26,60
VCCO - 3,15,20 66


CONTROL DATA CANADA LTD	SHIFTER Y TO A MUX MODULE ASSEMBLY - 210 PAK TYPE: 1CR0	C	A
		20-JAN-84	SHEET 16 LOC D12




CONTROL DATA CANADA LTD	A BARREL (BITS 46-63) CHIP 1 MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		20-JAN-84	SHEET 17	LOC D12




CONTROL DATA CANADA LTD	A BARREL (BITS 46-63) CHIP 2 MODULE ASSEMBLY - 210 PAK TYPE: 1CR0	C	A
		20-JAN-84 SHEET 18	LOC D12




CONTROL DATA CANADA LTD	R BARREL (BITS 36-55) CHIP 1 MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		20-JAN-84	SHEET 19 / LOC. D12	




CONTROL DATA CANADA LTD	R BARREL (BITS 36-55) CHIP 2 MODULE ASSEMBLY - 210 PAK TYPE: 1CR0	C	A
		20-JAN-84	SHEET 20 LOC. D12




CONTROL DATA CANADA LTD	R BARREL ASSEMBLY MODULE ASSEMBLY -210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET 21	LOC D12




CONTROL DATA CANADA LTD	- R PARITY CHECKER/GEN MODULE ASSEMBLY -210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET 22	LOC D12




CONTROL DATA CANADA LTD	PPM PARITY CHECKER/GEN MODULE ASSEMBLY -210 PAK TYPE: 1CR0		C	·	4
		19-JAN-84	SHEET 23	LOC. D12	



32 ACM -<T1>CLOCK
RK 9
CP19AB A022 +LOAD R LOWER
CP19AA B021 +LOAD R UPPER
32 ACJ -MC
CDak32
aq85
10104 J12 ak36
10104 AK36
10110 K12 AK57
MCL
MCU
MC1
MC2
TO R BARREL
CB1JP2 35
CB1JP1 35
23 ABG -R REG RK 9
7 AAG -PPM REG RK 9
R9 MUX
MUX 10174
23 ABH -PPM 10 BIT P
23 ABI -PPM 12 BIT P
AK29 H14V
AK25 H20V
AK30 H16V
AK26 J14V
AK28 H18V
AK27 J16V
CB1J40 19,20
CB1J41 19,20
CB1J36 19,20
CB1J37 19,20
CB1J42 19,20
CB1J43 19,20
CB1J38 19,20
CB1J39 19,20
CB1J44 19,20
CB1J45 19,20
4 ACZ - LOGIC ZERO
ABN 25
CONTROL DATA CANADA LTD
R MUX<BIT 36-45 ,P1,P2>
MODULE ASSEMBLY-210 PAK
TYPE: 1CR0
C
19-JAN-84
SHEET24
LOC. D12



CONTROL DATA CANADA LTD	R MUX (BITS 46-57) MODULE ASSEMBLY -210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET25	LOC D12





CONTROL DATA CANADA LTD	CHANNEL DATA CHANNEL 17 SELECT MODULE ASSY:210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET26	LOC D12




CODE	REG/BYTE SELECTED
0	P BITS 52-55
1	P BITS 56-63
2	Q BITS 52-55
3	Q BITS 56-63
4	A BITS 46-47
5	A BITS 48-55
6	A BITS 56-63
7	0

CONTROL DATA CANADA LTD	MAC REG/BYTE MUX MODULE ASSEMBLY -210 PAK TYPE: 1CR0	C	A
		19-JAN-84	SHEET27 LOC DI2



CL1SAC B113 -SELECTED PP AT RK 0
32 ACR -(T1)[CLOCK]
10105 AM23 C38
7 [CLOCK]
6 T
27 ABR
11 AAU -A BYPASS RK 0
REG/BYTE MUX
27 ADE
27 ABO
27 ABP
MUX 10164
27 ABQ + DISABLE
2 AAA LOGIC ZERO
V 1 AM21 D32
V 1 AM20 D26
V 1 AM19 D28
V 1 AM18 D30
CR1Q60 40
CR1Q52 38
CR1P60 40
CR1P52 38
CR1Q61 40
CR1Q53 38
CR1P61 40
CR1P53 38
CR1Q62 40
CR1Q54 38
CR1P62 40
CR1P54 38
CR1Q63 40
CR1Q55 38
CR1P63 40
CR1P55 38
RK 1
RGTR 10176 AM24 B38
CD
CDan20 D34
* PP REG DATA TO MAC
A115 CR1K56
B114 CR1K57
A114 CR1K58
A113 CR1K59
B112 CR1K60
A112 CR1K61
B100 CR1K62
A100 CR1K63
* NOTE : SHORT AND NO TERM
CONTROL DATA CANADA LTD
MAC REG/BYTE MUX (BITS 4-7)
MODULE ASSEMBLY -210 PAK
TYPE: 1CR0
C
A
19-JAN-84
SHEET28
LOC D12




CONTROL DATA CANADA LTD	Q PARITY GENERATOR MODULE ASSEMBLY -210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET 29	LOC D12




CONTROL DATA CANADA LTD	PPM ADDRESS CHECKER MODULE ASSEMBLY -210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET30	LOC D12




CONTROL DATA CANADA LTD	P PARITY GENERATOR CR ERROR SUMMARY MODULE ASSY:210 PAK TYPE: 1CR0		C		A
		19-JAN-84		SHEET 31	LOC D12




CONTROL DATA CANADA LTD	POWER ON MC CLOCK F/O MODULE ASSY:210 PAK TYPE: 1CR0	C	A
		30-JAN-84	SHEET 32 LOC D12




CONTROL DATA CANADA LTD	Q REG ASSEMBLY MODULE ASSEMBLY -210 PAK TYPE: 1CR0		C	A
		20-JAN-84	SHEET 33	LOC D12




CONTROL DATA CANADA LTD	P REG ASSEMBLY MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		19-JAN-84	SHEET 34	LOC. D12




CONTROL DATA CANADA LTD	R BARREL (BITS 56,57, P1,P2) Q BARREL (BITS 52-57) MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		20-JAN-84	SHEET 35	LOC. D12




CONTROL DATA CANADA LTD	P BARREL CHIP 1 MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		20-JAN-84	SHEET 36	LOC. D12




CONTROL DATA CANADA LTD	Q BARREL (BITS 58-63,P) P BARREL CHIP 2 MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		20-JAN-84	SHEET 37	LOC. D12




CONTROL DATA CANADA LTD	Q,P SLOT (BITS 52-55) MODULE ASSY:210 PAK TYPE: 1CR0		C	A
		20-JAN-84	SHEET 38	LOC D12




CONTROL DATA CANADA LTD	Q, P SLOT (BITS 56-59) MODULE ASSEMBLY - 210 PAK TYPE: 1CR0		C	A
		20-JAN-84	SHEET 39	LOC. D12




CONTROL DATA CANADA LTD	Q,P SLOT (BITS 60-63) MODULE ASSEMBLY - 210 PAK TYPE: ICR0		C	A
		20-JAN-84	SHEET 40	LOC. D12




CONTROL DATA CANADA LTD	1DQ0 BI-DIRECTIONAL CHANNEL BUS RECEIVER		C	B
		29-MAR-85	SHEET 02	




CONTROL DATA CANADA LTD	1DQ0 MCH REQUEST CW REG. CONTROL MCH CPU SELECT		C		B
		29-MAR-85	SHEET 03		




CONTROL DATA CANADA LTD	1DQ0 FUNCTION DECODE STARTING ADDRESS FORMATION		C	B
		29-MAR-85	SHEET 04	



-CLEAR ERRORS
BAA 5
18 TFN STB FCTN RGTR
FUNCTION REG.
2 AAA -CHAN DATA
FCN 0-7
X->Y CODER 10161 F20
C RGTR 10176 F28
G1 10101 H28
&
-READ FCTN BAB 8
-REQ SS FCTN BAD 3
-WRITE FCTN BAC 8
-START CPU BAE 6
-STOP CPU AAE 6
48
49
37
42
23
T
FCN 8-F
X->Y CODER 10161 F18
G1 10101 K36
50
-DS FCTN BAF 3,6
28 GFN -GOOD FCTN
G1 10101 E24
+D FCTN NBF 23
-D FCTN FNB 2
-MASTER CLEAR AAG 5
1 10104 G38
& 10110 J02
B055
-WRITE B006
X->Y CODER 10161 F16
START ADDRESS BITS 5-7
CODER 10165 K28
XMAX-->Y
28 FCN -ANY FCTN
7 ABG +CPU REQ
8 ABT +INVALID WRITE
8 ABU +INVALID READ
28 XPE -CH PE
& 10105 C18
AAH 10
-D FCTN BFN 2
13 BAK -BYTE COUNT
& 10105 K30
+(DS +RSS) FCTN AAI 14
X->Y CODER 10161 J22
-ENABLE FAKE RDY BAM 8
-ENABLE INCR S AKC 6
13 BAL -SELECT
NC
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268383 ONLY.
CONTROL DATA CANADA LTD
1DQ0 FUNCTION DECODE
STARTING ADDRESS FORMATION
C
B
29-MAR-85
SHEET 04A




CONTROL DATA CANADA LTD	1DQ0 MASTER CLEAR'S CLEAR ERRORS		C	B
		23-APR-85	SHEET 05	




CONTROL DATA CANADA LTD	1DQ0 MASTER CLEAR'S CLEAR ERRORS		C		B
		29-MAR-85	SHEET 05A		




CONTROL DATA CANADA LTD	1DQ0 START/STOP CPU MAC REQUEST C.S.		C	B
		23-APR-85	SHEET 06	




CONTROL DATA CANADA LTD	1DQ0 NANOCODE REQUEST CIRCUITRY		C	B
		29-MAR-85	SHEET 07	




CONTROL DATA CANADA LTD	1DQ0 TYPE CODE DECODING ACCESS CHECKING		C	B
		29-MAR-85	SHEET 08	



CONTROL DATA CANADA LTD	1DQ0 CONTROL WORD ENCODING		C	B
		29-MAR-85	SHEET 09	




CONTROL DATA CANADA LTD	1DQ0 NANOCODE ADDRESS FORMATION	C	B
		30-MAR-85	SHEET 10




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268383 ONLY.


CONTROL DATA CANADA LTD	1DQ0 NANOCODE ADDRESS FORMATION		C	B
		29-MAR-85	SHEET 10A	




CONTROL DATA CANADA LTD	TYPE: 1DQ0 NANOCODE ROMS MODULE ASSY:210 PAK		C	B
		29-MAR-85	SHEET 11	





CONTROL DATA CANADA LTD	1DQ0 TIMING CHAIN		C	B
		29-MAR-85	SHEET 12	




CONTROL DATA CANADA LTD	1DQ0 OP-CODE DECODE BYTE COUNTER		C	B
		29-MAR-85	SHEET 13	


13 AKR -CPU OP-CODE
13 BAL -SEL DS PAK
13 ACQ -CPU OP-CODE OR PMF
7 ABL -SELECT CPU-0
11 BAZ -WRITE
7 ABK -SELECT CPU-1
12 ACK -N4 TIME
18 FTB -FT1
12 ACJ -N6 TIME
7 XCR
18 FTC -FT1
11 BAY -ENBL RDY TO CPU
12 BAQ -N7 TIME
11 BAX -ENABLE RDY TO MCH
3 BAR -CONTROL WORD EMPTY
4 AAI +CD.S.+R.S.S.)FCN
28 RDY -MCH READY
2 ZER +LOGIC "0"
28 FCN -FUNCTION (ANY) *
28 XPE -CH PARITY ERROR
29 NPE -NANOCODE PARITY ERROR
12 AFZ -N2 TIME
23 ADP -R/W PARITY ERROR
26 BIA +BLOCK INACTIVE
9 BLK +BLOCK INACTIVE
UL18TM A063 +PMF EMPTY
UL28TM B056
12 BAG -MCH READY (F/F)
-SELECT DS-1 A026 DQ1EAB
-SELECT DS-0 B025 DQ1EAA
+SELECT DR-1 A025 DQ1EAD
+SELECT DR-0 B023 DQ1EAC
-XMIT CPU-0 BUS ACT 22
-XMIT CPU-1 BUS ACU 23
-BUS ENABLE ACV 13
-WRITE CPU-0 A049 DQ1EAE
-WRITE CPU-1 A127 DQ1EAF
-READY TO CPU-0 B113 DQ1EAG
-READY TO CPU-1 B112 DQ1EAH
+READY TO MCH B116 DQ1EAI
+ERROR TO MCH A128 DQ1EAJ
+INACTIVE A113 DQ1EAK
+PMF END PND 28
NOTE: * MUST BE AT END OF NET.
CONTROL DATA CANADA LTD
1DQ0
CPU BUS CONTROLS
CPU/CHAN COMMUNICATION
C
B
30-MAR-85
SHEET 14



23 ADO -CPU-1 BUS DATA
22 ADN -CPU-0 BUS DATA
PV22BA A050 -CPU-1 RJB BIT 0
PV22BB B051 -CPU-1 RJB BIT 1
PV22BC B052 -CPU-1 RJB BIT 2
PV12BA B049 -CPU-0 RJB BIT 0
PV12BB A051 -CPU-0 RJB BIT 1
PV12BC A052 -CPU-0 RJB BIT 2
7 ABK -SELECT CPU-1
2 ZER +LOGIC "0"
26 SSP -S.S. BITS
11 ACF -DATA MUX SELECTS
20 ADJ -CM/IOU DATA
2 AAB -CONTROL WORD
2 AAA -CHANNEL DATA
25 SSM -STAT. SUM.
24 EID -EID
MUX 1
MUX 2
X->Y
G7
GO
MUX 10164 E16
MUX 10164 D16
MUX 10164 E18
MUX 10164 D18
MUX 10164 E20
MUX 10164 D20
NC
V
15 0
15 1
15 2
M1
M0
-DATA MUX 2 BITS ACW 18,20, 22,27
-DATA MUX 1 BITS ACX 18
NC GI 10101 B20
A059 +BATTERY ON-LINE
CR04
A17
-BATTERY ON-LINE AKS 17
CONTROL DATA CANADA LTD
1DQ0 DATA MUXES BITS 0-2
C
B
30-MAR-85
SHEET 15




CONTROL DATA CANADA LTD	1DQ0 DATA MUXES BITS 3-5		C		B
		30-MAR-85	SHEET 16		




CONTROL DATA CANADA LTD	1DQ0 DATA MUXES BITS 6,7,PARITY		C	B
		30-MAR-85	SHEET 17	




CONTROL DATA CANADA LTD	1DQ0 CHANNEL REGISTER AND TRANSMITTER DATA MUX PARITY		C	B
		24-APR-85	SHEET 18	




CONTROL DATA CANADA LTD	1DQ0 CHANNEL REGISTER AND TRANSMITTER DATA MUX PARITY		C	A
		25-SEP-85	SHEET 18	




CONTROL DATA CANADA LTD	BIT-SERIAL CONTROL MODULE ASSY-210 PAK TYPE: 5MQ0		C	A
		25-SEP-85	SHEET 19	




CONTROL DATA CANADA LTD	1DQ0 BIT-SERIAL CONTROL		C	B
		01-APR-85	SHEET 19	




CONTROL DATA CANADA LTD	1DQ0 BIT-SERIAL SHIFT REG. AND OUTPUT SELECTOR		C		B
		30-MAR-85	SHEET 20		




CONTROL DATA CANADA LTD	1DQ0 BIT-SERIAL INPUT SELECTOR		C	B
		01-APR-85	SHEET 21	




CONTROL DATA CANADA LTD	1DQ0 MAC DATA REGISTER CPU-0 BUS	C		B
		01-APR-85	SHEET 22	




CONTROL DATA CANADA LTD	1DQ0 CPU-1 BUS MAC DATA PARITY CHECK		C	B
		01-APR-85	SHEET 23	




CONTROL DATA CANADA LTD	1DQ0 ELEMENT I. D.		C	B
		30-MAR-85	SHEET 24	



13 BAK -BYTE COUNT
EID48 A081 -EID 48
EID49 A080 -EID 49
EID50 A075 -EID 50
EID51 A074 -EID 51
EID52 B070 -EID 52
EID53 A070 -EID 53
EID54 A067 -EID 54
EID55 B063 -EID 55
EID56 B081 -EID 56
EID57 B079 -EID 57
EID58 B075 -EID 58
EID59 B073 -EID 59
EID60 A071 -EID 60
EID61 B069 -EID 61
EID62 A068 -EID 62
EID63 A064 -EID 63
2 XER +LOGIC "0"
B058
9 ABX -T.C.=0
9 ABY -T.C.=E
NC
G1
10101
J14
X->Y
G3
G0
MUX
10174
D30
D28
D26
D24
-EID BITS EID 15-17
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268383 ONLY.
CONTROL DATA CANADA LTD
1DQ0
ELEMENT I. D.
C
B
30-MAR-85
SHEET 24A




CONTROL DATA CANADA LTD	1DQ0 IOU/CM STATUS SUMMARY BITS BYTE CODE INCREMENTOR		C	B
		30-MAR-85	SHEET 25	




CONTROL DATA CANADA LTD	1DQ0 CPU STATUS SUMMARY BITS		C	B
		30-MAR-85	SHEET 26	




CONTROL DATA CANADA LTD	1DQ0 BYTE COUNT AND DATA TO CPUS'		C		B
		01-APR-85		SHEET 27	


13 BAK -BYTE COUNT
NC 12 G1 10101 A20
0 4 1 & 5 -CPU-0 BYTE COUNT BIT 0 A062 DQ1RAA
2 NC
1 7 1 6 -CPU-0 BYTE COUNT BIT 1 B061 DQ1RAB
3 NC
1 10 1 11 -CPU-1 BYTE COUNT BIT 1 A061 DQ1RAE
14 T
2 13 1 & 9 -CPU-1 BYTE COUNT BIT 2 B060 DQ1RAF
15 T
NC 12 G1 10101 B20
2 13 1 & 9 -CPU-0 BYTE COUNT BIT 2 B059 DQ1RAC
15
NC
0 10 1 11 -CPU-1 BYTE COUNT BIT 0 A060 DQ1RAD
14
NC
18 TDR -STROBE DATA REG.
15 ACW -DATA MUX BITS 0-2
16 ACY -DATA MUX 2 BITS 3-5
17 ADA -DATA MUX BITS 6,7,P
9 C RGTR 10176 C30
0 5 CD 2 -DATA TO CPU-0 BIT 0 B088 DQDD00
1 6 CD 3 -DATA TO CPU-0 BIT 1 A088 DQDD01
2 7 CD 4 -DATA TO CPU-0 BIT 2 B086 DQDD02
3 10 CD 13 -DATA TO CPU-0 BIT 3 A086 DQDD03
4 11 CD 14 -DATA TO CPU-0 BIT 4 B085 DQDD04
5 12 CD 15 -DATA TO CPU-0 BIT 5 A085 DQDD05
9 C RGTR 10176 C32
6 5 CD 2 -DATA TO CPU-0 BIT 6 B093 DQDD06
7 6 CD 3 -DATA TO CPU-0 BIT 7 A093 DQDD07
P 7 CD 4 PARITY B092 DQDDP0
0 10 CD 13 -DATA TO CPU-1 BIT 0 A092 DQEE00
1 11 CD 14 -DATA TO CPU-1 BIT 1 B091 DQEE01
2 12 CD 15 -DATA TO CPU-1 BIT 2 A091 DQEE02
9 C RGTR 10176 C34
3 5 CD 2 -DATA TO CPU-1 BIT 3 B100 DQEE03
4 6 CD 3 -DATA TO CPU-1 BIT 4 A100 DQEE04
5 7 CD 4 -DATA TO CPU-1 BIT 5 B099 DQEE05
6 10 CD 13 -DATA TO CPU-1 BIT 6 A099 DQEE06
7 11 CD 14 -DATA TO CPU-1 BIT 7 B098 DQEE07
P 12 CD 15 PARITY A098 DQEEP0
DCEC08 A031 -DISABLE CPU-0
-DISABLE CPU-0 AKJ 25
4 1 10104 G22 2 +CPU-0 REQUEST AKK 7
NDE17EX A078 +CPU-0 REQ. MAC
5 6 3 +CPU-0 READY AKL 12
PR1JBD A123 +CPU-0 READY
7 10 14 +CPU-1 REQUEST AKM 7
NDE27EX B083 +CPU-1 REQ. MAC
11 12 15 +CPU-1 READY AKN 12
PR2JBD A110 +CPU-1 READY
13 9
DCEC10 B038 -DISABLE CPU-1
-DISABLE CPU-1 AKO 25
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268383 ONLY.
CONTROL DATA CANADA LTD
1DQ0
BYTE COUNT AND DATA TO CPUS'
C
B
30-MAR-85
SHEET 27A



CONTROL DATA CANADA LTD	1DQ0 MCH SIGNALS IN F/F RESETS MAINTENANCE SCAN		C	B
		01-APR-85	SHEET 28	



CONTROL DATA CANADA LTD	1DQ0 NANOCODE PARITY CHECK		C	B
		23-APR-85	SHEET 29	

MEM PANEL

SHEET REVISION STATUS																								
24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	REV
01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01
01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	02	02	02	02	02	02	02
03	03	03	03	03	03	03	03	03	03	03	03	03	03	03	03	03	03	03	03	03	03	03	03	03
A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A

REVISION RECORD						
REV	ECO	DESCRIPTION	DRFT	DATE	CHKD	APP
01	———	INITIAL RELEASE	LRH	3-13-81	D.G. 3-20-81	Y.S. 3-20-81
02	CA42550	CONNECTOR PINOUT CHG.	D.D.	8/19/81	[illegible]	[illegible]
03	CA42626	RENUMBER CKT LOC	LRH	10-26-81	[illegible]	[illegible]
A	CA42944	CLASS A DRAWING	TK	12/14/82	[illegible]	[illegible]

1. CONNECTOR PIN ASSIGNMENTS SHOWN ON SHT 2
2. NO ECL TERMINATIONS SHOWN
3. UNUSED GATES (DESIGNATED BY EITHER A SINGLE INPUT OR OUTPUT):
   A42-5, B42-14, B40-2, B40-3, C44-10
4. UNUSED BUT COMMITTED GATES (DESIGNATED BY EITHER A SINGLE INPUT OR OUTPUT):
   D44-2, D44-3, E44-2, E44-3
5. NOT USED ON 64KX72 (ODNH-1/2 POPULATED MODULE)
6. LAST ⬡ USED FP ON PAGE 5
7.

ADDRESS BITS	NOMENCLATURE AND USAGE	
SYMBOL USED ON THIS SCHEMATIC	USAGE ROW/COLUMN RAM ADDRESS BIT	
A0	A0/A8	ADDRESS BITS MULTIPLEXED BETWEEN RAM ROW AND COLUMN ADDRESSES AS SHOWN
A1	A1/A9	
A2	A2/A10	
A3	A3/A11	
A4	A4/A12	
A5	A5/A13	
A6	A6/A14	
A7	A7/A15	
A8	A16	HIGHEST ORDER ADDRESS BIT THAT SELECTS RAS0,1 OUTPUT (SEE SHT 6) AND MUST BE STABLE THE ENTIRE MEMORY CYCLE.

INTER-DIVISIONAL DOCUMENT
Changes to this document require approval of all Using Divisions per CDC-STD 1.01.024. PD
AAL030 PRINTED IN U.S.A.

DETACHED LISTS

UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES
TOLERANCES
3 PLACE ± 2 PLACE ± ANGLES ±

DO NOT SCALE DRAWING

MATERIAL

FINISH

CONTROL DATA

FIRST USED ON	MI	
DWN	L R HILL	3-13-81
CHKD	D. GABOURY	3-20-81
ENGR	Y. Siplon	3-20-81
MFG	[illegible]	1-2-81
APPR	Y. Siplon	3-20-81

TITLE
SCHEMATIC
128K X 72, 64K X 72
ODPH, ODNH MI MEMORY MODULES

CODE IDENT	DRAWING NO
34010	C

SCALE


SHEET 1 OF 24

CONNECTOR PIN ASSIGNMENTS

SIG. NAME	B PIN NO.	A PIN NO.	SIGNAL NAME	SIG. NAME	B PIN NO.	A PIN NO.	SIGNAL NAME
-5.2V	B1	A1	-5.2V	NC (+12V) (3)	B66	A66	NC (+12V) (3)
-5.2V	B2	A2	-5.2V	BIT 40	B67	A67	T
BOARD SEL	B3	A3	GND	GND	B68	A68	GND
T	B4	A4	OPEN/GND (1)	BIT 41	B69	A69	T
GND	B5	A5	GND	+5V	B70	A70	+5V
T	B6	A6	T	BIT 42	B71	A71	T
-2.2V	B7	A7	-2.2V	GND	B72	A72	GND
-2.2V	B8	A8	-2.2V	BIT 43	B73	A73	T
T (4)	B9	A9	T	BIT 44	B74	A74	T
DATA BIT 0	B10	A10	T	BIT 45	B75	A75	T
GND	B11	A11	GND	GND	B76	A76	GND
BIT 1	B12	A12	T	BIT 46	B77	A77	T
BIT 2	B13	A13	T	BIT 47	B78	A78	T
BIT 3	B14	A14	T	BIT 48	B79	A79	T
GND	B15	A15	GND	GND	B80	A80	GND
BIT 4	B16	A16	T	BIT 49	B81	A81	T
BIT 5	B17	A17	T	BIT 50	B82	A82	T
BIT 6	B18	A18	T	BIT 51	B83	A83	T
GND	B19	A19	GND	GND	B84	A84	GND
BIT 7	B20	A20	T	BIT 52	B85	A85	T
BIT 8	B21	A21	T	BIT 53	B86	A86	T
BIT 9	B22	A22	T	BIT 54	B87	A87	T
GND	B23	A23	GND	GND	B88	A88	GND
BIT 10	B24	A24	T	BIT 55	B89	A89	T
BIT 11	B25	A25	T	BIT 56	B90	A90	T
BIT 12	B26	A26	T	BIT 57	B91	A91	T
GND	B27	A27	GND	GND	B92	A92	GND
BIT 13	B28	A28	T	BIT 58	B93	A93	T
BIT 14	B29	A29	T	BIT 59	B94	A94	T
BIT 15	B30	A30	T	BIT 60	B95	A95	T
GND	B31	A31	GND	GND	B96	A96	GND
BIT 16	B32	A32	T	BIT 61	B97	A97	T
BIT 17	B33	A33	T	BIT 62	B98	A98	T
BIT 18	B34	A34	T	BIT 63	B99	A99	T
GND	B35	A35	GND	GND	B100	A100	GND
BIT 19	B36	A36	T	BIT 64	B101	A101	T
BIT 20	B37	A37	T	BIT 65	B102	A102	T
BIT 21	B38	A38	T	BIT 66	B103	A103	T
GND	B39	A39	GND	GND	B104	A104	GND
BIT 22	B40	A40	T	BIT 67	B105	A105	T
BIT 23	B41	A41	T	BIT 68	B106	A106	T
BIT 24	B42	A42	T	BIT 69	B107	A107	T
GND	B43	A43	GND	GND	B108	A108	GND
BIT 25	B44	A44	T	BIT 70	B109	A109	T
BIT 26	B45	A45	T	BIT 71	B110	A110	T
BIT 27	B46	A46	T	A1	B111	A111	A0
GND	B47	A47	GND	GND	B112	A112	GND
BIT 28	B48	A48	T	A3	B113	A113	A2
BIT 29	B49	A49	T	A5	B114	A114	A4
BIT 30	B50	A50	T	T	B115	A115	T-FUTURE ADDRESS2
GND	B51	A51	GND	GND	B116	A116	GND
BIT 31	B52	A52	T	REFRESH	B117	A117	A6
BIT 32	B53	A53	T	T	B118	A118	WRITE
BIT 33	B54	A54	T	RAS	B119	A119	CAS
GND	B55	A55	GND	GND	B120	A120	GND
BIT 34	B56	A56	T	A8	B121	A121	DATA GATE
BIT 35	B57	A57	T	T	B122	A122	A7
BIT 36	B58	A58	T	-2.2V	B123	A123	-2.2V
GND	B59	A59	GND	-2.2V	B124	A124	-2.2V
BIT 37	B60	A60	T	T	B125	A125	T
+5V	B61	A61	+5V	GND	B126	A126	GND
BIT 38	B62	A62	T	T	B127	A127	T
GND	B63	A63	GND	T	B128	A128	T
BIT 39	B64	A64	T	-5.2V	B129	A129	-5.2V
NC (+12V) (3)	B65	A65	NC (+12V) (3)	-5.2V	B130	A130	-5.2V


NOTES:

1. OPEN ON ODPH MEMORY MODULE ASSEMBLY, FULLY POPULATED, TERMINATED (53702671)
   GND ON ODNH MEMORY MODULE ASSEMBLY, 1/2 POPULATED, TERMINATED (53702670)
2. PRINTED WIRING BOARD FOIL PROVIDES THE OPTION TO CONNECT A115 TO A42 PIN 13 BY ADDING A SHORT JUMPER WIRE.
3. EARLY M1 BACK PANELS SUPPLIED +12V ON THESE PINS.
4. T DESIGNATES A CONNECTION TO A 100 OHM TERMINATION TO -2.2V.



NOTE
1. ADDRESS BITS A0, A1, A2, AND A3 ARE NOT TERMINATED.


CONTROL DATA CORPORATION / DEVELOPMENT DIVISION	SCHEMATIC 128K X 72, 64K X 72 ODPH, ODNH M1 MEMORY MODULES	CODE IDENT 34010 C	SHEET 3 OF 24 PAGE



NOTE

1. ADDRESS BITS A4,A5,A6,AND A7 ARE NOT TERMINATED.


CONTROL DATA CORPORATION DEVELOPMENT DIVISION	SCHEMATIC 128K X 72, 64K X 72 ODPH, ODNH MI MEMORY MODULES	CODE IDENT 34010 C	SHEET 4 OF 24 PAGE



NOTE

1. A42, PIN 13 IS NOT TERMINATED AND CAN BE AN ADDRESS FOR DENSER RAMS.
2. THE CAS INPUT, (A119) AND THE WRITE INPUT, (A118) ARE NOT TERMINATED.

CONTROL DATA CORPORATION	SCHEMATIC	CODE IDENT 34010	
DEVELOPMENT DIVISION	128K X 72, 64K X 72 ODPH, ODNH MI MEMORY MODULES	C	SHEET 5 OF 24 PAGE




NOTES:

1. C44, PIN 2 (10172) IS NOT TERMINATED - SO INPUT A42 PIN 13 (SHT 5) CAN BE AN ADDRESS FOR DENSER RAMS.
2.


B121(A8) VOLTAGE	RAS ENABLED
-1.8 ("1")	RAS 0
-0.8 ("0")	RAS 1

3. ADDRESS BIT A8 (B121), REFRESH (B117), AND RAS (B119) ARE NOT TERMINATED.
4. BOARD SELECT (B03) AND DATA GATE (A121) ARE TERMINATED.


CONTROL DATA CORPORATION	SCHEMATIC 128K X 72, 64K X 72 ODPH, ODNH MI MEMORY MODULES	CODE IDENT 34010	
DEVELOPMENT DIVISION		C	SHEET 6 OF 24 PAGE




CONTROL DATA CORPORATION / DEVELOPMENT DIVISION	SCHEMATIC 128KX72, 64KX72 ODPH, ODNH MI MEMORY MODULES	CODE IDENT 34010	
		C	SHEET 7 OF 24 PAGE




CONTROL DATA CORPORATION	SCHEMATIC	CODE IDENT	
	128KX72, 64KX72	34010	
DEVELOPMENT DIVISION	ODPH, ODNH MI MEMORY MODULES	C	SHEET 8 OF 24 PAGE





CONTROL DATA CORPORATION	SCHEMATIC 128KX72, 64KX72 ODPH, ODNH MI MEMORY MODULES	CODE IDENT 34010	
DEVELOPMENT DIVISION		C	SHEET 9 OF 24 PAGE


NOTES:
(1) CONNECTOR PINS B30, B29, B28, AND B26 ARE NOT TERMINATED.
(2) GHJK ROWS USE RAS 0.
CDEF ROWS USE RAS 1.
+5V
X→Y
C2D 32768
C2D 16384
C2D 8192
C2D 4096
C2D 2048
C2D 1024
C2D 512
C2D 256
C1D 128
C1D 64
C1D 32
C1D 16
C1D 8
C1D 4
C1D 2
C1D 1
A65535
A00000
NC OR +5V
RAS
CAS
WRITE
C1
C2
C3
F
MEM XX64-150 G8
ALSO USED FOR REFRESH
AC3D
AF
DATA OUT
DATA IN
MEMORY 64K X 1 C8
MEMORY 64K X 1 H8
MEMORY 64K X 1 D8
ECL/TTL 10125 A8
-1.29 VR
TTL/ECL 10124 B8
BI-DIR
B30 DATA BIT 15
B29 DATA BIT 14
B28 DATA BIT 13
B26 DATA BIT 12
MEMORY 64K X 1 K8
MEMORY 64K X 1 F8
MEMORY 64K X 1 J8
MEMORY 64K X 1 E8
CONTROL DATA CORPORATION
DEVELOPMENT DIVISION
SCHEMATIC
128KX72, 64KX72
ODPH, ODNH MI MEMORY MODULES
CODE IDENT 34010
C
SHEET 10 OF 24
PAGE





CONTROL DATA CORPORATION / DEVELOPMENT DIVISION	SCHEMATIC 128KX72, 64KX72 0DPH, 0DNH MI MEMORY MODULES	CODE IDENT 34010 C	SHEET 11 OF 24 PAGE



NOTES:
(1) CONNECTOR PINS B41, B40, B38, AND B37 ARE NOT TERMINATED.
(2) GHJK ROWS USE RAS 0.
CDEF ROWS USE RAS 1.
+5V
A65535
A00000
C2D 32768
C2D 16384
C2D 8192
C2D 4096
C2D 2048
C2D 1024
C2D 512
C2D 256
C1D 128
C1D 64
C1D 32
C1D 16
C1D 8
C1D 4
C1D 2
C1D 1
NC OR +5V
RAS
CAS
WRITE
C1
C2
C3
F
MEM XX64-150 G12
ALSO USED FOR REFRESH
AC3D
AF
DATA OUT
DATA IN
MEMORY 64K X 1 C12
MEMORY 64K X 1 H12
MEMORY 64K X 1 D12
ECL/TTL 10125 A12
-1.29 VR
TTL/ECL 10124 B12
BI-DIR
B41 DATA BIT 23
B40 DATA BIT 22
B38 DATA BIT 21
B37 DATA BIT 20
MEMORY 64K X 1 K12
MEMORY 64K X 1 F12
MEMORY 64K X 1 J12
MEMORY 64K X 1 E12
SCHEMATIC
128KX72, 64KX72
ODPH, ODNH MI MEMORY MODULES
CONTROL DATA CORPORATION
DEVELOPMENT DIVISION
CODE IDENT 34010
C
SHEET 12 OF 24
PAGE




CONTROL DATA CORPORATION	SCHEMATIC	CODE IDENT 34010	
DEVELOPMENT DIVISION	128KX72, 64KX72 ODPH, ODNH MI MEMORY MODULES	C	SHEET 13 OF 24 PAGE



NOTES:
(1) CONNECTOR PINS B52, B50, B49, AND B48 ARE NOT TERMINATED.
(2) GHJK ROWS USE RAS 0.
CDEF ROWS USE RAS 1.
+5V
X→Y
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
A65535
A00000
NC OR +5V
RAS
CAS
WRITE
C1
C2
C3
F
MEM
XX64-150
G16
ALSO USED FOR REFRESH
AC3D
AF
DATA OUT
DATA IN
MEMORY 64K X 1 C16
MEMORY 64K X 1 H16
MEMORY 64K X 1 D16
MEMORY 64K X 1 K16
MEMORY 64K X 1 F16
MEMORY 64K X 1 J16
MEMORY 64K X 1 E16
ECL/TTL 10125 A16
TTL/ECL 10124 B16
-1.29 VR
BI-DIR
B52 DATA BIT 31
B50 DATA BIT 30
B49 DATA BIT 29
B48 DATA BIT 28
SCHEMATIC
128KX72, 64KX72
ODPH, ODNH MI MEMORY MODULES
CONTROL DATA CORPORATION
DEVELOPMENT DIVISION
CODE IDENT 34010
C
SHEET 14 OF 24
PAGE


NOTES:
(1) CONNECTOR PINS B57,B56,B54 AND B53 ARE NOT TERMINATED.
(2) GHJK ROWS USE RAS 0.
CDEF ROWS USE RAS 1.
+5V
A65535
A00000
NC OR +5V
RAS
CAS
WRITE
MEM XX64-150 G18
ALSO USED FOR REFRESH
DATA OUT
DATA IN
MEMORY 64K X 1 C18
MEMORY 64K X 1 H18
MEMORY 64K X 1 D18
MEMORY 64K X 1 K18
MEMORY 64K X 1 F18
MEMORY 64K X 1 J18
MEMORY 64K X 1 E18
ECL/TTL 10125 A18
TTL/ECL 10124 B18
-1.29 VR
BI-DIR
B57 DATA BIT 35
B56 DATA BIT 34
B54 DATA BIT 33
B53 DATA BIT 32
CONTROL DATA CORPORATION
DEVELOPMENT DIVISION
SCHEMATIC
128KX72, 64KX72
ODPH, ODNH MI MEMORY MODULES
CODE IDENT 34010
C
SHEET 15 OF 24
PAGE



NOTES:
(1) CONNECTOR PINS B64,B62,B60, AND B58 ARE NOT TERMINATED.
(2) GHJK ROWS USE RAS 0.
CDEF ROWS USE RAS 1.
+5V
C2D 32768
C2D 16384
C2D 8192
C2D 4096
C2D 2048
C2D 1024
C2D 512
C2D 256
C1D 128
C1D 64
C1D 32
C1D 16
C1D 8
C1D 4
C1D 2
C1D 1
A65535
A00000
NC OR +5V
RAS
CAS
WRITE
C1
C2
C3
F
MEM
XX64 - 150
G20
ALSO USED FOR REFRESH
AC3D
AF
DATA OUT
DATA IN
MEMORY 64K X 1 C20
MEMORY 64K X 1 H20
MEMORY 64K X 1 D20
MEMORY 64K X 1 K20
MEMORY 64K X 1 F20
MEMORY 64K X 1 J20
MEMORY 64K X 1 E20
ECL/TTL 10125 A20
-1.29 VR
TTL/ECL 10124 B20
BI-DIR
B64 DATA BIT 39
B62 DATA BIT 38
B60 DATA BIT 37
B58 DATA BIT 36
CONTROL DATA CORPORATION
DEVELOPMENT DIVISION
SCHEMATIC
128KX72, 64KX72
ODPH, ODNH MI MEMORY MODULES
CODE IDENT 34010
C
SHEET 16 OF 24
PAGE





CONTROL DATA CORPORATION	SCHEMATIC 128KX72, 64KX72 ODPH, ODNH MI MEMORY MODULES	CODE IDENT 34010	
DEVELOPMENT DIVISION		C	SHEET 17 OF 24 PAGE




CONTROL DATA CORPORATION	SCHEMATIC	CODE IDENT 34010	
DEVELOPMENT DIVISION	128KX72, 64KX72 ODPH, ODNH MI MEMORY MODULES	C	SHEET 18 OF 24 PAGE



NOTES:
(1) CONNECTOR PINS B83, B82, B81, AND B79 ARE NOT TERMINATED.
(2) GHJK ROWS USE RAS 0.
CDEF ROWS USE RAS 1.
+5V
X→Y
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
A65535
A00000
NC OR +5V
RAS
CAS
WRITE
C1
C2
C3
F
MEM XX64-150 G26
ALSO USED FOR REFRESH
AC3D
AF
DATA IN
DATA OUT
MEMORY 64K X 1 C26
MEMORY 64K X 1 H26
MEMORY 64K X 1 D26
MEMORY 64K X 1 K26
MEMORY 64K X 1 F26
MEMORY 64K X 1 J26
MEMORY 64K X 1 E26
ECL/TTL 10125 A26
TTL/ECL 10124 B26
-1.29 VR
BI-DIR
B83 DATA BIT 51
B82 DATA BIT 50
B81 DATA BIT 49
B79 DATA BIT 48
SCHEMATIC
128KX72, 64KX72
ODPH, ODNH MI MEMORY MODULES
CONTROL DATA CORPORATION
DEVELOPMENT DIVISION
CODE IDENT 34010
C
SHEET 19 OF 24
PAGE


NOTES:
(1) CONNECTOR PINS B89,B87,B86, AND B85 ARE NOT TERMINATED.
(2) GHJK ROWS USE RAS 0.
CDEF ROWS USE RAS 1.
+5V
X→Y
C2D 32768
C2D 16384
C2D 8192
C2D 4096
C2D 2048
C2D 1024
C2D 512
C2D 256
C1D 128
C1D 64
C1D 32
C1D 16
C1D 8
C1D 4
C1D 2
C1D 1
A65535
A00000
NC OR +5V
RAS
CAS
WRITE
C1
C2
C3
F
MEM
XX64-150
G28
ALSO USED FOR REFRESH
AC3D
AF
DATA OUT
DATA IN
MEMORY 64K X 1 C28
MEMORY 64K X 1 H28
MEMORY 64K X 1 D28
MEMORY 64K X 1 K28
MEMORY 64K X 1 F28
MEMORY 64K X 1 J28
MEMORY 64K X 1 E28
ECL/TTL 10125 A28
TTL/ECL 10124 B28
-1.29 VR
BI-DIR
B89 DATA BIT 55
B87 DATA BIT 54
B86 DATA BIT 53
B85 DATA BIT 52
CONTROL DATA CORPORATION
DEVELOPMENT DIVISION
SCHEMATIC
128KX72, 64KX72
ODPH, ODNH MI MEMORY MODULES
CODE IDENT 34010
C
SHEET 20 OF 24
PAGE




CONTROL DATA CORPORATION	SCHEMATIC	CODE IDENT	
	128KX72, 64KX72	34010	
DEVELOPMENT DIVISION	ODPH, ODNH MI MEMORY MODULES	C	SHEET 21 OF 24 PAGE



NOTES:
(1) CONNECTOR PINS B99, B98, B97 AND B95 ARE NOT TERMINATED.
(2) GHJK ROWS USE RAS 0.
CDEF ROWS USE RAS 1.
+5V
C2D 32768
C2D 16384
C2D 8192
C2D 4096
C2D 2048
C2D 1024
C2D 512
C2D 256
CID 128
CID 64
CID 32
CID 16
CID 8
CID 4
CID 2
CID 1
A65535
A00000
NC OR +5V
RAS
CAS
WRITE
C1
C2
C3
F
MEM XX64-150 G32
ALSO USED FOR REFRESH
AC3D
AF
DATA OUT
DATA IN
MEMORY 64K X 1 C32
MEMORY 64K X 1 H32
MEMORY 64K X 1 D32
MEMORY 64K X 1 K32
MEMORY 64K X 1 F32
MEMORY 64K X 1 J32
MEMORY 64K X 1 E32
ECL/TTL 10125 A32
TTL/ECL 10124 B32
-1.29 VR
BI-DIR
B99 DATA BIT 63
B98 DATA BIT 62
B97 DATA BIT 61
B95 DATA BIT 60
CONTROL DATA CORPORATION
DEVELOPMENT DIVISION
SCHEMATIC
128KX72, 64KX72
ODPH, ODNH MI MEMORY MODULES
CODE IDENT 34010
C
SHEET 22 OF 24
PAGE




CONTROL DATA CORPORATION	SCHEMATIC	CODE IDENT	
	128KX72, 64KX72	34010	
DEVELOPMENT DIVISION	ODPH, ODNH MI MEMORY MODULES	C	SHEET 23 OF 24 PAGE




CONTROL DATA CORPORATION	SCHEMATIC	CODE IDENT	
	128KX72, 64KX72	34010	
DEVELOPMENT DIVISION	ODPH, ODNH MI MEMORY MODULES	C	SHEET 24 OF 24 PAGE




CONTROL DATA CANADA LTD	CPU PORT REGISTER MODULE ASSEMBLY - 210 PAK TYPE: 1DA0		C	A
		20-APR-85	SHEET 02	




CONTROL DATA CANADA LTD	WRITE F/F MODULE ASSEMBLY - 210 PAK TYPE: 1DA0		C	1	A
		20-APR-85	SHEET 03		




CONTROL DATA CANADA LTD	REFRESH ADDR. AND PORT MUX SEL 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		20-APR-85	SHEET 04	




CONTROL DATA CANADA LTD	PORT MUX BITS 38-43 210 PAK ASSEMBLY TYPE: 1DA0		C		A
		20-APR-85	SHEET 05		



4 AAG +PORT MUX SEL
4 ADB -REFR ADDR 44
2 AAA -CPU PORT ADDR
33 AED [CLOCK]
C RGTR 10176 A04
C RGTR 10176 A06
CD
CL1A47 B016 -I/O 44 **
CL1A48 A013 -I/O 45 **
CL1A49 A017 -I/O 46 **
CL1A50 B012 -I/O 47 **
CL1A51 B017 -I/O 48 **
CL1A52 A012 -I/O 49 **
CL1A53 B019 -I/O 50 **
CL1A54 A019 -I/O 51 **
CL1A55 A020 -I/O 52 **
CL1A56 B018 -I/O 53 **
4 ADC -REFR ADDR 53
X->Y
G3
G0
MUX 10174 B04
MUX 10174 C04
MUX 10174 D04
MUX 10174 B06
MUX 10174 C06
NC
V
2** 44
15** 45
2** 46
15** 47
2** 48
15** 49
2** 50
15** 51
2** 52
15** 53
** -PORT MUX ADDR 44-53 AAI 8-10,28, 29
NOTE:
** EXTRA SHORT
CONTROL DATA CANADA LTD
PORT MUX BITS 44-53
210 PAK ASSEMBLY
TYPE: 1DA0
C
A
22-APR-85
SHEET 06



CONTROL DATA CANADA LTD	PORT MUX BITS 54-60,P4-P7 MODULE ASSEMBLY :210 PAK TYPE:1DA0	C	A
		20-APR-85	SHEET 07




CONTROL DATA CANADA LTD	ADDRESS PARITY CHECK & BANK START MODULE ASSEMBLY - 210 PAK TYPE: 1DA0		C	B
		01-AUG-85	SHEET 08	




NOTE: THIS DRAWING IS APPLICABLE ONLY TO PWB 19268189 AND 19288838


CONTROL DATA CANADA LTD	ADDRESS PARITY CHECK & BANK START MODULE ASSEMBLY - 210 PAK TYPE: 1DA0		C		B
		02-AUG-85	SHEET 08A		





CONTROL DATA CANADA LTD	BANK 0 + 1 ADDR REGISTER 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		20-APR-85	SHEET 09	





CONTROL DATA CANADA LTD	BANK 2 & 3 ADDR REGISTER 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		20-APR-85	SHEET 10	



18 ABJ +BANK 0 COL.SEL
9 AAS -BANK 0 ADDR
RGTR 10173 B12
RGTR 10173 A12
2CD 1CD
-ARRAY ADDR. BIT A7 B036
-ARRAY ADDR. BIT A6 A035
-ARRAY ADDR. BIT A5 B033
-ARRAY ADDR. BIT A4 A037 DAAA04
-ARRAY ADDR. BIT A3 B037 DAAA03
-ARRAY ADDR. BIT A2 A033 DAAA02
-ARRAY ADDR. BIT A0 B032 DAAA00
X->Y MUX 10174 C12
34 ACT -2 BANK SYS
B035 DAAA01
A036 DAAA08
34 ACW -RECON. SWITCHES
-5U
34 ACU +2 BANK SYS
34 XXB
34 XXA
34 XXD
34 XXC
& 10105 E10
& 10121 D12
-ARRAY ADDR. BIT A8 A038
05
NOTE: LINES MARKED *** ARE TO BE SHORT AS POSSIBLE.
X->Y CODER 10161 B20
-PAK SEL 4 A060 DA1BS4
A061 DA1BS3
A062 DA1BS2
B063 DA1BS1
-PAK SEL 1-4 AAW 18
-3D
+3U
28 ACE +LOGIC "0"
9 IB0 +INHIBIT BANK 0
-4D
+4U
MUX 10174 C20
MUX 10174 C22
CONTROL DATA CANADA LTD
BANK 0 ARRAY ADDRESS
210 PAK ASSEMBLY
TYPE: 1DA0
C
A
20-APR-85
SHEET 11


20 ABP +BANK 1 COL SEL
9 AAT -BANK 1 ADDRESS
RGTR 10173 B14
RGTR 10173 A14
-ARRAY ADDR. BIT A7 B041
-ARRAY ADDR. BIT A6 A040
-ARRAY ADDR. BIT A5 B039
-ARRAY ADDR. BIT A4 A042 DAAA14
-ARRAY ADDR. BIT A3 B042 DAAA13
-ARRAY ADDR. BIT A2 A039 DAAA12
-ARRAY ADDR. BIT A0 B038 DAAA10
34 ACT -2 BANK SYS
MUX 10174 C14
-ARRAY ADDR. BIT A1 B040 DAAA11
34 ACW -RECON. SWITCHES
-ARRAY ADDR. BIT A8 A041
-5U
34 ACU +2 BANK SYS
10105 E10
10121 D14
34 XXB
34 XXA
34 XXD
34 XXC
+CHIP SEL A043 DA1CCS
NOTE: LINES MARKED *** ARE TO BE SHORT AS POSSIBLE.
-3D
+3U
MUX 10174 C20
28 ACE +LOGIC "0"
9 IB1 +INHIBIT BANK 1
-4D
+4U
MUX 10174 C22
X->Y CODER 10161 B22
-PAK SEL 4 B064 DA1CS4
" " 3 A068 DA1CS3
" " 2 B069 DA1CS2
" " 1 A071 DA1CS1
-PAK SEL 1-4 AAY 20
CONTROL DATA CANADA LTD
BANK 1 ARRAY ADDRESS
210 PAK ASSEMBLY
TYPE: 1DA0
C
A
22-APR-85
SHEET 12



22 ABV +BANK 2 COL. SEL
10 AAU -BANK 2 ADDRESS
RGTR 10173 B16
RGTR 10173 A16
RGTR 10173 C16
2CD
1CD
-ARRAY ADDR BIT A8 A048 DAAA28
A7 B048 DAAA27
A6 A047 DAAA26
A5 B046 DAAA25
A4 A049 DAAA24
A3 B049 DAAA23
A2 A046 DAAA22
A1 B045 DAAA21
A0 B047 DAAA20
34 ACW -RECON. SWITCHES
X->Y
MUX 10174 C24
MUX 10174 C26
-3D
+3U
-4D
+4U
28 ACE
34 XXA
34 XXD
-5U
+5D
10121 D24
+CHIP SELECT A076
X->Y CODER 10161 B24
-PAK SEL 4 A072 DA1DS4
B074 DA1DS3
B076 DA1DS2
B079 DA1DS1
-PAK SEL 1-4 ABA 22
10 IB2 +INHIBIT BANK 2
NOTE: LINES MARKED
** ARE TO BE SHORT
AS POSSIBLE
CONTROL DATA CANADA LTD
BANK 2 ARRAY ADDRESS
210 PAK ASSEMBLY
TYPE: 1DA0
C
A
21-APR-85
SHEET 13


24 ADG +BANK 3 COL SEL
10 AAV -BANK 3 ADDRESS
34 ACW -RECONF. SWITCHES
28 ACE
34 XXA
34 XXD
33 ACR -CT1> [CLOCK]
DC1VAA B043 -BANK MUX SEL BIT 0
DC1VAB A045 -BANK MUX SEL BIT 1
10 IB3 +INHIBIT BANK 3
RGTR 10173 B18
RGTR 10173 A18
RGTR 10173 C18
2CD 1CD
-ARRAY ADDR BIT A8 B053 DAAA38
A7 B057 DAAA37
A6 B052 DAAA36
A5 A052 DAAA35
A4 A058 DAAA34
A3 B058 DAAA33
A2 B051 DAAA32
A1 A051 DAAA31
A0 A053 DAAA30
X->Y MUX 10174 C24
X->Y MUX 10174 C26
-3D
+3U
-4D
+4U
-5U
+5D
10121 D26
RGTR 10176 J06
10101 D16
CD
X->Y CODER 10161 B26
+CHIP SELECT A083 DA1ECS
-PAK SEL 4 B080 DA1ES4
B081 DA1ES3
B083 DA1ES2
A085 DA1ES1
-PAK SEL 1-4 ABD 24
-BANK MUX SEL ABC 15,16
NOTE: LINES MARKED ** ARE TO BE SHORT AS POSSIBLE
CONTROL DATA CANADA LTD
BANK 3 ARRAY ADDRESS
MODULE ASSEMBLY - 210 PAK
TYPE: 1DA0
C
21-APR-85
SHEET 14
A







CONTROL DATA CANADA LTD	BANK MUX BITS 40-51 MODULE ASSEMBLY - 210 PAK TYPE: 1DA0		C	A
		21-APR-85	SHEET 15	




CONTROL DATA CANADA LTD	BANK MUX BITS 52-60, P5-P7 MODULE ASSEMBLY - 210 PAK TYPE: 1DA0		C	A
		22-APR-85	SHEET 16	



NOTE: LINES MARKED *** ARE TO BE SHORT AS POSSIBLE.
33 ACR
RGTR 10176 J04
DC1GG0 A003 +START BANK 0
10117 D20
*** +START ABI 18
S 10131 K20
+T4L
S 10131 G20
3 AAE -(T1) [CLOCK]
21
3 AAD -(T1) [CLOCK]
10101 H26
33
20 ABQ +MC A
10105 G26
C2/G6
C1/G5
C0
C4
SR-4 10141 K14
C2,4D
C0,4D
C1,4D
+T0L
+T4L
SR-4 10141 K16
+T4E
18 ABK -(T2) [CLOCK]
SR-4 10141 K18
+T3E
+T2E
+T1E
+T0E
+BANK 2 STATE TIMES ABH 3, 18
CONTROL DATA CANADA LTD
BANK 0 STATE COUNTERS
210 PAK ASSEMBLY
TYPE: 1DA0
C
A
22-APR-85
SHEET 17




CONTROL DATA CANADA LTD	BANK 0 ARRAY CONTROL 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 18	




CONTROL DATA CANADA LTD	BANK 1 STATE COUNTERS 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 19	




CONTROL DATA CANADA LTD	BANK 1 ARRAY CONTROL 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 20	




CONTROL DATA CANADA LTD	BANK 2 STATE COUNTERS 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 21	




CONTROL DATA CANADA LTD	BANK 2 ARRAY CONTROL 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 22	




CONTROL DATA CANADA LTD	BANK 3 STATE COUNTERS MODULE ASSEMBLY - 210 PAK TYPE: 1DA0		C	A
		22-APR-85	SHEET 23	




CONTROL DATA CANADA LTD	BANK 3 ARRAY CONTROL MODULE ASSEMBLY - 210 PAK TYPE: 1DA0		C	A
		22-APR-85	SHEET 24	




CONTROL DATA CANADA LTD	MAC DATA OR CM ADDR MODULE ASSEMBLY 210 PAK TYPE: 1DA0		C	A
		22-APR-85	SHEET 25	




CONTROL DATA CANADA LTD	CEL, UEL1 AND UEL2 REG 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 26	




CONTROL DATA CANADA LTD	BOUNDS REGISTER 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 27	




CONTROL DATA CANADA LTD	UPPER BOUNDS COMPARE 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 28	




CONTROL DATA CANADA LTD	LOWER BOUNDS COMPARE 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 29	




CONTROL DATA CANADA LTD	MAC READ MUX 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 30	




CONTROL DATA CANADA LTD	MAC INTERFACE 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 31	




CONTROL DATA CANADA LTD	MAC CONTROL 210 PAK ASSEMBLY TYPE: 1DA0		C	B
		01-AUG-85	SHEET 32	



CONTROL DATA CANADA LTD	MAC CONTROL 210 PAK ASSEMBLY TYPE: 1DA0		C	A
		22-APR-85	SHEET 33	




CONTROL DATA CANADA LTD	O/I REGISTER 210 PAK ASSEMBLY TYPE: 1DA0		C	B
		01-AUG-85	SHEET 34	




NOTE: THIS DRAWING IS APPLICABLE ONLY TO PWB 19268189 AND 19268838


CONTROL DATA CANADA LTD	O/I REGISTER 210 PAK ASSEMBLY TYPE: 1DA0		C	B
		02-AUG-85	SHEET 34A	




CONTROL DATA CANADA LTD	CELL REGISTER BYTE 0,4 MODULE ASSY:210 PAK TYPE: 1DC0		C	A
		23-APR-85	SHEET 02	




CONTROL DATA CANADA LTD	CEL REGISTER BIT 0,1 MODULE ASSEMBLY-210 PAK TYPE: 1DC0		C		A
		19-APR-85	SHEET 03		




CONTROL DATA CANADA LTD	UEL1 BYTE 0,4 MODULE ASSEMBLY-210 PAK TYPE: 1DC0		C	A
		25-APR-85	SHEET 04	




CONTROL DATA CANADA LTD	UEL1 BYTE 5,6 MODULE ASSEMBLY-210 PAK TYPE: IDC0		C	B
		06-MAR-86	SHEET 05	




CONTROL DATA CANADA LTD	UEL1 REGISTER BYTE 7, BIT 0,1 MODULE ASSEMBLY-210 PAK TYPE: 1DC0		C	A
		23-APR-85	SHEET 06	





CONTROL DATA CANADA LTD	UEL2 BYTE 0,4 MODULE ASSY:210 PAK TYPE: 1DC0		C	A
		23-APR-85	SHEET 07	


9 FTF -FTI [CLOCK]
6 CLE +CLEAR ERROR
7 AAR -UEL 2 ERROR
13 AYC -MAC WR. UEL2 0 [CLOCK]
23 CPF +CPU FAULT
6 AAH -UEL 1 BIT 0
A058 -BOUNDS FAULT
24 WRT -CHECK BOUNDS
14 ABK -MAC WR BOUNDS BYTE 0 [CLOCK]
3 ACX -MAC DATA
30 IOS -IOU SELECTED
22 OIP -CPU-1 IN PORT
22 ZIP -CPU-0 IN PORT
2 ZER +LOGIC ZERO
17 ACR -2 ND PASS REQUEST
19 ARF -REFRESH REQUEST
30 PC0 -PORT CODE BIT 0
30 CPS -PORT CODE BIT 1
06
-UEL 2 BIT 0 AAS 7,11
+VALID UEL 2 ERROR AAT 13
-UEL2 BIT 1 AAU 11
-CM UEL B039 DC18EU
+BOUNDS FAULT AAY 4,5
-BOUNDS REG BIT 0 BN0 10
-BOUNDS REG BIT 1 BN1 10
-BOUNDS REG BIT 2 BN2 10
-2ND PASS REQ DLYD' DLA 4
-REFRESH REQ DLYD' DLD 4
-PORT CODE BIT 0 DLB 4
-PORT CODE BIT 1 DLC 4
-PORT CODE BIT 0 DC18P0
-PORT CODE BIT 1 DC18P1
CPU-0
IOU
CPU-1
10105 C06
10105 D12
10H104 D04
10H104
10105
10176 D16
10176 D02
10176 F12
10131 G08
10104 A16
10H109 C14
10104 D08
10121 E12
CONTROL DATA CANADA LTD
BOUNDS BIT VECTOR
UEL2 BITS 0,1
MODULE ASSY:210 PAK
TYPE: 1DC0
C
A
23-APR-85
SHEET 08




CONTROL DATA CANADA LTD	CLOCK FANOUT EC REGISTER BYTE 0,1,4 MODULE ASSY: 210 PAK TYPE: 1DC0		C	B
		05-MAR-86	SHEET 09	



4 AAF -UEL1 0,4
2 AAA -CEL 0,4
9 ABJ -EC 0,1,4
3 MMC -MAC MUX CONT
6 AAH -UEL1 BIT 0
3 AAB -CEL BIT 0
8 BN0
2 ZER
6 AAO -UEL1 BIT 1
3 AAD -CEL BIT 1
8 BN1
8 BN2
X->Y
G7
GO
MUX 10164 H08
MUX 10164 H10
MUX 10164 K10
MUX 10164 H22
MUX 10164 K12
MUX 10164 K24
MUX 10164 H12
MUX 10164 K26
6A
7A
PC
6B
7B
PA
VA
VB
15 0
15 4
15 1
15 5
15 2
15 6
15 3
15 7
ACM 12
CONTROL DATA CANADA LTD
MAC READ MUX 1
MODULE ASSY:210 PAK
TYPE:1DC0
C
A
25-APR-85
SHEET 10




CONTROL DATA CANADA LTD	MAC READ MUX 2		C	A
	MODULE ASSY:210 PAK	25-APR-85	SHEET 11	
	TYPE: 1DC0			




CONTROL DATA CANADA LTD	MAC INTERFACE MODULE ASSEMBLY-210 PAK TYPE: 1DC0		C	A
		25-APR-85	SHEET 12	



-MAC WRITE ABT 2,14
DQ1JAH B027 * -DIRECTION
12 ADA -BIT 0
& 10105 A08
MAC DATA BUS ** A040 DQ1KAI
9 FTE -FT1 [CLOCK]
C RGTR 10176 E10
CD
** SHORT TERMINATE AT POINT FARTHEST FROM THE CONNECTOR PIN
14 ABR +MAC WRITE P.E.
& 10105 K06
23
NC G1 10101 A12
-MAC DATA IN ABU 3,12
DQ1JAD A039 * -LOAD
& 1 A12
-LOAD ABZ 3,9,12
33
& 10110 A10
8 AAT
& 10104 B04
NC
& 10105 D12
-LOAD UEL2 BYTE 4 ACB 7
T1P5K B037 -RAW TI [CLOCK]
G1 10101 E14
14 ABS -B.C. REG DATA
X->Y CODER 10161 C02
& 10104 C04
-LOAD UEL2 BYTE 0 ACC 7
-LOAD UEL1 BYTE 7 ACD 6
-LOAD UEL1 BYTE 6 ACE 5
-LOAD UEL1 BYTE 5 ACF 5
+MAC RWITE UEL 2 BYTE 0 AYC 8
6 AAN +VALID UEL1 ERR
-MAC WRITE UEL 1 BYTE 0 AYB 6
X->Y CODER 10161 A02
& 10104 B14
-LOAD UEL1 BYTE 4 ACH 4
-LOAD UEL1 BYTE 0 ACI 4
-LOAD CEL BYTE 4 ACJ 2
-LOAD CEL BYTE 0 ACK 2
3 AAC
-MAC WRITE CEL BYTE 0 AYA 3
* SHORT AND DO NOT TERMINATE
CONTROL DATA CANADA LTD
MAC CONTROL
MODULE ASSY:210 PAK
TYPE: 1DC0
C
B
06-MAR-86
SHEET 13




CONTROL DATA CANADA LTD	MAC DATA PARITY CHECK, WRITE ENABLES MODULE ASSY:210 PAK TYPE: 1DC0		C	A
		25-APR-85	SHEET 14	




CONTROL DATA CANADA LTD	TAGS OUT RESPONSES TYPE:1DC0		C		A
		25-APR-85		SHEET 15	




CONTROL DATA CANADA LTD	BANK SELECTS BANK BUSY F/FS' MODULE ASSEMBLY-210 PAK TYPE: 1DC0		C	A
		25-APR-85	SHEET 16	




CONTROL DATA CANADA LTD	FIRST PASS F/FS'		C	A
	MODULE ASSY:210 PAK	25-APR-85	SHEET 17	
	TYPE: 1DC0			




CONTROL DATA CANADA LTD	REFRESH COUNTER MODULE ASSY:210 PAK TYPE: 1DC0		C	A
		25-APR-85	SHEET 18	




CONTROL DATA CANADA LTD	REFRESH MODULE ASSY:210 PAK TYPE: 1DC0		C	A
		25-APR-85	SHEET 19	




CONTROL DATA CANADA LTD	TAGS IN MODULE ASSEMBLY-210 PAK TYPE: 1DC0		C	A
		25-APR-85	SHEET 20	




CONTROL DATA CANADA LTD	BANK LOGS FOR UEL1 AND TAGS TYPE: 1DC0		C	A
		26-APR-85	SHEET 21	




CONTROL DATA CANADA LTD	MARK LINES MODULE ASSY:210 PAK TYPE: 1DC0		C	A
		23-APR-85	SHEET 22	



9 TIO -STROBE IOU PORT [CLOCK]
RGTR 10176 B38
CP1L60 A115 -IOU FCN BIT 0
CP1L61 B114 -IOU FCN BIT 1
CP1L62 A114 -IOU FCN BIT 2
CP1L63 B113 -IOU FCN BIT 3
CP1LPB A113 -IOU FCN BIT P
RGTR 10173 C30
30 AER -SEL CPU
10117 F30
-FCTN CODE ADK 24,32,33
30 AES "1"
-PORT SEL 1 (+SEL CPU)
2 ZER +LOGIC ZERO
22 ADG -MARK LINES 0-3 SET
22 ADH -MARK LINES 4-7 SET
10121 E30
+CPU PARTIAL WRITE ADJ 24
-CPU PARTIAL WRITE JDA 24
9 TCP -STROBE CPU PORT [CLOCK]
25 EC1 -SEL CPU-1
RGTR 10173 A34
UY23F0 B101 -CPU-1 FCN BIT0
UY13F0 A101
UY23F1 B100
UY13F1 A100
UY23F2 B099
UY13F2 A099
UY23F3 B098
UY13F3 A098
RGTR 10176 A30
X->Y CODER 10162 C20
RGTR 10173 A36
10H105 C42
+CPU FAULT CPF 8,24
UY23FP A109 -CPU-1 FCN PARITY
UY13FP B108 -CPU-0 FCN PARITY
UX2FLH A108 -CPU-1 FAULT
UX1FLH B106 -CPU-0 FAULT
A078 -CPU-1 RMA BIT 59
A053 -CPU-0 RMA BIT 59
A119 -CPU-1 RMA BIT 60
B125 -CPU-0 RMA BIT 60
-CPU ADDR 59 AKJ 26
-CPU ADDR 60 AKK 26
CONTROL DATA CANADA LTD
FUNCTION CODE
PORT REGISTER, MUX
TYPE: 1DC0
C
A
26-APR-85
SHEET 23




CONTROL DATA CANADA LTD	FUNCTION DECODE		C		A
	TYPE: 1DC0	24-APR-85	SHEET 24		




CONTROL DATA CANADA LTD	SYNDROME CHECK AND CPU SELECT MASTER CLEAR MODULE ASSY:210 PAK TYPE:1DC0		C	B
		05-MAR-86	SHEET 25	




CONTROL DATA CANADA LTD	CPU REQUEST MODULE ASSY:210 PAK TYPE: 1DC0		C	A
		24-APR-85	SHEET 26	




CONTROL DATA CANADA LTD	IOU REQUEST		C	A
	TYPE: IDC0	23-APR-85	SHEET 27	





CONTROL DATA CANADA LTD	RESPONSE CODE		C	A
	TYPE: 1DC0	23-APR-85	SHEET 28	




CONTROL DATA CANADA LTD	RESPONSE CODE READ MUX SELECTS TYPE:1DC0		C	A
		25-APR-85	SHEET 29	


19 ACV +2ND PASS OR REFRESH
26 ADP -CPU REQ DLYD'
26 ADN -CPU REQ
27 ADZ +IOU REQ DLYD'
27 ADY -IOU REQ DLYD'
26 ADO +CPU REQ DLYD'
27 ADX -IOU (+CPU) REQ
9 FTF -FTI [CLOCK]
1 10117 D24
1 10H117 E26
-SELECT CPU AER 20,23
-PORT SEL BIT 1 B071 DC1UP1
-PORT SEL BIT 0 B068 DC1UP0
-PORT SELECT AES 16,23
& 10105 C26
+IOU OR CPU SELECTED SIK 33
-IOU OR CPU SELECTED SIC 24,32
RGTR 10176 D16
-CPU+IOU SELD' ICS 33
-CPU+IOU SELECTED DC1UCI 21
& 10105 H14
-CPU SELECTED CPS 8,22
+CPU SELECTED AEQ 22,26
& 10105 H14
-IOU SELECTED IOS 8
+IOU SELECTED AEP 27
C1MHZL B096 -1MHZ
-1MHZ MEG 18
22 ZIP -CPU-0 IN PORT
32 FNB -REFRESH RESYNC
1 10117 E04
-PORT CODE BIT 0 PC0 8
9 FTB -FTI [CLOCK]
28 NDA (-'A FCN FINISHED)
S 10135 GJ D28
& 10105 H38
1 10104 H40
-ENABLE REFRESH CNTR IRC 18
32 SLA (-A FCN SELD')'
RGTR 10176 C28
DDIDP1 B056 -IOU PAR OUT PAK 2
09
SHORT
08
S 10135 GJ F08 "SHORT"
& 10110 J30
+WAIT AEO 3,16,24
+WAIT QFM 19
24 TPF -2 PASS FCN
9 FTE -FTI [CLOCK]
17 BTP -END 1st PASS
25 MCM +MASTER CLEAR
-ENABLE STROBE 2-PASS REG A069 DC1U2P
2 ZER +LOGIC ZERO
9 ABD -FORCE BAD PARITY
2K 10160 A20
RGTR 10176 C18
2 -IOU PARITY OUT A052 DCIDP0
DDIDP3 B057 -IOU PAR OUT PAK 4
DDIDP2 A057 -IOU PAR OUT PAK 3
DDIDP0 A056 -IOU PAR OUT PAK 1
CONTROL DATA CANADA LTD
PRIORITY
FRC OR 2-PASS WAIT
TYPE:1DC0
C
A
23-APR-85
SHEET 30



9 FTA -FT1 [CLOCK]
RGTR 10176 D20
24 AWR -WRITE
32 W2P -2ND PASS WRITE
16 STB -START
5 BWR +BLOCK WRITE
10H101 E20
-WRITE BANK 0 B062
-WRITE BANK 1 A062
-WRITE BANK 2 A061
-WRITE BANK 3 B061
10117 E04
RGTR 10176 E34
+LOAD ANY BANK DC1VLB 21
-LOAD BANK SELECT 1 DC1VL1 21
-LOAD BANK SELECT 0 DC1VL0 21
CODER 10165 F32
XMAX-->Y
16 NSB +START 0-3
-BANK MUX SEL BIT 1 DC1VAB 21
-BANK MUX SEL BIT 1 GSA 17
10105 C26
-LOADS D ANY BANK DLY LAB 32
RGTR 10176 D30
RGTR 10176 D26
RGTR 10176 F38
B102 DC1VAD
B064
-BANK MUX SEL BIT 0 DC1VAA 21
GSB 17
B126 DC1VAA
A126 DC1VAB
9 FTG -FT1 [CLOCK]
RGTR 10176 D36
-BANK ENDING AET 7,15,17
-BANK ENDING ZAX 7,28
CONTROL DATA CANADA LTD
BANK SELECTS AND BANK WRITES
MODULE ASSY:210 PAK
TYPE: 1DC0
C
A
25-APR-85
SHEET 31




CONTROL DATA CANADA LTD	170 EXCHANGE REQ. 180 INTERRUPT TYPE: 1DC0		C	B
		06-MAR-86	SHEET 32	




CONTROL DATA CANADA LTD	DELAY FOR INPUT ERROR CHECKING MODULE ASSY:210 PAK TYPE: 1DC0		C	B
		06-MAR-86	SHEET 33	



CONTROL DATA CANADA LTD	PORT REGISTERS MODULE ASSY:210 PAK TYPE: 1DD0		C		B
		27-MAR-85		SHEET 02	




CONTROL DATA CANADA LTD	PORT MUX TYPE: 1DD0		C		B
		27-MAR-85	SHEET 03		




ECC SELECT	
3	DATA BITS <0&1>
2	PARITY LEFT,RIGHT
1	DATA BITS <0&1>
0	ECC BITS <0&1>


CONTROL DATA CANADA LTD	PORT MUX FANOUT 1 LEVEL PARITY CHECK CHECK BIT SELECT TYPE: 1DD0	C	B
		27-MAR-85	SHEET 04




ECC SELECT	
3	DATA BITS <0&1>
2	PARITY LEFT,RIGHT
1	DATA BITS <0&1>
0	ECC BITS <0&1>


CONTROL DATA CANADA LTD	PORT MUX FANOUT 1 LEVEL PARITY CHECK CHECK BIT SELECT TYPE: 1DD0		C	B
		27-MAR-85	SHEET 04A	


3 AAD -PORT MUX DATA
2K 10160 F28
2K 10160 E32
2K 10160 E28
2K 10160 F32
2K 10160 F26
2K 10160 B22
2K 10160 F30
2K 10160 A22
C RGTR 10176 A42
CD
PAK 1 GROUP A4
A085 DD15A4
PAK 1 GROUP A
B070 DD15A1
PAK 1 GROUP M
B084 DD15AM
PAK 1 GROUP A2
A070 DD15A2
-ECC BIT 0 AAG 4
-ECC BIT 1 AAH 4
DD25AL A059 PAK 2 LEFT GROUP A
DD35A1 B058 PAK 3 A1 GROUP B
DD45A1 B053 PAK 4 A1 GROUP C
DD25AR A060 PAK 2 RIGHT GROUP D
DD35A2 B060 PAK 3 A2 GROUP E
DD45A2 A061 PAK 4 A2 GROUP F
27 ACS -STROBE DATA HOLDING REG. [CLOCK]
PARITY, LEFT ACX 4
PARITY, LEFT A069
PARITY, LEFT A071
PARITY, LEFT ACW 4
CONTROL DATA CANADA LTD
ECC GENERATION
1st AND 2nd LEVEL
TYPE: 1DD0
C
28-MAR-85
SHEET 05
B



3 AAD -PORT MUX DATA
2K 10160 F28
2K 10160 E32
C RGTR 10176 A42
CD
PAK 1 GROUP A4
A085 DD15A4
PAK 1 GROUP A
B070 DD15A1
2K 10160 E28
2K 10160 F32
PAK 1 GROUP M
B084 DD15AM
PAK 1 GROUP A2
A070 DD15A2
2K 10160 F26
2K 10160 B22
-ECC BIT 0 AAG 4
2K 10160 F30
2K 10160 A22
-ECC BIT 1 AAH 4
DD25AL A059 PAK 2 LEFT GROUP A
DD35A1 B058 PAK 3 A1 GROUP B
DD45A1 B053 PAK 4 A1 GROUP C
DD25AR A060 PAK 2 RIGHT GROUP D
DD35A2 B060 PAK 3 A2 GROUP E
DD45A2 A061 PAK 4 A2 GROUP F
27 ACS -STROBE DATA HOLDING REG. [CLOCK]
PARITY, LEFT ACX 4
PARITY,LEFT A069
PARITY, RIGHT A071
PARITY, RIGHT ACW 4
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268191 ONLY.
CONTROL DATA CANADA LTD
ECC GENERATION 1ST AND 2ND LEVEL TYPE: 1DD0
C
B
27-MAR-85
SHEET 05A




CONTROL DATA CANADA LTD	DATA REGISTER BI-DIRECTIONAL BUS BANK 0 MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		27-MAR-85	SHEET 06	INST 01




CONTROL DATA CANADA LTD	DATA REGISTER BI-DIRECTIONAL BUS BANK 1 TYPE: 1DD0		C		B
		27-MAR-85	SHEET 07	INST 01	



CONTROL DATA CANADA LTD	DATA REGISTER BANK 2 BI-DIRECTIONAL BUS MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		27-MAR-85	SHEET 08	




CONTROL DATA CANADA LTD	DATA REGISTER BI-DIRECTIONAL BUS BANK 3 TYPE: 1DD0		C	B
		27-MAR-85	SHEET 09	INST 01





BANK MUX SELECT	
3	BANK 3 DATA (C0-15) C0,C1
2	BANK 2 DATA (C0-15) C0,C1
1	BANK 1 DATA (C0-15) C0,C1
0	BANK 0 DATA (C0-15) C0,C1

CONTROL DATA CANADA LTD	BANK SELECT MUX TYPE: 1DD0	C	B
		27-MAR-85	SHEET 10 INST 01





CONTROL DATA CANADA LTD	ARRAY DATA REGISTER ECC REGENERATION 1st LEVEL TYPE: 1DD0		C	B
		27-MAR-85	SHEET 11	INST 01


10 AAJ ARRAY DATA
RGTR 10175 J16
RGTR 10175 J18
RGTR 10175 J20
RGTR 10175 K20
RGTR 10176 C12
2K 10160 K14
2K 10160 K12
2K 10160 K16
2K 10160 J12
2K 10160 J14
2K 10160 K18
-A1 A045 DD1BA1
-A2 B039 DD1BA2
-A4 A040 DD1BA4
-M B043 DD1BAM
-LEFT B048 DD1BAL
AAL 12
-RIGHT A053 DD1BAR
AAM 12
25 ABX -FT1 [CLOCK]
ARRAY DATA AAK 12,13
-SLOW CHECK BITS C0,C1 SCB 12
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268191 ONLY.
CONTROL DATA CANADA LTD
ARRAY DATA REGISTER ECC REGENERATION 1ST LEVEL TYPE: 1DD0
C
27-MAR-85
SHEET 11A
8




CONTROL DATA CANADA LTD	SYNDROME GENERATION AND DECODE TYPE: 1DD0		C	B
		27-MAR-85	SHEET 12	



G1 10101 B16
DDSYN6 B049 * -SYNDROME BIT 6
DDSYN5 A050 * -SYNDROME BIT 5
DDSYN4 B047 * -SYNDROME BIT 4
G1 10101 D12
DDSYN3 B031 * =SYNDROME BIT 3
DDSYN2 A031 * -SYNDROME BIT 2
=1 10107 A10
& 10105 B10
11 AAL -LEFT
11 AAM -RIGHT
DD2BAL A106 -1ST LEVEL ECC 0
DD3BA1 B106 -1ST LEVEL ECC 1
DD4BA1 A108 -1ST LEVEL ECC 2
11 SCB -SLOW CHECK BITS C0,C1
27 ACV +LOGIC "0"
DD2BAR A111 1ST LEVEL ECC
DD3BA2 B110
DD4BA2 A110
11 AAK ARRAY DATA C0,C1
2K 10160 D38
2K 10160 D40
2K 10160 E38
2K 10160 E40
X->Y CODER 10162 E24
X->Y CODER 10162 D18
-CORRECTION BITS AAO 13
-SYNDROME BIT 1 AAP 13
-SYNDROME BIT 0 AAQ 13
-SYNDROME BIT 0 B108 DDSYN0
-SYNDROME BIT 1 B109 DDSYN1
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268191 ONLY.
* SHORT AND NO TERMINATOR
CONTROL DATA CANADA LTD
SYNDROME GENERATION AND DECODE
TYPE: 1DD0
C
27-MAR-85
SHEET 12A
8




CONTROL DATA CANADA LTD	ERROR CORRECTION MODULE ASSY:210 PAK TYPE: 1DD0	C		B
		27-MAR-85	SHEET 13	INST 01




CONTROL DATA CANADA LTD	SECOND PASS DATA SELECTOR BYTES 0L, 2L TYPE: 1DD0		C	B
		27-MAR-85	SHEET 14	INST 01




CONTROL DATA CANADA LTD	SECOND PASS DATA SELECTOR BYTES 4L,6L TYPE: 1DD0	C		B
		27-MAR-85	SHEET 15	INST 01




CONTROL DATA CANADA LTD	DATA IN HOLDING REG. EXCHANGE ADDRESS REG. FREE RUNNING COUNTER TYPE: 1DD0 MODULE ASSY:210PAK		C	B
		27-MAR-85	SHEET 16	




CONTROL DATA CANADA LTD	DATA IN HOLDING REG. EXCHANGE ADDRESS REG. FREE RUNNING COUNTER TYPE: 1DD0 MODULE ASSY:210PAK	C		B
		27-MAR-85	SHEET 16A	



CONTROL DATA CANADA LTD	OUTPUT DATA MUX TYPE: 1DD0	C		B
		27-MAR-85	SHEET 17	INST 01





CONTROL DATA CANADA LTD	FANOUT TO CPUs' DATA OUT PARITY CHECK 1ST LEVEL TYPE: 1DD0		C	B
		29-MAR-85	SHEET 18	INST 01




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268191 ONLY.

CONTROL DATA CANADA LTD	FANOUT TO CPU'S DATA OUT PARITY CHECK 1ST LEVEL TYPE: 1DD0		C	8
		27-MAR-85	SHEET 18A	



IOU ADU DATA SELECT
3 SYNDROME & CHECK BITS
2 CMC DATA OUT BITS (1&0)
1 IOU DATA 48-49 BITS (1&0)
0 IOU DATA 48-49 BITS (1&0)
17 ABD -CMC DATA OUT
22 ABO -RESPONSE TO IOU
13 AAU -SYNDROME BITS
27 ADC -READ CHECK/ SYNDROME
27 ADE -SEL SYNDROME
13 AAS -CHECK BITS
22 IP1 -IOU PARITY IN
CM1M48 B006 -IOU DATA 48
CM1M49 B003 -IOU DATA 49
CM1M50 A006 -IOU DATA 50
CM1M51 A003 -IOU DATA 51
27 ACR -FT1 (CLOCK)
13 DT2 -ARRAY DATA @ T2
27 EPC -ENABLE PARITY CHECK
RGTR 10173 C02
2CD C02
1CD
X->Y MUX 10174 F02
2K 10160 D28
10101 D02
2K 10160 F16
2K 10160 F20
RGTR 10176 A20
10113 F18
RGTR 10173 H14
RGTR 10173 G14
RGTR 10173 F14
RGTR 10173 E14
2CD E14
A047
-DATA TO ADU ABE 20-22
-IOU DATA IN ADB 31
+DATA OUT P.E. 0 A055 DD1JEA
+DATA OUT P.E. 1 B055 DD1JEB
1 CMC DATA OUT (2-15)
0 IOU DATA IN BITS (0-3)
CONTROL DATA CANADA LTD
IOU ADU DATA SELECT
IOU ADU ADDRESS F/O
TYPE=1DD0
C
B
27-MAR-85
SHEET 19
INST 01




CONTROL DATA CANADA LTD	IOU ADU BUFFER NIBBLES A AND B TYPE: 1DD0		C	B
		29-MAR-85	SHEET 20	INST 01




CONTROL DATA CANADA LTD	IOU ADU BUFFER NIBBLES C AND D MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		29-MAR-85	SHEET 21	INST 01




CONTROL DATA CANADA LTD	ADU PARITY WRITE NIBBLES A,B,C,D MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		27-MAR-85	SHEET 22	INST 01



CONTROL DATA CANADA LTD	ADU PARITY WRITE NIBBLES A,B,C,D MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		27-MAR-85	SHEET 22A	




CONTROL DATA CANADA LTD	ADU ADDRESS FORMATION MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		28-MAR-85	SHEET 23	INST 01




BANK SELECT	
3	BANK 0
2	BANK 1
1	BANK 2
0	BANK 3

CONTROL DATA CANADA LTD	BANK HOLDING REGISTERS FOR ADU TAGS MODULE ASSY:210 PAK TYPE: 1DD0	C	B
		28-MAR-85	SHEET 24 INST 01




CONTROL DATA CANADA LTD	PARTIAL WRITE CONTROL EXCH. ADDRESS AND FRC CONTROL MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		28-MAR-85	SHEET 25	INST 01



* SHORT AND NO TERMINATOR


CONTROL DATA CANADA LTD	BANK ENABLE AND LOAD BANK MUX SELECT MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		28-MAR-85	SHEET 26	INST 01




* SHORT AND NO TERMINATOR

NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268191 ONLY.


CONTROL DATA CANADA LTD	BANK ENABLE AND LOAD BANK MUX SELECT MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		28-MAR-85	SHEET 26A	




CONTROL DATA CANADA LTD	MISC CONTROL MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		28-MAR-85	SHEET 27	INST 01




CONTROL DATA CANADA LTD	CPU PARITY IN,OUT MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		28-MAR-85	SHEET 28	



PORT PARITY MUX
3 CPU PARITY BYTES 4L,6L
2 ADU PARITY BITS
1 CPU PARITY BYTES 0L,2L
0 ADU PARITY BITS
DPZERO A038 +LEFT HAND PAK
27 SCP -SELECT CPU
23 ADP -ADU PARITY
DDCP4L A039 PARITY, BYTE 4L
DDCP6L B037 PARITY, BYTE 6L
2 AAC -LOAD CPU PORT [CLOCK]
27 ACP -LOAD CPU PORT [CLOCK]
C RGTR 10176 B04
DFWMP0 A015 -CPU DATA P0
DFWMP2 A011 -CPU DATA P2
CD
2K 10160 E08
2K 10160 E06
2K 10160 F06
2K 10160 F08
0L
2L
4L
6L
2 A
2 B
2 C
2 D
X->Y
G3
G0
MUX 10174 F12
MUX 10174 E12
P0
P1
P2
P3
-PORT MUX PARITY PMP
10113 E10
-PARITY,BYTE 0R A037 DDCP0R
-PARITY,BYTE 2R B036 DDCP2R
B035 *USED
A036 *USED
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268191 ONLY.
DD1IP0 B032 -HALF BYTE PARITY OUT "SHORT"
DP4IP0 B029 -HALF BYTE PARITY OUT "SHORT"
=1 10107 A10
-BYTE 0 PARITY OUT A033 DDCDP0
CONTROL DATA CANADA LTD
CPU PARITY IN,OUT
MODULE ASSY:210 PAK
TYPE: 1DD0
C
B
27-MAR-85
SHEET 28A




CONTROL DATA CANADA LTD	ADU PARITY P0,P1 MODULE ASSY:210 PAK TYPE: 1DD0		C	--------	B
		28-MAR-85		SHEET 29	INST 01



CONTROL DATA CANADA LTD	ADU PARITY P2, P3 TYPE: 1DD0		C	B
		28-MAR-85	SHEET 30	INST 01



CONTROL DATA CANADA LTD	IOU PORT REGISTER BITS 48 TO 51 MODULE ASSY:210 PAK TYPE: 1DD0		C	B
		28-MAR-85	SHEET 31	INST 01




NOTE 1:
10110 SECTIONS MAY NOT BE RE-ARRANGED.

NOTE 2:
TOTAL FOIL LENGTHS FROM 10121 TO CONNECTOR PINS MUST BE THE SAME FOR ALL PATHS.

NOTE 3:
CRYSTALS MUST BE POSITIONED SO THEY CAN LIE FLAT.

NOTE 4:
ALL THREE CRYSTALS MUST BE TERMINATED.

CONTROL DATA CANADA LTD	1DP0 MASTER OSCILLATOR FIRST STAGE FANOUT		C	B
		25-APR-85	SHEET 02	




NOTE:
10110 SECTIONS MAY NOT BE RE-ARRANGED.


NOTE: TOTAL FOIL LENGTHS FROM 10121 TO CONNECTOR PINS MUST BE THE SAME FOR ALL PATHS.

NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.

CONTROL DATA CANADA LTD	1DP0 MASTER OSCILLATOR FIRST STAGE FANOUT	C		B
		25-APR-85	SHEET 02A	




CONTROL DATA CANADA LTD	1DP0 T1 2ND STAGE TUNNING AND FANOUT TO CMC		C	B
		24-APR-85	SHEET 03	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.

CONTROL DATA CANADA LTD	1DP0 T1 2ND STAGE TUNNING AND FANOUT TO CMC	C	B
		25-APR-85	SHEET 03A




NOTE 1:
DO NOT TERMINATE PIN 2 OF DL17S OR DL10'S' DO TERMINATE PIN 7 OF DL17S AND DL10'S.'
NOTE 2:
FOIL LENGTHS FOR AND OUTPUTS OF DL10S' AND OUTPUTS OF JUMPER BOXES MUST BE AS SHORT AS POSSIBLE.
NOTE 3:
PATHS FROM 10101 THROUGH DL17S TO ' 10121 MUST ALL BE THE SAME LENGTH, WITHIN ONE INCH.
NOTE 4:
DO NOT USE PADS 1,8 AND 16 IN JUMPER BOXES.


CONTROL DATA CANADA LTD	1DP0 T2 2ND TUNING AND FANOUT TO CMC	C	B
		24-APR-85	SHEET 04




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.


CONTROL DATA CANADA LTD	1DP0 T2 2ND TUNING AND FANOUT TO CMC		C	B
		25-APR-85	SHEET 04A	


4 ABW -T2
3 ACW -T1
DC1H2P A045 -2ND PASS
10110 C24
10101 B24
10101 A24
10101 A16
10101 A18
10101 B20
10101 B22
10101 A20
10101 A22
-RAW T2 B071
-RAW T2 A071
-RAW T2 A070
-RAW T2 B070
-RAW T2 B072 T2B6E
-RAW T2 A072 T2B6F
-RAW T2 A069 T2B6G
-RAW T2 B069 T2B6H
A050
B049
B048
A048
-RAW T1 B057 T1B5A
-RAW T1 A057 T1B5B
-RAW T1 B052 T1B5C
-RAW T1 A053 T1B5D
-RAW T1 B061 T1B5E
-RAW T1 A061 T1B5F
-RAW T1 A060 T1B5G
-RAW T1 B060 T1B5H
-RAW T1 B062 T1B5I
-RAW T1 A062 T1B5J
-RAW T1 A059 T1B5K
-RAW T1 B059 T1B5L
-RAW T1 B067 T1B5M
-RAW T1 A067 T1B5N
-RAW T1 A064 T1B5O
-RAW T1 B064 T1B5P
-RAW T1 B068 T1B5Q
-RAW T1 A068
-RAW T1 A063 T1B5S
-RAW T1 B063
NOTES:
* TOTAL FOIL LENGTHS FROM OUTPUTS OF 10110 TO CONNECTORS PINS MUST BE EQUAL WITHIN ONE INCH.
** SHORT AND DO NOT TERMINATE.
CONTROL DATA CANADA LTD
1DP0
T1 2ND STAGE TUNING AND FANOUT TO CMC
C
24-APR-85
SHEET 05
B


6 AAC -FT1
B099 * + DUAL CPUS INSTL'D'
6 AAB -FT1
16CNTR 10136 D12
16CNTR 10136 C12
C RGTR 10176 A04
C RGTR 10176 A22
-1 MHZ ENABLE B016
-1 MHZ ENABLE A017
-1 MHZ ENABLE A020
-1 MHZ ENABLE A015
-1 MHZ ENABLE B013
-1 MHZ ENABLE A013
-DUAL CPUS' ABV 8,9
-1 MHZ ENABLE A116
-1 MHZ ENABLE A118
-1 MHZ ENABLE B022
-1 MHZ ENABLE B025
-1 MHZ ENABLE B026
-1 MHZ ENABLE B020
-CPU 0 OI BIT 28 ABW 8
B041 * +CONCURRENT A170
A046 (PAK TEST)
+LOGIC ZERO AAL 2-4,8
B046 * +A170 OPTION INSTALLED
-CPU OI BIT 29 AAM 8
B051 PMF INSTALLED CPU 0
-CPU OI BIT 31 AAN 8
B045 +SECDED CS CPU 0
-CPU 0 OI BIT 30 CP1 8
CR01 (B43) +LOGIC ZERO A125 DPLG0A
CR02 (A43) +LOGIC ZERO B125 DPLG0B
(FOR SERIAL NUMBER)
A037 * +CONCURRENT A170
B040 * +A170 OPT CPU 1
A033 * +SECDED CS CPU 1
A041 +PMF INSTLD CPU 1'
+LOGIC ZERO LAA 9
-CPU 1 O.I. BITS 28-31 ABX 9
* DO NOT TERMINATE
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192
CONTROL DATA CANADA LTD
1DP0
1 MHz CLOCK ENABLE
CPU OPTION INSTALLED
C
B
25-APR-85
SHEET 05A




CONTROL DATA CANADA LTD	1DP0 1 MHz CLOCK ENABLE CPU OPTION INSTALLED		C	B
		24-APR-85	SHEET 06	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.

CONTROL DATA CANADA LTD	1DP0 BIT SERIAL MAC INTERFACE	C		B
		25-APR-85	SHEET 06A	




CONTROL DATA CANADA LTD	1DP0 BIT SERIAL MAC INTERFACE		C	B
		25-APR-85	SHEET 07	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.

CONTROL DATA CANADA LTD	1DP0 BIT-SERIAL SHIFT REG. CPU 0 EC REGISTER		C	B
		25-APR-85	SHEET 07A	





CONTROL DATA CANADA LTD	1DP0 BIT-SERIAL SHIFT REG. CPU 0 EC REGISTER		C	B
		24-APR-85	SHEET 08	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.


CONTROL DATA CANADA LTD	1DP0 MAC READ MUX		C	B
		26-APR-85	SHEET 08A	


8 BAA -DATA MUX SEL
8 BAB -DATA MUX SEL
8 BAC -DATA MUX SEL
8 AAI -EC REG
12 CAL -M1 EC
7 AAF -ENBL MUX
8 CAN -OSC SEL
REG
6 AAL +LOGIC "0"
6 ACX
6 CP1 -CPU 0 OI BIT 30
6 ABY -DUAL CPU INSTAL LED
6 AAM -CPU OI BIT 29
6 AAN -CPU OI BIT 31
-READ DATA AAK 11
MUX 10164 F10
MUX 10164 E22
MUX 10164 E16
MUX 10164 E18
MUX 10164 D20
MUX 10164 E20
MUX 10164 D22
MUX 10164 D16
X->Y
G7
GO
15 0
15 4
15 1
15 5
15 2
15 6
15 3
15 7
CONTROL DATA CANADA LTD
1DP0
MAC READ MUX
C
B
24-APR-85
SHEET 09


7 BAA -DATA MUX SEL
7 BAB -DATA MUX SEL
7 BAC -DATA MUX SEL
10 IAA -EC REG
5 LAA +LOGIC "0"
6 FAA -ENBL MUX
5 ABX -CPU 1 IO REG
12 VCR -VC REG
5 ABV
X->Y
G7
GO
MUX 10164 F26
MUX 10164 F28
MUX 10164 F30
MUX 10164 D26
MUX 10164 D28
MUX 10164 D30
MUX 10164 E26
MUX 10164 E28
-READ DATA KAA 10
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.
CONTROL DATA CANADA LTD
1DP0
MAC READ MUX
CPU-1 EC REG,OI,VC REG
C
B
26-APR-85
SHEET 09A




CONTROL DATA CANADA LTD	1DP0 MAC READ MUX CPU-1 EC REG, OI, VC REG		C	B
		24-APR-85	SHEET 10	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.

CONTROL DATA CANADA LTD	1DP0 BIT-SERIAL SHIFT REG. CPU EC REGISTER		C	B
		26-APR-85	SHEET 10A	




CONTROL DATA CANADA LTD	1DP0 BIT-SERIAL SHIFT REG. CPU EC REGISTER		C	B
		24-APR-85	SHEET 11	




NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.

CONTROL DATA CANADA LTD	1DP0 CLOCK FREQUENCY SELECT		C	B
		26-APR-85	SHEET 11A	




CONTROL DATA CANADA LTD	1DP0 CLOCK FREQUENCY SELECT		C	B
		24-APR-85	SHEET 12	





NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.

CONTROL DATA CANADA LTD	1DP0 VOLTAGE MARGIN CONTROL REGISTER		C	B
		26-APR-85	SHEET 12A	



CONTROL DATA CANADA LTD	1DP0 VOLTAGE MARGIN CONTROL REGISTER		C	B
		24-APR-85	SHEET 13	


12 VCR
X/Y 10125 C38
X/Y 10125 C40
X/Y 10125 C42
X/Y 10125 D42
D42
-L29VR
-L25VR
CA3083 B38
CA3083 B40
CA3083 B42
CA3083 B30
-5.2V
-5.2
+5V
C053 .1UF
C051 .1UF
C052 .1UF
C050
C054 0.1UF
C055
C056
C039 C037 C047 C036 C038
C043 C041 C048 C040 C042
C046 C044 C049 C045
A073 +5 VOLTS
B073 +5 VOLTS
B111
B108
A104
A106
B109
B106
A115
B104
A112
B113
A103
B103
B112
A109
B105
A108
NOTE: THIS DRAWING IS APPLICABLE TO PWB 19268192.
CONTROL DATA CANADA LTD
VOLTAGE MARGIN
MODULE ASSY: 210 PAK
TYPE: 1DP0
C
B
26-APR-85
SHEET 13A


13 VCR -V.C. REG.BITS
CA3083 B38
CA3083 B40
CA3083 B42
CA3083 A32
NOTE: 1
+5V
X/Y 10125 C38
X/Y 10125 C40
X/Y 10125 C42
X/Y 10125 D42
D42
-1.29VR
-1.25VR
-5.2V CPU-1 (PLUS) B111
-2.2V CPU-0 (PLUS) B108
-2.2V CPU-0 (MINUS) A104
-2.2V MEM/IOU (MINUS) A106
-2.2V MEM/IOU (PLUS) B109
-5.2V MEM (MINUS) B106
-5.2V CPU-1 (MINUS) A115
-5.2V CPU-0 (MINUS) B104
-5.2V CPU-0 (PLUS) A112
-5.2V IOU (MINUS) B113
+5V MEM/IOU (MINUS) B112
-5.2V IOU (PLUS) A109
-5.2V MEM (PLUS) B105
-2.2V CPU-1 (PLUS) A103
+5V MEM/IOU (PLUS) A108
-2.2V CPU-1 (MINUS) B103
C039 C037 C047 C036 C038
C043 C041 C048 C040 C042
C046 C044 C049 C045 C055
C056
C053 0.1UF
C051 0.1UF
C054 0.1UF
C052 0.1UF
-5.2V
C050
A073 +5 VOLTS
B073 +5 VOLTS
+5V
NOTE: 1
EACH LINE FROM THE CA3083 TO A CONNECTOR PIN MUST BE CONNECTED TO GROUND VIA A 0.1UF CAPACITOR P/N 19115401
NOTE 2:
THE ABOVE PINS GO TO THE SWITCHING POWER SUPPLY CONTROL.
CONTROL DATA CANADA LTD
1DP0
VOLTAGE MARGIN DRIVERS
C
24-APR-85
SHEET 14
B

SHEET REVISION STATUS																								REVISION RECORD					
24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	09	08	07	06	05	04	03	02	REV	ECØ	DESCRIPTIØN	DRFT	DATE	CHKD	APP
01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01	01		INITIAL RELEASE	HN	3-30	NZ	
A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A	A		CLASS A RELEASE	DF	1-85	NZ	

CØNNECTØR PIN ASSIGNMENTS

SIGNAL NAME	B PIN NØ	A PIN NØ	SIGNAL NAME
-5.2 V	B1	A1	-5.2 V
-5.2 V	B2	A2	-5.2 V
BØARD SEL	B3	A3	GND
T	B4	A4	GND
GND	B5	A5	GND
T	B6	A6	T
-2.2 V	B7	A7	-2.2 V
-2.2 V	B8	A8	-2.2 V
T	B9	A9	T
DATA BIT 0	B10	A10	T
GND	B11	A11	GND
BIT 1	B12	A12	T
BIT 2	B13	A13	T
BIT 3	B14	A14	T
GND	B15	A15	GND
BIT 4	B16	A16	T
BIT 5	B17	A17	T
BIT 6	B18	A18	T
GND	B19	A19	GND
BIT 7	B20	A20	T
BIT 8	B21	A21	T
BIT 9	B22	A22	T
GND	B23	A23	GND
BIT 10	B24	A24	T
BIT 11	B25	A25	T
BIT 12	B26	A26	T
GND	B27	A27	GND
BIT 13	B28	A28	T
BIT 14	B29	A29	T
BIT 15	B30	A30	T
GND	B31	A31	GND
BIT 16	B32	A32	T
BIT 17	B33	A33	T
BIT 18	B34	A34	T
GND	B35	A35	GND
BIT 19	B36	A36	T
BIT 20	B37	A37	T
BIT 21	B38	A38	T
GND	B39	A39	GND
BIT 22	B40	A40	T
BIT 23	B41	A41	T
BIT 24	B42	A42	T
GND	B43	A43	GND
BIT 25	B44	A44	T
BIT 26	B45	A45	T
BIT 27	B46	A46	T
GND	B47	A47	GND
BIT 28	B48	A48	T
BIT 29	B49	A49	T
BIT 30	B50	A50	T
GND	B51	A51	GND
BIT 31	B52	A52	T
BIT 32	B53	A53	T
BIT 33	B54	A54	T
GND	B55	A55	GND
BIT 34	B56	A56	T
BIT 35	B57	A57	T
BIT 36	B58	A58	T
GND	B59	A59	GND
BIT 37	B60	A60	T
+5 V	B61	A61	+5 V
BIT 38	B62	A62	T
GND	B63	A63	GND
BIT 39	B64	A64	T
NC	B65	A65	NC

SIGNAL NAME	B PIN NØ	A PIN NØ	SIGNAL NAME
NC	B66	A66	NC
BIT 40	B67	A67	T
GND	B68	A68	GND
BIT 41	B69	A69	T
+5 V	B70	A70	+5 V
BIT 42	B71	A71	T
GND	B72	A72	GND
BIT 43	B73	A73	T
BIT 44	B74	A74	T
BIT 45	B75	A75	T
GND	B76	A76	GND
BIT 46	B77	A77	T
BIT 47	B78	A78	T
BIT 48	B79	A79	T
GND	B80	A80	GND
BIT 49	B81	A81	T
BIT 50	B82	A82	T
BIT 51	B83	A83	T
GND	B84	A84	GND
BIT 52	B85	A85	T
BIT 53	B86	A86	T
BIT 54	B87	A87	T
GND	B88	A88	GND
BIT 55	B89	A89	T
BIT 56	B90	A90	T
BIT 57	B91	A91	T
GND	B92	A92	GND
BIT 58	B93	A93	T
BIT 59	B94	A94	T
BIT 60	B95	A95	T
GND	B96	A96	GND
BIT 61	B97	A97	T
BIT 62	B98	A98	T
BIT 63	B99	A99	T
GND	B100	A100	GND
BIT 64	B101	A101	T
BIT 65	B102	A102	T
BIT 66	B103	A103	T
GND	B104	A104	GND
BIT 67	B105	A105	T
BIT 68	B106	A106	T
BIT 69	B107	A107	T
GND	B108	A108	GND
BIT 70	B109	A109	T
BIT 71	B110	A110	T
A1/A10	B111	A111	A0/A9
GND	B112	A112	GND
A3/A12	B113	A113	A2/A11
A5/A14	B114	A114	A4/A13
T	B115	A115	A8/A17
GND	B116	A116	GND
REFRESH	B117	A117	A6/A15
T	B118	A118	WRITE
RAS	B119	A119	CAS
GND	B120	A120	GND
A18	B121	A121	DATA GATE
T	B122	A122	A7/A16
-2.2 V	B123	A123	-2.2 V
-2.2 V	B124	A124	-2.2 V
T	B125	A125	T
GND	B126	A126	GND
T	B127	A127	T
T	B128	A128	T
-5.2 V	B129	A129	-5.2 V
-5.2 V	B130	A130	-5.2 V

NØTES:

1. T DESIGNATES A CØNNECTIØN TØ A 100 Ω TERMINATIØN TØ -2.2 V.
2. NØ ECL TERMINATIØNS SHØWN.
3. UNUSED GATES (DESIGNATED BY EITHER A SINGLE INPUT ØR ØUTPUT): A42-5, B42-14, B40-2, B40-3.
4. UNUSED BUT CØMMITTED GATES (DESIGNATED BY EITHER A SINGLE INPUT ØR ØUTPUT): D44-2, D44-3, E44-2, E44-3, C44-10.
5. A18, HIGHEST ØRDER ADRS BIT SELECTS RASØ. I ØUTPUT (SEE SHEET 4), MUST BE STABLE THE ENTIRE MEMØRY CYCLE.

DETAILED LISTS

DØ NØT SCALE DRAWING

MATERIAL

FINISH

	ARDEN HILLS ØPERATIØN
FIRST USED ØN	CRM3
DRN	H NØRD 3-30
CHKR	N ZAK 3-30
ENGR	
MFG	
APPR	


TITLE

SCHEMATIC
524K X 72
3HBH, M3CR MEMØRY MØDULE

CAGE IDENT	DRAWING NØ
34010 D	24670814

SCALE


SHEET 02





NOTE:

1. ADRS BITS A0/A9, A1/A10, A2/A11 AND A3/A12 ARE NOT TERMINATED.

DEVELOPMENT DIVISION	LEVEL 4 DIAGRAM SCHEMATIC 524K X 72 3HEH, M3CR MEMORY MODULE	2467C814	A
		CM 4.3-01	03


A114
ADRS BIT A4/A13
B114
A5/A14
A11T
A6/A15
A122
ADRS BIT A7/A16
NC
10101
A40
TP33
TP32
TP30
TP29
ECL/TTL
10125
K40
J40
H40
G40
F40
E40
D40
C40
+5 V
-5.2 V
-1.25VR
TP4
TP3
TP1
TP2
TO PAGES 07-24
NOTE:
1. ADRS BITS A4/A13, A5/A14, A6/A15 AND A7/A16 ARE NOT TERMINATED.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH, MSCR MEMORY MODULE
DEVELOPMENT DIVISION
24670814
A
CM 4.3-02
04


NC
NC
10101
A42
NC
NC
NC
NC
NC
NC
TP38
TP35
TP34
A119 -CAS
A118 -WRITE
A115 AB/A17
FROM PAGE 06
RAS1
FROM PAGE 06
RAS0
+5 V
-5.2 V
-1.29VR
ECL/TTL
10125
K42
J42
H42
G42
F42
E42
D42
C42
TP13
TP8
TP14
TP15
[RAS0]K42
[CAS]K42
[WRITE]K42
[AB/A17]K42
[RAS0]J42
[CAS]J42
[WRITE]J42
[AB/A17]J42
[RAS0]H42
[CAS]H42
[WRITE]H42
[AB/A17]H42
[RAS0]G42
[CAS]G42
[WRITE]G42
[AB/A17]G42
[RAS1]F42
[CAS]F42
[WRITE]F42
[AB/A17]F42
[RAS1]E42
[CAS]E42
[WRITE]E42
[AB/A17]E42
[RAS1]D42
[CAS]D42
[WRITE]D42
[AB/A17]D42
[RAS1]C42
[CAS]C42
[WRITE]C42
[AB/A17]C42
TO PAGES 07-24
NOTE:
1. ADRS BIT AB/A17 IS NOT TERMINATED.
2. THE CAS INPUT, (A119) AND THE WRITE INPUT, (A118) ARE NOT TERMINATED.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH, MOR MEMORY MODULE
DEVELOPMENT DIVISION
24670814
A
CM 4.3-03
05




NOTES:

1.

B12I(A18) VOLTAGE	RAS ENABLED
-1.8 (''1'')	RAS 0
-0.8 (''-0'')	RAS 1

2. ADRS BIT A18 (B12I), REFRESH (B11T), AND RAS (B11I) ARE NOT TERMINATED.
3. BOARD SELECT (B03) AND DATA GATE (A12I) ARE TERMINATED.


DEVELOPMENT DIVISION	LEVEL 4 DIAGRAM SCHEMATIC 524K X 72 3HEH, M3CR MEMORY MODULE	2467D814	A
		CM 4.3-04	06



NOTES:

1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS B14, B13, B12, AND B10 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0.
   CDEF ROWS USE RAS 1.


DEVELOPMENT DIVISION	LEVEL 4 DIAGRAM SCHEMATIC 524K X 72 3MBH. M3CR MEMORY MODULE	2467D814	A
		CM 4.3-05	07



NOTES:

1. ⚠ ALSO USED FOR REFRESH.
2. CONNECTOR PINS B20, B18, B17, AND B16 ARE NOT TERMINATED.
3. CHUK ROWS USE RAS 0
   CDEF ROWS USE RAS 1.


CDC	LEVEL 4 DIAGRAM SCHEMATIC 524K X 72 3HBH, M3CR MEMORY MODULE	24670814	A
DEVELOPMENT DIVISION		CM 4.3-06	08





NOTES:


1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS B25, B24, B22 AND B21 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
   CDEF ROWS USE RAS 1.


CDC	LEVEL 4 DIAGRAM SCHEMATIC 524K X 72 3HBH, MSCR MEMORY MODULE	24670814	A
DEVELOPMENT DIVISION		CM 4.3-07	09



+5 V
MEMORY 262KX1 C08
MEMORY 262KX1 H08
MEMORY 262KX1 D08
MEMORY 262KX1 K08
MEMORY 262KX1 F08
MEMORY 262KX1 J08
MEMORY 262KX1 E08
A262144 A0000000
131,072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
▷MEM 262K X 1 G08
DATA OUT
DATA IN
FROM PAGE 06 [DATA GATE]B38-4
ECL/TTL 10124 B08
ECL/TTL 10125 A08
-1.29VR1
-5.2 V
DATA BIT 15
DATA BIT 14
DATA BIT 13
DATA BIT 12
B30
B29
B28
B26
NOTES:
1. ALS08 USED FOR REFRESH.
2. CONNECTOR PINS B30, B29, B28, AND B26 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH, MOCR MEMORY MODULE
DEVELOPMENT DIVISION
Z4670814
A
CM 4.3-08
10


+5 V
X+Y
131,072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
A262144
A000000
[RAS 0]G42
[CAS]G42
[WRITE]G42
C1
C2
C3
F
▷MEM
262K X 1
G10
DATA OUT
DATA IN
MEMORY
262KX1
C10
H10
D10
K10
F10
J10
E10
[DATA GATE]B38-13
TTL/ECL
10124
B10
NC
-5.2 V
DATA BIT 19
DATA BIT 18
DATA BIT 17
DATA BIT 16
B36
B34
B33
B32
ECL/TTL
10125
A10
-1.29VR
T
NOTES:
1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS B36, B34, B33, AND B32 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH, MOCR MEMORY MODULE
DEVELOPMENT DIVISION
2467D814
A
CM 4.3-09
11


+5 V
A262144
A0000000
131,072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
MEMORY 262KX1 C12
MEMORY 262KX1 H12
MEMORY 262KX1 D12
MEMORY 262KX1 K12
MEMORY 262KX1 F12
MEMORY 262KX1 J12
MEMORY 262KX1 E12
▷MEM 262K X 1 G12
DATA OUT
DATA IN
[DATA GATE]B38-5
10124 B12
DATA BIT 23
DATA BIT 22
DATA BIT 21
DATA BIT 20
B41
B40
B39
B37
10125 A12
-1.25V
-5.2 V
NC
T
NOTES:
1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS B41, B40, B39, AND B37 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH, W3CR MEMORY MODULE
DEVELOPMENT DIVISION
2467D814
A
CM 4.3-10
12


+5 V
MEMORY 262KX1 C14
MEMORY 262KX1 H14
MEMORY 262KX1 D14
MEMORY 262KX1 K14
MEMORY 262KX1 F14
MEMORY 262KX1 J14
MEMORY 262KX1 E14
ECL/TTL 10125 A14
ECL/TTL 10124 B14
-5.2 V
DATA IN
DATA OUT
[DATA GATE]B38-12
DATA BIT 27
DATA BIT 26
DATA BIT 25
DATA BIT 24
B46
B45
B44
B42
NC
T
NOTES:
1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS B46, B45, B44, AND B42 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
SHEN. MSCR MEMORY MODULE
DEVELOPMENT DIVISION
24670814
A
CM 4.3-11
13



+5 V
X+Y
131,072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
A262144
A0000000
MEMORY
262KX1
C16
D16
H16
K16
F16
J16
E16
MEM
262K X 1
G16
AC30
DATA ØUT
DATA IN
ECL/TTL
10125
A16
-1.29V0
-5.2 V
TTL/ECL
10124
B16
DATA BIT 31
DATA BIT 30
DATA BIT 29
DATA BIT 28
B52
B50
B49
B48
NC
T
NOTES:
1. ALS20 USED FOR REFRESH.
2. CONNECTOR PINS B52, B50, B49, AND B48 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH. MSCR MEMORY MODULE
DEVELOPMENT DIVISION
2467D814
A
CM 4.3-12
14





NØTES:


1. ALSØ USED FØR REFRESH.
2. CØNNECTØR PINS B57, B56, B54, AND B53 ARE NØT TERMINATED.
3. GHJK RØWS USE RAS 0
   CDEF RØWS USE RAS 1.


DIGITAL EQUIPMENT CORPORATION	LEVEL 4 DIAGRAM SCHEMATIC 524K X 72 3HEH, MSCR MEMORY MODULE	CODE IDENT NUMBER 24670814	REV A
DEVELOPMENT DIVISION		SHEET CM 4.3-13	PAGE 15



+5 V
X÷Y
131,072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
A262144
A000000
P-MEM
262K X 1
A20
AC30
A2
DATA OUT
DATA IN
EQL/TTL
10125
A20
-1.25V
-5.2 V
MEMORY
262KX1
C20
H20
D20
K20
F20
J20
E20
TTL/ECL
10124
B20
DATA BIT 39
DATA BIT 38
DATA BIT 37
DATA BIT 36
B64
B62
B60
B58
NC
FROM PAGE 06 [DATA GATE]B38-5
NOTES:
1. ALS8 USED FOR REFRESH.
2. CONNECTOR PINS B64, B62, B60, AND B58 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HBH, MSCR MEMORY MODULE
DEVELOPMENT DIVISION
2467C814
A
CM 4.3-14
16



+5 V
A262144
A000000
131.072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
▷MEM
262K X 1
U22
DATA OUT
DATA IN
[RAS 0]G42
[CAS]G42
[WRITE]G42
MEMORY
262KX1
C22
H22
D22
K22
F22
J22
E22
B22
A22
EQ/TTL
10125
10124
-5.2 V
[DATA GATE]B38-12
DATA BIT 43
DATA BIT 42
DATA BIT 41
DATA BIT 40
BT3
BT1
B69
B67
NC
T
NOTES:
1. ALSØ USED FØR REFRESH.
2. CØNNECTØR PINS BT3, BT1, B69, AND B67 ARE NØT TERMINATED.
3. GHJK RØWS USE RAS 0
CDEF RØWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH, MSCR MEMØRY MØDULE
DEVELOPMENT DIVISION
246T0814
A
CM 4.3-15
17



+5 V
X+Y
131,072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
A262144
A000000
C1
C2
C3
F
P MEM
262K X 1
G24
DATA OUT
DATA IN
MEMORY
262KX1
C24
D24
H24
K24
F24
J24
E24
EQL/TTL
10125
A24
-5.2 V
TTL/ECL
10124
B24
NC
DATA BIT 47
DATA BIT 46
DATA BIT 45
DATA BIT 44
BT8
BT7
BT5
BT4
[DATA GATE]B38-4
T
NOTES:
1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS BT8, BT7, BT5, AND BT4 ARE NOT TERMINATED.
3. CHUK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH, M3CR MEMORY MODULE
DEVELOPMENT DIVISION
2467D814
A
CM 4.3-16
18



+5 V
MEMORY 262KX1 C26
MEMORY 262KX1 H26
MEMORY 262KX1 D26
MEMORY 262KX1 K26
MEMORY 262KX1 F26
MEMORY 262KX1 J26
MEMORY 262KX1 E26
MEM 262K X 1 G26
ECL/TTL 10125 A26
ECL/TTL 10124 B26
-5.2 V
DATA OUT
DATA IN
[DATA GATE]B38-13
DATA BIT 51
DATA BIT 50
DATA BIT 49
DATA BIT 48
B83
B82
B81
B79
NC
NOTES:
1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS B83, B82, B81, AND B79 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HBH, MOCR MEMORY MODULE
DEVELOPMENT DIVISION
2467D814
A
CM 4.3-17
19


+5 V
X+Y
131,072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
A262144
A0000000
MEMORY 262KX1 C28
MEMORY 262KX1 H28
MEMORY 262KX1 D28
MEMORY 262KX1 K28
MEMORY 262KX1 F28
MEMORY 262KX1 J28
MEMORY 262KX1 E28
MEM 262K X 1 G28
ECL/TTL 10125 A28
ECL/TTL 10124 B28
-5.2 V
-1.29V
DATA OUT
DATA IN
[DATA GATE]B38-5
DATA BIT 55
DATA BIT 54
DATA BIT 53
DATA BIT 52
NC
NOTES:
1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS B83, B87, B86, AND B85 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH. MSCR MEMORY MODULE
DEVELOPMENT DIVISION
24670814
A
CM 4.3-18
20


+5 V
X-Y
A262144
A000000
131.072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
▷MEM
262K X 1
G30
DATA OUT
DATA IN
MEMORY
262KX1
C30
H30
D30
K30
F30
J30
E30
ECL/TTL
10125
A30
-1.29V
-5.2 V
ECL/ECL
10124
B30
DATA BIT 59
DATA BIT 58
DATA BIT 57
DATA BIT 56
B94
B93
B91
B90
NC
FROM PAGE 06 [DATA GATE]B38-12
NOTES:
1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS B94, B93, B91, AND B90 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HBH, MOCR MEMORY MODULE
DEVELOPMENT DIVISION
2467C814
A
CM 4.3-19
21


+5 V
X+Y
131,072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
A262144
A000000
[AB/A17]G42
[A7/A16]G40
[A6/A15]G40
[A5/A14]G40
[A4/A13]G40
[A3/A12]G38
[A2/A11]G38
[A1/A10]G38
[A0/A9]G38
[RAS 0]G42
[CAS]G42
[WRITE]G42
C1
C2
C3
F
▷MEM
262K X 1
G32
AC30
AP
DATA ØUT
DATA IN
MEMORY
262KX1
C32
H32
D32
K32
F32
J32
E32
[AB/A17]C42
[A7/A16]C40
[A6/A15]C40
[A5/A14]C40
[A4/A13]C40
[A3/A12]C38
[A2/A11]C38
[A1/A10]C38
[A0/A9]C38
[RAS 1]C42
[CAS]C42
[WRITE]C42
[AB/A17]H42
[A7/A16]H40
[A6/A15]H40
[A5/A14]H40
[A4/A13]H40
[A3/A12]H38
[A2/A11]H38
[A1/A10]H38
[A0/A9]H38
[RAS 0]H42
[CAS]H42
[WRITE]H42
[AB/A17]D42
[A7/A16]D40
[A6/A15]D40
[A5/A14]D40
[A4/A13]D40
[A3/A12]D38
[A2/A11]D38
[A1/A10]D38
[A0/A9]D38
[RAS 1]D42
[CAS]D42
[WRITE]D42
[AB/A17]K42
[A7/A16]K40
[A6/A15]K40
[A5/A14]K40
[A4/A13]K40
[A3/A12]K38
[A2/A11]K38
[A1/A10]K38
[A0/A9]K38
[RAS 0]K42
[CAS]K42
[WRITE]K42
[AB/A17]F42
[A7/A16]F40
[A6/A15]F40
[A5/A14]F40
[A4/A13]F40
[A3/A12]F38
[A2/A11]F38
[A1/A10]F38
[A0/A9]F38
[RAS 1]F42
[CAS]F42
[WRITE]F42
[AB/A17]J42
[A7/A16]J40
[A6/A15]J40
[A5/A14]J40
[A4/A13]J40
[A3/A12]J38
[A2/A11]J38
[A1/A10]J38
[A0/A9]J38
[RAS 0]J42
[CAS]J42
[WRITE]J42
[AB/A17]E42
[A7/A16]E40
[A6/A15]E40
[A5/A14]E40
[A4/A13]E40
[A3/A12]E38
[A2/A11]E38
[A1/A10]E38
[A0/A9]E38
[RAS 1]E42
[CAS]E42
[WRITE]E42
[DATA GATE]B38-4
TTL/ECL
10124
B32
-5.2 V
NC
DATA BIT 63
DATA BIT 62
DATA BIT 61
DATA BIT 60
B99
B98
B97
B95
EQL/TTL
10125
A32
-1.29V
T
NOTES:
1. ALSØ USED FØR REFRESH.
2. CONNECTØR PINS B99, B98, B97, AND B95 ARE NØT TERMINATED.
3. GHJK RØWS USE RAS 0
CDEF RØWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH, MSCR MEMORY MODULE
DEVELOPMENT DIVISION
2467D814
A
CM 4.3-20
22


+5 V
MEMORY 262KX1 C34
MEMORY 262KX1 H34
MEMORY 262KX1 D34
MEMORY 262KX1 K34
MEMORY 262KX1 F34
MEMORY 262KX1 J34
MEMORY 262KX1 E34
262K X 1 G34
DATA OUT
DATA IN
[DATA GATE]B38-13
TTL/ECL 10124 B34
-5.2 V
ECL/TTL 10125 J34
-1.29V
DATA BIT 67
DATA BIT 66
DATA BIT 65
DATA BIT 64
BIO8
BIO3
BIO2
BIO1
NC
T
NOTES:
1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS BIO5, BIO3, BIO2, AND BIO1 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH, MOCR MEMORY MODULE
DEVELOPMENT DIVISION
24670814
A
CM 4.3-21
23


+5 V
131,072
65536
32768
16384
8192
4096
2048
1024
512
256
128
64
32
16
8
4
2
1
A262144
A0000000
P-MEM
262K X 1
838
DATA OUT
DATA IN
MEMORY
262KX1
C36
D36
H36
K36
F36
J36
E36
ECL/TTL
10125
A36
-1.29VB
-5.2 V
TTL/ECL
10124
B36
DATA GATE]B38-5
DATA BIT 71
DATA BIT 70
DATA BIT 69
DATA BIT 68
B110
B109
B107
B106
NC
T
NOTES:
1. ALSO USED FOR REFRESH.
2. CONNECTOR PINS B110, B109, B107, AND B106 ARE NOT TERMINATED.
3. GHJK ROWS USE RAS 0
CDEF ROWS USE RAS 1.
LEVEL 4 DIAGRAM
SCHEMATIC
524K X 72
3HEH, MSCR MEMORY MODULE
DEVELOPMENT DIVISION
2467C814
A
CM 4.3-22
24

CORPORATE HEADQUARTERS, P.O. BOX O, MINNEAPOLIS, MINN 55440
SALES OFFICES AND SERVICE CENTERS IN MAJOR CITIES THROUGHOUT THE WORLD

LITHO IN U.S.A.

CONTROL DATA