
**NOVEMBER 24, 1977** 

#### **HOW CONSUMER VIDEO-RECORDER FORMATS MATCH UP/106**

Calculator programs speed tuned-circuit design/118

Microprocessors in action: keeping apple orchards healthy/125

# ECCIONICS OF A MCGRAW-HILL PUBLICATION CONTROL OF THE PUBLICATION CONTROL O



# AND HERE'S WHAT'S IN IT FOR THE OEM.



The PDP-11/60.

The newest generation of PDP-11 power.

Positioned right between the PDP-11/34 and PDP-11/70.

And delivered in a complete package designed to combine this new level of performance with superior uptime.

We started with the performance. With its integral bipolar cache memory, the 11/60 gives you an effective cycle time of 532ns. But it doesn't stop there. Its

built-in floating point, offered as standard, allows you to run FORTRAN IV-PLUS, our fastest FORTRAN. And the optional high-speed floating-point processor can execute single- or double-precision add/subtract in  $1.0 \,\mu\text{sec}$ , single-precision multiply in  $1.5 \,\mu\text{sec}$ , and double-precision multiply in  $3.7 \,\mu\text{sec}$ .

In addition, you get a Writable Control Store (WCS) option that boosts the performance while allowing OEMs to expand the machine's capabilities into their own unique areas.

Then we maximized the uptime. The 11/60 was designed under our unique Reliability And Maintainability Program (R.A.M.P.) in order to maximize inherent reliability while minimizing repair time and the consequences of failure.


With innovations like Failsoft
System Architecture, you get features
like: an automatic bootstrap self-diagnostic that verifies the soundness of the
system at start-up; error logging to spot
potential hardware problems before
they become critical; and the ability to
run even when parts of the CPU are
down. And if you do your own maintenance, the optional Diagnostic Control
Store module can troubleshoot to the
board level in seconds.



And we wrapped it all together in our new H9500 Series cabinet. The H9500 Series was developed to answer a host of reliability and serviceability problems inherent in other designs. Yet it still accepts 19" (48.26 cm) rack-mountable equipment.

The new cabinet incorporates: swing-out card cages and built-in cable troughs for better access and less signal noise; electrically isolated programmer and cabinet panels; quieter, more powerful fans; even modular

power supplies. And it's available with single- and double-width expansion cabinets, in 5' (1.5 m) and 4' (1.3 m) versions, to fit your needs exactly.



The PDP-11/60.


All things considered, the ultimate in mid-range OEM computers.

Digital Equipment Corporation, PK-3-M28, Maynard, MA 01754. (617) 897-5111, ext. 6253. In Europe: 12, av. des Morgines, 1213 Petit-Lancy/ Geneva. Tel. 93 33 11. In Canada: Digital Equipment of Canada, Ltd.


## OEM PRODUCTS GROUP

Circle Number 900 on Reader Service Card

## WITH THE PDP-11/60, A NEW GENERATION OF POWER COMES TO THE MID-RANGE MARKET.



# ANOTHER VINTAGE YEAR FOR CHERRYS



We planted the seeds for these Cherrys 25 years ago. Today they're the pick of the switching crop. Good, sturdy, hardworking switches with years of know-how, experience and refinement behind them . . . and a bright future ahead. What kinds of switches? You name it, Cherry's got it.

What kinds of switches? You name it, Cherry's got it. Snap-action switches with unique Cherry coil spring mechanism for long mechanical life. Gold crosspoint contact switches for low energy solid state circuits. Thumbwheel switches in a full range of alphanumeric readouts and output codes. Individual keyboard switches and complete keyboard assemblies with electronics. Rotocode® switches . . . a new rotary switch with coded electrical output.

If your products are made or sold overseas you'll be glad to know that Cherry's switches are available worldwide from our modern manufacturing plants in the USA, England, Germany and Japan and a licensee in Australia. All our switches have passed rigid performance requirements of independent testing laboratories. Many of our switches have been listed, certified or approved by various international testing and approval agencies.

Check the complete crop of Cherry switches. Ask for our latest 84 page catalog. For immediate action just phone (312) 689-7700.



CHERRY ELECTRICAL PRODUCTS CORP. 3608 Sunset Avenue, Waukegan, Illinois 60085

SWITCHES and KEYBOARDS — Available locally from authorized distributors.



#### The International Magazine of Electronics Technology

#### **41 Electronics Review**

MEMORY: Minifloppy gets two heads for 0.4-megabyte store, 41 MICROPROCESSORS: Zilog offers broad range of languages, 42 Motorola one-chip microprocessor could be most powerful, 43 SOLID STATE: Signetics plans processor-compatible converters, 44 INDUSTRIAL: Robot sets sights on objects on table, 46 INSTRUMENTS: Microprocessor drops microwave counter price, 48 MICROCOMPUTERS: Son of LSI-11 is smaller, cheaper, 50 AUTOMOTIVE: Microcomputer gets job on production line, 52 NEWS BRIEFS: 52 COMPANIES: Government may win IBM case, 54

#### 65 Electronics International

JAPAN: Electron beam scans 2-μm patterns directly, 65 THE NETHERLANDS: Air force adopts digital network from Collins, 66 AROUND THE WORLD: 66

#### 75 Probing the News

COMPANIES: Motorola makes microcomputer comeback, 75 CONSUMER: Audio world gets the word: digital, 78 BUSINESS: Slowdown has little effect, 81 THE IEEE: Can Getting, Hogan heal the rift?, 84 PACKAGING & PRODUCTION: Ceramic carriers make inroads, 86 GOVERNMENT: NASA's star continues to wane, 90

#### 99 Technical Articles

INDUSTRIAL: IR-reading vidicons map clearer pictures, 99 CONSUMER: Two formats go head to head in VTR confrontation, 106 DESIGNER'S CASEBOOK: Limiter controls phone-line signal power, 114 Synchronous timing loop controls windshield wiper delay, 115 CIRCUIT DESIGN: Cascaded tuned-circuit design simplified, 118 MICROPROCESSORS: Monitor optimizes apple-tree spray cycle, 125 ENGINEER'S NOTEBOOK: LED array forms low-cost scope display, 128 Variable oscillator reacts to magnetic-flux changes, 130

#### 141 New Products

IN THE SPOTLIGHT: C-MOS converters resolve 12 bits, 141 Multimeter delivers extra functions, 144 MICROPROCESSORS: 4-bit slice acts as sequencer, 148 SUBASSEMBLIES: Smart display offers low drain, 154 INDUSTRIAL: 10-channel RTD scanner sells for \$595, 166 PACKAGING & PRODUCTION: Software aids pc-board design, 175 COMPONENTS: One-pole, 20-A mercury relay sells for \$6, 188 INSTRUMENTS: Meter resolves 0.1 microhm on 1-m $\Omega$  range, 194 COMMUNICATIONS: 3-in-1 modem provides direct phone link, 200 MATERIALS: 220

#### Departments

Publisher's letter, 4
Readers' comments, 6
News update, 8
Editorial, 12
People, 14
Meetings, 30
Electronics newsletter, 35
Washington newsletter, 59
Washington commentary, 60
International newsletter, 63
Engineer's newsletter, 132
New literature, 226
New books, 234

#### Services

Employment opportunities, 238 Reader service card, 253

#### **Highlights**

#### Cover: Pyroelectric TV tubes defeat flicker, 99

Recent technological advances have improved the picture from pyroelectric vidicons, which read the infrared radiation from heat-emitting bodies in order to produce a thermal image. A big gain is the provision of a flicker-free image under all conditions.

Cover collage by Art Director Fred Sklenar.

#### Sun shines on Motorola-Austin, 75

The Austin, Texas, summer of 1976 was a bleak one for Motorola's metal-oxide-semiconductor microcomputer division, with key employees leaving and production problems growing by the day. Now prized contracts with GM, Ford, and Chrysler are in hand, the problems have been licked, and devices are rolling off the line.

#### Calculator designs tuned-circuit arrays, 118

Designing cascaded tuned circuits requires a series of complex calculations, but the figuring can be turned over to a calculator. This first part of a two-part series gives the programs for designing single and synchronous tuned circuits.

#### Microprocessor aids apple growers, 125

Using data from environmental sensors, a microprocessor-based computer located in the orchard can predict the severity of apple scab, a common fungus infesting apple trees. Thus growers can apply fungicide less frequently but more effectively. Another in the Microprocessors in Action series.

#### And in the next issue . . .

Microcomputer roundup: the new chips, the new applications . . . where the action is at this year's International Electron Devices Meeting . . . fluorescence boosts usability of liquid-crystal displays.

#### **Electronics**

#### EDITOR-IN-CHIEF: Kemp Anderson

**EXECUTIVE EDITOR: Samuel Weber** 

MANAGING EDITOR: Arthur Erikson, International

SENIOR EDITORS: Laurence Altman, William F. Arnold, Ray Connolly, Lawrence Curran, John Johnsrud, H. Thomas Maguire, Stephen E. Scrupski, Gerald M. Walker

ART DIRECTOR: Fred Sklenar

ASSOCIATE EDITORS: Howard Wolff, Alfred Rosenblatt

DEPARTMENT EDITORS Aerospace/Military: Ray Connolly Circuit Design: Vincent Biancomano Communications & Microwave: Richard Gundlach Components: Lucinda Mattera Computers: Raymond P. Capece Consumer: Gerald M. Walker Instrumentation: Stephen E. Scrupski New Products: H. Thomas Maguire, Michael J. Riezenman Packaging & Production: Jerry Lyman Solid State: Laurence Altman

CHIEF COPY EDITOR: Margaret Eastman

COPY EDITORS: Ben Mason, Mike Robinson

ART: Charles D. Ciatto, Associate Director Paula Piazza, Assistant Director

EDITORIAL SECRETARIES: Janet Noto, Penny Kaplan

EDITORIAL ASSISTANT: Marilyn B. Rosoff

FIFLD FDITORS

Boston: Lawrence Curran (Mgr.) Pamela Hamilton Los Angeles: Larry Waller (Mgr.) Midwest: Larry Armstrong (Mgr.) New York: Bruce LeBoss (Mgr.) San Francisco: William F. Arnold (Mgr.) Washington: Ray Connolly (Mgr.) Frankfurt: John Gosch London: Kevin Smith Paris: Arthur Erikson Tokvo: Charles Cohen

McGRAW-HILL WORLD NEWS Editor: Michael Johnson Brussels: James Smith Milan: Andrew Heath Moscow: Peter Hann Paris: Andrew Lloyd Stockholm: Robert Skole Tokyo: Robert E. Lee

PUBLISHER: Dan McMillan

ADVERTISING SALES MANAGER: Paul W. Reiss

MARKETING ADMINISTRATION MANAGER: Wallis Clarke

CIRCULATION MANAGER: Karl Peterson

MARKETING SERVICES MANAGER: Tomlinson Howland

RESEARCH MANAGER: Margery D. Sholes

#### Publisher's letter

Video cassette recorders have already been identified as the hottest new consumer electronics product to come along since color television. What's more, they are one of the most important developments affecting TV broadcasting. The VTR, in effect, makes the consumer a broadcast executive, deciding when a program will be seen or watching one program while taping another.

For the technical details on the two most important competing consumer VTR designs, we went to Sony Corp. and Victor Co. of Japan. That meant an assignment for our man in Japan, Charlie Cohen. You'll find his report on page 106.

As Electronics' Tokyo bureau chief for some dozen years, Charlie is known for his thoroughness in researching an article as well as for his rare grasp of the Japanese language-spoken and written. He needs these assets in putting together the complex story of technological progress in Japan.

Fortunately, Charlie, who has his engineering degree from the University of Tokyo, knows his way around Japanese electronics companies as well as he knows the confusing streets of Tokyo and Osaka. As a Sony research manager once confided, "He knows more about what's going on in my company than I do."

The equations that characterize the behavior of cascaded inductancecapacitance tuned circuits were developed by and written in a form convenient to theoreticians. Their interest was explaining and optimizing tuned-circuit properties.

Engineers, however, have the task of making the circuits work in specific applications. That's why Al

Haves, author of the two-part series on cascaded tuned circuit design that starts on page 118 in this issue, turned the equations into design formulas that can be solved on a programmable calculator.

"There's nothing I like better," he says, "than to take a set of theoretical equations having little or no practical use, and to convert them into a set of useful cookbook-type formulas that can be quickly and accurately solved with the great tool now available to the engineer: the calculator."

"An engineer's prime function," he continues, "is to transform the theory into meaningful results. That's what differentiates the engineer from the physicist. And the calculator is the tool that permits the engineer to fulfill his function."

Hayes became a radio amateur at age 13, and this "had everything to do with my becoming an engineer." He graduated from MIT in 1942 and during the postwar years held a variety of jobs. He first worked in the basic technical and editorial fields, holding positions with the American Radio Relay League and then as editor for CQ magazine. Later he went to Emerson Radio, as senior project engineer working on military projects, and Ampex Corp. where he worked mostly on audiocircuit design. After 15 years with Lockheed in California working on rf circuits and systems, Hayes, in 1968, began consulting work, which has now turned into his full-time profession.

November 24, 1977 Volume 50, Number 24 97, 133 copies of this issue printed

November 24, 1977 Volume 50, Num. Published every other Thursday by McGraw-Hill, Inc. Founder: James H. McGraw 1860-1948. Publication office: 1221 Avenue of the Americas, N.Y., N.Y. 10020, second class postage paid at New York, N.Y. and additional mailing offices.


Executive, editorial, circulation and advertising addresses: Electron-tics, McGraw-Hill Building, 1221 Avenue of the Americas, New York, N.Y. 10020. Telephone (212) 997-1221. Teletype 12-7960 TWX 710-581-4879. Cable address: M.C.G.R. W.H.L.L.N.E. W.Y.O.R.K. Subscriptions limited to professional persons with active responsibility in electronics technology. No subscriptions accepted without complete identification of subscriber name, title or job function, company or organization, and product manufactured or services performed. Based on information supplied, the publisher reserves the right to reject non-integration and product manufactured or services performed. Based on information supplied, the publisher reserves the right to reject non-integration, and product manufactured or services performed. Based on information supplied, the publisher reserves the right to reject non-integration, and product manufactured or services performed. Based on information supplied, the publisher reserves the right to reject non-integration, and the product manufactured or services performed. Based on information supplied, the publisher reserves the right to reject non-integration, and product manufactured or services performed. Based on information supplied, the publisher reserves the right to reverse the right to reject non-integration. The production of the pr

Officers of McGraw-Hill Publications Company: Gordon L. Jones, President: Paul F. McPherson, Executive Vice-President: Group Vice-President: Gene W. Simpson; Senior Vice-Presidents: Russell F. Anderson; James E. Boddorf, Planning & Development: David G. Jensen, Manufacturing: Ralph R. Schulz, Editorial; Vice-Presidents: Denis Ceran, European Operations; David P. Forsyth, Research; Douglas Greenwald, Economics; James E. Hackett, Controller; Robert L. Leyburn, Circulation; Edward E. Schirmer, Sales.
Officers of the Corporation: Harold W. McGraw, Jr., President, Chales, Senior Vice President and Secretary, Ralph J. Webb, Treasurer.
Title registered in U.S. Patent Office; Copyright Of 1977 by McGraw-Hill, Inc. All rights reserved. The contents of this publication may not be reproduced in whole or in part without the consent of copyright owner. Subscribers: The publisher, upon written request to our New York office from any subscriber, agrees to refund that part of the subscription price applying to copies not yet mailed. Please send change-of-address notices so rocomplaints to Fulliment Manager; subscription orders to Circulation Manager, Electronics, at address below. Change-of-address notices should provide old as well as new address, including postal zip code number. If possible, attach address label from recent issue. Allow one month for change to become effective.
Postmaster: Please send form 3578 to Fulfillment Manager, Electronics, P.O. Box 430, Hightstown, N.J. 08520.

# ferroresonant stabilized power supplies

- High efficiency: 75-80%
- Automatic current limiting (not foldback)
- Inherent overvoltage protection
- Wide source range
- Brownout protection to 90V a-c

- Source effect (line regulation) ± 0.5%
- Low ripple less than 50 mV
- 12V, 24V, 28V and 48V models
- Up to one kilowatt output



KEPCO, INC. • 131-38 SANFORD AVENUE • FLUSHING, N.Y. 11352 U.S.A. • (212) 461-7000 • TWX #710-582-2631 • Cable: KEPCOPOWER NEWYORK

Circle 4 on reader service card



## Save 5 Ways with Abbott's New 77% Efficient Power Supplies!

Abbott has a Hi-Efficiency series of power modules that can save 5 ways in your system. The Model "VN" series converts 47-440 Hz AC lines to regulated DC power and uses a new approach in switching technology that provides a highly reliable line or sixty-three high efficiency power modules.

#### The Model "VN" series saves in the following 5 ways:

1 SAVES POWER – High frequency pulse width modulation and C/MOS digital IC control circuitry allow efficiencies of up to 77% in the Model "VN" series. This high efficiency realizes almost twice the output power per input watt than dissipative regulators.

**2** SAVES SIZE – Off line techniques and IC technology combine for packages of 70% less volume compared to dissipative regulators.

**3** SAVES WEIGHT—High efficiency means less power dissipated and less heat generated, thereby reducing or eliminating the need for bulky heat-sinking and forced air cooling. This translates into less total weight and smaller system size.

4 SAVES TIME – You can quickly get the power supply you need because we have an extensive line of models to choose from. Outputs of 25, 50 and 100 watts are available at any voltage between 4.7 and 50.0 VDC. With popular voltages in stock, chances are the unit you need is available immediately.

**5** SAVES MONEY — At only \$299 for 25w, \$339 for 50w, and \$359 for 110w in small quantities, the "VN's" are among the lowest priced Hi-efficiency units on the market.

Abbott also manufactures 3,500 other models of power supplies with output voltages from 2.7 to 740 VDC and output currents from 4 milliamps to 20 amps. They are all listed, with prices, in the new Abbott Catalog. Included are:

60 to DC
400 to DC
28 VDC to DC
28 VDC to 400 12-38 VDC to 60 12-38

Please see pages 3156-3168 Volume 2 of your 1977-78 EEM (ELECTRONIC ENGINEERS MASTER Catalog) or pages 644-653 Volume 2 of your 1977-78 GOLD BOOK for complete information on Abbott Modules.

Send for our new 60 page FREE catalog.

#### abbott transistor

LABORATORIES,

5200 W. Jefferson Blvd./Los Angeles 90016 (213) 936-8185 Telex: 69-1398 INCORPORATED

1224 Anderson Ave./Fort Lee, N.J. 07024 (201) 224-6900 Telex: 13-5332

#### Readers' comments

#### It's safer

To the Editor: With regard to the resettable electronic fuse [Designer's casebook, Sept. 15, p. 117], I feel it's rather dangerous to be able to defeat the fuse merely by holding down the push button.

A better scheme would be to have the push-button supply current connected only to the relay and not to the load. Simply disconnect the side of the push button directly connected to the load and reconnect it to a resistor,  $R_4$ , whose value is equal to  $R_2$ . Connecting the free end of  $R_4$  to the junction of the coil and  $R_2$  completes the modification.

Esther Finlay Vancouver, B. C. Canada

#### Conspicuous omission

To the Editor: I read with interest your article "Converters adjust to LSI, bi-FET op amps emerge" [Oct. 27, p. 112], in which you quoted a list of companies that already have or are about to have microprocessor-oriented converter products on the market.

It should be noted that the only company to have announced and already have in volume production a fully microprocessor-compatible converter subsystem was conspicuously absent from that list. The company is Signetics and the product is the NE5018, a complete 8-bit digital-to-analog converter with voltage reference, output operational amplifier, and data latches.

In addition, Signetics will soon be announcing a series of microprocessor-oriented analog-to-digital converters, as well as expanding its line of digital-to-analog products

of digital-to-analog products.

Peter Guest

Interface Product Line Manager Signetics Corp. Sunnyvale, Calif.

• We are well aware of Signetics' efforts in microprocessor-compatible data converters, and we apologize for the obvious omission on our part. For more about the converter chips forth-coming from Signetics, "Converters designed for microprocessors," beginning on page 44.

PRESENTING VMOS FROM A BIG TIME PRODUCER.


With a major producer like Fairchild behind it, you know VMOS is going to be a big star someday. So remember the name: Enhancement Mode Power Vertical Mosfet. Stagename: Fairchild VMOS.

VMOS transistors are going to make the big time by combining the advantages of vacuum tubes — or lower power FETS — with those of conventional power transistors.



#### AN AWARD WINNING PERFORMER.

Fairchild VMOS gives you high input impedance with direct interface to CMOS. It's capable of super switching times — 10 ns at 1 A. It has



highly linear transfer characteristics. high GM, easy paralleling and biasing, protected gates, low Rds (on) and no second breakdown or thermal runaway. And here's the initial cast of characters:

	Package	PD	ID	<b>BVDSS</b>
2N6657	TO-3	25 W	2.0 A	60 V
2N6658	TO-3	25 W	2.0 A	90 V
FVN2	TO-39	6.26 W	2.0 A	60 V
2N6661	TO-39	6.25 V	2.0 A	90 V

Cross-section of Fairchild's VMOS power transistor.

#### **INTRODUCING A SUPERSTAR SUPPORTING CAST.**

In addition to N-Channel VMOS, Fairchild is also producing the world's first P-Channel Power Mosfets with all the features of N-Channel. This

Device Type	Package	PD	ID (max)	BVDSS	Rds (on)
FVP1	TO-3	25 W	2.0 A	60 V	6
FVP2	TO-39	625 W	15 A	60 V	12

means you can now get a complementary product line in VMOS technology from a major Power source.

#### FEATURE PERFORMANCE AT A MATINEE PRICE.

Whether you're designing CATV, MATV amplifiers, audio drivers, core


memories, switching regulators, analog switches, pin diode drivers, lasers, transducer drivers, or microprocessor interfaces, state of the art designs are now possible. And just as importantly, they're now affordable with Fairchild Power VMOS. Here are some examples:

		100-999
T	2N6657	\$4.20
	2N6658	\$5.05
	FVN2	\$1.85
	2N6661	\$2.95
	FVPI	\$4.25
	FVP2	\$1.85

#### **NOW PLAYING AT A DISTRIBUTOR NEAR YOU.**

For more information on VMOS, contact your Fairchild sales office or representative today. Or use the direct line at the bottom of this ad to reach our Power Division. Fairchild Camera and Instrument Corporation, 464 CALL US ON IT. Ellis Street, Mountain View, CA 94042. Tel: (415) 962-3343. TWX: 910-379-6435. **(415) 962-3343** 





#### **News update**

■ Sperry Rand Corp.'s Sperry division in Great Neck, N. Y., is delivering to the Air Force samples of a nonvolatile random-access memory said to be 30 times harder to nuclear radiation than present integrated circuits and produced with the metal-nitride-oxide-silicon process. The military is eager to obtain MNOS memory arrays that are radiationresistant and can perform in severe environments [Electronics, May 13, 1976, p. 301.

Developed under a \$650,000 contract from the Defense Nuclear Agency and the U.S. Air Force Weapons Laboratory at Kirtland Air Force Base in New Mexico, the 256bit memory has a write cycle time of 2.8 microseconds, or three times the write speed of present MNOS electrically alterable read-only memories, claims William Rubin, the Sperry division's research director.

"The technology has matured to the point that we're seeking immediate funding for pilot production,' Rubin notes. He believes the next phase of funding will be first to translate the lab parts into production designs and next to develop memory designs that incorporate these chips for various applications in strategic missile and satellite programs. Full production-quality nonvolatile MNOS ROMs could be available in 12 to 18 months.

■ The U.S. Army recently accepted the first U.S. Roland missiles off the assembly line of the Hughes Aircraft Co.'s manufacturing facility in Tucson, Ariz. The armament for the U. S. Roland short-range all-weather air defense system, the missile is designed to knock out of the air lowlevel attackers trying to sneak in under radar detection. It represents the first major European-designed weapons system selected for production for the U.S. Army [Electronics, Jan. 22, 1976, p. 68].

The U.S. Roland missile is interchangeable with the European version, and more than 90% of the firing-control unit's replaceable parts are interchangeable.

**Bruce LeBoss** 

Gas Sensing Semiconductor

quickly senses even small amount of gas.



**Applications** 


- 1. Natural Gas-Leak Alarm
- Propane Gas-Leak Alarm
   Carbon Monoxide Detector
- 4. Automatic Fan Control 5. Fire Alarm (Detecting
- combustible gases contained in smoke)
  6. Alcohol Detector
- (Detector for drunken 7. Air Pollution Monitor
- Please contact any of the addresses below directly for

catalogs and price/delivery information

#### FIGARO ENGINEERING INC.

- Head Office: 3-7-3 Higashitoyonaka, Toyonaka City, Osaka, 560, JAPAN TELEX: 05286155 FIGARO J CABLE: FIGARO TOYONAKA TEL: (06) 849-2156
- North America: 3303 Harbor Boulevard, Suite D-8, Costa Mesa, California 92626, U.S.A. TELEX: 678396 CABLE: FIGARENGIN COSTAMESA TEL: (714) 751-4103

Circle 254 on reader service card



Circle 255 on reader service card

P.O. Box 287 South Laguna, CA 92677

(714) 545-3734 • TWX910 596-1325 MOCROTEC LBEH

**INDUSTRIES** 

# RCA first in CMO

# First in CMOS microprocessors.

CDP 1802

CDP 1851

microcomputers - all in CMOS.

RCA 1800 combines elegant COSMAC architecture with CMOS benefits. Result: the performance you want - plus maximum flexibility with minimum parts count.

Cost-effective COSMAC architecture. Since our CDP1802 CPU accepts compact 1-byte instructions, you need less memory. Registers store data with 1-byte access. And they act as pointers, so individual instructions don't need addresses.

Built-in I/O. The CPU has interrupt, DMA, flags in and bit control out, so you need less I/O. And we offer a

#### The RCA 1800 Microprocessor Family

COSMAC CPU

CDP 1821S 1024x1 High-speed RAM CDP 1822 256x4 Low-cost RAM CDP 5101 256x4 Industry-standard RAM CDP 1822S 256x4 High-speed RAM CDP 1824 32x8 RAM CDP 1831, 2 512x8 ROM (with or without latch) CDP 1833, 4 1024x8 ROM (with or without latch) CDP 1852 Byte I/O CDP 1853 I/O decoder CDP 1854 UART CDP 1856, 7 Bus buffer/separators CDP 1858, 9 Address latch/decoders CDP 1861 TV interface Coming in 1978 CDP 1823S 128x8 High-speed RAM

Programmable I/O CDP 1855 Multiply/Divide Unit And these major parts: 4K RAM, 4K EPROM, 1-chip COSMAC

wide range of low-cost I/O devices, including our unique 2-mode UART. Easily expandable memory. Build up to 65K without adding any address management parts. RCA offers the ROMs you'll need and CMOS RAMs as well.

Full-range design support. From the basic Microtutor learning tool to a complete COSMAC Development System with floppy disk. All geared to help you translate the CMOS advantage into true system cost effectiveness.

For more information, contact your local RCA Solid State distributor. Or contact RCA Solid State headquarters in Somerville, NJ: Sunburyon-Thames, Middlesex, England; Quickborn 2085, W. Germany; Ste.-Anne-de-Bellevue, Quebec, Canada; Sao Paulo, Brazil; Tokyo, Japan.

When you say CMOS, say RCA first.



# Advanced Micro Devices fills in the blanks.

The Texas Instruments TTL Data Book has most of the Schottky and Low-Power Schottky parts you need for most designs. Most. The Advanced Micro Devices book has the rest.

The 625-page AMD Schottky and Low-Power Schottky Data Book. It fills in all the blanks with a whole new generation of parts: Complex MSI/LSI, optimized to fit today's microprocessor and memory-oriented system architecture.


Many of these parts combine several functions in space-saving 20-pin packages. They'll create all kinds of new room on your PC boards. They'll cut your power usage dramatically, take away half your interconnections, and make your systems much, much faster.

These new parts are catching on so fast we've been getting alternate source commitments even before we can get them on the market. So when you're designing high performance digital systems, remember—don't do anything until you check both books.

The Advanced Micro Devices
Schottky and Low-Power Schottky
Data Book. Powerful solutions to
microprocessor and memory design
problems. Send us the coupon and
we'll send you the book. (File it under
"Schottky," right there next to that
big gold one.)


#### For example:

8 Input Multiplexer With Control Register.



It's our way of saying three things: 54/74LS151 multiplexer plus 54/74LS175 register plus assorted gate packages. It's one 20-pin part that does the work of three or four 16-pin parts. You save space. You save money. You increase speed. By about 40%.

#### Programmable Up/Down Counter With 3 State Outputs



It does the work of a 54/74LS169A plus a three-state buffer plus two or three gate packages. Figure it out. You save lots of space. Add to that a savings of about 40% of your power, 40% of your time, and the total is mighty impressive.

# Schottky and Low Power Schottky Data Book. ARABARA ARABARA ARABARA ARABARA ARABARA ARABARA

#### Fill in the blanks:

Name \_\_\_\_\_\_
Company \_\_\_\_\_
Mailing Address \_\_\_\_\_

## Advanced Micro Devices

Bipolar LSI. N-channel, silicon gate MOS. Low-power Schottky. Multiple technologies. One product: excellence.



#### IEEE: a house divided . . .

Once again the election of officers for the Institute of Electrical and Electronics Engineers has underscored the deep division within the institute's ranks. One side favors professional, socio-economic programs and the other side is opposed to them. As usual, the vote also drove home the horrendous apathy among members.

Despite the wide publicity surrounding this year's election, the placing on the ballot of a well-known and outspoken industry executive, and the numerous reminders to vote, fewer than 50,000 of the nearly 140,000 eligible to vote returned usable ballots. What, one wonders, does it takes to get IEEE members interested enough in their organization to respond?

At any rate, neither the division within the minority nor the apathy among the majority will disappear overnight. It appears that with this election the IEEE has reached a pause in its five-year-long effort to become a professional as well as a technical organization. It has not been an easy transition, and in fact, the transition is not yet complete.

Therefore the friction between those demanding a faster-acting U. S. Activities Board and those wanting a more deliberate pace will continue. Even the anticipated pause in the coming year is controversial. Is it a time to take stock and renew professional efforts or will it be simply a period of benign neglect of member needs?

Some years ago "Engine" Charlie Wilson, the Secretary of Defense in the Eisenhower Administration, caused a row when he said that what's good for General Motors (his former company) is good for America, meaning that good auto business creates jobs, paychecks, and a demand for more cars.

Today, the newly elected top officials of IEEE appear to be saying that what's good for the electronics industry—more business and/or R&D spending—is good for engineers. True, full employment of engineers with a future promising more of the same tends to put the lid on engineer dissatisfaction and restore the don't-rock-the-boat syndrome.

But we think that times have changed. What's good for engineers should be decided by engineers. They should have more of a say about their career than before, rather than being told what's good for them, and that includes decisions from inside as well as outside the U. S. Activities Board.

What the officers of the institute must now decide from all the noise out there is the true signal from engineers. Indeed, one of the most difficult problems hampering professional activities has been the design of a means of picking up and decoding signals from the members. And the first step in that direction has been taken with an extensive survey of membership opinions.

If there is to be a pause in professional activities this year to take stock, let it be the time to develop ongoing communication with the members. Otherwise, an organization in which the articulate members are an evenly divided minority and the majority of members are not communicating will be virtually ungovernable.

# Meet the 250-MHz portable with 5 mV/div sensitivity at bandwidth

In high performance portable oscilloscopes, Tektronix offers you the most complete selection.

Designed to service high speed computers and communications systems, the TEKTRONIX 475A is the latest addition to our line of portable oscilloscopes. With 250-MHz bandwidth and 5 mV/div sensitivity, you can accurately detect glitches, minor variations or aberrations in high frequency waveforms.

Since the full 250-MHz bandwidth of the 475A is available at the probe tip, you can easily measure low-level signals. Even those of only nanoseconds in duration.

The front-panel controls are arranged in the same format as our 465 and 475 Portable Oscilloscopes . . . so you will already be familiar with our new 475A. There's no need for retraining.

Consider the capabilities of the 475A when evaluating portable scopes for your service applications:

- 250-MHz bandwidth.
- 5 mV/div sensitivity.
- 1% horizontal sweep accuracy.
- 1 ns/div sweep-rate capabilities (using 10X mag).
- delayed sweep to view waveform segments downstream from the trigger.
- trigger view to verify trigger presence and characteristics.
- lighted volts/division readout to indicate vertical scale factor when using 1X or 10X probes.
- 8 x 10 cm crt for high-signal resolution.
- \$3450 (add \$445 for the Option 44).


When combined, these capabilities offer you the most performance for your dollar.


To add Delta Delayed Sweep, built-in DMM capabilities, and automatic readout of displayed time intervals to the 475A, order the factory-installed Option 44. With it, you can make timing measurements faster than with conventional procedures. Together the 475A and Option 44 provide you with an economical, portable package for your field service needs.

For more information or a demonstration of the high-performance TEKTRONIX 475A, contact a Tektronix Field Engineer near you or write Tektronix, Inc., P.O. Box 500, Beaverton, Oregon 97077. In Europe write Tektronix Limited, P.O. Box 36, St. Peter Port, Guernsey, Channel Islands.

U.S. Sales Prices FOB Beaverton, Oregon







#### ZIP DIP® II SOCKET/RECEPTACLE SERIES

## IMPROVED TEXTOOL SERIES INCREASES VERSATILITY AT COMPETITIVE PRICES

The ZIP DIP II socket/receptacle series offers all the advantages of TEXTOOL's original zero insertion dual-in-line package models plus increased socket versatility and reduced receptacle pricing.

The ZIP DIP II socket features an enlarged entry for use with an even wider range of devices and a flat top plate for easier entry and extraction. Contacts are on even 100 mil spacing (300-400-600 mil) for more convenient mounting on standard hardware.

A built-in "stop" insures that the ZIP DIP II handle can't be easily over-stressed. Top mounted assembly screws facilitate the replacement of damaged or worn internal parts. TEXTOOL has strengthened both hardware and plastic for increased reliability and screw mounting of the socket to the ZIP DIP II receptacle makes possible a more positive locking system.



The ZIP DIP II receptacle (left) has all the features of previous ZIP DIP receptacles, yet at a lower price. It virtually eliminates mechanical rejects, is a disposable plug-in unit re-

quiring no soldering and has a typical life of 25,000-50,000 insertions. The receptacle is ideal for high volume hand testing and, since replacement time is eliminated, a test station can process literally millions of devices before it must be replaced.

Detailed information on these and other products from TEXTOOL . . . IC, MSI and LSI sockets and carriers, power semiconductor test sockets, and custom versions . . . is available from your nearest TEXTOOL sales representative or the factory direct.



PRODUCTS, INC.

1410 W. Pioneer Drive • Irving, Texas 75061 214/259-2676

#### **People**

## Business software makes for problems, Hosler charges

Jay R. Hosler makes a very good living as a computer systems consultant. However, he says things that make him less than popular among suppliers of these systems to small businesses.

Most of the hundreds of suppliers "are unable to provide a system for small businesses that works well," says the 39-year-old Woodland Hills, Calif., veteran of 20 years in computer services. "It's not the hardware, which in many cases is superb, but the so-called standard software packages."

Inflexibility. The software for even such simple chores as inventory control and keeping track of payroll, billing, and accounts receivable just does not live up to the flexibility that is promised, Hosler says. Quite often, they cannot handle all the special needs even users in the same business have. "What suppliers call a simple change in programming turns out to call for a software specialist," Hosler continues, and will cost much more money than the user ever figured. "Don't get into electronic data processing unless you have \$100,000 to spend, or you'll run out of money," he warns.

Hosler was making these irreverent statements earlier this month in Los Angeles at Interface West, a conference and exposition dealing with small computer systems and applications. Although his views certainly did not please the systems suppliers who exhibited there, "users will appreciate his level of candor," one of the show's organizers said, while seeming to wince a bit. Hosler has been a full-time consultant for less than a year, after finishing almost four years as chief systems scientist working on retailing systems for TRW Communications, and he is nothing if not candid.

Not so easy. "It all looks so easy, potential users don't want to hear how tough it is," he says. "Even something that sounds as easy as varying the number of characters in a printout line often turns out to

mean redoing most of the program." Other changes, such as those involving the nuances of different businesses accounting schemes, need even more expensive work.

"You can't start with a one-of-a-kind software package and end up with what a small business needs," he says. "They all get down to individualized packages, or they don't do the job they're designed for." One result is that "a class of free-lance software consultants who know a specific system is making a very good living following up on initial sales and cleaning up the snafus." In fact, Hosler expects that "computer screw-ups will reach catastrophic proportions."


They could be minimized if manufacturers would agree on having absolutely standardized programs and users would settle for fewer variations, he says. "But the evidence is we're going the other way as customers demand even more diversity."

## Cheaper testers will improve LSI, says Megatest's Bisset

If users inspected incoming devices themselves instead of farming the job out to testing services, the data they would feed back to suppliers would soon be getting them better large-scale integrated circuits, asserts Stephen Bisset, a 27-year-old electrical engineer from Australia. About 2½ years ago, he helped start Megatest Corp., an LSI-tester manufacturer in Sunnyvale, Calif. Last month, Megatest introduced a low-cost tester with a base price of only \$26,000 [Electronics, Nov. 10, p. 29].

"Users will now be able to justify in-house testing economically, and the amount of data being fed back to the semiconductor manufacturers will climb dramatically," Bisset claims. "This data will, in turn, enable the makers to tighten up on their own test programs and catch failures before they are shipped."

Users limited. The number of different companies performing tests has been relatively small, he points out, precisely because of the high



"We saved \$42,000 by cutting down redrawing time the first year we switched to reprographic techniques."

Earl Lind, Graphics Supervisor Solar, an International Harvester Group, San Diego.

"Solar makes gas turbines. Big ones. And they are shipped all over the world. Generally, each customer orders a slightly different version of the basic engine.

"Before we switched to reprographic techniques, we would redraft the entire drawing, even if the change was no more than 10%. Now we make a blowback from microfilm or create a same-size photo copy, opaque unwanted detail, then redraft as required. Or—if the changes are going to be minor—we reproduce it on wash-off film and let the drafter wet-erase what is not wanted and then draw in the new details.


'We figure—even with the limited mechanized processor we had when we first went to reprographics—that we saved \$42,000 in engineering drafting time the first year. And that saving was in spite of the fact that we had to start up a new facility and hire two technicians to run it.

Later we installed a Kodak Supermatic processor and relocated our drafting reproduction area next to our photo lab and copy camera area. As a result, we've found that we're saving about 50% of the processing time for the photo lab and the copy camera facility. Everything we turn out—from publicity photos to engineering drawings—is going through the Supermatic processor." Reprographics can help you, too.

Send for more details about Solar's use of reprographic techniques, plus, a complete listing of Kodak products and other applications. Write: Eastman Kodak Company, Graphics Markets Division, Dept. R04804 Rochester, N.Y. 14650.

VERSATILITY IN REPROGRAPHICS





# New Film-Foil Capacitors for low capacitance purposes

Features: High dielectric strength with high temperature stability. Cast resin encapsulation ensures complete moisture resistance. Aluminium foil electrodes and polyester dielectric.

WIMA FKS 2 5 mm lead spacing 1000 pF to 0,015 μF. Very low self inductance. Ideal where size is critical.

WIMA FKS 3 7.5 and 10 mm lead spacing. Solid end contacts with low inductance. 1000 pF to 0,1 µF. Space saving, general purpose range.



#### **WILHELM WESTERMANN**

Spezialvertrieb elektronischer Bauelemente P.O. Box 2345 · Augusta-Anlage 56 D-6800 Mannheim 1 · Fed. Rep. of Germany Tel.: (621) 408012

#### **People**



**Tester.** Stephen Bisset says new instrument tests any LSI package with 40 pins

price of the testers. The price has been high because the testers have tried to be universal devices, able to handle all parts, Bisset states. Moreover, the new testers operate "without reducing the quality of testing," he says. In other words, they test for the same things the more expensive instruments test for.

Low price tags should win many more over to the new generation of equipment, themselves built with LSI devices and with real-time emulation modules that replace the buffer memory of the large programmable systems and duplicate the device under test. Indeed, Megatest's president predicts, his company should do \$5 million worth of business next year, largely with the new systems, a sizable jump up from this year's \$1 million.

Bisset came to the U.S. about eight years ago and got a BEE degree from California Institute of Technology. After working for Hewlett-Packard Co., he went to Intel Corp., where he was the architectural designer for many of the 8080 family of peripheral devices.

He expects to get involved in testing almost everything. "So far, we haven't run into a digital part with 40 or fewer pins that can't be tested with our system," he says.

# MEASUREMENT BYS

product advances from Hewlett-Packard


# HP's new System 45: an efficient way to handle a small department's computing needs

In its compact, desktop-sized chassis, HP's new Series 9800 System 45 blends the speed and power of a minicomputer with the friendliness and convenience of a programmable desktop calculator. System 45 incorporates in a single package the high performance hardware and accessibility that scientists, engineers, designers and managers need to solve computational problems right in their own work area.

In less than 35.1 kilograms (77.5 pounds) System 45 integrates:

- an interactive keyboard with alphanumeric, control, editing, and special function keys.
- a dual processor that provides overlapped processing for increased throughput.
- a CRT with high-resolution graphics capability and an alphanumeric mode that offers an 80-character, 24-line screen.
- two built-in, 217k byte, high-speed tape transports, one of which is optional.
- 16k bytes of read/write memory expandable to 64k bytes.
- a unified mass storage that permits available storage devices to be addressed with device independent commands.
- ready-made I/O capability for BCD, bit parallel, bit serial, real-time clock and HP-IB interfaces.
- a powerful language—ANSI standard BASIC, with FORTRAN-like capabilities available on command—plus a library of utility and application programs.

For scientific computation and data analysis, System 45 handles data characterizations, statistical and numerical analyses, and other complex routines.



HP's new System 45 is an integrated system with built-in peripherals that provide a new level of speed, power and flexibility; easy-to-use turnkey system uses enhanced BASIC.

For computer aided design, System 45 places the entire design process directly under your control. It lets you display parts tables, parts cross sections, or produce complete drawings.

For data acquisition, System 45 interfaces directly with instrumentation, with 15 levels of interrupt for flexible control.

For business administration, System 45 lets you increase efficiency in various areas of business such as: forecasting, in-

ventory control, payroll, optimization and even text processing.

System 45 is also expandable. To meet your needs in the future, HP offers you an extensive line of peripherals including: flexible disks, large fixed discs (up to 50M bytes), a full page printer, plotters and more.

For more information, check B on the HP Reply Card.

#### IN THIS ISSUE-

Large P-N junction displays • SOS μP in two new 180 cps printers • New flexible synthesizer

# New signal source combines choice of waveform and high accuracy with easy programming

Extend signal capability of popular 8654 and 8640 generators down to 10 kHz

Its very wide frequency range of 0.001 Hz to 50 MHz makes the 8165A the fastest waveform generator of its kind. Output amplitude and signal quality satisfy many analog and digital applications. Its easy-to-use HP-IB interface ensures rapid system integration at minimum cost.

The 8165A programmable signal source generates precision sines, square waves, pulses and triangles. Crystal control provides a frequency accuracy of 0.001% across the entire range.

Its variable, 20V peak-to-peak amplitude, and clean, 5 ns transition time pulses are perfect for digital applications. Amplitude and offset are programmable with 2% accuracy to 5 MHz.

Microprocessor control sets new standards in operator convenience. Keyboard and LED's together with the instrument's high accuracy, allow direct entry and display of desired waveform parameters.


In systems, the intelligent 8165A cuts software development costs and computer

time. Keystroke programmable means identical control sequences for front panel and bus-entered commands. Programming mnemonics for all keys are indicated on the front panel. Error detection and learn mode are also provided.

The 8165A stores parameters for 10 complete waveforms. An entire waveform can be stored and subsequently recalled simply by pressing two panel keys or by a single program step. Batteries provide storage of all parameters for up to four weeks.

External trigger, synchronous gate, counted burst, VCO, FM and optional sweep modes provide the flexibility to use the 8165A in many different applications. The selectable 50 ohm source may be disabled, inverted or operated in dc mode. All specifications are guaranteed from 0 to 50°C for full confidence in system applications.

For more information check K on the HP Reply Card.





New HF down converter now covers test applications in the 10 kHz to 11 MHz band.

A new down-converter, HP 11710B, translates signal inputs of 50.01 to 61.00 MHz from RF signal sources such as the HP 8654 and 8640 to the 10 kHz to 11 MHz frequency range. This wider frequency coverage provides a convenient extension to other applications such as IF testing at 262 kHz.

The 11710B preserves both the AM or FM modulation of the input signal. In fact, it permits higher FM peak deviations than the generators themselves.

Output flatness is ±0.5 dB referenced to 4 MHz and level accuracy is ±(1 dB + input level accuracy). Harmonics are greater than 35 dB below carrier (dBc) and spurious signals are below -60 dBc.

The internal reference oscillator is stable enough to yield a drift of less than 0.05 ppm/hr. and typical overall frequency accuracy of  $\pm 2$  ppm.

A function selector allows straight-through switching so the total range (0.01 to 1100 MHz) of the signal source is available at the 11710B output port. Source inputs are tracked from 0 to -107 dBm in the down-converted mode and there is less than 1 dB loss in the straight-through modes.

For more information, check M on the HP Reply Card.

## Extensive program support for HP 67/97

Hewlett-Packard presents a large selection of problem-solving software for personal programmable calculators. The software works with the HP-67 and HP-97 calculators to provide solutions for a wide range of applications including engineering, science or business.

You can solve your computational problems without writing programs—by using the Application Pacs. And with our Users' Library Solutions, you follow the easy step-by-step instructions to enter the program yourself.

Application Pacs. Each Pac contains an instruction manual with up to 25 preprogrammed magnetic cards. Current Pacs include Statistics, Math, Business, Surveying, Games, Electrical and Mechanical Engineering—plus the new Navigation, Civil Engineering and Clinical Lab Pacs. They save you time and trouble researching, writing, debugging and documenting.

The Users' Library. Over 1000 HP-67/97 programs and over 5000 easily modified HP-65 programs are currently available from the Library.

Users' Library Solutions Books A series of comprehensive books containing the most popular programs from our Users' Library covering applications in Engineering, Home Construction Estimating, Aviation, Energy Conservation and more. Each booklet contains 10 to 12 programs.

For more details on these calculators and these programs, check A on the HP Reply Card.




New software solutions for the HP-67 and HP-97 have been added to help increase your problem solving potential.

#### MEASUREMENT COMPUTATION NEWS

## New sweeper plug-ins offer expanded wideband performance



Double-octave and communications band RF plug-ins for HP 8620C sweeper provide 2.0 to 8.6 GHz frequency coverage.



.2 Freq. (GHz) 8.6

Insertion characteristics of 4-8 GHz bandpass filter. Lower rejection band (left portion of trace) shows freedom from harmonics in HP 86240B RF source.

Three new RF plug-ins with doubleoctave frequency coverage have been added to the HP 8620 Sweep Oscillator family.

The new HP 86240B covers 2.0 to 8.4 GHz with up to 20 mW output (leveled to ±½ dB), yet its harmonic content at 10 mW output is more than 50 dB down. This is achieved by incorporating a YIG filter into the same magnet housing containing

the oscillator-tuning YIG sphere. The high power is achieved through use of a 100 mW GaAs FET amplifier ahead of the YIG filter.

Model 86240A, the non-filtered version of the 86240B, delivers over 40 mW output, has competitively low harmonics, and is attractively priced.

With frequency coverage from 3.6 to 8.6 GHz, the new 86240C is the ideal upconverter for RF distortion analysis of 4, 6 and 8 GHz microwave radio links. Group delay is ≤1 ns over 30 MHz sweeps, and linearity is ≤0.5%. This plug-in delivers 40 mW output and has 10 MHz FM bandwidth for noise loading applications.

For more information on these and other RF units for the 8620C sweeper, check N on the HP Reply Card.

#### HP Journal features NMOS-II

An article of interest, regarding HP's on-going research and development in LSI technology, is featured in the November 1977 issue of the HP Journal. It deals with HP's NMOS-II process, which made possible the high-performance, large-scale integrated circuits for fast 16-bit micro-

processors, 16k read-only memories and a variety of special purpose random-logic chips.

The newest product featuring NMOS-II is the System 45 (cover article). For your copy of the HP Journal, check P on the HP Reply Card.

## New logic state analyzer is portable, totally programmable

# Can signature analysis make your service operation more efficient?



A new small but powerful logic state analyzer interacts with its user through an easy-to-master keyboard. And, it's programmability option provides the capability of a functional automatic digital test station.

The new 1602A logic state analyzer was designed for ease of use in production, field service and engineering. The layout of the keyboard leads you through a natural progression of keystrokes and entries are displayed, enabling you to check their accuracy every step of the way.

For use in design and troubleshooting of digital systems, the 16-bit wide and 64-word deep memory operates at clock speeds to 10 MHz, allowing the instrument to capture virtually any 64-word sequence in a system.

Measurements of system activity are displayed on the analyzer's LED readout in hexadecimal, decimal, octal, or binary format, eliminating the need for base conversions by the operator.

For more consistent and repeatable measurements, the HP Interface Bus op-

tion allows you to make automated functional tests of digital systems. The HP-IB option makes the 1602A totally programmable and able to dump its 64-word memory into the bus on command, for analysis by a desktop computing controller such as the HP 9825A.

Simplicity of use is also apparent in the quick connect and disconnect standard edge connector on the probe. Point-to-point probing on new equipment installed with similar connectors is now fast and easy. The single pod contains all 16 data lines, clock, qualifier and ground.

Weighing only  $4.5\,\mathrm{kg}$  (ten pounds), it is small enough to fit into a briefcase. The price is small, too.

For more details, check E on the HP Reply Card.

There's a good chance that it can. HP and over 100 other companies are currently implementing this new digital service strategy. And, they are cutting repair times, reducing spares inventories and streamlining documentation.

Today's microprocessor-based products are tough to troubleshoot. Tomorrow's digital products may be tougher, and the costs of board exchange, the traditional digital service strategy, tend to escalate rapidly in fast-growth, high-technology product lines.

Design signature analysis into your new products. Document the troubleshooting procedures with the appropriate signatures. Then, use the HP 5004A Signature Analyzer for component-level troubleshooting:

- on-site
- · at the field office
- · at the service center
- on the production line

This portable tester detects and displays unique signatures associated with nodes in digital products. By comparing actual signatures to correct ones as shown in the product manual, a technician can backtrace to the faulty node in a malfunctioning product.

Check into signature analysis. Make your service operation more efficient and prepare for the future at the same time.

For a data sheet and an application note, check J on the HP Reply Card.



Many companies are streamlining field service of microprocessor-based products by trouble-shooting to the component level with the 5004A signature analyzer.

# New $4\frac{1}{2}$ digit autoranging DMM with 1 m $\Omega$ , 1 $\mu$ V dc, 10 $\mu$ V ac sensitivity

The new HP 3466A 4½ digit, sixfunction autoranging digital multimeter combines low cost with high accuracy for both bench and field use.

Dc measurements can be made from 1  $\mu$ V to 1.2 kV with a mid-range accuracy of  $\pm 0.03\%$ . True rms ac measurement range is from 10  $\mu$ V to 1200 volts with a midrange accuracy of  $\pm 0.03\%$  over a 20 Hz to 100 kHz bandwidth.

Ac and dc current measurement range is 10 nanoamps to two amps. Resistance range is 1 milliohm to 20 megohms with a mid-range accuracy of  $\pm 0.03\%$ .

An ohm zero adjustment on the front panel is provided. Milliohms may be offset on the front panel, allowing the zeroing out of test leads when making printed circuit, transformer, coil, or switch contact measurements.

A new diode test measurement capability is offered. The 3466A DMM displays the voltage drop across the diode junction in the forward direction, allowing the user to measure and identify germanium, silicon, light-emitting and Schottky diodes in units of volts, even though the instrument is in the ohms function.

The standard HP 3466A includes rechargeable, lead-acid batteries which provide 8 hours of continuous use. Option 001 offers ac power only. Should battery power be required in the future, the DMM can easily be modified in the field.

For more information, check H on the HP Reply Card.



Because of its ability to make wideband selectable ac plus dc true rms voltage and current measurements, the new HP 3466A digital multimeter can also measure such signals as digital pulse trains and sinusoidal waveforms.

## Hard copy made easy with two new smart printers



A "smart printing" algorithm selects the optimal path and speed for the print head of two new printers. You also get high resolution print that is crisp, clear and readable—even on the sixth sheet of a multiple-part form.

Two new "smart" printers operating at 180 characters per second are now available from Hewlett-Packard. Both printers are controlled by a silicon-on-sapphire (SOS) microprocessor system designed by HP. The HP 2631 is designed for environments requiring a low-cost, high-performance printer. The HP 2635, with a keyboard, is suited to interactive environments.

The microprocessor control optimizes data manipulations, and printing and control functions. Consider the path taken by the print head. It is fast and bidirectional, that is, the printer chooses the most efficient direction to print: right to left or left to right, increasing throughput as much as 50%. By the time one line is printed, the next several lines have been processed and stored in a buffer.

When ten or more adjacent spaces have been detected within a line, the head speeds to the next printable character at an accelerated rate of 450 cps.

The HP 2631/2635 offer as standard

features those capabilities that are often optional on other printers. For example, there are three print modes that can be intermixed on a line—normal, expanded, (for titles and headings) and compressed. Vertical line spacing is variable under program control; the choices are 1, 2, 3, 4, 6, 8 or 12 lines per inch.

Both printers support the entire US ASCII 128-character set, including control codes which are accessible through the display functions. Use of a 7-column by 9-row dot matrix allows printing of true descenders, commas, semi-colons, and underlining. The printers also accommodate subscripts and superscripts.

A variety of interfaces are available including HP-IB, 8-bit duplex, 8-bit differential, and a general purpose parallel interface for OEM applications.

For more information, check F on the HP Reply Card.

## New HP-IB switches for automatic test systems

#### HP-IB

The availability of individual HP-IB switch products gives you modularity and flexibility in the design of your automatic test equipment (ATE) system.


These microprocessor-based switch products provide a flexible, highperformance and cost-effective solution for computer and desktop controllerbased systems.




Up to 8 switch mainframes are controlled by the microprocessor-based **HP 9411A Switch Controller**, also

capable of performing comprehensive self tests and fault isolation of all signal relays in the switching units.


Three new switches provide commercially available solutions to an important part of the ATE system—connecting the system to the unit-under-test (UUT).



HP 9412A Modular Switch provides high-density, multi-function switching of signals up to 10 MHz. The built-in interface panel eliminates the massive cabling normally found in ATE switching configurations and significantly improves signal performance. The 9412A accommodates five types of switch cards in any combination up to a total of 25 cards.



**HP 9413A VHF Switch** provides flexible high-frequency switching of pulse and video signals up to 500 MHz. The unit accommodates up to 12 coaxial switch modules of two types: dual  $1 \times 4$  or single  $1 \times 8$ .



HP 9414A Matrix Switch provides maximum flexibility for high-density, high-performance switching, allowing any UUT pin to be switched to any instrument in the ATE system. The 16-input Matrix Switch can be configured in 30-pin increments (UUT pins) up to 120 pins, expandable to 240 pins.

New automatic test systems are also available from Hewlett-Packard complete with HP-IB hardware and new software. The system controller is the HP 1000 with HP's powerful Real Time Executive (RTE) operating system. RTE allows concurrent program preparation and testing. Comprehensive test program languages are available including BASIC, FORTRAN IV and TESTAID-III for digital testing.

For more information on individual HP-IB switch products and the new generation HP automatic test system, check L on the HP Reply Card.

# Current tracing: a better way to detect supply to ground shorts

You've got a tight schedule to meet and those five bad boards on your desk can make the difference. Unfortunately, every one of them has a power supply to ground short and you don't have the time it takes to repair them. Each of the boards is valuable, so you don't want to scrap them, but it would take a couple of hours to fix each one and when you were finished, chances are the circuit traces would be damaged, IC legs cut and resoldered, or worse.


Well, there's a better way—current tracing. This technique allows you to find  $V_{\rm cc}$  to ground shorts in minutes, using two powerful hand-held IC troubleshooters from HP.

One, the 546A Logic Pulser, is connected between supply and ground on the unpowered faulty board and pushbutton programmed to output a 100 Hz pulse stream. The pulser delivers 650 mA current pulses that are easy to trace right to the one faulty point on the board.

The 547A Current Tracer allows you to find faults based on one simple principle: current flows to the lowest impedance point in a circuit, in this case a short between  $V_{\rm cc}$  and ground. So, just adjust the sensitivity control so the tracer's lamp is about half-brilliance and follow current pulses to the fault.

No board scrapping, no trace cutting, no unnecessary unsoldering and still the boards are repaired in a fraction of the time possible using any other method.

For more information, check C on the HP Reply Card.



HP's 546A Pulser and 547A Tracer help locate logic damage to the circuit under test.

#### Sliding load for 3.5mm coaxial lines operates from 2.0 to 26.5 GHz

For impedance measurements in coaxial transmission lines, the ultimate standard for a matched line is a sliding load. By sliding the load element along the line, its own small reflection effect can be eliminated.

Since the new APC-3.5 connector now permits design activity in 3.5 mm coaxial lines above 18 GHz, HP's new 911C sliding load will provide for more accurate measurements from 2.0 to 26.5 GHz.

The 911C features interchangeable APC-3.5 fittings—either male or female connectors may be checked. For minimum discontinuity, the center con-

ductor slides and locks. The movable terminating element has 5.5 cm travel—greater than  $\lambda/4$  at the lowest operating frequency.

The connector and transmission line reflection coefficient for the female configuration is  $<.02 + .001 \times f$  (where f is frequency in GHz) 2 to 26.5 GHz. The male version is <.02 across the full band. For the load element itself, the maximum reflection coefficient is <0.01 from 2 to 10 GHz and <0.035 from 10 to 26.5 GHz.


For details, check D on the HP Reply Card.



New sliding load provides well matched termination for APC-3.5 component test.

#### HEWLETT-PACKARD COMPONENT NEWS

#### New displays with high light output



New large junction seven-segment displays are categorized for luminous intensity.

Now available from Hewlett-Packard are new, high-efficiency red, and yellow displays designed for use in high light ambient conditions.

Output is typically 2300 millicandellas per segment at 100 mA peak, 20 mA average. These displays are designed for use in instruments, airplane cockpits, weighing scales and point of sale terminals.

The seven-segment displays offer a wide viewing angle and are easily mounted on P.C. boards or sockets. DIP spacing is the industry standard 7.62 mm

(0.3 in.) on 2.54 mm (0.1 in.) centers.

The HDSP-3530/4030 are 7.62 mm (0.3 in) high while the HDSP-3730/4130 are 10.9 mm (0.43 in). These devices utilize high efficiency LED chips made from GaAsP on a transparent GaP substrate. The LEDs have a large area P-N junction permitting higher peak currents.

For more specifications, check I on the HP Reply Card.

#### HP publishes optoelectronics applications manual

Practical solutions to the most common applications problems of optoelectronic devices are fully analyzed in Hewlett-Packard's *Optoelectronics Applications Manual*, one of the first books on these versatile design tools from a leading firm in the field.


The Manual covers such subjects as photometry/radiometry, contrast enhancement in visible displays, and reliability of optoelectronic components and their mechanical handling.

Designed both as a practical guide to the use of optoelectronic devices and as a foundation for the development of new design ideas, this volume demonstrates the broad potential for these components that exists in systems being designed today.

Of special interest to experienced designers is the *Manual's* treatment of CTR degradation, a controversial and frequently misunderstood subject among users of optically coupled isolators.

Members of the applications engineering staff of the Hewlett-Packard Optoelectronics Division were involved in the preparation of the *Manual*, published by McGraw-Hill.

Copies are available from your HP franchised distributor.



#### Flexible synthesizer uses $\mu P$ for FDM testing and other applications requiring precision signal source

The new 200 Hz to 80 MHz HP 3335A Synthesizer/Level Generator is designed for frequency division multiplex (FDM) testing as well as traditional synthesizer applications such as testing filters, mixers, phase detectors, attenuators or modulators.

With a resolution of 0.001 Hz and amplitude flatness of 0.15 dB over its entire range, the 3335A is useful for applications including testing of low-density carrier, radio baseband, high density cable carrier, in R & D, and in production tests. For automated instrumentation systems, the unit includes the HP Interface Bus as standard.

Microprocessor control provides flexibility in this moderate cost, high resolution synthesizer. In the sweep mode, the microprocessor computes the individual frequencies on each side of the center frequency and then controls automatic, manual and single sweep modes. At turnon, the  $\mu P$  sets the instrument to 1 MHz and minimum amplitude so output loads will not be damaged.

Up to ten different instrument settings including frequency, amplitude, sweep width and center frequency may be stored in the ten memory registers for later recall—useful in a production environment where a specific list of repetitive test functions must be performed.



New microprocessor-based frequency synthesizer is used in applications wherever a high resolution, precision amplitude test signal is needed.


The 3335A synthesizer may be used as a tracking generator for the HP 3745A/B Selective Level Measuring Set for fast, accurate loop-back measurements and for end-to-end measurements. For unattended performance checks of systems on-line or for offset tracking of systems off-line, the generator/receiver system may be controlled via the HP Interface Bus.

Standard version of the 3335A synthesizer provides 50 and 75-ohm unbalanced outputs. Other options accommodate North American and CCITT communications applications.

For additional information on the synthesizer, check G on the HP Reply Card. For details on the 3745A/B SLMS, check O on the HP Reply Card.

East-4 Choke Cherry Road, Rockville, MD 20850, Ph. (301) 948-6370. South-P.O. Box 10505, Atlanta, GA 30348. Ph. (404) 434-4000. Midwest-5201 Tollview Dr., Rolling Meadows, IL 60008. Ph. (312) 255-9800. West-3939 Lankershim Blvd, North Hollywood, CA 91604, Ph. (213) 877-1282. Europe-Central Mailing Depot., P.O. Box 529, Amstelveen-1134, Netherlands, Ph. (020) 47 20 21 Japan-Yokogawa-Hewlett-Packard Ltd., Ohashi Bldg., 1-59-1 Yoyogi, Shibuya-ku, Tokyo 151, Ph. 03-370-2281/92.





New product information from


**HEWLETT-PACKARD** 

Editor: Iona M. Smith

**Editorial Offices:** 

1507 Page Mill Road Palo Alto, California, 94304 U.S.A.

# PIC 1650



# Gl's 8-bit microcomputer...

in a single low cost chip.

Low price is one of many ways you can save with the PIC 1650—Programmable Intelligent Computer. GI's bit-oriented chip also saves on external components, packaging and design time to help you get your product to market faster at lower cost.

There's a programmable 512 by 12-bit ROM on the chip along with four sets of eight TTL compatible input/output lines. Use the I/O as 8-bit data paths or manipulate single bits using a single instruction. The 32 x 8 register file meets RAM requirements and the on-chip oscillator takes

care of timing. All you need for power is a 5-volt supply.

Whatever your stand-alone controller objective may be, PIC 1650 will do it. You can, for example, scan a keyboard, drive a display, control a vending machine or even regulate traffic. And if you need even lower cost, we have the PIC 1655 ... or for higher performance, we have the PIC 1670.

You can depend on GI Microelectronics for full software, hardware and applications support. There are cross assembler/simulator programs and an in-circuit emulation system for efficient program verification and the added flexibility of RAM programming. Write or call General Instrument Microelectronics, 600 West John Street, Hicksville, New York 11802, Telephone (516) 733-3107.

We help you compete.

GENERAL INSTRUMENT CORPORATION MICROELECTRONICS







We designed them that way. Because a mass termination connector should help you save time and effort before, during and after assembly.

Their unique folded contact design, with dual camming and latching ears, assures you of four-point electrical contact and mechanical grip for each conductor. And that means superior overall reliability and protection. In addition, these fork-type contacts make it especially easy to visually inspect each termination before the cover is applied.

And even after the cover is on, each contact can still be visually checked for proper locking and latching. Because every AMP Latch cover has a built-in inspection port over each termination. This also permits electrical testing without cover removal, saving additional production time. And if repair ever is necessary, we've made that easier, too, by designing special hand and pen tools.


There are more reasons why you should choose AMP Latch connectors such as quick, easy terminating with the AMP shuttle tool, and the broad variety of pin headers and connectors. You also get AMP backup . . . expert design and production help that's yours for the asking from AMP connector engineers.

Why not contact Customer Service, at (717) 564-0100 for complete details on the AMP Latch connector line? Or write us direct. AMP Incorporated, Harrisburg, PA 17105.


AMP has a better way.



Circle 29 on reader service card







The new Commander comes in one, two and three-bay styles, each with a choice of various rear compartments, cabinets, drawers and shelves. It's the work station that gives you the options to choose what you need for storage or housing equipment. Comes in 19 standard colors.

For a full-color brochure on the Commander and Concorde, phone Bud toll free: (800) 321-1764; in Ohio, (800) 362-2265.



Complete manufacturing facilities at two locations:



Bud Industries, Inc. 4605 East 355th Street Willoughby, Ohio 44094

Bud West, Inc. 3838 North 36th Avenue Phoenix, Arizona 85019


Circle 30 on reader service card

#### CONCORDE SERIES

A new contemporarystyled rack from Bud! Designed as a companion piece for the Commander; yet, can stand on its own in any system.

# 1977 Answer Book. It makes your job easier. \$25.

Who makes what? Over 4000 products, more than 5000 manufacturers with their local contracts and distributors, directory of trade names and catalogs, post-paid inquiry cards for 5-second ordering of current catalogs.



#### **Meetings**

Electro-Time/77 U. S.—Design and Manufacture of Electronic Watches, International Society for Hybrid Microelectronics, Florida Chapter, Marco Beach Hotel, Marco Island, Fla., Dec. 1–2.

Semiconductor Interface Specialists Conference, IEEE, Carillon Hotel, Miami Beach, Dec. 1 – 3.

Chicago Fall Conference on Consumer Electronics, IEEE, Ramada-O'Hare Inn, Des Plaines, Ill., Dec. 5-6.

International Electron Devices Meeting, IEEE, Washington Hilton Hotel, Washington, D. C., Dec. 5-7.

National Telecommunications Conference, IEEE, Marriott Hotel, Los Angeles, Dec. 5 – 7.

**1977** Winter Simulation Conference, IEEE, National Bureau of Standards, Gaithersburg, Md., Dec. 5 – 7.

Miami International Conference on Alternative Energy Sources, U.S. Energy Research and Development Administration et al., Fountainebleau Hotel, Miami Beach, Dec. 5-7.

Computer Networks Symposium, National Bureau of Standards, Gaithersburg, Md., Dec. 15.

1978 Winter Consumer Electronics Show, Electronic Industries Association, Las Vegas Convention Center and Hilton Hotel, Las Vegas, Jan. 5-8.

Conference on Integrated and Guided Wave Optics, IEEE, Salt Lake Hilton, Salt Lake City, Utah, Jan. 16-18.


Reliability and Maintainability Conference, IEEE, Biltmore Hotel, Los Angeles, Jan. 24–26.

Power Engineering Society Winter Meeting, IEEE, Statler Hilton Hotel, New York, Jan. 29 – Feb. 3.

International Solid State Circuits Conference, IEEE, San Francisco Hilton, San Francisco, Feb. 15 – 17.

#### **SSR UPDATE**

## Our International Connection



The European market demanded a high voltage AC solid state relay with a challenging combination of performance features such as:

- 3750VRMS optical input/output isolation to meet VDE and IEC specs
- 800 volts peak blocking voltage for high overvoltage transient immunity
- 480VRMS output voltage rating for reliable 3-phase switching
- 200V/μsec min. off-state dv/dt rating
- Steady state load current ratings up to 40 Amps

We met that challenge with our all-new 621 Series. Fact is, Teledyne designed it from the ground up to achieve all of the above-from pc board layout with wide tracking distances for high voltage isolation to a highly functional case configuration with deep recessed terminals. Other features include logic compatible input drive circuitry, and zero voltage turn-on to reduce EMI.

For complete specification data, contact your local Teledyne Relays sales office. You'll find we have the experience, products, and technical support to meet all your SSR needs.



#### OTHER TELEDYNE AC SSRs

601 Series\*

5 and 10A (to 600V peak). Optically isolated, zero voltage turn-on. Screw terminals, quick disconnects, and pcb pin options.

B. 611 Series\*
10, 15, 25 and 40A (to 600V peak).
Optically isolated, zero voltage
turn-on. Dual purpose screw/quick
disconnect terminals.

Low profile (0.5" max.) pc board SSRs. Output rating 3A, up to 600V peak. Optically isolated, zero voltage turn-on.

D. 671 Series
I/O Converter Modules. Special
purpose SSRs for use in
programmable controllers, machine tool controls, etc. Mounting panel available.

SerenDIP® Series\*

TO-116 DIP package. Output rating 1A/280VRMS. Logic compatible 3.8 to 10VDC input.

High voltage transient suppressors designed specifically for use with all Teledyne AC SSRs.

\*UL recognized/CSA certified.

#### TELEDYNE RELAYS

3155 West El Segundo Boulevard, Hawthorne, California 90250 Telephone (213) 973-4545









Talk about prices...
It's still 1973

An example: Our Model B5-3 was \$24.95 in 1973. Four years later, during a period when "across-the-board" price increases were routine,

Power-One's Model B5-3 is still \$24.95! The same is true with practically all of our standard models.

Amazingly, Power-One open frames were price competitive in '73. Think what they are today.

Genuine D

Power-One's 83 different models easily represent the broadest selection of open frame power supplies in the industry. And these are "off-the-shelf" standards — ready for delivery. Ready when you need them.




#### Talk about shipments... Over 250,000 to date

Power-One shipped its first open frame power supply in May, 1973. We've now crossed the quarter-million

mark. Over 100,000 units were delivered last year alone. That makes Power-One the largest producer of open frame power supplies in the world.

What does this mean to you? Only that a great number of individuals and companies have found continuing and complete satisfaction in our products.

We think you will, too.



We've not only outdistanced our competitors, we've even dethroned Heinz as the king of variety.





#### Talk about facilities...60,000 square feet of open frames

Our recent move to the largest complex dedicated solely to the manufacture of open frames has been geared to a single objective — that of making the best product of its kind even better.

Through proprietary production techniques, combined with the finest, most modern equipment available today, our new, enlarged facilities will enable us to continue to hold down costs...while ever improving quality, delivery, and service.

So next time you're in the area, stop by. See for yourself who we are, what we are, and most important, why we're the world's largest manufacturer of open frame power supplies.

#### Talk about reliability... We burn them in so they don't burn out

Every single unit that bears the Power-One label undergoes a full functional test, followed by a minimum 2-hour burn-in plus a final full functional test. We repeat . . . every single unit!

We consider this tough burn-in testing one of the key factors in our company's growth. We know of no other company that conducts more than a single operational test on their standard production-line units. Consequently, we know of no other open frames that match up to Power-One's for long life and overall reliability.

#### Talk about catalogs... Get our new '78 edition now

It's all new, and all inclusive. Complete specifications on every standard model, along with dimensional mounting drawings, product photos and descriptions, prices and ordering information. Even customs and modified standards are covered.

So please, don't delay. Get your free copy now. Circle the reader's service number or, for faster delivery,

RUSH
me a copy
of your new
'78 edition catalog.

Name

Title

Company

Address

City

Phone

Phone

Title

State

Zip

Phone

"Think about


# POUR-OIE.

D.C. POWER SUPPLIES

Power One Drive, Camarillo, California 93010 • Phone: (805) 484-2806 • TWX: 910-336-1297

# A-B quality trimmers for the same price as "B" trimmers.

Accept nothing less than Allen-Bradley quality in trimmers, especially when it doesn't cost you any more. The real decision is whether to use our Type 90 or Type D. Both are cermet, single-turn with a choice of top, side or through-the-board adjustment. We have what you need; our distributors have it when your need is now. Ask for Publication 5242 (Type 90) and 5240 (Type D).





## Quality in the best tradition.



#### Electronics newsletter\_

# HP producing daylight LEDs for outdoor display

The light-emitting diode is coming out of the dark to compete with liquid-crystal, incandescent, gas-discharge, and other display technologies for daylight applications. That is the view of Hewlett-Packard Co., which is selling discrete red and yellow LEDs that can be viewed in direct sunlight or in ambient lighting as bright as 10,000 foot-candles. To get that performance, HP has developed a high-contrast gray package and high-efficiency chips with large, active pn junctions.

For direct viewing in sunlight, however, the customer would use a commercially available acrylic neutral-density gray filter to block out the sun's rays. The seven-segment displays are aimed at automotive, avionic, instrumentation, and measurement markets.

# Analogic to sell I/O subsystems to end users . . .

Analogic Corp., which has been quietly supplying analog input/output subsystems on an OEM basis to such firms as Intel, Zilog, and Texas Instruments, is about to enter the end-user market with its own series of I/O subsystems for the TI TM-990 16-bit microcomputer family. The Wakefield, Mass., company is not saying much in advance of a formal introduction Nov. 30., but the input board is believed to be built around the firm's MP 6812 modular data-acquisition system. The output board is expected to use Analogic's MP 1480 industrial digital-to-analog converter module, offering 12 bits of current or voltage output.

### . . . as Analog Devices races for same market

Meanwhile, Analog Devices Inc., in Norwood, Mass., is racing to have similar I/O subsystems ready for the TM-990/100 next month instead of next February as planned earlier [Electronics, Sept. 15, p. 33]. There are three boards in the Analog Devices line. The RTI-1240 analog input board has up to 32 single-ended or 16 differential channels. The RTI-1241 offers those same channels, the same optional resistor programmable-gain instrumentation amplifier, and two 12-bit d-a converters and optional 4-to-20-ma current loop outputs. The third board, the RTI-1242, includes eight software-programmable high-current logic driver outputs and eight analog output channels using 12-bit d-a converters. Only the 1242 will be ready in December; the others, in January.

#### Japanese VLSI chief to speak on first day of IEDM conclave

Engineers at the International Electron Devices Meeting in Washington, D. C., Dec. 5 to 8, will be treated to something besides the sessions on circuit and device technology that are the meat of the conference. The special feature: a scheduled appearance on Dec. 5 of Yasuo Tarui, head of Japan's VLSI laboratory. Tarui, one of the most knowledgeable semiconductor specialists in Japan, will offer a comprehensive view of Japanese semiconductor technology, concentrating on present and future large-scale and very-large-scale integration techniques.

#### Bay State group aims to fight taxes, fill jobs

Concerned with problems they say are inhibiting their growth in the state, executives of 37 high-technology companies have formed the Massachusetts High Technology Council to try to solve those problems. At least 20 member companies are from the electronics industries, with Ray Stata, chairman and president of Analog Devices, serving as council president.

Council estimates for 1983 show that for every job created in Massachusetts by high-technology companies, one will be created outside the state

#### Electronics newsletter

by those same companies. Stata says the council will work with government and educational institutions to better match the skills of the labor force with the needs of member companies and to slow state and local spending to relieve the individual tax burden.

#### MicroNova enhanced for communications market push

In an effort to sell its microNova microcomputers in the communications and industrial markets, Data General Corp. is announcing 11 hardware products and 7 software packages. Most of the software is from the firm's minicomputer line. Communications enhancements include control and multiplexing boards that, together with control and emulation software, will allow the microNova to communicate with IBM-compatible systems over various high-speed protocols.

# Subsystem ATE market to reach \$162 million by 1980

The automatic test equipment market for subsystem testing is expected to grow from \$78 million last year to \$162 million in 1980, a compound annual growth rate of over 20%, forecasts Prime Data Inc. of San Jose, Calif. In its new 201-page report, "Subsystem Testing," the market-research firm predicts U. S. manufacturers' shipments of ATE for circuit-board testing will more than double from \$62 million in 1976 to \$135 million in 1980, with hybrid testers accounting for \$69 million.

# New design center developing custom 16-bit processor

Perkin-Elmer Corp.'s Data Systems Group in Tinton Falls, N. J., is developing a custom 16-bit microprocessor tailored to the needs of its Interdata (small computers), Wangco (mass storage devices), and Terminals (video displays and printers) divisions. The n-mos processor is expected to be available in 1978, as its design and architecture are already defined. Circuit detail and implementation of the design are under way at the group's new LSI Design Center, the nucleus of which is the former Precision Micro Design Inc. of Scotts Valley, Calif., acquired last month.

#### Multiplier chip from Raytheon to be accurate to 0.1%

Monolithic analog multipliers are generally accurate to within only 1% or so. But Raytheon Semiconductor of Mountain View, Calif., using proprietary circuit techniques, is about to introduce a chip that compensates for nonlinearity, holding it to as little as 0.1%, which is as good as that offered by many modular devices. Priced at \$6.50 in hundreds, the upcoming RC4200 is targeted for use in low-distortion audio modulation circuits, voltage-controlled active filters, and precision oscillators. It is a current, rather than a voltage, device and produces an output that is the product of two input currents divided by a third.

#### Addenda

Look for Allen-Bradley Co. to move its domestic components manufacturing from Milwaukee to El Paso and San Antonio, Texas, over the next three years. The reason: none of its competitors' resistor plants is in a big industrial city, and it figures it can save about 60% on labor by phasing out over 1,200 Milwaukee jobs. . . . RCA Corp.'s major businesses are all profitable except for RCA American Communications Inc. in Piscataway, N.J., says president Edgar H. Griffiths. But, he adds, Americom "probably will cross into profitability in 1979."

### While others promise to improve 2901 Bit-Slice performance, Signetics delivers the promise.

#### Introducing the Signetics 2901-1. It's 30% faster than the 2901, and distributors have it now.

When the 2901 microprocessor slice gained wide industry acceptance, Signetics began an intensive program to improve bipolar bit-slice performance.

That effort has resulted in the 2901-1, the best 4-bit slice around.

Signetics 2901-1 does everything the 2901 does, but does it better and faster. With a typical cycle time of 65 nsec, the 2901-1 offers the speed and microinstruction flexibility to handle many applications.

It's great for emulating minicomputers—or for designing high-performance controllers for tape/disk systems and communications networks. And it's available today in large production volume.

Full 2901-1 Product Support.

There are many good reasons to select the Signetics bit-slice

for your high-performance application. Aside from the fact that the part is very reliable, available today and 30% faster than the 2901 - Signetics provides unmatched product support.

Check the table below for some of the key ICs supporting the 2901-1. In it you'll find cost-saving LSI peripherals like our 8X02 Control Store Sequencer. Generating a 10-bit address for microprogram memory sequencing, this single IC greatly simplifies bitslice implementation. Soon, other exciting ICs will be added to the 8X02 Sequencer family.

Signetics offers the most complete selection of Bipolar Memory ICs, including 24 PROMs and 22 RAMs. You can also choose from more than 150 standards in Schottky and Low-Power Schottky.

A	vailable Now	Available Now		
8X02*	Control Store Sequencer	82S09*	Bipolar 64x9 RAM	
82S115*	Bipolar PROM 512x8	82S16*	Bipolar 256x1 RAM	
82\$140/141*	Bipolar PROM 512x8	8T26A*	Inverting Bipolar Quad Bus	
82\$146/147*	Bipolar PROM 512x8 (Fast)		Transceiver	
82\$136/137*	Bipolar PROM 1024x4	8T28*	Non-inverting Bipolar Quad	
82\$180/181*	Bipolar PROM 1024x8		Bus Transceiver	
82S184/185*	Bipolar PROM 2048x4	8T97*	Non-inverting Bipolar Hex	
82\$190/191	Bipolar PROM 2048x8		Tri State Buffers	
82S100/101*	Bipolar Field Programmable	8T98*	Inverting Bipolar Hex	
	Logic Array		Tri State Buffers	
82\$102/103	Bipolar Field Programmable	74S182	Look-Ahead Carry Block	
	Gate Array	3001*	Microprogram Control Unit	

\*Second source available


Microprogramming Made Easier. With our Microassembler, you get software support which makes it easier to write microprograms. This powerful design

tool frees you from the task of hand-coding binary ones and zeroes. Instead, it lets you tailor the Microassembler to the specific needs of your system.

Besides producing PROM programming tapes, our Microassembler also generates listings that can serve as your microprogram's primary documentation.

Of course, the 2901-1 is fully backed by Signetics applications engineers, both at the factory and in the field. Their in-depth microprocessor knowledge can work to extend your design resources.

The Signetics 2901-1 microprocessor slice: reliable - and backed by peripheral circuits, software support and knowledgeable applications engineers. Count on it for complete design flexibility now-and in the future. Available today! For details, use the coupon below, or contact your local Signetics distributor.






Signetics Corporation 811 East Arques Avenue Sunnyvale, California 94086

Telephone 408/739-7700

P.O. Box 9052, S  Please send 2901-	nation Services, 811 E. Arques Ave., Sunnyvale, CA 94086 -1 data file. ht: have an applications engineer			
	ext			
Name	Title			
	Division			
Address	MS			
City	State Zip			
Please also send lite support circuits:	erature for the following 2901-1 key EM1124			

# Stop wasting space and dollars.



### Use our faster 8K ROM.

Monolithic Memories' new 6280-2 bipolar 8K ROM costs \$10 in volume and guarantees 55nS TAA.

The 6275-1 bipolar 16K ROM, with 110nS access time, gives you the best speed/density product going.

You're no longer forced to specify a 4K ROM to get access speeds below 70nS. Our new 6280-2 1024x8 bit ROM ends that with 55nS maximum access time in commercial grade models, or 70nS access in MIL-temp models. Slower versions (6280-1 at 100nS max. TAA) are available in volume at prices down to \$8.50.

For higher density applications we've got 9K (6260-1) and 10K (6255-1) ROMs, both with 100nS access.


Or for the ultimate in bipolar ROM density, look into our 6275-1 bipolar 16K ROM, the world's fastest at 110nS access. All are available in open collector or tri-state outputs and in commercial or MIL-temp ranges.

#### Flexible design with bipolar speed.

Already working with a 20-pin 4K ROM? That's okay.

Our 6280-2 is available in 20-pin, 22 or 24-pin packages, with pinouts designed as drop-in replacement for whatever you're using. And the 22 and 24-

pin versions have compatible PROMs available off the shelf. Add to this the inherent speed and simplicity of Monolithic Memories' bipolar technology for a total design package you can't beat.



#### Design in now, plug in 5 weeks.

Delivery on most orders is five weeks from receipt of your bit pattern. Masking charge is only \$750 per pattern in minimum quantities of 100 pieces.

#### From the undisputed world leader in bipolar memories.

Every year since its incorporation in 1970, Monolithic Memories has delivered more bipolar read only memory than any other company in the world. We introduced the first 1K PROM, the first 2K PROM, the first 4K PROM and the first 8K PROM. Look for much more from Monolithic Memories. Call (408) 739-3535 TWX 910-339-9229 or write 1165 East Arques Avenue, Sunnyvale, CA 94086.

#### For technical assistance see your Monolithic Memories' area representative:

ALABAMA
Huntavilie
Rep. inc.
(205) 881-9270
ARIZONA
Scottsdele
Summit Sales
(602) 994-4887
CALIFORNIA
Culver City
Bestronics
(213) 870-919
Mountain View
Thresum Associates
(415) 985-9180
San Diego
Littlefield & Smith
City
Wassociates
(415) 985-9180
COLORADO
Wheatridge
Waugaman Associates
(303) 423-1920
CONNECTICUT
North Haven
Comp Rep Associates
(203) 239-976
CONNECTICUT
North Haven
Comp Rep Associates
(203) 239-976
CONNECTICUT
Connecti

Clearwater Dyne-A-Mark (813) 441-4702 Fort Lauderdale Dyne-A-Mark (305) 771-6501 GEORGIA Tucker

Tucker Rep. Inc. (404) 938-4358 ILLINOIS Rolling Meadows Sumer (312) 394-4900

INDIANA Indianapolis Electro Reps (317) 255-4147

IOWA Cedar Rapids S & O Sales (319) 393-1845 KANSAS

KANSAS Olathe Rush and West (913) 764-2700 MARYLAND Baltimore Monolithic Sales (301) 296-2444

(301) 296-2444
Rockville
Monolithic Sales
(301) 340-2130
MASSACHUSETTS

Needham Helghts
Comp Rep Associate:
(617) 444-2484
MICHIGAN

MICHIGAN Grosse Point Greiner Associates (313) 499-0188 MINNESOTA Minneapolla Nortec Sales (612) 835-7414 MISSOURI Ballwin Rush and West (314) 394-7271 NEW JERSEY Teaneck R. T. Reid Assoc. (201) 692-0200

(201) 692-0200
NEW YORK
Rochester
L-Mar Associates
(716) 328-5240
Syracuse
L-Mar Associates
(315) 437-7779
NORTH CAROLINA

NORTH CAROLINA Raleigh Rep. Inc. (919) 851-3007 OHIO

(919) 851-3007
OHIO
Clincinnati
Makin Associates
(513) 871-2242
Mentor
Makin Associates
(216) 464-4330
OREGON
Portland
N. W. Marketing
(503) 297-2581

(503) 297-2581
PENNSYLVANIA
Oreland
CMS Marketing
(215) 885-5106
TENNESSEE
Jefferson City

TENNESSEE
Jefferson City
Rep. Inc.
(615) 475-4105
TEXAS

(214) 661-9400

UTAH

Salt Lake City

Waugaman Associates

Waugaman Associates (801) 363-0275 WASHINGTON Bellevue Northwest Marketing

Northwest Marketing (206) 455-5846 WISCONSIN Milwaukee Sumer (414) 259-9060

CANADA ONTARIO Milton Cantec (416) 624-9696 OTTAWA

Cantec (613) 225-0363 QUEBEC Pierre Ponds Cantec (514) 620-3121

Monolithic Memories

Bipolar is our business.

# Don't waste money and ruin PROMs. Move up to a first-rate programmer.

#### What defines a first-rate programmer?

A first-rate programmer is easy to use, safe (U.L. listed), reliable, backed with a long-term warranty, and flexible enough to handle advances in PROM technology, a combination you get only with a Pro-Log programmer.

#### Our systems take the mistakes out of programming.

Our Series 90 PROM Programmer walks you through the programming process so there's less chance for misprogramming. Separate sockets for master and copy PROMs make it impossible to accidently destroy a valuable

#### Vendor-approved programming, full portability, free 2-year warranty.

Using vendor-approved PROM personality modules, Pro-Log's field-proven programmers program every major MOS and bipolar PROM. They also program generic PROM families and do gang programming.

They weigh less than 20 pounds so they go where you need them. And they're backed by the longest warranty in the industry, 2 full years parts and labor.

#### A first-rate programmer is economical, too.

A Series 90 master control unit costs only \$1,800. A Series 92 PROM Duplicator master control unit costs only \$1,145. Single PROM personality modules cost from \$325 to \$450. Generic modules start at \$350. Gang modules which program 8 PROMs simultaneously are \$895. All modules come U.L. listed and fit both the Series 90 and the Series 92. Options include CMOS RAM buffer (to 4K bytes), RS-232 (terminal or modem) interface, TTY, parallel interfaces, paper tape reader, U.L. listed erase light, checksum option, and Auto-baud.\*

#### Find out what else a truly firstrate programmer has to offer.

Call or write for a free pamphlet giving you comparison 2411 Garden Road, Monterey, CA 93940. Phone (408) 372-4593.



# Two heads give minifloppy on-line 0.4-megabyte store

Shugart drive unit reads both sides of 51/4-inch disk without flipping it; other makers likely to follow suit

Two heads are certainly better than one for the midget minifloppy disks, since a read/write head for each side of the disk means twice the storage capacity. And for Shugart Associates Inc., it means nearly a half megabyte of storage on a 51/4-inch-diameter flexible disk—not bad for what started out last year as a low-cost source of about 110 kilobytes of memory for word processors.

"Users want more on-line capacity," says W. Ferrell Sanders, vice president of marketing at Shugart in Sunnyvale, Calif. "Since we put two heads on our standard [8-in.] floppy drive in April, people have been asking when we would do it on the minifloppy." The miniature disk's unformatted capacity with double-density encoding is 437.5 kilobytes. Formatting reduces this capacity to about 320 kilobytes.

No flipping. Merely using both sides of the disk is not new. Information Terminals Corp., the Sunnyvale, Calif., media maker, sells its two-sided Flippy minidiskette to drive makers like Wangco Inc. and Pertec Computer Corp.'s icom division. But the user must flip the disk over, like a phonograph record.

But "having a lot of storage is not as important as having it on line," maintains George H. Sollman, director of product management at Shugart. "People don't want to flip a disk over, any more than they want to slip a new one in."


Others agree that customers are hungry for on-line storage. Says Ray Brooke, flexible-disk program manager in Pertec's Microsystems division, Woodland Hills, Calif., "We have to promise all new customers that our forthcoming double-sided drive isn't far off." At Wangco, product marketing manager Barrie Clark is looking to go double-sided on his standard floppy the first part of next year, with the two-headed minifloppy to follow shortly after.

While Shugart can claim compatibility between its new double-sided model 450 and its older model 400—single-sided disks can be "played" on the 450—manufacturers using the

Flippy technology might have trouble. According to Sollman, by originally one-upping Shugart with 40 tracks instead of 35 on their disks for more storage, both Wangco and Pertec may have sacrificed compatibility with a double-sided future. This is because, for assembly purposes, "the heads must be offset by at least four tracks," Sollman says.

With the heads offset, the tracks must be offset too. The 40th track on the under side of the disk lies in toward the disk's center, where track 44 would be on a single-sided disk. Bit densities are the highest there, and data is not reliable enough.

The question of reliability at position 44 is not challenged. Says



**Doubling up.** Shugart's model 450 minifloppy drive records on both sides of the small diskette. Up to 437.5 kilobytes can be recorded using double-density encoding.

#### **Electronics review**

Wangco's Clark: "We plan to drop back to 35 tracks per side when we go to two heads. We're not worried about compatibility between [our older flipped] single- and [the new] doubled-sided disks; after all, data on the flip side of the disk would run backwards on a two-headed drive."

Still readable. However, Pertec's Brooke says it wants to be able to read its present 40-track diskettes. Accordingly, the head positioner in its drive will be able to travel to the 44th track position. But, counters Sollman, "the window in the [polyvinyl chloride] envelope protecting the diskettes doesn't extend far enough to allow a head to reach the 44th position; special envelopes could be made up, but if a standard

diskette was ever used, it would destroy a head's spring gimbal."

Besides simply adding another head, Shugart improved the access time of its model 450 to 25 milliseconds track to track, as opposed to the 400's 40 ms, and also reduced the error rate to one bit in 109 from 1 in 108 for recoverable errors. Shugart expects the doubled-sided drive to phase out the one-siders, since the features represent a premium of about only 25% over the cost of the single-sided drives.

The model 450 drive has a unit quantity price of \$450, while the 400 sells for \$355. Discounts to original-equipment manufacturers reduce these numbers to \$320 and \$255 in quantities of a hundred.

#### **Microprocessors**

### Microprocessor-maker Zilog offers wide choice of programming languages

With the introduction of compilers for high-level Cobol and Fortran [Electronics, October 27, p. 34], hard-charging Zilog Corp. soon will have six languages for all of its microprocessors, including the pacesetting Z-80, the upcoming Z-8 one-chip controller, and the Z-8000 16-bit machine. Next month it will announce business and scientific versions of Basic, which will be followed by two members of its own high-level family of systems-oriented languages called PLZ.

In offering a wide choice of applications-oriented and system-implementation languages, the high-flying Cupertino, Calif., company is putting more pressure on its microprocessor competitors. The reason, for the move, declares Ralph K. Ungermann, executive vice president, is that "high-level languages will be absolutely essential in the next few years" as microcomputers get designed into more complex systems. "If you don't offer them, you'll be locked out of the market."

He adds that Zilog is going to high-level languages because in any microcomputer system, software amounts to most of the cost. A high-level language lets a user cut those costs, he says. Thus, Zilog, as a soft-ware-oriented chip maker, believes it has an edge. But its competitors are following suit. Intel Corp., for one, is about to unveil a Fortran compiler to add to its PL/M applications-oriented language for its microcomputers and could have other languages on the way.

Most microprocessor companies offer only low-level assembly languages that merely instruct the processor through routing and branching routines, with no block structuring. These inflexible programs cannot cope with increasingly sophisticated applications.

Program arsenal. In the compilers for block-structured, high-level languages, Zilog presents the applications engineer with an arsenal of applications-oriented programs. But even these "solve only half the problem, because many systems engineers want to write their own software," Ungermann explains. "You have to have a system-implementation language—a high-level language for operating systems."

Zilog thinks that the PLZ family meets the three basic criteria it has established for such a system-implementation language for microprocessors. "You have to get into the architecture of the machine," Ungermann explains. "You have to deal with interrupts; you have to have the ability to write inside the machine and write in a high-level language." Secondly, the language has to generate very efficient code, because microcomputers have limited address capability. Finally, the compiler must be simple to implement, since a microprocessor-based system has a limited memory.

Characteristics. Such systems languages must also have high-level structures, instead of the routing and branching of assembly languages, says Charlie Bass, software department technical director. For PLZ, Zilog aimed at three structural characteristics: how to declare the data, how to control the program flow, and how to manipulate data. The first two characteristics are handled by a specially devised syntax common to all the PLZ languages in the family, Bass adds. Only the third will differ from the other programs in the family.

The first two family members that Zilog has put together are the PLZ/ASM assembly language and the PLZ/SYS systems language. Due next year from the semiconductor maker are one for dynamic allocation of data for large list-processing applications, one for elaborate mathematics for scientific applications and one for text processing. Since the PLZ/ASM is an assembly language, "you have the full power of the Z-80 available to you," Bass says.

The common syntax among the PLZ family programs should be easy for anyone familiar with any Algollike language, such as Pascal or PL-1, he continues, and "I can teach them within one hour." The entire grammar for the common syntax fills only two 8½-by-11-inch pages. The important thing is that the user "can translate that syntax onto the machine with no loss of efficiency," Bass says.

#### **Microprocessors**


### Motorola promises powerful one-chip

Semiconductor makers have been quick to turn their microprocessor development efforts toward the aspect of the business they like best: churning out high volumes of low-cost single-chip parts. Motorola Inc., however, has taken its time. While its new MC6801 will be a late entry in the one-chip microcomputer derby [Electronics, Sept. 29, p. 69], it should be the most powerful one yet.

To be available in samples in July, 1978, the Motorola device is designed to combine most of the functions of the six-chip-minimum MC6800 system while retaining the full software compatibility that allows it to take advantage of existing peripherals. But Motorola has added several new features that set it above its competitors as a stand-alone controller.

For example, the 6801 offers its parents' 72 instructions and sports several more, including an 8-by-8-bit hardware multiply that hints at a 16-bit internal arithmetic capability-allowing a system designer to pare his memory requirements and enhance his throughput. "We'll still offer 1.0-, 1.5-, and 2.0megahertz speeds," says Gary J. Summers, marketing manager for n-channel MOS microcomputers at the firm's Austin, Texas, facility (see p. 75), "but throughput will be substantially greater because of the new instructions."

The part also features an innovative serial input/output capability that lets it work in serial and parallel modes simultaneously. Up to 30 lines can be used for I/O when the device is configured as a stand-alone controller, or it can be expanded to address a full 8,192 bytes of additional memory. In either case, two I/O lines can be channeled back into the chip's serial I/O section. That means two 6801s can communicate using only two lines, instead of the usual 8 or 16, leaving as many as 56 lines in a paired system free for other



**Full.** Motorola's 6801 single-chip microcomputer has the 6800's processor, clock, and serial I/O functions plus 128 bytes of RAM, 1,024 bytes of ROM (twice the capacity of the 6830 ROM), 11/2 times the 6821's parallel I/O, and timer functions.

#### Motorola plans high-end microprocessor too

Motorola is not ignoring the high end of the microprocessor business—it is also readying a beefed-up version of its MC6800 system. For the new MC6809, the firm is discarding the software common to the rest of the family in favor of 85 new instructions with 255 operation codes. Source codes, however, have not changed, so that existing development tools can be used.

The 2-megahertz part, which will hang onto the 6800's 8-bit data bus, is designed around 16-bit internal processing—a technique Motorola expects will cut the operating system's memory by 40% and double its throughput. Also, the Austin, Texas, design team has increased the number of addressing modes to 16 and quadrupled register space. Other improvements include a memory-ready pin to allow the fast part to work with slow memory, a processor-busy pin, and better interrupt handling, such as fast interrupt-request and -acknowledge pins, and vectored interrupts. The transistor-transistor-logic-compatible chip, to be sampled in the third quarter of next year, will operate from a +5-volt supply and boasts an on-board clock.

input/output needs of users.

Two more lines can be used for an on-chip, 16-stage clock-timer that can measure incoming pulses in addition to performing the classic timing function. "With the extra timer line, the 6801 can respond to events as well as initiate them, a feature that could count frequencies in television tuners or revolutions on a tape deck," Summers adds.

Memory matches that of the biggest one-chippers, with 2,048 bytes of masked read-only memory on the chip. The firm has doubled the standard scratchpad random-access memory to 128 bytes. "But we don't plan to offer an erasable programmable ROM version of the 6801," Summers says. "Instead, we'll offer a companion part with erasable-PROM, RAM, timer and 1/0

#### **Electronics review**

that can be used either to emulate the 6801 or as extra memory." The microcomputer also has a standby mode that lowers power while maintaining 32 bytes of RAM.


#### Solid state

## Converters designed for microprocessors

Compatibility with microprocessors is quickly becoming the dominant requirement for data converters, as both semiconductor and hybrid manufacturers scramble to get suitable devices on the market. So it is no surprise that a half dozen 8-bit monolithic chips from Signetics Corp. feature such compatibility. A relative newcomer to the converter field, the Sunnyvale, Calif., firm disclosed its plans earlier this month at the Midcon/77 show in Chicago.

The company is not alone in developing the devices, which, with their ±0.2% accuracy, could handle many chores in medical and automotive applications, as well as others in process control and data transmission. Others working on new monolithic units include Motorola Semiconductor, National Semiconductor, Analog Devices, Precision Monolithics, Texas Instruments, and Intersil. "Microprocessor compatibility enables the converter logic to be controlled by software, minimizing the circuitry required for system operation," says Narpat Bhandari, a senior scientist in Signetics' Analog

Heading his firm's list is a pair of integrating analog-to-digital converters that are the first to use a new triple-slope conversion technique that provides inherent automatic zeroing, says Bhandari. They are also the first commercial monolithic converters built with a low-power Schottky process, a technology traditionally serving digital devices but used here to afford circuit complexity coupled with high speed. Rounding out Signetics' a-d converters is a successive-approximation unit built with the even denser linear inter-




**Monolithic.** A-d integrating converter, a, from Signetics needs only one external component. By internally raising the comparator threshold, b, the converter creates a third slope (labelled V<sub>clamp</sub> in c) that helps to zero the output automatically.

grated-injection-logic process.

In digital-to-analog converters, available the first quarter of 1978, Signetics plans to build on its recently introduced 5018, the first self-contained 8-bit d-a chip to be microprocessor compatible. There will be a current-output version and a pair of self-contained 8-bit units with extra-tight accuracy.

For interfacing directly with a microprocessor's data bus, Signetics' triple-slope a-d converter, (a) in the diagram, has buffered three-state outputs, as well as lines for such functions as signaling end of conversion and chip enabling. Moreover, it needs only one out-board part—the capacitor required for integration; voltage reference, and clock, usually added externally, are on chip.

Also saving parts that would have to be added for auto zero is the triple-slope technique. "This extra slope avoids having to switch the capacitor voltage to zero at the start of the conversion," explains Bhandari. The slope is created by clamping the inverting input of the comparator at an internally gener-



ated voltage, as shown in (b), "raising its threshold to several hundred millivolts."

Except for its initial operation, triple slope is much like the conventional dual-slope integration technique. At the start of conversion, the clamping current charges the capacitor. When the voltage reaches the clamping level, the comparator goes



The TR 502 and TR 501 tracking generators are working partners for 7L13 and 7L12 spectrum analyzers.

Make frequency response measurements on rf devices with the TR 502 and 7L13. This combination of a constant level, calibrated rf source and high performance spectrum analyzer provides you with a wide dynamic range (110 dB) and narrow resolution bandwidth (30 Hz) ideal for crystal filter or cavity measurements.

For selective frequency counter applications use the TR 502's Aux. R.F. output to drive a frequency counter.

Select and determine signal frequencies up to 1800 MHz with -128 dBm sensitivity at 30 Hz resolution bandwidth. When used with the DC 502 550 MHz Frequency Counter the spectrum display center frequency, indicated by a bright dot, is automatically counted.

In addition, the TR 502 and 7L13 form a **super-stable CW source.** The TR 502/7L13 system has 10 Hz stability in zero-span (non-swept) mode.

The TR 502 or TR 501 are powered with a TM 503 Power Module, leaving room for a DC 502 or other counter.

TR 502 Tracking Generator \$4650 (recommended for use with 7L13)

\$3900

TR 501 Tracking Generator (recommended for use with modified 7L12) TM 503 Power Module Opt 7 \$ 195 DC 502 Digital Counter Opt 7 \$1195

See the TR 502 or TR 501 work in your application. Ask for a demonstration or more information. Write: Tektronix, Inc., Box 500A, Beaverton, Oregon 97077. In Europe, write: Tektronix Limited, P.O. Box 36, St. Peter Port, Guernsey, Channel Islands.

U.S. Sales Prices F.O.B. Beaverton, Oregon 97077

\*Baseband and audio swept frequency systems are also available.
Ask for information.



#### **Electronics review**

high, the clamping current turns off, the input current turns on, and the counter starts counting.

Designated the 5030 and the 5031, the triple-slope chips can convert inputs of from 0 to 2 v in 10 milliseconds to an accuracy of within  $\pm \frac{1}{2}$  least significant bit, and they operate from a single 5-v supply. The 5030 has its on-chip reference brought out (so it may be used for ratiometric conversions), while the 5031 offers overranging. Bhandari expects Signetics to have samples in the first quarter of 1978.

The third a-d chip—the successive-approximation device—is still under development. Besides an onchip clock and reference, it will include three-state output buffers needed for direct microprocessor compatibility. It will handle inputs from 0 to 10 v, and complete a conversion in about 40 microseconds.

Signetics' current-output version of its 5018 d-a converter, the 5118, will have a high-compliance output for driving loads directly. Settling time will be under 200 nanoseconds.

Additionally, there will be a pair of microprocessor-compatible d-a converters, the 5019 and the 5119, with 9-bit accuracy, or  $\pm \frac{1}{4}$  LSB, rather than the more usual  $\pm \frac{1}{2}$  LSB.  $\square$ 


#### Industrial

### Robot sights objects on table

A small Troy, Mich., firm is gambling that there is a market for a robot that shoots craps. Basically an articulated arm and hand fastened to a table moving along two axes, the robot was the star of this month's Autofact (for automated factory) meeting in Detroit.

Auto-Place Inc. was able to get its production prototype to continuously load a cup with dice and dump them out. It could also search the playing field for the dice and report the number of spots exposed on each before picking them up and dropping them back into the cup.

The application is trivial, but the



**Armed.** Mirror above two-fingered hand of 2-ft-high Auto-Place robot projects field of view into camera atop 55-in,-long arm. Microcomputer then controls arm and hand moves.

promise is real: by outfitting a robot with a microcomputer and a pair of television cameras, Auto-Place has given a simple manipulator arm the ability to "see" what it is doing and make decisions based on what it has seen. That is an advantage that the firm hopes to parlay into the first commercial robot that can find parts on a moving conveyor. It will ship its first AP-C2 robot, as it is called, to one of Detroit's auto companies early next year.

New character. Robots, of course, have already found their niche in many monotonous or unhealthy manufacturing applications, where, programmed to go through a specific series of gripping and moving actions, they continue doing the same job. Now, "provided with a sense of 'vision,' the blind robot takes on a completely new character," says Ronald D. Potter, operations manager for the firm. "It can change its programmed sequence of motions, or its motion end points, based on the visual feedback."

The Auto-Place unit will command a hefty \$50,000. That is five times the price of the Series 50 robot that is at the heart of the system. The difference pays for two cameras, a microcomputer, servo-driven X-Y table, rotary hand, interface electronics, and software.

Solid-state camera. One General Electric TN2000 solid-state video camera is positioned above the conveyor to give the microcomputer an image of 188 by 244 picture elements, which it uses for controlling the X-Y motion that places the robot hand directly over the part. The second camera is mounted on the robot arm with the image, used to orient the robot's hand to the part, reflected to it by a mirror.

In its Detroit demonstration, Auto-Place used dice on a stationary field. The microcomputer employs simple edge-detection techniques, taking only fractions of seconds both to find the dice on the black background and orient the robot hand to the square objects it was to pick up.

# IE MEANS ATE

# We're the only ones with Field Proven Capabilities in High Speed Dynamic Testing

"The difference in software is the difference in testers."

#### **AXIOMATIC**

IE's automatic test system software is truly state of the art. More importantly, it is field proven for high speed digital/hybrid test applications.\*

#### **FEATURES**

- Computer-Aided Design Capability
- •Time-Domain Digital Circuit Simulation
- Atlas Programming Language
- On-Line Editing Capability
- •Computer Guided Digital Probe
- ·Computer Guided Analog Probe

And the hardware that works with it has also been field proven for over two years.



#### IE'S FLEXIBLE AUTOMATIC TEST SYSTEMS OFFER THE FOLLOWING FEATURES:

- REAL TIME HIGH-SPEED DIGITAL . . . for testing complex, microprocessor-based digital assemblies with multiple programmable data and strobe rates.
- REAL TIME DIGITAL INTELLIGENT PROBE... probe clip permits location of faulty components while functioning at high-speed data rates.
- REAL TIME ANALOG INTELLIGENT PROBE . . . analog probe permits location of faulty components, while unit under test is being exercised with dynamic functions.
- REAL TIME SIMULATOR . . . minimizes test programming costs and capable of simulating microprocessor assemblies with one nanosecond resolution.
- EXTENSIVE ANALOG CAPABILITY . . . stimulus and measurement devices which cover an extensive amount of analog capability are available in the IE system.
- INSTANT FIELD SERVICE . . . both hardware and software instantly serviced via telephone modem hookup. Exclusively by IE . . . matched by no one.

IE's automatic test systems are unrivaled for cost effective solutions to the most demanding test requirements. If you have complex testing requirements for digital, analog or hybrid assemblies, including microprocessor-based products, IE will define the most cost effective solutions. Write or call: Walter Mitchell, senior vice president, Instrumentation Engineering, 769 Susquehanna Avenue, Franklin Lakes, New Jersey 07417, 201-891-9300.





SOME OF OUR USERS WHO HELPED US PROVE IT ARE:

NCR · · · · · · · · · · · 8 Times
ITT 12 Times
Western Electric · · · · · · · 10 Times
Xerox · · · · · · · · · · · · 13 Times
Siemens 9 Times
RCA · · · · · · · · · · · 3 Times
Burroughs · · · · · · · · 2 Times
Hamilton Standard · · · · · · · 2 Times
Sperry Rand · · · · · · · · · 2 Times
Gould · · · · · · · · · · 2 Times



While others are talking, we're doing it.

#### **Electronics review**

The arm and hand move in seconds.

"The first camera just looks for the leading edge of the object and directs the robot arm to it," Potter says. "Then we rotate the armmounted camera about its axis to line up the edge of a die with a line of picture elements. Then the head rotates to the same angle that the camera does. This eliminates the problem of loading a complete frame of picture elements into memory and analyzing it with complex pattern recognition software."

Basic program. The firm uses an Imsai 8080 microcomputer programmed in Basic for its prototype, but will change to Intel's System 8020 microcomputer for production versions. Interface between the microcomputer and its two cameras is

confined to a single printed-circuit board that carries a potentiometerset threshold control to convert the video signals to binary ones and logic to count picture elements and scan lines, indicating to the computer where in the camera's field of view the part is located.

Besides controlling the motion of the robot and the small electric motor that rotates its orientation camera, the microcomputer can perform area-summation calculations—hinting at the inspection tasks the system can do. Earlier vision-equipped robots sold by the firm have not had the search and find capability, but have been used to pick up and inspect parts, including thermometers and timing mechanisms for munitions.

# in California makes the point: it has just one microwave circuit module instead of the three found in previous models, and it costs \$4,500 or so instead of around \$6,000.

The modules involved are essentially harmonic mixers for making a series of frequency conversions from which the unknown frequency is identified and subsequently counted. But the model 5324A counter needs only one of them to mix the unknown input with harmonic frequencies. In place of the other two, it uses a pair of digital counters and a microprocessor, which also allows the designers to throw in an amplitude-measuring capability.

Single sampler. The 5324A relies on a single thin-film microwave sampler circuit, shown in the block diagram. The sampler is driven by the unknown input signal and by the output from the sampler driver. which consists of a series of frequencies harmonically related to the instrument's main synthesizer. The output of the sampler consists of sum and difference frequencies created between the unknown input and the harmonics. This output is then converted down to a range of intermediate frequencies. But only one of these frequencies is within the i-f amplifier's bandwidth. This frequency is the one counted in counter A.

The problem now is to determine which harmonic was mixed with the unknown input and whether the i-f frequency is a sum or difference frequency, so that the unknown input frequency can be determined. This is the microprocessor's job. A second synthesizer output, offset by a known amount  $\Delta F$  from the main synthesizer, is then mixed with the unknown. The resulting frequency is counted in counter B.


Two multiplexers also play roles in the system. One switches between the two synthesizers, connecting each to the sampler driver. The other switches the i-f output to one of the

**Simpler.** With the inclusion of a microprocessor, just one sampler is needed in HP's model 5324A microwave counter to make the series of frequency conversions from which the unknown frequency is determined.

#### Instruments

#### Microprocessor calculations drop price of Hewlett-Packard microwave counter

A major reason for the continued high price of microwave test equipment is the continued high price of microwave circuitry. But costs drop significantly when calculations that the microwave circuits do in analog fashion are instead done by a microprocessor. A new microprocessorbased microwave counter from Hewlett-Packard's Santa Clara division



Share in the success you helped create ...

# ANNOUNCING THERCABIMOS BONANZA.

BiMOS is the RCA Linear IC technology that is not only being made by the millions, but used by the millions.

Now we're adding new BiMOS products and new BiMOS prices so you can make even wider use of the highly cost-effective performance of BiMOS op amps.

#### CA3140 2-for-1 Bonanza

At our new price for the mini-dip 3140, you can buy twice as many as you could at the old. So now, for the same dollar, you can double your use of the most useful op amp since the 741.

#### CA3240 2-in-1 Bonanza

Our new CA3240E gives you two 3140's in one mini-dip package. At less than twice our new

low 3140 price. Your new designs can be achieved with half as many packages. And the 3240 is available now in prototype quantities. In both mini-dip and 14-lead DIP.

#### CA3140 CA307G Gold CHIP Bonanza

It's your choice. Two CA3140E's or one 3140 and one CA307G. They both have the same new low price. This BiMOS/Gold CHIP team-up gives you a variety of ways to beat the 741 where you want more performance. Or beat many premium Bifet types where you want lower price or greater availability.


Get your share of the BiMOS Bonanza now. Contact your local RCA Solid State distributor. Or contact RCA Solid State headquarters in Somerville, NJ; Sunbury-on-Thames, Middlesex, England; Quickborn 2085, W. Germany; Ste.-

> Anne-de-Bellevue; Quebec, Canada; Sao Paulo, Brazil; Tokyo, Japan.

**Note:** All price references are based on the unit prices in effect November 1, 1977. Prices optional with distributors.

Tokyo, Japan.

Note: All price references are based



RCA Linear IC experience is working for you.

RGЛ

#### **Electronics review**

two counters. The microprocessor then can take the two results from counter A and B and, knowing the frequency offset  $\Delta F$ , can calculate which harmonic is being mixed with the unknown and thus can calculate the unknown frequency input.

With this scheme, the counter can measure input signals, applied through a type N microwave connector, up to 18 gigahertz. Signals down to 10 hertz also can be measured by applying the input to a separate type BNC input jack and measuring the signal frequency directly in counter A.


Amplitude level. The microprocessor also enables the counter to measure and display signal level. It does this by using a peak-detecting diode to compare the input signal level with that of a known output of an internal 100-kilohertz oscillator. To compensate for individual diode characteristics over the full 10-Hz to 18-GHz frequency range, the characteristic of the diode is stored in a read-only memory. The microprocessor refers to the stored characteristic curve for data at the measured frequency to determine the correction factor to be applied to the amplitude measurement.

Amplitude is displayed in decibels referred to 1 milliwatt on the right-hand side of the light-emitting diode display, while the left-hand side displays the unknown frequency. For frequency-only measurements, the display shows unknown frequencies to 11-digit precision, which corresponds to 1 hertz at 18 GHz.

#### **Microcomputers**

### Son of LSI-11 is smaller, cheaper

If Digital Equipment Corp.'s LSI-11 microcomputer was anything when announced back in February 1975, it was small and cheap—under \$1,000 for a central processor unit with memory. The 16-bit computer-on-aboard has done well, chalking up sales of 16,000 units. But the advance of large-scale-integrated



**Handful.** DEC's new LSI-11/2 microcomputer, with its four boards mounted in its backplane/cardcage, drastically undercuts the original LSI-11 in price and volume.

circuitry could not be ignored, and DEC's second-generation design, which relies on 16,384-bit random-access-memory chips, slashes both price and size—in some configurations to nearly a quarter the older system's volume—and appeals to a broader range of original-equipment manufacturers than its predecessor.

Slimmed down. "We've removed some of the price, form factor and memory density arguments that were used against the LSI-11," says Jack MacKeen, microcomputer product line manager in DEC's Components Group, Marlboro, Mass. Adds technical support manager John L. Hughes, "OEMs can build the new LSI-11/2 into places the LSI-11 couldn't go."

The LSI-11/2, introduced this month [Electronics, Nov. 10, p. 25], knocks about \$3,000 off the price of its parent. It costs \$3,815 in single quantities for a processor, 32,768 16-bit words of RAM, a board with four

independently programmable serial line-interface units, plus a board with circuitry for implementing the IEEE 488 instrument bus. This much microcomputer fits on just four boards, slid into a four-slot backplane/cardcage. By comparison, an equivalent LSI-11 requires 16 boards, and the boards are twice as big. The new version will be available in quantity by March.

MacKeen predicts "a gradual replacement of [the LSI-11] with the LSI-11/2, but I still foresee one or two years of life in volume for the LSI-11." Most likely to buy the LSI-11s are those who have already designed them in.

New entry. There is also a dramatic change at the low end of the LSI-11/2 product spectrum. A DEC spokesman admits the company "didn't feel comfortable" with the entry level price of the LSI-11. So the entry level for the LSI-11/2 has been cut to \$459 in 50-unit quantities. This buys a central processor on a single board that DEC has designed without memory. The cheapest LSI-11 comes in at \$990 but this is for a CPU and 4,096 words of RAM.

Why no memory on the new board? Rolando Esteverena, LSI-11 market and product planning manager, points out that this accommodates users who build their own memories or have unusual combinations of memory types.

The circuit boards for the LSI-11/2 measure 8.43 by 5.18 inches instead of the 8.43 by 10.37 inches of the LSI-11 board. The basic fourchip microprocessor set is the same. but four to six LSI circuits replace 19 packages of series 7400 transistortransistor logic for interfacing the CPU to the microcomputer bus. This package reduction, plus the use of 16-kilobit RAMS instead of the LSI-11's 4-kilobit RAMS, "contributes dramatically to the price and volume reductions," says MacKeen. DEC is offering various memory options. A board will accommodate 4,096, 8,192, 16,384, or 32,768 words of 16-bit RAM and include on-board refreshing. The CPU and an 8-kiloword-by-16-bit memory sells for \$851, ranging to \$1,643 for a

# Get Smart.

ADDS Regent · Smart for the price of Dumb.



#### **Electronics review**

processor plus 32 kilowords by 16 bits of memory (in quantities of 50).

Also being announced with the LSI-11/2 is a new version of the RT-11 real-time operating system that supports four high-level languages—Fortran, Basic, APL and Focal. Esteverena stresses the new microcomputer is fully compatible with all other PDP-11 software.

#### **Automotive**

## Microcomputer gets assembly-line job

Last month, Ford Motor Co. put its electronic engine control in the public's hands, equipping its Lincoln Versailles with an onboard computer that controls ignition timing and exhaust gas recirculation. But the firm has started using the same microprocessor that is at the heart of the engine control microcomputer as a manufacturing tool as well. The 12-bit metal-oxide-semiconductor device that Ford developed jointly with Tokyo Shibaura Electric Co. (Toshiba) has gone to work on six test stands on a new distributor production line at Ford's Ypsilanti, Mich., parts plant.

Low-cost potential. For Ford, it is the first step toward using the same computers in the factory as it ships under the hood—a goal that is several years away because the auto units are still too simple. "We're interested in applying the EEC [electronic engine control] to manufacturing for two reasons," says David F. Moyer, director of Ford's Systems Research Laboratory, which designed the microprocessor. "Its cost will be low because we'll be buying millions of them for cars, and its rugged package will be ideal for the factory environment, which is as severe as the vehicle's.'

For handling the test-stand chores, "we expect the down-the-road EEC to have increased process-control capability," adds Richard H. Sherman, a research engineer.

And the Dearborn, Mich., car maker's use of microcomputers on

#### **News briefs**

#### Zenith reorganizes top administration

On the heels of a third quarter loss of almost \$3 million, Zenith Radio Corp. moved earlier this month to strip the power from its chairman and president, John J. Nevin. While retaining the chief executive slot at the Chicago firm, the ailing Nevin will yield the title of president and chief operating officer to Revone W. Kluckman, formerly senior vice president of manufacturing and material. The board of directors also brought back retired chairman Joseph S. Wright to head a newly formed executive committee. The moves apparently stem from a series of poor decisions that led to a declining market share, a position that Zenith sought to correct by slashing prices, laying off a quarter of its domestic work force, and moving some assembly operations offshore [Electronics, Oct. 13, p. 69].

#### Clarke to become AlL's president

Cutler-Hammer Inc.'s AIL division in Deer Park, N. Y., a manufacturer of advanced electronic and microwave systems, will have a new president come Jan. 1, 1978. John P. Clarke, vice president for operations, will succeed Winfield E. Fromm, who has been appointed corporate group vice president of Cutler-Hammer's newly formed Instruments and Systems Group. In addition to AIL, the group includes electronic test equipment manufacturer Ailtech in Farmingdale, N. Y., semiconductor components producer Yig-Tek in Santa Clara, Calif.

#### GT&E installs third fiber-optic system

This month General Telephone and Electronics Corp. will start installation of its third fiber-optic communications system in less than seven months. It will install a 6.5-mile fiber-optic system between Brussels and Vivoorde, Belgium, jointly with the Regie de Télégraphes et Téléphones, the government organization that owns and operates Belgium's telecommunications net.

Initially, two glass fibers will carry 480 simultaneous telephone calls, but by mid-1979 more advanced units will connect two more of the cable's seven fibers bringing the capacity to a total of 2,400 simultaneous telephone calls. GT&E will provide the equipment.

the new distributor line underscores a second goal: to introduce functional testing at steps along the manufacturing process. "Typically, the manufacturing process is tested for dimension—which is easy to blueprint—and not for function; functional control is now pretty much confined to end tests," Moyer points out. "We need computers to back that functional measurement further into the process, and microcomputers lower that cost."

At Ypsilanti, distributor testing has been handled for the past four or five years by a pair of 16-bit minicomputers that test finished products and report the results to a third, 32-bit host computer. The two remote minis, each hooked to about a dozen separate test stands, drive the distributors dynamically through their operating range. "But when we expanded the lines, we found it more

cost-effective to use microcomputers, one on each test stand," Moyer says.

Ford has also added another microcomputer on the new line upstream from the test stands, to check the calibration of the distributor's centrifugal advance mechanism. This test is run when the distributor is only 20% complete, when it is less costly for Ford to reject a faulty part. It is also possible to adjust how the mechanism is put together even before the first parts come off the line. The centrifugal mechanism alters spark timing as a function of engine speed, relying on weights attached to springs on an assembly that spins. The mechanism is adjusted by bending the post to which the springs are attached.

Averages. "The microcomputer is programmed to keep a running average of the speed at which the weights fly out," Moyer explains;

# SORENSEN IS THE SOURCE. FOR TWICE AS MANY OPENFRAME POWER SUPPLIES.

Now, Sorensen offers you almost twice as many single outputs, plus new duals, to make your selection of OEM DC power supplies just that much simpler.

#### Check our features:

- 115/208/230 VAC input standard.
- Made in U.S.A. with quality components.
- · Conservatively designed and rated.

- No overshoot with turn-on, turn-off or power failure.
- Low heat dissipation, high temperature stability.
- UL recognition.
- One-year warranty, backed by worldwide service organization.
- Stocked for immediate delivery.

Single Output				Single Output			
Model	Voltage ± 5% adjustable	Output Current (Adc) @ 40°C*	Price	Model	Voltage ± 5% adjustable	Output Current (Adc) @ 40°C*	Price
SOC 2-3 SOC 2-6	2V 2V	3.0 6.0	\$ 35 58 72 113 149	SOC 15-9.5 SOC 15-13	15V 15V	9.5 13.0	\$113 149
SOC 2-10 SOC 2-18 SOC 2-25	2V 2V 2V	10.0 18.0 25.0		SOC 24-1.0 SOC 24-2.2 SOC 24-3.5	24V 24V 24V	1.0 2.2 3.5	35 58 72
SOC 5-3 SOC 5-6	5V 5V	3.0 6.0	35 58	SOC 24-6.6 SOC 24-9	24V 24V	6.6 9.0	113 149
SOC 5-10 SOC 5-18 SOC 5-25	5V 5V 5V	10.0 18.0 25.0	113 149 SOC 28 SOC 28 35 SOC 28	SOC 28-0.8 SOC 28-2.0 SOC 28-3.1	28V 28V 28V	0.8 2.0 3.1	35 58 72
SOC 12-1.6 SOC 12-4.0 SOC 12-6.0	12V 12V 12V	1.6 4.0 6.0		SOC 28-6 SOC 28-8	28V 28V	6.0 8.0	113 149
SOC 12-11.0 SOC 12-15.0	12V 12V	11.0 15.0	113 149	Dual Output			
SOC 15-1.5 SOC 15-3.0 SOC 15-5.0	15V 15V 15V	1.5 3.0 5.0	35 58 72	SOC 15D-1 SOC 15D-2 SOC 15D-4.5 SOC 15D-6	12V to 15V 12V to 15V 12V to 15V 12V to 15V	1.0 2.0 4.5 6.0	\$ 50 76 115 154

#### Check our specifications:

AC Input Power: 105-125V, 190-226V, 210-250V (available by using taps on transformer).

Frequency 50 to 63Hz. (Derate Io 10% at 50Hz.)

Voltage Regulation (comb. line and load): ±0.15% +6mV for 105 to 125 Vac and 100% load change.

Voltage Ripple and Noise: 1.5mVrms, 5mVpp.

Temperature Coefficient: 0.03% per °C.

Stability (24 hours): 0.2% after 1-hour warm-up.

Remote sensing: 100mV maximum drop in each leg. Operating Temperature: 0°C to 60°C.

Storage Temperature: -20°C to +85°C.

Overvoltage Protection: Available on all models except 2 volt. Specify by adding "VP" suffix to model number. Add \$8 to unit prices. (\$12 to unit prices over \$100.)

Current Foldback: Automatic, factory-set to 140% rated

(40°C) output current. **Cooling:** Convection. **Finish:** Black anodize.


Call us for OEM discounts: (603) 668-4500.





# **OF THE 1977** COMPONENT

MITEL'S MD4301 CMOS/LSI DETECTOR/TIMER



- 6.5 V to 12.5 V Operation Fet Input Amplifiers On-Chip DRIVER—Over 300 mA

#### **IDEAL FOR**

- Smoke/Fire Detectors—Ion Chamber and Photoelectric Types.
- Gas Detectors—Natural, Propane, Silane, Etc.
- Temperature Detectors Freezers, Stoves, Furnaces,
- Pressure Detectors Weights, Forces, Strains,
- Timers/Controllers-Burn-In Units, Sprayers, Heaters, Etc.

For more information write or phone 18 AIRPORT BLVD. BROMONT, QUEBEC, CANADA JOE 1L0 (514) 534-2321 TLX.: 05-267474 Semiconductor

#### **Electronics review**

from this, it computes where the bend should be and actually controls the making of the bend.

Ford's next step is to simplify the factory microcomputer-now an eight-board system that relies on the host computer for the test procedures for about 150 different distributor models produced at Ypsilanti. "All computation is now done in the microprocessor at the test stand, but we want to bring some of it to the host," Sherman says. "That way, the microprocessor can concentrate on measurement and control, leading us to an even simpler microcomputer."

Also, Ford plans to change the communications system from a system polled by a head-end computer to one that is decentralized, giving each microcomputer the abilty to put messages on a common bus.

#### Companies

#### Government may win case against IBM

Recent Government testimony in the antitrust action against IBM Corp. has made the outcome clear, says an attorney closely following the suit. "In my view, the Department of Justice now is concluding a winning case," reports J. Thomas Franklin, a specialist in computer litigation at the Boston law firm of Sweeney & Franklin.

Key assumption. So certain is Franklin of the result that he advises computer firms "to base your business strategy on the assumption the government will win the case." The Boston lawyer analyzed the antitrust action for the Computer and Commnications Industry Association, an Arlington, Va., organization of independent manufacturers and suppliers, at its meeting last week in Beverly Hills, Calif.

What has convinced Franklin is the testimony starting last summer of Alan McAdams, the prosecution's chief economic advisor. In pulling together rambling evidence already presented, McAdams provided what Franklin calls a "new perspective

that IBM has maintained its monopoly power largely by strategies intended to avoid product-to-product competition."

McAdams offers numerous examples of IBM's strategy of announcing advanced equipment that does not and will not exist, in order to keep customers away from smaller competitors. One was the 3705 communications controller in 1972, which McAdams claims knocked out the Memorex 1207 unit that offered more functions and was 40% cheaper. "This noncompetition was more effective than if IBM had marketed and delivered a real product," says Franklin. He also cites McAdams's testimony alleging that the company blocked Xerox's entry into the general-purpose computer market, and that General Electric Co. lost out to IBM's nonexistant products in the time-sharing computer business.

Avoiding competition in these ways is a theme that greatly helps the government draw a critical distinction between valid and illegitimate competition, Franklin believes. Thus, McAdams's testimony aids what Franklin feels is the central part of the Government's case-"the intent issue, on which the court will judge whether IBM acted illegally."

The result of the competitive dearth, says Franklin, is that non-IBM firms show pre-tax losses of more than \$1 billion for 1960 to 1972, while the industry behemoth's profits exceeded that figure.

Relief. The possibility of interim relief, or a temporary court injunction against IBM practices, was raised at the CCIA meeting, both by Franklin and by participants. A confidential proposal by the association to the Department of Justice is said to ask that IBM disclose details of its new products and interfacing at the time of first customer solicitation. Since CCIA members sell products plug-compatible with IBM, this policy would serve to keep the competitive situation at status quo, pending the decision of the trial. Franklin observes. The Government case winds up soon. IBM starts its defense in early 1978 and should complete it in one to four years.

DDC has put together the most advanced hybrid packages with CMOS/LSI logic to give you the world's smallest synchro-to-digital tracking converters. The HSDC-14 and HSDC-10 series are made to the demanding performance and environmental specifications which characterize DDC's total hybrid capability.


HSDC-14 converters have 14-bit resolution and are available with standard accuracies of either ±4 minutes or  $\pm 2.6$  minutes. They are complete in two hermetically sealed 36 pin DDIP modules; a control transformer and a data processor. The HSDC-10 offers 10-bit resolution and ±21 minute accuracy in a single 36 pin module.

Both converters are available with differential solidstate synchro or resolver inputs with high AC and DC common mode rejection, which makes transformer isolation unnecessary for most applications. Separate isolation transformers can also be supplied. The HSDC-14 modules may be used to form a control transformer, a control differential transmitter, or a two-speed converter.

Designed for military and aerospace electronics, HSDC-14 and HSDC-10 converters are also suited for the most exacting industrial or instrumentation requirements where small component size, lowest power drain and highest MTBF are essential. Processing to MIL-STD-883 Class C is standard and Class B screening is a standard option. For more information or assistance write or call your nearest DDC representative, listed in EEM, or call Herman Santos at (516) 567-5600.

DDEshrinks onverters







A Wholly Owned Subsidiary of ILC Industries, Inc.


Airport International Plaza, Bohemia, New York 11716 516-567-5600 TWX 510-228-7324

West Coast: 7337 Greenbush Ave., North Hollywood, CA 91605 • 213-982-6454 Southwest: 5050 North 19th Ave., Suite 420, Phoenix, AZ 85015 • 602-249-0703

ILC DOVER is the sole designer

space suits

# POWER OP-AMPS TO INDUCTIVE



Intersil's Power Op Amps don't blowout when a motor stalls or suddenly reverses direction. Because they're fully protected against inductive kickback and short circuits by Intersil's unique monolithic internal protection circuitry. That means they sink large surge currents caused by back EMFS. Also, external programmable current limiting circuitry protects the load under abnormal conditions. And the electrically isolated package allows safe, efficient operation.


#### Three Power Op Amps: up to 2.7 Amps $@ \pm 24V$ .

The 8520 family has been specifically designed to drive linear and rotary actuators, electronic valves, push-pull solenoids, DC and AC motors ... a full range of other power control applications.

- ... Available in 1 Amp, 2 Amp, 2.7 Amp versions.
- ... Power bandwidth: 20 KHz.
- ...D.C. gain: 100 dB.
- ...Input offset voltage: 3 mV max.
- ... Input offset current: 100 nA.
- ...Input voltage range: ± 10V.
- ... Power supply range:  $\pm$  5 to  $\pm$  30V.
- ... Quiescent current: 20 mA.

#### Power DAC replaces 100 components.

Lose the components you can do without. Gain the reliability you need. Intersil's Power DAC family—the combination of 8520 Op Amps and AD7520 D/A Converters reduce component count, system size, weight and cost. All while increasing system reliability. All Intersil Power Op Amps and D/A Converters are manufactured to MIL-STD-883 and the 8520 is 100% power cycled to further insure reliability.




The block diagram above includes the use of a AD7520 to control the 8520 and shows a digitally programmable power driver.

#### Low cost AD7520/AD7521 DACs.

The AD7520/AD7521 are monolithic 10 and 12 bit multiplying digital-to-analog converters for

# THAT STAND UP KICKBACK.



digital control. They are pin-for-pin compatible and an equivalent second source to Analog Devices AD7520/AD7521 family.

- ... Latchup free operation
- ...Low power dissipation: 20mW (max)
- ...Low nonlinearity Tempco: 2 PPM of FSR/°C (max)
- ... Current settling time: 500 nS to .05% of FSR
- ...Supply Voltage: +5 to +15V
- ...DTL/TTL/CMOS compatible.

#### Immediate availability.

Intersil's 8520 Op Amps and AD7520 DACs are available at your Intersil Distributor. Now. For complete information, Data Sheets and Application Notes, simply return the coupon. Or, call your Intersil Distributor.

#### Intersil Franchised Distributors

Advent/Indiana · Arrow Electronics · CESCO · Century Electronics · Component Specialties · Components Plus Diplomat/IPC · Diplomat/Southland · Elmar Electronics Harvey/Binghamton • Intermark Electronics • Kierulff Electronics • LCOMP • Liberty Electronics • R.A.E. Ind. Elect. Ltd. • RESCO • Schweber Electronics • Sheridan • Zentronics

#### Sales Offices:

CALIFORNIA: Santa Clara, California (408) 984-2170 Carson, California (213) 532-3544 · COLORADO: Denver, Colorado (303) 750-7004 • FLORIDA: Fort Lauderdale, Florida (305) 772-4122 • ILLINOIS: Hinsdale, Illinois (312) 986-5303 · MASSACHUSETTS: Lexington, Massachusetts (617) 861-6220 · MINNESOTA: Minneapolis, Minnesota (612) 925-1844 • NEW JERSEY: Englewood Cliffs, New Jersey (201) 567-5585 · OHIO: Dayton, Ohio (513) 866-7328 TEXAS: Dallas, Texas (214) 387-0539 · CANADA: Brampton,



Sounds good. Send me your application Notes and Data Sheets. ☐ App. Note: Power D/A Converters using 8520.

☐ Data Sheet: AD7520 10, 12 Bit multiplying D/A converters.

☐ Data Sheet: Heat sink and mounting hardware.

☐ Data Sheet: 8520 Power Amplifier Motor and Actuator Driver. Name

Company\_\_\_

State\_\_\_\_\_

Country\_\_

Circle 57 on reader service card

# Getting ready for the transition to non-PCB capacitors?

### SPRAGUE IS READY!

For today's ecology-conscious world, Sprague offers five types of capacitors for a-c applications that meet industry needs for PCBfree capacitors. Utilizing non-toxic and nonpolluting materials, these non-PCB capacitors are **HERE NOW**, enabling you to prepare for the not-too-distant future, when PCB impregnants will no longer be available.



#### TYPE 500P ECCOL® Heavy-Duty Capacitors

Over a million now in use in the computer industry. Estimated service life of some 90,000 hours. Non-toxic biodegradable impregnant. Improved performance characteristics; lower dissipation factor, less capaci-tance change over temperature range than that of PCB-impregnated capacitors. Capacitance range, 1 to 55 µF. Available in four voltage ratings ranging from 330 VAC to 660 VAC.

Write for Engineering Bulletin 4550.

Circle 101



#### TYPE 520P ECCOL® General-Purpose Capacitors

Intended for the appliance industry and other applications which do not require heavy-duty use. Estimated service life of 60,000 hours at rated voltage and temperature. Non-toxic biodegradable impregnant. Pressure-activated current interrupter prevents case rupture in event of excessive internal pressure. Capacitance range, 1 to  $50~\mu\text{F}$ . Available in 330, 370, 440, and 660 VAC ratings.

Write for Engineering Bulletin 4551.

Circle 102



#### TYPE 440P ALUMACLAD™ Appliance Capacitors

220 VAC UL recognized. Metallized polyester film dielectric system, uses no oil or liquid impregnant of any type. Tubular aluminum case, with epoxy end seals. Axial single-blade quick-connect terminals. Ratings from 4 to 15  $\mu$ F. Ideal for room airconditioners, recreational vehicle heating and airconditioning equipment, fan and blower motors, pump motors, refrigerators, electric typewiters, etc.

Write for Engineering Bulletin 4601.

Circle 103



#### TYPE 315P/325P General-Purpose Metallized-Film Capacitors

Low-loss metallized polypropylene film dielectric system. Type 315P, dry film; Type 325P, oil-filled, UL recognized. Pressureactivated current interrupter prevents case rupture in event of excessive internal pressure. 1/5 THE WEIGHT AND 1/3 THE SIZE OF COMPARABLE PAPER/OIL CAPACI-TORS. Standard ratings from 4 to 60 µF at 330 VAC, and from 4 to 45 μF at 440 VAC.

Write for Engineering Bulletin 4710.

Circle 104



#### TYPE 365P/366P ECCOL® Commutating Capacitors

For non-sine wave applications. Non-toxic biodegradable impregnant has flash point of 430°F. Operate over wider temp. range with less cap. change. Type 365P has paper dielectric, with capacitance values from 2 to 75 μF @ 200 and 300 VAC. Type 366P uses dual paper / polypropylene film dielectric for increased volt-ampere ratings, with capacitance range of .25 to 40  $\mu F$  @ voltages from 400 to 800 VAC.

Write for Engineering Bulletin 4702.

Circle 105

For complete data on any of these capacitor types, write for the appropriate engineering bulletin(s) to: Technical Literature Service, Sprague Electric Co., 35 Marshall St., North Adams, Mass. 01247.

THE BROAD-LINE PRODUCER OF ELECTRONIC PARTS



#### Washington newsletter\_

# White House budgeting more research money . . .

Federal support of basic research in electronics and other technologies will rise in the fiscal 1979 budget that goes to Congress in January, reversing a steady decline of several years. Presidential science adviser Frank Press says a comprehensive White House review of Federal agency research support is complete, and "its results will be reflected in next year's" R&D budgets. Budget figures on an agency basis are still being juggled, but high-technology areas like electronics will benefit most, according to an official in Press's Office of Science and Technology Policy. Military research is likely to be a major beneficiary; the National Aeronautics and Space Administration, whose future role is under separate review, is expected to gain little (see p. 90).

#### ... and seeking new incentives for industry R&D

The prospect of increased Federal incentives for industry to increase R&D investment and reduce the lengthening lead time between R&D and product development was also held out to engineering academy members by the White House science chief. A new Federal policy on industrial research and development is being developed, Press says, and corporate R&D vice presidents are being asked about the impact on their efforts of Federal regulations on "competition, taxation, licensing, patent policy," and related issues. But a new Carter policy in this area will not come quickly. The reason is that the OSTP staff has been cut to 22 as a result of a White House reorganization, and Press's office must coordinate its effort on behalf of research with the Commerce Department and the White House Domestic Policy Group.

# FAA charged with releasing proprietary data

The Federal Aviation Administration is being accused of abusing the Freedom of Information Act by releasing to anyone who requests it—including foreign organizations—proprietary "technical data furnished in confidence by manufacturers" to support FAA type-certification of equipment. The accuser is the Aerospace Industries Association. Its president, Karl G. Harr Jr., wants Congress or the FAA's parent Department of Transportation to amend or clarify the law to differentiate government-owned information from proprietary data furnished so that an agency can perform its statutory function. "A simple FOI request can secure for a foreign requester technical information which the manufacturer owning the information cannot disclose without an export license from the State Department," Harr charges. One result: reduced reliability and safety of aircraft systems if hardware is made by unqualified sources.

#### Distress sales of 23-channel CBs seen through Dec. 31

Watch for unprecedented distress sales of 23-channel citizens' band radios through Dec. 31. That possibility follows the Federal Communications Commission's refusal earlier this month to change a Jan. 1 sales cutoff date for radios type-accepted before Sept. 10, 1976. FCC and industry estimates place U. S. 23-channel inventories between 4 million and 5 million units clogging the market. After the cutoff, FCC and industry officials agree, sales of "used" 23-channel units are expected to continue, since the FCC's enforcement powers are limited and its prohibition exempts sale of used transceivers or those that have been returned under warranty, traded in, or rebuilt.

#### Justice won't let AT&T off the hook

Telecommunications equipment makers got good news when they received early this month their first positive statement of Carter Administration policies on the ongoing antitrust action against American Telephone & Telegraph Co. and the development of a competitive market. Suspicions have been growing in Washington that Attorney General Griffin Bell might accept an out-of-court settlement of the suit, thereby discouraging developing competition. But the Justice Department's John Shenefield, the new assistant attorney general for antitrust, ended such suspicions in his recent address to the Federal Bar Association. Key points made by Shenefield before the FBA, where Federal Communications Commission lawyers and lobbyists listened carefully, follow. Ray Connolly

A decade ago, we had essentially one phone company that gave you everything it thought you should have. There were few viable options. There was no Carterfone, no specialized carriers, no domestic satellites, . . . and no computer rules. As a telephone industry spokesman recently told the House subcommittee, his business 10 years ago was a "closed economic system."

#### No settlement

Substantial battles and competitive controversies are looming across the FCC's horizon. In the telephone industry, the biggest and most obvious upcoming battle is, of course, the AT&T litigation. Contrary to what you think you have heard, that very important case isn't moving to Capitol Hill, it is not going to be transferred to the commission, and there aren't going to be any half-baked settlements. Instead, the case is very quickly getting into shape and will be litigated vigorously.

We also expect to be heavily involved in major "son of Carterfone" developments at the FCC. . . . Developments like these pose substantial, interesting competitive questions. The message that I want you all, especially those of you from the Federal Communications Commission, to carry away is that when you confront such questions, "think competition."

If anyone or thing is to "blame" for competition in this field, I expect one could blame the enormous changes in American society that took place after the various "closed economic systems" were set up in the '30s and '40s. In telecommunications, however, underlying forces for change achieved greater velocity, because they coincided with very rapid technological change. The advent of computers and data

communications as important modern business components triggered customer demand for a wide range of new terminal and transmission capabilities and services.

To its credit, the FCC sincerely tried to at least accommodate some of these sweeping changes. Had they not done so, however, do you seriously believe that all forward movement would have been halted? Market forces, new customer demands, and new technologies are strong imperatives even the most intransigent of regulators would find difficult to stop.


#### Limiting regulation

What we must try to do in this last quarter of the 20th Century is find ways to minimize if not eliminate regulatory friction. In the communications field perhaps this is easier than in others. Here, competition does not have to be "destructive" of existing firms for the reason that the total pie at stake is not static, but instead rapidly growing. A burgeoning technology, moreover, has the effect of creating new, additional economic pies each year—new commercial opportunities. All the terminal competition AT&T confronts, for example, aggregates significantly less than just one year's incremental growth [for AT&T].

It is important to focus not on who provides what, but on service as a whole. It should be a matter of regulatory indifference whether service to the public is provided by company A or company B or by both companies combined. So long as the requisite service is provided overall, regulators should not intervene in an effort to thwart or channel the ordinary forces of the marketplace.

When the FCC is implored by established firms to take special steps and to parcel out special economic protection, the FCC's watchword or reply, without some special reason, should be "Be quiet." This in essence is what the commission has said over the past decade in the face of carrier suggestions that the competitors be eradicated, and the abundance of new competitive services and the absence of any telephone industry collapse bear witness to the wisdom of this general policy.

I come into the telecommunications policy business with few preconceived notions or biases due to extensive experience. The feature that is most striking to novices like myself is that those who are most vociferous in opposing "further experiments with competition" have done so well and prospered in the face of the competition we have already.







When it comes to connectors, there are vendors — and there are interconnection specialists. There's quite a difference. When your interconnection problem can't be solved by off-the-shelf (or off-the-cart) equipment, that's when you need us. Our speciality is solving interconnection problems. That means, for starters, designing a system to fit your unique requirements. Then tooling up, manufacturing, and assembling the system at our completely-equipped plant. And finishing up with on-time delivery, installation, and service.

We've been solving interconnection problems for many "blue chip" companies for 20 years. So your problem won't throw us. And with our high standards of quality, we won't throw you for a loop, either. Don't settle for just any off-the-street solution. See the interconnection specialists.

# FABRI®TEK INC. NATIONAL CONNECTOR DIVISION 9210 Science Ctr. Drive • Minneapolis, MN 55428

(612) 533-3533

Pakin badyanel sistems to Jeorgia.

Moded connectors alephone connectors

#### International newsletter.

#### UK government supporting work with electron beams

Determined to stay in the race toward submicrometer dimensions in very-large-scale integrated circuits, the United Kingdom is buying three electron-beam machines from Cambridge Scientific Instruments, an early pioneer in the field. Two of the \$450,000 machines will be purchased by the Department of Industry for the Plessey and General Electric research centers. The third, bought by the Science Research Council, will be at the Rutherford Laboratory, near Oxford, for the use of the universities of Edinburgh, Southampton, Surrey, and Sheffield. Cambridge Scientific Instruments first produced electron-beam equipment in the late 1960s, but government funds ran out, and a key project leader, Philip Chang, left for the U. S. to join IBM Corp., the present electron-beam front runner. In the UK effort, both direct exposure on wafers and mask making will be examined, and in addition the work is intended to develop electron-beam hardware and software.

#### Japanese study sees good trade position in technology items

In terms of comparative trade advantages with the U. S., Japan is strong in communications equipment and radios and television sets, says a recent study of the Ministry of International Trade and Industry. Assessing high-technology manufactured goods, Japan puts itself ahead in most categories of finished products. The U. S. has no strong electronics areas, says the study, which uses five rankings from strong to weak. Japan rates itself as weak in computers, while the U. S. is considered only moderately strong. In electrical and electronic medical equipment and instruments, the U. S. is termed average and Japan weak. Besides communications equipment the U. S. is called moderately weak in all consumer items. Semiconductors and other electronics products not considered finished goods are excluded from the MITI study, a summary of which was released in Washington by the U. S.-Japan Trade Council.

#### Longines exports 8080-based optical readers

Longines, part of the billion-dollar-a-year Swiss watch group ASUAG, is taking diversification efforts in computer peripherals a step further by marketing its range of 8080-based optical readers in France. The products, including mark and character readers, were first introduced in Switzerland a year ago. Longines also has started to tackle the German market and plans are to sell throughout Europe eventually. The firm says it has gathered considerable electronics and computer-related experience through its watch activities, where various sports timers use microprocessors.

# Vidicon picks up color images from monochrome film

Color television technology will soon make it possible to replace expensive and quick-to-fade color-film microfiches with inexpensive and permanent black-and-white substitutes that will provide improved color images. Hitachi Electronics Co. will pull this rabbit out of its hat with the help of its frequency-separation single-pickup-tube color camera. In the microfilm system, the stripe filter usually on the vidicon faceplate is inserted near the film plane in the still camera that makes the microfiches. The filter produces density changes in film. During readout, the vidicon faceplate picks up the pattern of stripes on the film, which is the same size as the usual stripe filter. Thus the camera output is a standard NTSC color signal for viewing on a nearby monitor or for transmission to a remote monitor.



Ever thought of manufacturing and marketing in Europe? We at Grundy International may be able to offer you the chance NOW.

As a long established medium-sized British Group of companies with considerable design and manufacturing expertise in electronic and electromechanical equipment, a strong international marketing operation and good existing links with European Commerce and Industry as well as within the various Defense Departments, we can offer you:

LONDON England

- \* A Marketing Capability
- \* A Product Design and Development Capability
- \* Manufacturing under License to Testing Quality Standards (DEF.05-21)
- \* Specialist Sub-Contracting
- \* A Local Servicing Capability

If you are a small or medium-sized manufacturer of electro-mechanical/electronic equipment wanting to expand by establishing an export business in Britain, Europe or the Third World, write TODAY with details of your products—

To Owen Boydell, Managing Director. FRANKFURT W. Germany

PARIS France



S.W. GRUNDY INTERNATIONAL LTD., Somerset Road, Teddington, Middlesex TW11 8TD. England. Tel: 01-977 1171. Telex: 929728-Grundytedd.

Circle 64 on reader service card

#### **Electronics international**

Significant developments in technology and business


### Electron beam scans 2-μm patterns directly onto Japanese wafers

Japanese researchers have taken two major steps along the road to electron-beam fabrication of very-large-scale integrated circuits. With direct electron-beam exposure of photoresist on wafers, they have fabricated a 1,096-bit memory with a minimum line width of 2 micrometers. They also have used electron-beam exposure to produce a complete set of 2- $\mu$ m masks for an improved version of an experimental 65,536-bit random-access memory.

These advances at the Musashino Electrical Communication Laboratory are at least in line with equivalent work in the U. S. For example, IBM Corp. has a production line of direct-exposure electron-beam machines that are routinely producing 2.5- $\mu$ m minimum line widths. The company says these machines can be easily extended to pattern geometry with 1- $\mu$ m detail [Electronics, Nov. 10, p. 96]. Moreover, the Japanese mask fabrication is easily as good as the work going on in the laboratories at IBM and Texas Instruments Inc.

The 1-k memory is the prototype for the lab's 65-k devices [Electronics, April 28, p. 68], so it had already been produced with conventional masks and with masks made with electron beams. However, direct electron-beam exposure offers two big advantages. It improves the precision with which extremely fine patterns can be laid down. Since no masks are used, short production runs—for instance, for mainframe computers—and design changes become more feasible.

Disturbing. Bombardment of the chip by the electron beam of about 20 kilovolts does disturb the wafer's crystal surface, so processing changes are necessary if satisfactory yield is to be obtained. Researchers at the laboratory, which is part of the Nippon Telegraph and Telephone Public Corp., have worked out several such changes. Among them



**Mighty fine.** Japanese direct-scanning electron-beam system produced this  $2.5-\mu$ m-wide word line and  $2-\mu$ m-wide bit line. Photo was taken through a scanning electron microscope.

is a positive-resist-and-liftoff of aluminum metallization to provide process masking equivalent to negative resist, which is not available for chips. When spread on a wafer that varies in flatness, the available negative photoresists develop either breaks or pinholes. Also, processing schedules are optimized to anneal out surface damage caused by the electron beam. As a result, the researchers say they can hold transistor threshold voltages and other characteristics to the same tight specifications they maintain for optically exposed devices.

The electron-beam masks of 9

rows of 10 devices each are fabricated on 75-millimeter-square glass plates. They were produced with an electron-beam unit using a control system modified by the laboratory to give a resolution of  $0.03 \mu \text{m}$  over a  $2-\mu \text{m}^2$  area. For large areas, the target stage is moved and exposure is carried out in two or more steps [Electronics, Dec. 23, 1976, p. 48]. The fabrication time is about a sixth that required with optical-pattern generators.

The masks promise higher yield than optically generated versions because they are more precise and have cleaner, sharper edges. The

#### **Electronics international**

precision within a mask has been held to  $\pm 0.1 \mu m$ , and registration between masks to  $\pm 0.2 \mu m$ .

#### The Netherlands

## Air force opts for Collins digital network

Security and survival are the watchwords of military communications systems, and the Royal Dutch Air Force had them fixed firmly in mind when it ordered its new pulse-codemodulated digital voice network from Rockwell International's Collins Radio Group. To go into opera-

tion early next year, the system will provide virtually unbreakable encryption of digital communications. Transmissions will be digitized at eight switching nodes and sent over microwave links.

The Dutch system is a complete digital net, except where voice subscribers are linked by land lines to the switching nodes. Initially, there will be some 8,200 voice subscribers and 170 data subscribers, including teletypewriters, at 2,400 bits a second. The system will be fully compatible with analog networks and can be directly interfaced with digital facilities.

But secure communications do not mean much if the message cannot get through. To ensure its survival, the Dutch system, called Ascon for automatic switched communications network, has several key features. For one, there is an automatic routing scheme built into each of the eight switching nodes that provides 800 different ways to send a message around Ascon.

The configuration of the nodes also contributes to the ability to survive. The arrangement is one of two slightly overlapping diamonds with radio links then running from all adjacent nodes. An abstraction using lines for the links would look much like a cube.

With this configuration, every node will have microwave links connecting it to each of three other nodes, which improves chances of communication if part of Ascon were to malfunction or be damaged. In the standard grid setup for microwave links, the nodes on the peripheries are connected to only two other nodes. Moreover, Ascon subscribers with communications of sufficiently high priority may have lines to several nodes.

Keeping costs down. As well as minimizing the problem of antenna placement in the flat, densely populated Netherlands, the cubic configuration will cost less than a checkerboard grid. The air force will be paying \$13 million for hardware, software, and installation.

To keep costs low, Ascon relies on off-the-shelf hardware, including switching nodes using computer-controlled digital tandem switches with a capacity of 1,536 channels from Collins of Richardson, Texas. It is designed for 100% growth by the addition of only four nodes, which would make what might be called a double cubic configuration.

Independent of the processors controlling the switching nodes is a supervisory and control system called Syscon that monitors all transmission and switching equipment for troubleshooting and security maintenance. It can isolate malfunctions, and it can give a full overview of radio-link and multiplexing capability—including anticipation of complaints and failures.

#### Around the world

#### High-frequency parts give trimmer dc-to-line inverter

Low-frequency power from high-frequency components is the slimming secret of an inverter design worked out by the Electrical Research Association of Great Britain. The input circuit is a high-frequency, pulse-width-modulated inverter followed by a high-frequency, potted-core transformer, which steps the secondary up to the peak output voltage and provides isolation. The output feeds a cyclo-inverter—a bridge-like arrangement of silicon controlled rectifiers in which the logic capability of the device is exploited to reduce the frequency down to a dc-to-1-kilohertz range.

Basically, the SCR bridge directs several cycles of the high-frequency input to one output terminal to produce half of the output cycle, then directs the same number to the other terminal. The result is an output frequency that is an integral submultiple of the input frequency. Solid-state optoisolators convey gating signals from the transformer primary winding to the output circuitry, and triggering on both pulse edges keeps the circuits locked in synchronism. Thus the transformer never sees the low-frequency component of the output wave, so it can operate at 20 kHz.

The research association has developed a miniature inverter pack for a peripheral manufacturer and will expand its technique to other applications if sponsors come forward. Researchers point out that 20-kHz switching transformers with useful current outputs of several amperes have already been developed for switching power supplies, which have been shrunk by techniques similar to those used with the inverter.

#### IC regulator for power supplies includes diodes

Including rectifying diodes on the same chip as a series-pass regulator makes building a regulated supply chiefly a matter of adding a transformer and an electrolytic capacitor. To build its new regulator integrated circuit, SGS/Ates of Italy puts a collector sink and a base diffusion around the anode diffusion. An emitter area is diffused into the anode region to decrease the gain of the parasitic diode formed by the collector substrate junction. These measures reduce the diode's leakage by a factor of 10.

To be available in the U. S., the chip, the L 192, will first come in a 250-milliampere version with a pair of rectifier diodes. A 500-mA version with a four-diode rectifying bridge will follow. Output voltages for the L 192 can be 5, 21, 15, or 24 V. Load regulation for a 200-mA change in load current is 0.5% of the output voltage. Line regulation is better than 65 decibels at a 15-V output voltage. Price will run around 50 cents each for quantities of 10,000 and up, according to a company spokesman.



# How to turn a computer into a disk jockey. The μPD372 Floppy Disk Controller.

Now you can turn almost any micro or minicomputer into a genuine floppy disk jockey with the help of just one small chip.

Our  $\mu$ PD372 Floppy Disk Controller. Or if your computer prefers playing tapes, we also have the  $\mu$ PD371 Tape Cassette Controller.

Either one can take the place of from 50 to 60 TTL packages to save you space as well as money. The 372 is

completely compatible with IBM, Minifloppy,™\* and other formats and controls up to 4 floppy disk drives. The 371 controls up to 2 tape cassette drives. They come with complete documentation and — best of all — they're available now.

The  $\mu$ PD372 and 371 are just part of our complete family of microprocessor products including 8080As, dynamic and static RAMs, ROMs,

Electrically Erasable PROMs, and 8212, 8214, 8216, 8224, 8228/38, 8251, 8255 and other support chips. All backed by full documentation, applications support, and software.

The  $\mu$ PD372. The  $\mu$ PD371. And the hits just keep on comin'.

NEC Microcomputers, Inc. Five Militia Drive, Lexington, MA. 02173. 617-862-6410


\*TM Shugart Associates

### **NEC** microcomputers, inc.

REPS: East—C&D Sales 301 296-4306, Contact Sales 617-273-1520, Harry Nash Assoc. 215-657-2213, Rome 516-249-0011, Tech-Mark 607-748-7473, 716-223-1252, 315-652-6229, Trionic Assoc. 516-466-2300; South—Perrott Assoc. 305-792-2211, 813-585-3327, 305-275-1132, 20th Century Mktg. 205-772-9237, Wolffs Sales Serv. Co. 919-781-0164; Midwest—Electronic Innovators 612-884-7471, W. Pat Fralia Co. 817-640-9101, 817-649-8981, 713-772-1572, Intech 216-826-3400, 513-278-6507, K-MAR Eng. & Sales 816-763-5385, R.C. Nordstrom & Co. 313-559-7373, 616-429-8560, Technology Sales 312-438-3300; West—Cerco 714-560-9143, DVZ Assoc. 303-534-3649, Electronic Component Mktg. 714-879-9460, Summit Sales 602-994-4587, Trident Assoc. 408-734-5900, Tri Tronix 206-232-4993, 505-265-8409; Canada—R.F.Q. Ltd. 416-626-1445, 514-626-8324.

DISTRIBUTORS: ASI Electronics (Baltimore), Bell Ind. (Bellevue WA), Century Electronics (Albuquerque, Salt Lake City, Wheatridge CO), Diplomat (Chicopee Falls MA, Clearwater FL, Elk Grove Village IL, Farmington MI, Minneapolis, Mt. Laurel NJ, Salt Lake City, St. Louis, Sunnyvale, Totowa NJ, Woodbury NY), Future Electronics (Montreal, Ottawa, Rexdale Canada), Harvey Electronics (Fairfield NJ, Lexington MA, Norwalk CT, Woodbury NY), Intermark Electronics (San Diego, Santa Ana, Sunnyvale), G.S. Marshall (Sunnyvale), Mirco Electronics (Phoenix), Resco (Raleigh), R-M Electronic (Kentwood MI, Madison Hgts MI), Semicomp (Costa Mesa CA), Semiconductor Specialists (Burlington MA, Chicago, Dallas, Dayton, Farmington MI, Hazelwood MO, Indianapolis, Kansas City, Milwaukee, Minneapolis, Pittsburgh, Malton Canada), Sterling Electronics (Albuquerque, Dallas, Houston, New Orleans, Phoenix, San Diego, Seattle, Sun Valley CA, Watertown MA), Summit Distributors (Buffalo), Summit Electric (Rochester), Technico (Columbia MD, Roanoke VA), Western Microtechnology Sales (Sunnyvale), Zeus Components (Elmsford NY).

# If you thought Panasonic




# FOR CONSUMER APPLICATIONS SFRIFS

#### **ALUMINUM**

From .47 μF to 2200 μF, and from 6.3 through 100 VDC. Axial or radial leads. Temp. range: −40 ℃ to +85 ℃. Standard tolerance: +50%, −10%.



# only supplied 'lytics for TV...



# FOR GENERAL APPLICATIONS EL&SQ SERIES


#### **TANTALUMS**

Our EL series with resin dipped axial leads. From 0.1  $\mu$ F to 47  $\mu$ F, and 3.15 through 50 VDC. Temp. range:  $-55^{\circ}$ C to  $+85^{\circ}$ C. Standard tolerance:  $\pm 20^{\circ}$ 6. Ideal for micro-motor, electronic calculator, camera and similar applications. Our SQ Series with resin dipped radial leads. From 0.1

Our SQ Series with resin dipped radial leads. From 0.1  $\mu$ F to 220  $\mu$ F, and from 3.15 through 50 VDC. Temp. range:  $-55\,^{\circ}$ C to  $+85\,^{\circ}$ C. Standard tolerance:  $\pm20\%$  ( $\pm10\%$  available).

# A choice of packaging, too.

Panasonic offers you a wide line of aluminum and tantalum electrolytic capacitors, plus the flexibility of bulk, reel or tape packaging for axial lead units, and lead forming or crimping for both axial and radial units. And they can be ordered from our Secaucus headquarters or your local Panasonic distributor.



CLIP THIS COUPON FOR SAMPLES, DETAILS AND PRICES.

Panasonic Electronic Components, One Panasonic Way, Secaucus, N.J. 07094, (201) 348-7268

☐ Yes. Send me samples, details and prices on your:

Aluminum

Z DL D3H D4H

My application involves:

☐ I can't wait for the mails. Have your representative call.

resentative call.

Name \_\_\_\_\_\_Title\_\_\_\_\_

Firm \_\_\_\_\_\_Address \_\_\_\_\_ State\_\_\_\_\_Zip \_\_\_\_\_

Phone \_\_\_\_\_\_

### Panasonic sust slightly ahead of our time


Circle 69 on reader service card

# FOR ALL HI-REL APPLICATIONS APP

With characteristics similar to those of our tantalum those of our tantalum capacitors, but at lower prices. From 1 μF to 220 μC, and from 16 through 63 VDC, and from 16 through 63 VDC, axial or radial leads. Temp. Standard tolerance: ±20%.

# Stretch your mind. Think Amphenol connector systems.

Don't back off from your big idea. We can help you make it work. And work right.




Dare to be different. We'll back you up with Amphenol connectors. We may already have the kind that'll make your big idea work.


But if we have to create something totally new to match your idea, we'll go all out—even to designing the required termination tooling. Our connector design specialists are known for the way they tackle the unknown. With a spirit that yields the answers.

Think of it this way: we can help you avoid a lot of false starts. And give you measurable quality and economy. The people who use the Amphenol connectors shown here know that's true. They think of us first when they need connectors for consumer and business products, data and word processing equipment, aerospace and military applications, telephony, and more.

Got a mind-stretching idea? Then include Amphenol connectors in your thinking. To get started on the right track, just call us at (312) 986-2320 or write to: Amphenol North America Division, Bunker Ramo Corporation, Dept. A17B, 900 Commerce Drive, Oak Brook, Illinois 60521.



Medical interface cables for critical applications. Provide reliable patient monitoring and medical electronics interface. Custom-made for reliability, good looks.



No more unsoldering for IC replacement. Dual-inline IC's or planar leadless MOS/LSI's plug right into 800 Series devices.




Connectors that go beyond waterproof. Self-sealing, low-cost 44 Series shrugs off water. And fuel, road salt, ozone and more. For automotive, transportation, and marine uses.





Rack-and-panel connectors that advance the state of the art. 94 Series environmental connectors utilize polymer-retention discs to retain the 20, 16 and shielded size contacts.





Precision optical connectors from stock.

Optimum components for emitter-to-cable, cable-to-detector, and cable-to-cable junctions. All with standard SMA size mating.

The right idea at the right time.

**AMPHENOL** 



PMI's COMDAC companding D/A converter. When you think about what it can do, nothing seems very far-fetched. Not long ago, we ran a little contest in one of the electronics magazines. We asked engineers to come up with the most creative ideas they could think of to put PMI's unique COMDAC—the first and only companding D/A converter—to work. We got lots of responses with exciting ideas. But the interesting part is that no less than five engineers said they'd had terrific ideas-but they couldn't submit them because their corporate attorneys were starting patent searches.

That's the kind of brainstorming that COMDAC has generated since we first introduced it.

The reason is simple: nature is nonlinear. People, plants, animals, water, wind—we don't live in a straight-line world. We live in a world of curves, slopes, and human response systems (ears, eyes, touch) that do not follow straight-line paths. In trying to reduce these things to digital data, or to imitate them, we've always fallen short.

#### Until COMDAC.


With the help of COMDAC you can linearize analog signals. COMDAC can supply the shades of grey, the sweeping curves, the "vive la différence!" of the natural world. COMDAC uses logarithmically companded digital techniques for D/A conversion; with just eight bits, it provides the dynamic range of a 12-bit DAC — 72dB or 4096:1. With that range, it can produce a convincing facsimile of the human voice, for example. Your watch radio can awaken you gently, with soothing, motherly tones, or shake you out of bed with a drill sergeant's scream -



Consider these applications—some of which are already a reality:

- Digitized audio—music, sound effects, voice (μP controlled)
- XYZ positioning (automated drill presses, for example)
- Motor controls
- Echo/reverb devices (for electronic guitars, electronic organs, synthesizers)
- Voltage-controlled oscillators and filters
- · Servo motor controls

COMDAC™ TRANSFER CHARACTERISTICS



- Altimeters
- Waveform generation (with PROM)
- VU meters (for better response)
- Voice recognition (imagine a typewriter you could dictate letters to!)
- Tone generators
- · Voice encryption
- Voice warning systems (they're already using them in aircraft)
- LOG sweep generators
- Data acquisition
- · Recording studios
- Verbal response systems (like, your car could give you the word when it's overheating)

Keep in mind that COMDAC is not just a concept. It's a working reality. In the last two years, we've delivered half a million and cut the price in half. And since the 8-bit COMDAC can do many things a

12-bit DAC can do, think of what you will save by using a low-cost 8-bit system to do the job of the expensive 12-bit approach.

With a little bit of thought, a creative engineer—that's you—can come up with some really dazzling ideas. The surface has just been scratched. If you'd like a copy of all our contest entries, circle the bingo number below. We'll send technical literature that will help you with your application. Want a sample COMDAC? Send us a request on your letterhead.

Precision Monolithics, Incorporated 1500 Space Park Drive, Santa Clara, CA 95050 (408) 246-9222. TWX: 910-338-0528 Cable MONO





# The P400 makes excuses obsolete.


A new product comes on line and the circuit boards start piling up. This is when the excuses begin:

"I can't get near the computer."


'I need more programmers." "I just got schematics last

"I need five more test programmers."

It's a difficult time for a test engineer because the success of an important product can hang in the balance.



But Teradyne's P400 Automatic Programming System has changed all that. Used with L100 series test systems, the P400 creates the entire test program



automatically. It gives you all input patterns, provides all diagnostic data, and resolves all races. It cuts programming time from weeks to days. And it does it all without tying up the computer on your production tester or increasing your programming staff.

Suddenly, new programs can be ready on time, even in the face of the tightest schedules. And even for the most complex boards.

Just as important, the P400 spares you all the boring work it usually takes to deliver new programs. You get typically better than 95% fault coverage simply by using the telephone to access a large computer containing the P400 software.




The P400 Automatic Programming System.

Now there's no reason for

being late.

And we think that's the way you want it.





183 Essex Street, Boston, Mass. 02111

Analysis of technology and business developments

# Micros ride high at Motorola

Microcomputer division, once suffering from critical production woes, now is prepared to ship more parts in 1978 than anyone else

by Laurence Altman, Solid State Editor

The summer of 1976 was bleak for Motorola's MC6800 microcomputer group. The group's design and wafer unit had moved from Phoenix, Ariz., to the new facility in Austin, Texas, and the line wasn't yielding. Billings—that is, shipments—in August and September ran dangerously below bookings, always a sign of deep trouble in a factory, and key people were deserting.

Meanwhile, Motorola's 6800 was being designed into systems, and users were clamoring for their parts. Delinquencies were piling up, even for major customers.

Adding to the pressure caused by the production problems, Motorola was competing for the big prize—the General Motors microcomputer contract, slugging it out against the toughest competition in the business. To be successful, Motorola would clearly have to fix the problems in the factory since the division would have to supply annually 10 million-plus complex integrated circuits to an automobile manufacturer known as a stickler on quality and very tough on vendors that slipped schedules. In short, could Motorola turn it around?

Success. Motorola could and did. Today, its Austin microcomputer line has one of the highest large-scale-integration production capacities in the world. Billings are tracking bookings better than in any other previous period. Delinquencies in the 6800 line are lower than in

any other product line in the corporation with the exception of a few mature discrete lines. Yields and reliability (0.007 failure rate) on microcomputer chips are among the best in the industry, leading to a fourfold increase in output over the last 12 months. The result: not only did Motorola get the GM contract, potentially worth tens of millions of dollars a year, but it landed the lion's share of Ford's engine control program, beating out competition that included Intel Corp. and Texas Instruments Inc.

That is why Colin Crook, microcomputer operations director, can say flatly, "Motorola's Austin plant will ship more microcomputers in 1978 than any other facility in the world." And to the charge that the huge auto contract will gobble up Motorola's microcomputer supply capacity for years, making it little more than a captive supplier to one or two customers, Crook says, "With our yields and production capability, if we had another contract the size of General Motors', we still wouldn't fill our capacity."

Central to the turnaround in microcomputers at Austin, most observers agree, is Crook. "Eighteen months ago, our production line was a disaster area," he recalls. "If we didn't solve our problems fast, we'd lose everything we'd built up in microcomputers over the previous two years."

Crook reached into Motorola's highly successful standard com-

**Riding an upcurve.** Motorola's Daniels, Goldman, Crook, and Summers are the men running the successful microcomputer production and design facility at Austin, Texas.

#### Probing the news


plementary-mos products group to find the men he needed. He took Murray Goldman out of C-mos manufacturing and put him in charge of the group's production. He took Gary Daniels, senior C-mos design engineer, and made him head of the design team. He has brought in young, aggressive marketing types like Gary Summers from the San Francisco Bay area. And he put microcomputer production on a daily priority schedule.

The results were quick and dramatic. By January 1977, six months after the low point, Motorola's microcomputer production was matching the steep curve of increased bookings (see chart at far right), and new designs were coming out of the factory with unprecedented yields and remarkable reliability levels.

Standard base. With the GM and Ford contracts under its belt and factory production racing along, Motorola is now turning to the standard-product market to broaden its base of microcomputer penetration. "We view our coming auto production experience as an opportunity to drive our standard-product chip costs down," Crook says. "With our anticipated volume, we can become the most aggressive microcomputer chip supplier in the business."

To this end, Motorola's micro-computer design group is launching a wide-ranging product entry program. According to Daniels, the chip design manager, "The key to our new product development is family compatibility. All our new CPUs, single-chip microcomputers, and complex peripherals use the same 6800 software and development systems. That goes for our one-chip 6801, all the way to our new 16-bit 6809. A user can move up the ladder with 6800 designs without major new system software development."

If Motorola stays on schedule, the new chips will indeed extend the 6800 family into all areas of microcomputer design. Coming in the first quarter of 1978, for low-end controllers, is the 6801 one-chip microcomputer, which consists of an 8-bit central processing unit, clock gener-



**Telling the tale.** Failure rate of the MC6800 microcomputer, left, has dropped dramatically since 1974. At the same time, gap between orders and shipments has been closed, right.

ator, and driver; 2,048 bytes of program read-only memory and 128 bytes of random-access memory (as much as any one-chipper); and 30 input/output lines and two 16-bit timer functions. Next, for mediumperformance minimum-chip applications, there is the already available two-chip 6802/6846 system, as powerful as the standard six-chip 6800 configuration. The 6802 combines the functions of the 6800 CPU and clock and the 6810 RAM, while the 6846 ROM-combination chip is equivalent to two 2-k 6830 ROMS, one half of the 6820 peripheral interface adapter, and one third of the 6840 programmable timer module.


Then there is the host of new peripheral controllers developed either at Motorola or at Hitachi, which has a 6800 second-source agreement with Motorola. There is a floppy-disk controller, a direct-memory-access controller, a cathode-raytube controller, a combination ROM-1/0-timer chip, an advanced datalink controller, and a generalpurpose interface adapter for interfacing the 6800 bus with the IEEE 488 bus. Also coming in the peripheral area is a unique video-display generator chip that provides all horizontal, vertical, and burst timing, all refresh addressing, and all signals for generating alphanumeric and graphic signals, both black-andwhite and color.

Finally, there is the 6809 16-bit CPU, which with 6800 peripherals and memory can implement designs in the middle and high end of the

minicomputer scale. Capable of 10 times greater performance than the original 6800, it will be available during the third quarter of 1978, along with the one- and two-chip systems.

Silicon systems. In the future. Crook believes, the microcomputer revolution will cause major dislocations in the traditional computer industry. "To be successful in the microcomputer business," he says, "you must realize that it's different from any other business that exists today. It is not like the semiconductor business and it is not like the traditional computer business. The ability to map ever more sophisticated computing systems onto silicon each year is a concept whose implications may not be fully realized, even by some people who are responsible for making it happen. Success will come to those who understand the relationship between the silicon and the system. Nothing short of a merging of the two entities into a tightly knit unit will achieve success."

Motorola is well along on developing the technology and system designs required for the next generaton of microcomputer products. High-performance scaled MOS processes capable of 10 times better performance than today's processes and more powerful architecture to better utilize this increased circuit capability are top priority programs both at Motorola's new production lines in Austin and at its sister systems group in Phoenix.



# Five success stories: Each of these proprietary LSI circuits made one of our customer's new products perform better and cost less.

That's our business. Making our customers' products better by applying the advanced technologies of large-scale integration. We've done it hundreds of times, in a wide and growing spectrum of product applications.

Take, for example, the multimeter circuit we designed for an instrument manufacturer. By miniaturizing functions in the circuit, we made the product more portable and more reliable. We also saved the customer a good deal of money in assembly labor—enough to amortize his development costs within a year.

development costs within a year.

Or consider the pair of ICs we developed for a CB radio manufacturer. One of the devices, a Bipolar AM Receiver, handles all functions between antenna and audio. The other chip, a CMOS digital frequency synthesizer, includes a prescaler, a PLL and VCO. Providing over 80% of the electronics required to produce a CB transceiver, this chip set is just one example of how we can combine



KEY: 1. DVM Circuit, 3½ digit, A/D converter; 2. LCD Watch Circuit, 6-digit, 6-function; 3. CB Scanner with ROM; 4. Cardiac Pacemaker; 5. PLL Frequency Synthesizer.

both digital and linear processes to tailor a cost-efficient system solution.

And we are as reliable as you can get when it comes to making custom LSI circuits. Our proven production processes—HD/CMOS, Bipolar and the deposition of thin-film

resistors on LSI chips—consistently produce high yields.

Exceptional noise immunity and high switching speeds are standard performance features—especially in our HD/CMOS circuits. And because they consume less power than microprocessoror IC-based systems, our devices operate on comparatively smaller, less-expensive power supplies.

If your potential application requires more than a handful of standard ICs and discrete components, you ought to think about the advantages of converting to custom LSI. Contact us today and we'll help you write your own success story.



We sell more than circuits. We sell solutions. 3100 Alfred Street, Santa Clara, CA 95050, (408) 247-5350

Consumer electronics

# Audio world gets the word: digital

Other Japanese firms follow Sony to market with PCM recording and playback schemes

by Charles L. Cohen, Tokyo bureau manager

It's only a matter of time until all stereophonic recording will be done with digital techniques. That's the message from Japan, where several manufacturers are rushing to market with systems that use lasers to play back plastic disks whose audio signals are pulse-code-modulated [Electronics, Sept. 29, p. 42].

The mass market of the future will most likely center around standard 30-centimeter disks because they can be mass-produced inexpensively the same way they are now made for analog recordings. But the key word is "standard"—until there is industrywide agreement on specifications, PCM disks will be impractical and the answer will be tape.

American observers agree with this assessment. Alex DeKoster, senior acoustic engineer at Acoustic Research Inc. of Norwood, Mass., a leading maker of stereo equipment, points to agreement among hardware makers as key. Beyond that, says DeKoster, "I'm tremendously impressed with the dynamic range of PCM audio. Although it will start out as an expensive toy, demand will force the price down. I think it's the audio of the future." He estimates that it will take three or four years for expensive consumer playback systems to catch on, then another

five or six years before the price dips to the average consumer's level.

At Fisher Corp. in Chatsworth, Calif., engineering manager Herbert Lippold, while agreeing that standardization is vital, also is concerned about how such an audio system is supported—that is, what and how much software is made available.

Takeoff point. Though quick standardization of the medium may be a pipe dream, what PCM audio has going for it, beyond the technological advances and the marketing ability of the industry, is the fact that its time may be here. Analog technology is mature and no great advances are expected; digital technology, on the other hand, has progressed to the point where all the needed components are at hand, and price reductions in many of the key components are expected. What's more, video tape recorders have just reached the takeoff point, making them available as basic building blocks, and semiconductor lasers the missing link in disk systemsappear poised to move from lab to production line. Finally, phaselocked-loop synthesizers and crystals for tight control of both tape and disk drives are in good supply.

The beauty of pulse-code modulation in digital recording systems is



At the controls. Technician works on laser disk recorder being developed by Mitsubishi. Company has displayed three experimental systems—two using tape, one using disks.

that frequency response and dynamic range are essentially independent of the characteristics of the disk or tape, and there is no crosstalk between channels. Furthermore, signals are retimed during playback, completely eliminating all wow and flutter. In all the systems announced so far, frequency response is flat within a fraction of a decibel to 20 kilohertz, and dynamic range is at least 85 dB—superior to that of any room that might be used for listening to the music and about 20 dB greater than that of most analog systems.

Early PCM recording systems for professional use all have tape as their recording medium, and initial consumer units will continue the trend. A start has been made by Sony Corp., which is offering consumers a PCM adapter for use with its two-hour Beta Format video tape recorders for \$1,920.

Experimental adapters with similar characteristics have been shown by Victor Co. of Japan, Matsushita Electric Industrial Co., and Mitsubishi Electric Corp. Mitsubishi also has shown another system in which



VTR was combined with electronics designed especially for PCM audio recording and playback, resulting in an audio-video unit the size of a video tape recorder alone.

Experimental disk playback systems, separate from VTRS, have been shown by Mitsubishi, Sony, and Hitachi Ltd. Audio manufacturer Pioneer Electronic Corp., which has just set up a joint venture with MCA Inc. to produce industrial video disk systems, has said it has worked on audio PCM disk systems in its lab. And Matsushita has hinted that it is a member of the group that has developed an audio PCM disk.

Similarities. Despite the completely different technologies used, the basic PCM coding scheme for both disks and tape can be identical, meaning digital program material on tapes and records may be converted from one to the other by digital processing with no loss in fidelity. Sony followed this course in the consumer PCM video tape adapter that it announced in September and the experimental PCM disk system that it showed later the same month.

Mitsubishi, on the other hand, showed two tape systems and one disk system, each with a slightly different coding scheme. Mitsubishi uses 12-bit coding on its disk system, compared with 13 bits on its two tape systems and on Sony's tape and disk systems. The advantage is that 12-bit data converters are much less expensive than those offering 14-bit resolution. But a shift from hybrid to laser-trimmed monolithic devices should create major price reductions in both analog-to-digital and digital-to-analog converters.


Differences. A basic difference between the Sony and Mitsubishi philosophies is in the method of recording information on disks. Mitsubishi employs frequency modulation—actually, frequency-shift carrier. This technique uses several cycles of what would be the white level on a video disk for 1, several cycles of what would be the black level for 0, and several cycles of what would be extended sync-pulse frequency for sync between PCM words. Redundancy bits are added to the coded audio to catch errors, and the sample is repeated to correct errors. so that loss of sync is rare.

Sony, on the other hand, employs a direct recording scheme for disks similar to that used for computer tapes. Much higher-density recording is achieved, but complex sync plans must be used because there is a much greater risk of losing sync.

Although each company thinks its own system is best, all agree that a standardized format is needed to achieve success with prerecorded disks. Hitachi engineers think similarly but feel it will be a while before the time is ripe for standardization. Therefore they are putting all their efforts into developing basic hardware, including a channeled-substrate injection laser made with planar technology. Hitachi claims to be the only company with a practical semiconductor laser for disk playback, though other companies claim they too will have lasers by the time standards are agreed upon and companies are ready to begin production. Meanwhile, Hitachi is using for its experiments a PCM format developed by its subsidiary, Nippon Columbia Co., to record master tapes for conventional long-playing records on a 2-inch lateral-scan video tape recorder.

Setting new rotary switching standards


# it's small... it's enclosed... it's affordable,..




# it's Grayhill Series 71!

- from logic switching up to 1/4 amp
- 1/2" diameter
- contamination-free construction

Here's maximum versatility and quality in a compact switch that reflects state-of-the-art capabilities and state-of-the-economy pricing. Grayhill's Series 71 Switches are available with such options as up to 12 positions, 30° or 36° angle of throw; up to 6 poles per deck, up to 12 decks; fixed or adjustable stops; solder lug or PC terminals; 1/8", 1/4", or 4mm shaft diameters, and concentric shafts. They have a gold plated contact system, diallyl phthalate insulation, molded-in terminals. For complete information, see EEM or contact Grayhill, Inc. 561 Hillgrove, La Grange, IL 60525.





We'd like to announce the end of 'by guess and by gosh' in designing output filter chokes. Ferroxcube now offers a complete line of gapped pot cores, in 3C8 material, with standardized gap length and standardized A<sub>L</sub> values.

3C8 material from The Cube

The gap lengths have been optimized to prevent saturation of the core due to high DC fields, while simultaneously providing maximum impedance to the AC ripple current.

Gapped pot cores, bobbins and hardware are available in 14, 18, 22, 26, 30, 36 and 42 mm sizes. For complete specifications, call on The Cube.



FERROXCUBE Division of Amperex Electronic Corporation, Saugerties, New York 12477 (914) 246-2811

A North American Philips Company



### **Probing the news**

**Business** 

# **Electronics shrugs off slowdown**

Semiconductor makers' consensus is for 18% to 20% increase over last year as computer and component sectors also show strength

by Howard Wolff, Associate Editor

Although the U.S. is experiencing a slowdown in its economic growth rate during the second half of 1977, the electronics industries appear to be sailing through in good shape. Semiconductor makers see 1977 as a year of reasonable sales growth, and other industries—such as computers and components—are enjoying very strong years.

Setting the tone for the semiconductor outlook is Charles M. Clough, marketing vice president for Texas Instruments Inc.'s Semiconductor Products group in Dallas. "Business in the last half of the year will be stronger than the first," he says. "Growth for 1977 will come in pretty much as we expected—around 18%." And unlike 1976, this year's fourth quarter will be up strongly over the third quarter, he adds.

Computer companies, particularly those in the peripherals business, are the stars of TI's scenario. Fourth-quarter computer-industry bookings will at least match those of the third quarter, and the first quarter of 1978 will be up. "We expect to see a booking rate that's up 15% to 20% over our 1977 rate," Clough says. There is a slump in the consumer market, however, which Clough attributes to seasonal vagaries; but sales to auto makers are still strong, mirroring the sales of automobiles themselves.

In Silicon Valley, "business is reasonably good," according to E. Floyd Kvamme, vice president and director of operations at National Semiconductor Corp., Santa Clara, Calif. "I think the industry has been in the most general increase it's ever been in." He predicts "steady, albeit

slow, growth" into the early part of next year, with "demand increasing on a fairly good slope." Like Clough, he pegs the computer industry as the hot area, with demand for memories high. Kvamme's expectation for 1977 is a 20% increase, based on National's June-to-June fiscal year.

Wilfred J. Corrigan, president of Fairchild Semiconductor, Mountain View, Calif., agrees that 1977 saw reasonable growth. Computer business has been good for Fairchild, too, with equipment business and video games also strong. But consumer business has averaged out as "pretty tough," Corrigan says, because of Fairchild's problems with digital watches.

There also were soft spots for Advanced Micro Devices Inc., Sunnyvale, Calif., which president Jerry Sanders says has grown by 50% this year over 1976. Sanders explains that, though AMD's earnings are up, things could be better: heavy invest-

up more like 16% to 18%"—and that 1978 will bring "lingering question marks in the world market that will hold semiconductor growth to about 10%." He is seconded by Bernard V. Vonderschmitt, vice president and general manager of RCA Corp.'s

Solid State division, Somerville, N. J., who also anticipates only 10%

domestic and overseas facilities that are still to earn their way. Sanders sees 1977 winding up with a 12% to 15% industrywide increase for semiconductor business and 20% for integrated circuits.

Question marks. John R. Welty, senior vice president and general manager of Motorola's Semiconductor group, Phoenix, says that a slowdown in the second half kept 1977 from achieving its predicted

20% to 25% increase—"it will end

ment in research and development


and in yield-improving methods have

not produced as quickly as expected,

and AMD also has opened major

A good year. That's the verdict from Ti's Clough (right) and IBM's Cary (below). Both also expect the trend to carry into 1978.





#### **Model 8300**

.01° Resolution
Lazy Eight Ambiguity
Indicator
Programmable for Synchro
or Resolver and Line-Line
Voltage
2 channel

#### **Model 8800**

0.005° accuracy, 5½ digits Small-size, remotely programmable Synchro and/or resolver – auto line/line select 2 channel IEEE Interface (optional) for ATE

CALL OR WRITE FOR COMPLETE SPECIFICATIONS



NORTH ATLANTIC

industries, inc.

200 TERMINAL DRIVE, PLAINVIEW, NEW YORK 11803 cable: noatlantic / twx: 510-221-1879 / phone: (516) 681-8600

#### Probing the news



**Not bad.** For Fairchild's Corrigan, 1977 was a year of reasonable growth.

to 12% growth for 1978 after what he estimates at 15% for this year.

The vista enjoyed by computer makers is a lustrous one. IBM Corp., Armonk, N. Y., chalked up records for gross and net in its third quarter, which ended Sept. 30. Chairman Frank T. Cary says the reason is "the volume of outright purchases of data-processing equipment—also a record for any quarter."

Detroit's Burroughs Corp. sees similar strength. President Paul S. Mirabito says orders in the third quarter increased 14% over last year's quarter, while backlogs have increased 28% since the beginning of the year. And Robert L. Puette, marketing manager for Hewlett-Packard Co.'s Data Systems division, Cupertino, Calif., says business has been "exceptionally strong."

Big gains. For Digital Equipment Corp. of Maynard, Mass., the first quarter of fiscal 1978, just ended, saw a 48% increase in total operating revenues over the same quarter last year, to \$302.6 million. And for rival Data General Corp. in Southboro, Mass., the year was outstanding, says senior vice president Herbert J. Richman. Fiscal 1977, which ended Sept. 24, was a year of \$254,687,000 in sales, compared with 1976's total of \$178,753,000.

Perhaps the brightest outlook is for components. Joy and optimism are unalloyed at Allen-Bradley Co.'s Electronics division in Milwaukee, where shipments are up 26% and the plant is working three shifts a day, six or seven days a week, and still can't meet demand.

# The best MOS memories: Fujitsu's 8227/8116 **4K/16K MOS** RAMS deliver highest reliability.

□ Please send me data on the 8227/8116 MOS RAMs □ Please send me the Fujitsu reliability story □ Please send me Fujitsu's short-form Product Selector □ Please send me the Fujitsu Product Catalog □ Please call me about an immediate application  Name			
□ Please send me the Fujitsu reliability story □ Please send me Fujitsu's short-form Product Selector □ Please send me the Fujitsu Product Catalog □ Please call me about an immediate application  Name		me data on the 822	27/8116 MOS
Selector  Please send me the Fujitsu Product Catalog  Please call me about an immediate application  Name  Title  Organization  Address  City  State	☐ Please send		
Please call me about an immediate application  NameTitle  Organization  Address  CityState	Selector		
OrganizationAddressState			
AddressState	Name		Title
CityState	Organization		
	Address	na dia 25° ani a	
ZipTelephone: ()_	City		State
	Zip	Telephone: (	)

You demand 4K and 16K RAMs with compatibility, maximum performance, versatile packaging, lowest price, prompt volume delivery and uncompromised reliability. Fujitsu delivers the industry's winners in every respect.

You get functional and pin compatibility with the industry-standard MK4027 and MK4116. But our devices were created from scratch, not licensed. The differences will make you the big winner.

Speed is your first bonus. 150-ns access time from our 'H' version. 200 ('E') or 250 ns ('N') for lower cost designs. No one delivers higher performance.

Packaging is your second big bonus. Both Fujitsu devices are available in 16-pin ceramic dip form, or in plastic for extra savings (8116 in Q1 1978). Either way, you're ahead.

**Price? You win again.** We match the toughest price competition in the world. Fairly. How? Higher yields from superior double-poly processing that's meticulously controlled and supervised.

**Delivery? You're still ahead with Fujitsu.** Our volume shipments already show Fujitsu to be the second largest supplier of MK4116-compatible 16K RAMs.

Reliability is where you're the really big winner with Fujitsu. Our in-the-socket field reliability is clearly superior. In fact, we 'wrote the book' on reliability—just ask for your copy. Our reliability book shows you how reliability is designed and processed into every device we ship. It starts with the initial concept and continues through design to pilot production, into full-scale manufacture. At Fujitsu, reliability is the result of deliberate management decision, implemented at all levels in the company.

Just how reliable are Fujitsu RAMs? Statistically—measured over millions of device-hours in user sockets worldwide—our delivered reliability is up to an order of magnitude better than competition.

Super reliability at no extra cost puts you way ahead. Why? Because the device that fails in the field can cost many times its original price to replace; worse, it can cost you your reputation. So when you consider the benefits to you and your customers of superreliable RAMs, Fujitsu memories, like our MB8227 and MB8116, make sense.

### FUJITSU AMERICA INC

2945 Oakmead Village Court Santa Clara, CA 95051 (408) 985-2300

Telex: 357402 • TWX: 910-338-0047

The IEEE

### Can IEEE's rift be healed?

That's the question facing Getting and Hogan as they prepare to take over as president and executive vice president

by Gerald M. Walker, Senior Editor





It has been called both "a disaster" and "reassuring," but whatever the personal opinions, the election is over for the Institute of Electrical and Electronics Engineers. The question that remains: can two high-level executives from California—Ivan Getting, president of Aerospace Corp., and C. Lester Hogan, vice chairman of Fairchild Camera and Instrument Corp.—manage the severely split institute as president and executive vice president?

The reason for the wide divergence of reactions—and the reason for the deeply divided membership and the closeness of the vote—is the continuing conflict over how to run professional activities.

Staunch supporters of an activist stance view the results as a setback, especially with Hogan's narrow victory as a petition candidate over Carlton Bayless, division manager for Pacific Telephone and Telegraph Co. Bayless was nominated by the board of directors to succeed himself.

Supported by a collection of industry executives and university deans, some of whom had held IEEE positions, Hogan made no bones

about his disagreement with the way in which the U.S. Activities Board has been spending the \$1.5 million in dues allotted it from U.S. members [Electronics, Aug. 4, p. 20]. Bayless, on the other hand, has backed the institute's move into social and economic programs, though he is considered a moderate compared to engineering consultant Irwin Feerst, who lost to Getting, the board's nominee.

Close vote. To members who agree with Hogan's criticism of USAB, the result is reassuring, but it is not the mandate desired by the Good Government Group that financed Hogan's campaign. The vote was 24,793 for Hogan and 24,644 for Bayless. Getting received 28,161 to 21,753 for Feerst.

Now that the smoke from this acrimonious campaign has cleared, Hogan has modified his stance somewhat. "I stated my views strongly to make certain there was no doubt, about them," he maintains. "But I will not force my personal point of view onto the institute. I am prepared to represent the feelings of the members. I have no special commitment to the Good Govern-

**The victors.** Ivan Getting, far left, is the new president and C. Lester Hogan the new executive vice president of the IEEE.

ment Group. My only obligation is to reunite the membership."

However, Hogan very quickly began working to get someone of his choice selected as vice president of USAB. He also expects to have a say in the selection of a permanent general manager, if that position has not been filled by the time Hogan takes office on Jan. 1.

Getting is faced with the task of keeping the board of directors in one piece after the hard feelings that Hogan generated with his comments about the poor quality of leadership in the IEEE. However, he blames the controversy on the tone of Feerst's attacks on the board.

Like Hogan, Getting insists he has no intention of dismantling USAB. "A positive program is needed," he says. "Professional registration is a chief issue at present, and I think we can have it resolved by the end of 1978."

As for Feerst, who has made the race as a petition candidate for president three times, he hints that this election may have been his last try.

"As engineers, we should now recognize it's time for a new design instead of trying to fix the present one." he says.

The only vote that was not close was for a proposition calling for submission of all board-nominated candidates for office by May 1 and all petition candidates by June 1 instead of July and August. It passed by 3 to 1. Two others, to reduce the number of regions to seven and to put all dues increases to a membership vote, did not get the necessary two-thirds majorities to pass.

### Just what you expect from the CMOS leader

# Get greater 8-bit latch selection from Motorola

Not one, or only two, but five different 8-bit latches for you to dove-tail with your individual requirements.

All are buffered output standard CMOS designed to meet JEDEC B Series specifications. They are fully compatible with both our extensive CMOS B Series and our many other CMOS circuits. Three of these MSI devices were designed by Motorola to meet emerging system needs. We designed the other two as second sources for good existing parts.

MC14099B, second sourcing the CD4099B, is an 8-bit addressable latch with an input of a single-direction write only port.

MC14599B, similar in many respects to the MC14099B, has significant difference in the input, a three-state bidirectional inputs which provides communication optimized for bus expansion and readily allows information retrieval. The MC14099B and MC14599B are available now.

MC14598B, a busoriented addressable latch,

DISABLE CHIP ENABLE DATA -BUFFERS LATCHES D5 DECODER MC14599B 18 PINS WORD DISABLE. - D 2 - D4 DATA -OUTPUT DECODER 16 PINS MC14099B RESET DATA STROBE ENABLE 000 3-BIT BINARY THREE-STATE LATCHES COUNTER BUFFERS -D5 - FULL 16 PINS MC14597B ENABLE RESET STROBE BUFFERS LATCHES DECODER 18 PINS MC14598B ENABLE DATA CLOCK 8-STAGE STATE SHIFT LATCHES BUFFERS - Q'S SERIAL OUTPUTS 16 PINS

also is similar to the MC14099B, but it has threestate outputs capable of driving bus lines. The output buffers drive either one TTL load or four LSTTL loads. The MC14598B is scheduled for introduction this month.

MC14597B is a busoriented 8-bit latch and features an on-board counter at the input for stepping data into the latches. Outputs are the same as those of the MC14598B. The MC14597B also is due out this month.

Last to be introduced (December), but by no means least, is the MC14094B, second sourcing the CD4094B. This device actually amounts to an eight-stage serial shift register, with a storage latch for each stage which strobes data to parallel B Series three-state outputs.

There it is. Just what you should expect from the CMOS leader. For information on Motorola's CMOS 8-bit latches, write to Motorola Semiconductor Products Inc., P.O. 20912, Phoenix, Arizona 85036, or circle the reader service number.



MOTOROLA Semiconductors

The mind to imagine...the skill to do.

MC14094B

Packaging & Production

# Chip carriers are making inroads

New technique, in which leadless ceramic devices are mounted on ceramic mother boards, means less weight than DIPs or hybrids

by Jerry Lyman, Packaging & Production Editor

A relatively new packaging technique is quietly muscling in on the market for complex, high-density electronic functions heretofore the preserve of component-laden printed-circuit boards and multichip hybrid integrated circuits. The reason: that new technique—mounting leadless ceramic chip carriers on a ceramic mother carrier—means smaller and lighter though denser systems and better thermal and electrical performance and reparability than does the DIP-pc approach.

The chip carriers, developed by 3M Co. of St. Paul, Minn. [Electronics, March 17, p. 81], are now being produced by 3M and Kyocera International Inc., San Diego, Calif. They are square, cofired ceramic packages with gold bumps on their bottom face. They are made the same way as high-reliability ceramic dual inline packages but are much smaller.

At first, the packages, which have 16 to 64 input/output counts, are reflow-soldered to some type of interconnect substrate. In 1975, 3M developed simple ceramic multilayer boards for mounting four chip carriers on a substrate the size of a dual in-line package. That ceramic mother board had side-brazed leads that could be inserted into holes on a large pc board. Then came other ceramic-mother-board approaches that interfaced the mother carrier directly with a connector.

The ceramic mother boards are presently available from 3M and Kyocera. But because of delivery problems, some firms have to make their own while buying the chip carriers from those suppliers.

There are four pioneer users of the new technique. Texas Instruments

	Weight (grams)	Area (cm²)	Yield	Cost
Printed wiring board	52	81	high	low
Chip carrier/mother carrier	12	12	high	medium
Hybrid	10	6	low	high

Inc. in Dallas, Honeywell Aerospace in St. Petersburg, Fla., and RCA Corp.'s missile and surface radar operation in Moorestown, N. J., all use it in products for the military. The fourth, Motorola Inc.'s Fort Lauderdale, Fla., operation, apparently is the first to incorporate it in commercial systems.

In papers delivered late last month at the International Symposium on Microelectronics in Baltimore, TI and Motorola pronounced themselves well satisfied with the new technique: not only does it permit packing densities approaching those of multichip hybrids, but it permits them to pretest the chips mounted on the carriers and thus avoid the low hybrid yield that is caused by low chip yields.

In putting together a hypothetical circuit containing 20 digital ICS (see table), Texas Instruments compared three techniques: DIP and pc board, chip carrier and mother carrier, and multichip hybrid. Not surprisingly, TI calculated that the combination of chip carrier with mother carrier would weigh less and occupy less space than the pc board, yet would have the same high yields. As for cost, it ranks second to pc boards.

Says Texas Instruments' Jon Prolop: "With increased automation,

the chip-carrier method could approach the cost of the pc board. And, though it will never eliminate the complex multichip hybrid, which is the ultimate in high density and performance, it is indeed an attractive alternative."

At Motorola, says Subash Khadape, "we are taking steps to reduce carrier assembly costs on pocket pagers and two-way radios." Motorola buys its chip carriers in a 330-piece array that is snapped apart along scribed lines. For the future, the firm's manufacturing engineers are considering automatically wirebonding identical chips into each chip carrier of the array. Then the loaded chip carrier could be split into individual carriers, tested, and reflow-soldered to individual mother boards.

Big reduction. The size and weight advantages of the chip carrier over DIP counterparts are considerable. On average, chip carriers available today are a sixth the size of DIPs. And TI says that it has found it a simple matter to obtain size and weight reductions of 60% in assembled circuits.

Another point made by TI is not widely known. That is the thermal improvement achievable with a chipcarrier – mother-carrier assembly:

# Sperry Univac's new mainframe-on-a-board: What you do with it is your business.

Whether your systems business is scientific, instrument control, or data communications, know this:

Our new V77-200 delivers more computing power than any other computer-on-a-board you can buy. Handling up to 32K/16-bit words of 660ns MOS memory.


Reason enough to call it the world's first mainframe-on-a-board. But there's more.

Because our new V77-200 comes loaded with "big machine" features. Like 8 programmable registers with byte, word and double word manipulation. Up to 32-bits of arithmetic precision. A powerful set of 187 instructions. Hardware multiply/divide. Direct memory access. Programed I/O. Multi-device automatic program loaders. A real-time clock. And a teletype/CRT controller. All standard. And all on a single 10.8" x 17" board.

There's even Virtual Console Logic that eliminates the need for a programmer's console by allowing you to control the V77-200 from a teletype or CRT keyboard.

You get "big machine" performance, too. Example: a microinstruction cycle time of 165ns that allows multiplication functions to be handled in just 4.9 microseconds—divide in just 8.

Plus your choice of OEM-tailored options. Like a variety of connector planes and general purpose interface boards for custom I/O designs. Three different 660ns memory boards (in 8K, 16K, and 32K-word modules). An operator's console. Power-fail detect and data save. Memory parity. Hardware for up to 64 priority vectored interrupts. An integral or modular power supply. And a system chassis. All the "unbundled" pieces you need for quick and easy system integrations.



The new V77-200 also saves you time and money by allowing you to use Sperry Univac's well-established floppy or disk-based VORTEX real-time operating system. In effect, allowing you to concentrate on the development of your application software.

And giving you access to Sperry Univac's extensive library of software subsystems, language

processors, and system utilities.

Best of all, the

world's first mainframe-on-a-board has a base price of just \$1200. Plus a discount plan designed to give even modest-volume OEM buyers a big break. And you can take delivery in a matter of days—not months.

No matter how you configure it, the new V77-200 is the most economical Sperry Univac yet. Delivering the kind of price/performance value that just makes good sense. No matter what business your systems are in.

For more information on the world's first mainframe-on-a-board, please contact: Sperry Univac Mini-Computer Operations, 2722 Michelson Drive, P.O. Box C-19504, Irvine, California 92713, Telephone (714) 833-2400.



### Probing the news

Ti's thermal analysis indicates that one particular unit using conventional pc board assembly had a junction temperature of 125°C, while the functionally equivalent chip carrier assembly registered 99°C. This improvement is due to the superior thermal conductance of ceramicmore than two orders of magnitude above that of G-10 printed-circuit material.

Removable. Finally, the chip carrier is distinctly easier to repair than the pc boards. Extremely large DIPS are very difficult to remove without damaging the board. In a series of tests, TI subjected an array of chip carriers reflow-soldered to a mother carrier to a simulated repair cycle in which a chip carrier was removed and replaced an averge of 15 times before it or its mother carrier was damaged.

Texas Instruments and Motorola have used the technique in a variety of applications ranging from the exotic to the commonplace. For example, designers at TI have applied the new packaging concept extensively to avionic and missile packages using both custom and standard chip carriers and mother carriers. In a charge-coupled-device integrated reformatter package, the Dallas company's designers use five custom chip carriers plus one standard chip carrier on a 10-conductivelayer cofired ceramic substrate with a brazed-on lead frame. One of the chip carriers houses one custom CCD, two custom complementary-metaloxide-semiconductor drivers, and one transistor. In Ti's arrangement, four of the carriers are mounted on a

Also at TI, eight CCD memory chips are packaged in eight chip carriers and reflow-soldered to a thick-film mother carrier. This scheme allows 524,288 bits of memory to be packed into 7% of the space required for a conventional pc board assembly.

For a missile, Ti's designers go to a custom, circular mother carrier to house a microprocessor, read-only and random-access memories, and input/output buffer devices all on chip carriers. In this system, chipcarrier packaging techniques reduce volume by 67% and weight by 75%. Because of these reductions, it was possible to cut the length of the missile itself.

Motorola also has some novel applications of the technique. In one circuit using chip carriers, a purely resistive substrate mounted on a carrier with a transparent cover is laser-trimmed to fine-tune an active filter. In another small chipcarrier - mother-carrier system, Motorola's designers have mixed leadless inverted devices in with chip carriers.

Failure-free. For its part, RCA's Missile and Surface Radar division has been using chip carriers, chiefly in avionics programs, for about four years. John Bauer, manager of design and development, says, "Re-


# Were Commonwealth

Chicago's Commonwealth Edison uses Ramtek color graphic displays for rapid display and status reporting of pipelines, valves, pumps, and other generating station data. A clear, color-coded display is updated every 5.0 seconds, giving nearinstantaneous visual scan-log-alarm functions, bar graphs, one-line piping diagrams, flow status, etc.

Before the Ramtek systems were installed, status reporting was by hardwired mimic boards, black and white alphanumeric CRTs and typers.

The Ramtek system not only costs less, it also allows more information to be presented to the operator in a form that is quickly and easily under-

stood. This results in better operator efficiency, and faster alarm reaction time. In Commonwealth Edison's 16,000 Megawatt system, thirty Ramtek color graphics displays will be utilized.




liability has been excellent, and no consistent failure mechanism has turned up in either carrier or mother board." The division has an advantage: it can buy many of the chips it needs already packaged and tested from RCA's Solid State division. And both RCA and Honeywell Aerospace

are experimenting with a package that combines the film-carrier chiphandling process with the ceramic-chip-carrier packaging process, permitting automatic bonding of the chip on film to the carrier's cavity, which is then sealed.

Honeywell's experimental work

comes after about two years of using the chip carriers with its own ceramic mother boards. Calvin Adkins, a senior designer on many of the division's military programs, says: "We went to this technique when our hybrid substrates got larger than 2 by 2 inches. At this point it was difficult to seal the overall hybrid, and the chip carriers, each with its own hermetic seal, solved the problem. No field failures have been reported in systems built around the chip carrier." Honeywell is trying to use only four sizes of carriers: devices requiring 16, 18, 24, and 48 pinouts.

Will the chip carrier win a larger following? The success of the concept, says Motorola's Khadape, "hinges on two vital factors: standardization and automation." Some progress has been made in standardization [Electronics, March 17, p. 81] but much remains to be done in automating the mounting and soldering of chip carriers to mother carriers.



Commonwealth Edison monitors on-off, full-empty, flow status, and other parameters on a Ramtek FS-2400. Color is assigned for steam, water, no-flow, and oil flow to differentiate visually between materials and status. On the RM-9000, resolutions from 240 lines x 320 elements to 512 lines x 640 elements are available.

Commonwealth Edison is but one of a growing number of customers who are finding that Ramtek's raster scan modular graphics and imagery systems are giving them the expandability, flexibility, and increased productivity they need. Besides the basic alphanumeric and imaging capability, Ramtek offers a wide variety of other functions including graphics—vectors, conics, plots, bar charts—pseudocolor, and grey-scale translation.

Ask about our new Ramtek RM-9000 family that is totally controlled by a standard 8080 microprocessor that really makes it easy to develop and download your own control software.

To find out more about how Ramtek can show off for you, call or write: Ramtek Corporation, 585 North Mary Avenue, Sunnyvale, California 94086 (408) 735-8400.



#### Government

### NASA's star to continue falling

Frosch, on the job as administrator just five months, to maintain agency's emphasis on terrestrial applications

by Ray Connolly, Washington bureau manager

Until the space shuttle becomes operational in 1980, aerospace electronics contractors see few new business opportunities at the National Aeronautics and Space Administration. It is an agency plagued not only by declining budgets and staff reductions but also by a White House almost indifferent to its wants. Few industry officials believe that Jimmy Carter's new NASA administrator, Robert A. Frosch, can or will be permitted to alter that image.

Carter's stated goal for NASA is to make more and better use of existing technology for terrestrial applications. Frosch, not yet on the job five months, and now beginning to discuss details of his post, is following that line. "We have come out of 20 years of development in space," he says, "and we have a tremendous technological capability which has only begun to be applied to terrestrial—that is, remote-sensing—applications." He sees NASA's future as "maturing the use of space" for such applications.

Such observations by the 49-year-old physicist are being interpreted by industry to mean no new major programs and a decline in research-and-development money. In their absence, NASA appears ready to continue with ongoing unmanned programs like the Tiros-N prototype meteorological satellite set for a 1978 launching [Electronics, July 7, p. 76] and the Nimbus-G, to go up the same year for experimental air and water pollution monitoring.

Frosch tends to confirm such industry fears when he observes that "after we have consolidated and sensed payoffs" from such programs, "we will be in a position to under-



**Looking to land.** NASA administrator Robert A. Frosch wants to "mature the use of space" for remote-sensing applications.

stand what it is we can do with the shuttle. Then we can begin to think about a next step."

Next steps. Satellite engineers, for example, should start to think about the impact of the shuttle in terms of cheaper and better engineering, Frosch says. "You are no longer putting a satellite on an expendable vehicle, doing the best you can with it, and then kissing it good-bye. You can truly assemble things in space. check them out, and then retrieve them later" for maintenance or repair. "We've talked a good deal internally about what that means, but I think we are just beginning to think about it. It's an area in which industry might be very useful."

With the new Department of Energy now in the Washington limelight, corporate technology managers question how much White House support NASA can count on.

They note that Frosch—no new-comer to Washington's bureaucratic wars, having served as assistant Navy secretary for R&D during a decade of Pentagon duty—was not even appointed until more than six months after Carter's election, when the fiscal 1978 budget hearings were already well advanced in Congress.

In an October forecast of the NASA market over the next five years, the Electronic Industries Association projected a budget decline that "will likely continue through 1982." Apparently, NASA's needs will be subordinated to Carter's goal of balancing the budget by 1981.

Frosch himself is still laboring with problems he found on his desk on joining NASA. Chief among them are the \$4.017 billion appropriation for fiscal 1978 that one headquarters staffer notes "doesn't even cover inflation factors" and a directive to cut agency personnel by 500 jobs to 23,237 by the end of the fiscal year while at the same time hiring 425 minority or female workers. Although Congress lopped only \$17 million off Carter's revised budget request, most of that—\$13 million—fell on research and development.

Nor has Frosch been helped by declining public and press interest in NASA since the end of the lunarlanding effort. "In talking with industry and related groups," he says, "I find there is tremendous interest in applications and science programs, but people feel they haven't heard about those things. They have heard about some, but only a little, and have seen little interpretation about what those new programs mean" in terms of benefit to the nation.

# ELEC-TROL RELAYS



# YOUR BEST BET FOR REED AND SOLID STATE RELAYS

For those of you who haven't used our relays yet – here are two good reasons for making Elec-Trol your first call.

(1) Reed Relays We sell more dry reed relays than any other manufacturer in the United States. We offer packaging styles like DIP's, Open Lines, Encased Lines, Molded Lines, and Blue Boys—in a complete range of coil voltages and contact forms. You can get optional features like magnetic shielding, electrostatic shielding, and contact run-ins. Also available—the best in mercury-wetted.

(2) Solid State Relays We're coming on strong with printed circuit board and standard high-power-switching models that feature: zero-crossover switching, photo isolation between input and output, positive on/off control, TTL compatibility, long life, immunity to shock and vibration, and competitive pricing.

So the next time you're thinking relays—think Elec-Trol. Send for a quick overview of our products. Ask for our Short Form Catalog.

Elec-Trol, Inc., 26477 N. Golden Valley Road, Saugus, CA 91350, (213) 788-7292, (805) 252-8330. TWX 910-336-1556.

**ELEC-TROL** 

### MOLDED-LINE REED RELAYS



### TOUGH CUSTOMERS!

Now for about one-third less than the price of most standard sealed reed relays, Elec-Trol offers its new Molded-Line Reed Relays. Not only do these new units meet the highest performance standards but they are also totally molded in epoxy to stand up against the kind of extreme moisture conditions and mishandling that would sideline ordinary relays. These new "tough customers" provide complete protection even when totally immersed in cleaning solvents.

With every relay you get these features—highest quality, thoroughly tested, dry reed switches • dry-circuit to 10-watt load switching capability • terminal spacing based on the 0.1" X 1.0" standard configuration • compact units in sizes from .310" to .630"W X .335"H X .950"L. And you may select from the following options—magnetic shielding • electrostatic shielding • contact run-in for one million operations.


These tough new units are available with their hermetically sealed reed switch contacts in Forms 1A through 4A. For more information, use the reader service card. For immediate action, contact your local distributor, representative, or the factory direct.


Elec-Trol, Inc., 26477 N. Golden Valley Road, Saugus, CA 91350, (213) 788-7292, (805) 252-8330. TWX 910-336-1556.


**ELEC-TROL** 

# Designers

**Toggle Switches** Bat, lever lock, Designer Line, sealed. Big, broad









**Pushbutton Switches** Choice of sizes, colors, circuits, ratings. Styled to "turn you on".

Tool Handle & Slide Switches Variable speed, reversing. Double insulated.











# Choice.

the exact switch or relay you need—when you need it.

It's no wonder so many designers specify Cutler-Hammer. For quality, reliability, availability, and style. For commercial, industrial, and military applications.

We simply offer more—of everything!

### Snap Switches Lever, roller, leaf, and

Lever, roller, leaf, and pushbutton actuators. Four terminal styles.









Switch Accessories Guards. Boots. Seals. Caps. Decorator facenuts. And much more to protect, code or customize.





Rotary Switches
Precision and general
purpose. Single and
multiple wafer





Illuminated Switches
Rockers, paddles,





Relays















CUTLER-HAMMER

SPECIALTY PRODUCTS DIVISION, Milwaukee, Wis. 53201



# MICROPHOTOS



Your IC lead frames look like this at 30X enlargement (unretouched). Because they are punched out of metal, the edges are rough, jagged and irregular. In contrast, the flat sides of the lead frame are smooth, even and perfectly plated.




An ordinary edge-bearing socket contact after 5 insertions of DIP lead frame. Contact has been spread apart to show inside faces of contact. Notice how the contact has scars and abrasions from rough, irregular edge of IC lead frame. Electrical contact is degraded and resistance is increased. Reliability is obviously reduced.

Lead frame in place in an ordinary edge-bearing contact.



ROBINSON-NUGENT "side wipe" socket contact after 5 in sertions of DIP lead frame Contact has been spread apart to show inside face of contact. See how the RN contact—because it mate with the smooth, flat side of the IC lead frame—retain its surface integrity. Thi 100% greater lead frame contact results in continue high reliability.


Lead frame in place i RN "side-wipe" contac








High reliability IC sockets ...we've got 'em all!




# expose'junk'socket problems

# Secret of RN high reliability 'side-wipe' DIP sockets revealed by microphotos

Here's microscopic proof that high reliability Robinson-Nugent "side-wipe" DIP sockets make 100% greater contact than any edgebearing socket on the market. This advance design provides constant low contact resistance, long term dependability—trouble-free IC interconnects. Yet RN high reliability DIP sockets cost no more than ordinary sockets!




Get the high reliability that eliminates trouble. RN "side-wipe" DIP sockets make contact with the wide, flat sides of your IC leads. You get 100% greater surface contact for positive, trouble-free electrical connection.



### WRITE TODAY


for catalog and informative book "What to Look for in IC Interconnects." Free

from Robinson-Nugent—the people who make more kinds of high reliability IC sockets than anyone.



They're even packaged for high reliability. "Protecto-pak" packaging delivers consistently perfect RN sockets to your production line—for automated or manual assembly.





# Intel delivers $\mu$ Scope 820. Finally, a diagnostic instrument just right for the Age of the Microprocessor.

Troubleshooting microprocessor systems is easier than ever with Intel's new  $\mu$ Scope<sup>TM</sup> 820 Microprocessor System Console. It's a powerful, programmable, fully portable real-time diagnostic instrument. And it's designed specifically to speed and simplify system checkout of your microprocessor-based products.

 $\mu$ Scope 820 is really the first test instrument of its kind. It's built around its own microprocessor, to provide a "smart" solution that's highly sophisticated, yet easy to use. Because it's user programmable with interchangeable plug-in ROMs or PROMs, it's like taking a design engineer along on every service call. And because it's fully portable, the  $\mu$ Scope 820 console goes wherever the action is—to the design lab, the production line or into the field.

Unlike logic analyzers, the  $\mu$ Scope 820 console provides a genuine solution for test and service personnel. It provides the same inside look at system operation that you get with a logic analyzer. But the  $\mu$ Scope 820

goes far beyond the mere collection of data. Its internal microprocessor system can actually analyze the data it collects. It does that with diagnostic programs you design specifically for your end product.

Rather than passively watching system operation, the  $\mu$ Scope 820 console lets you execute application programs or diagnostics you develop, in real time or single steps. And it provides full breakpoint capability



High level command keys, operator prompting, and binary/hexadecimal display of all system registers, I/O ports and memory give you greater control and make it easier to use than any other test instrument.

Until now the only way to get this kind of diagnostic capability was to use your Intellec® Microcomputer Development System. Now we've taken the Intellec features that have proven most useful for field service and production-level system checkout and have packaged them in this self-contained 20-lb attache case.

That's portability.

And we've enhanced that portability with a  $\mu$ Scope 820 price of just \$2000,\* complete with personality probe and all accessories. So you can afford to put a μScope 820 console wherever you need one, and free your development lab instruments to concentrate on development. No longer must you invest in in-house-designed custom test instruments for each of your end products. And the µScope 820 console will be available with a selection of front panel overlays, "personality" cards and system probes to support a variety of microprocessors.

To get your copy of our µScope 820 brochure and to arrange for a demonstration right in your lab, contact your local Intel distributor or sales representative. Or write: Intel Corporation, 3065 Bowers Avenue, Santa Clara, California 95051. Telephone (408) 987-8080. In Europe contact: Intel International, Rue de Moulin a Pàpier, 51-Boite 1, B-1160, Brussels, Belgium. Telex 24814. In Japan contact: Intel Japan, K.K., Flower Hill-Shinmachi East Bldg. 1-23-9, Shinmachi, Setagaya-Ku, Tokyo

154. Telex 781-2846.

# intel delivers.

\*Domestic U.S. price only, quantities 1-10.

It's a stand-alone sweep-signal generator that provides all the performance of much higher priced competitive instruments.


To back up that sweeping statement, consider the following: The Model 2002 sweeps from 1 MHz to 2.5 GHz in four bands with 20 milliwatt output,  $\pm 1\%$  display linearity, and  $\pm 0.5$  dB flatness. Consider also that it includes an internal 10 dB per step attenuator which in conjunction with a continuously variable pin diode attenuator

results in an output power range of +13 to -77 dBm. Plus a band-stacking option that lets you cover the entire 1 to 2500 MHz frequency range in one sweep. A  $\pm 2$  dB amplitude slope adjustment that compensates for frequency dependent variations in test set-ups is also available along with a deluxe marker module containing 1, 10, 50 and 100 MHz harmonic markers that operate over the entire frequency range of the unit. Finally, consider the price: \$2,700 for the basic

unit and only a total of \$3,200 if ordered with the bandstacking, deluxe marker module and slope adjustment options. Compare the prices against those of available competitive units.

WAVETEK Indiana Incorporated, 66 N. First Ave., P.O. Box 190 Beech Grove, Indiana 46107 Telephone: (317) 783-3221 TWX 810-341-3226

WAVETEK



### **Technical articles**



# Today's infrared-reading vidicons map clearer pictures

To provide a flicker-free picture, new thermal-sensing system uses an image-difference processing technique

by A. G. Shephard, Thomson-CSF Electron Tube Division, Boulogne-Billancourt, France


☐ Fighting a forest fire, examining a woman for breast cancer, and checking electronic circuitry for hot spots all have something in common. They can benefit by the added dimension of information provided by a pyroelectric-target television tube that uses the infrared radiation emitted by the object on which it is focused to produce a "heat picture." Such a thermal image may appear on a standard TV monitor (above) and will provide a view of how any heat-emitting system or phenomenon—including the human body—is functioning at the time the image appears.

The technology that goes into the thermal tubes is not that different from that of conventional TV-camera tubes. Processing signals from the IR spectrum does require special attention to reading the temperature

changes that activate the tube's target area and to providing modulation of the incoming radiation when the object is not moving across the field of view.

The thermal imaging that results can find widespread applications in the medical, industrial, and surveillance fields. Such pyroelectric vidicons solve the problem inherent in detectors used in conventional thermographic camera systems, which convert the incoming radiation to voltage and require supercooling to reduce the noise to an acceptable level. A new thermal-imaging tube, the Pyricon, solves another serious problem: provision of a flicker-free image under all conditions.

The Pyricon's construction (Fig. 1) resembles that of a standard vidicon, a small TV-camera tube. The significant differences are the IR-transmitting window and the



**1. Basic structure.** A camera incorporating a Pyricon tube and simple focusing system shows the similarity between an infrared-reading vidicon and a standard visible-light vidicon. The only real differences are an IR-transmitting faceplate and a pyroelectric target.

target's pyroelectric material, which is sensitive to IR light rather than visible light (see "The pyroelectric effect and poling," p. 103). The lens focuses incoming thermal radiation onto the target, which absorbs heat energy. This absorption creates a temperature distribution that in turn causes electrostatic charges to appear on the surface of the pyroelectric target.


#### Reading the thermal image

The resulting potential distribution, which reproduces the thermal image, can be read by an electron beam as in a standard vidicon. In effect, the reading cancels the potential distribution by depositing charges on the target's face—a process called charge compensation. The initial potential at a particular point of the target determines the quantity of charge deposited there. These charges produce the video output signal by capacitive coupling to the backing electrode, which is an evaporated metal layer on the opposite face of the target.

Since the pyroelectric effect depends upon changes in temperature on each part of its target, a pyroelectric tube will not pick up an image from a steady-state object—the temperature will vary over the target, but it will remain constant at each particular point. Of course, if the object is moving, or if some form of IR pulsing illuminates the scene, there is no problem. Otherwise, there must be some means of moving the image on the tube's target or some way of modulating the incoming steady-state radiation. This important consideration will be discussed below.

Another factor to consider is that certain IR bandwidths are strongly attenuated by the atmosphere (Fig. 2). However, some bands do transmit well at certain wavelengths, called atmospheric-transmission windows. So the pyroelectric tube's faceplate and the camera's lens are chosen for optimum performance at these wavelengths (Fig. 3).

To insure that no image information is lost, the scanning electron beam must be able to read all positive and negative charges appearing on the surface of the target. Thus the basic potential of the target surface must be sufficiently high so that even the most negative potential



**2. Transmission windows.** When viewing distant objects, infrared radiation is strongly attenuated by the atmosphere. Black-body spectral radiation curves for common temperatures are superimposed to show the importance of transmission "windows."

variations will still permit beam access.

Two different operating modes can be used. However, the anode-potential-stabilized mode, in which the target potential is held close to that of the anode, results in relatively low sensitivity. So almost all thermal-imaging systems use the cathode-potential-stabilized mode. Positive charges raise the target potential up to a positive potential, which is close to the cathode potential. The pedestal potential, which must be constant over the target surface, is greater than the variations in potential caused by increases and decreases in the target's temperature, so the electron beam can always read the target.

In the presence of a thermal image, the signal current is the sum of the pedestal current and the current caused by the temperature variations in the pyroelectric target. In the absence of a thermal image, the beam will deposit electrons that lower the target potential by a value equal to the pedestal. Then a minute pedestal current flows through the target.

#### **Producing pedestal potentials**

Two means of generating the pedestal potential are commonly used, each having particular advantages and disadvantages. In one, positive gaseous ions deposited on the target surface generate the pedestal. The ions are created by the electron beam striking gaseous molecules, which can come from a gas reservoir in the tube or from gas introduced in bulk into the envelope during fabrication. The reservoir is generally the preferred mechanism, as it allows complete control over the tube in all operating modes. Increasing the reservoir-heater supply voltage (variable between 2 and 5 volts root-mean-square) increases the number of free gas molecules and thus the number of positive ions.

The other technique for generating the pedestal potential uses a gasless tube. The cathode is pulsed negatively during horizontal flyback so that the electron beam strikes the target with sufficient energy to create

### What thermal-imaging systems actually see

A common misconception is that shades of gray or various colors in a display of a thermal-imaging system indicate different temperatures. Although sometimes true, it is far from being so in all cases.


Passive thermal imaging systems detect electromagnetic radiation spontaneously emitted by all objects at temperatures above 0 K. Consider the ideal case known as the black body: a substance that absorbs all radiation incident upon it at all temperatures and then radiates it. Although such a black body can never be realized, a hollow sphere with a small opening is a close approximation. Any radiation entering the opening undergoes many attenuating reflections and is almost completely absorbed.

The spectral distribution of the radiation intensity of radiation emitted from black bodies for various temperatures is shown below. Radiation for all black bodies at identical temperatures is the same, so that the total energy radiated by a black body (the area under the curve) is characteristic of its absolute temperature,  $\theta$ . The relationship is expressed as  $R=\sigma~(\theta^4-\theta_0^4)$ , where  $\theta_0$  is the absolute temperature of the surroundings and  $\sigma$  is a constant. The target of a pyroelectric vidicon detects a change in this energy caused by an apparent change in


the object's temperature, so long as the change in infrared radiation is within the spectral range of the system.

However, the black body is an idealized case. With actual objects, there is great variance in the emissivity (the ratio of the energy emitted by an object to the energy emitted by a black body at the same temperature). Although the emissivity of human skin at room temperature is close to unity, the emissivity of polished metals is only a few tenths. Moreover, the emissivities of objects of the same material but of different surface finishes can differ.

Although general-surveillance tasks and medical diagnostics are relatively straightforward, industrial and scientific applications may contain hidden pitfalls. For instance, the different emissivities and spurious reflections of the different materials used to construct a complex object such as a traveling-wave tube can give a completely false idea of temperature distribution. This is shown right: on the top is a photograph of a traveling-wave tube; below are two images of it reproduced by the Pryicon showing the apparent temperature distribution before and after the traveling-wave tube was sprayed with flat-black paint. Such techniques render the emission characteristics approximately constant over the whole surface of the object.







secondary electrons with an emission coefficient greater than one. The loss of the negatively charged electrons results in an increase in positive charge on the target surface, which produces the required pedestal.

Two principal techniques are available for modulating incoming radiation to produce changes in radiation power impinging on the target. They are necessary when the camera is focused on a stationary object that is in a steady state. The choice is:


1. Moving the image on the target by panning the camera or nutating the lens—rotating it without changing its orientation.

2. Interrupting the flux of radiation falling on the target by chopping with a sectored disk or similar device.

The first method was commonly used in the early thermal-imaging cameras because it is easy to accomplish. However, the constant movement of the image on the target means that the image on the TV monitor also moves. Electronic compensation can stabilize the display, but residual movement is often visible, and objects that are relatively warm with respect to the rest of the scene leave "comet tails" and smears. In addition, eliminating the fixed-pattern noise caused mostly by small irregularities in the target material is difficult.

Chopping the incoming radiation is preferred, since it provides a stable image and fixed point of view. It is not used in most of the available cameras because it requires signal processing not found in standard video cameras—although this processing is simple to implement.

The problem with chopping is that the raw output signal is from the tube is of alternating polarity. When the chopping disk is open, a warm part of the scene heats



**3. Targeting materials.** Pyricon pickup-tube performance can be optimized for different atmospheric-window regions in the infrared spectrum. A target material, such as germanium coated for operation in the 8-to-14- $\mu$ m region, provides a high spectral sensitivity.


up the corresponding area of the target and produces a signal of a certain polarity. When the chopper cuts off the radiation, the target's warm part starts to cool, producing a signal of the same form but of opposite polarity. The TV-monitor image would, of course, be completely unusable because it would consist of alternating hot-is-white and hot-is-black fields.

Even inverting alternate parts of the signal would not be completely satisfactory, as the pedestal signal would still alternate in polarity, causing a heavy flicker. Simple subtraction of the pedestal before inversion does not work because it would require a rigorously uniform pedestal signal. Moreover, fixed-noise patterns, caused by pedestal variations as well as by target irregularities, would still be visible.

#### Eliminating flicker

The Pyricon camera system uses an image-difference processing technique that eliminates flicker. A synchronous motor drives a sectored disk, which chops the incoming thermal radiation at 25 or 30 hertz depending on whether the European or American standard frame rate is used. The video amplifier's signal feeds into a frame processor (Fig. 4), which stores and compares alternate fields (half images) to produce an output signal in which the fixed-pattern noise has been removed and the video component doubled. The circuitry also flattens and reduces the pedestal. Then it inverts alternate fields to give a constant-polarity video signal in which the small pedestal is alternately positive and negative. The signal then passes into two parallel black-level-control circuits, where both pedestal signals are brought to a standard black level of the output signal.

As in standard video cameras, various synchronization and blanking pulses are added to give a 625- or 525-line interlaced standard video signal. Consisting of eight shades of gray, the signal can be displayed directly on any commercial monitor and can be recorded on stan-



**4. Flicker-free operation.** Chopped radiation from the tube's video amplifier is fed into the frame processor, which stores and compares alternate image fields to remove fixed-pattern noise, double the video component, and flatten and reduce pedestal voltage.

dard video-tape equipment. The gray shades range from white (hottest) to black (coolest), but it is important to note that they may not correspond exactly to the temperature distribution on the object from which the image is drawn (see "What thermal-imaging systems actually see," p. 101).

The black-and-white signals can be processed further in a colorizer and fed to a standard color monitor to give real-time color-coded isotherms, or other types of specialized display. The basic technique is relatively straightforward. Each of the eight possible levels in the gray scale is allotted a 3-bit code, black being 000 and white 111. The camera signal is sampled at a

### The pyroelectric effect and poling

The operation of the pyroelectric vidicon is based on the properties of certain types of crystals, called ferroelectrics, that are electrically polarized in a well-defined direction, known as the polar axis. The degree of polarization is temperature-dependent. The magnitude of this pyroelectric effect increases with temperature until what is known as the Curie point is reached. Beyond this, the polarization disappears.

Another effect of heating or cooling a thin slice of a ferroelectric crystal is to create an accumulation of charge in a direction perpendicular to the polar axis—a positive charge when the crystal is heated, and a negative when it is cooled. Moreover, the charge is proportional to the variation in polarization caused by the temperature change.

As well as increasing the pyroelectric effect, temperature increases rapidly hike the crystal's dielectric constant, which reduces the efficiency with which the charges can be read by the electron beam in the vidicon. Therefore, the maximum useful pyroelectric effect is obtained at a temperature somewhat below the Curie point. For triglycine sulphate, a commonly used material, the Curie point is 39° C, and the maximum useful temperature is between 35°C and 37°C.

Since the pyroelectric effect results from electric dipoles inside the material lining up with the polar axis, it is at a maximum when all the dipoles are oriented in the same direction. This orientation may be achieved by a process called poling, which consists of applying a strong do electric field across the crystal.

To obtain this dc field in a pyroelectric vidicon, its target is bombarded with high-velocity electrons. Secondary-electron emission stabilizes the target surface next to the fine mesh screen, (grid 4 in Fig. 2) at mesh potential—typically between 225 to 275 volts. The resulting electric field correctly aligns the dipoles.

A tube that needs poling will give images in which the sensitivity is not constant, causing gray, contrastless areas, a marbled appearance, or sets of closely spaced, parallel lines. The standard procedure is to carry out the 1-minute poling operation just after turning on the camera—although if it has been off for only a few minutes, repoling is often not necessary. A user-controlled push button triggers special circuitry in the camera control unit that automatically ensures the required electrode voltage-switching sequence. Unless such an accident as target overheating occurs, poling need not be repeated during operation.

5-megahertz rate, giving 500 samples per TV line. The appropriate code for each sample goes to a color monitor where each bit in a 3-bit word controls one of the three guns in the color tube. Thus, 111 results in all three guns working (white), whereas 000 means none are working (black). 100, 010, and 001 result in only one gun working, giving the basic red, green, or blue of the color tube. Other combinations will result in two guns working, giving well-defined composite colors.

#### **Assessing performance**

As with all imaging systems, the best way to appreciate performance is to look at the displayed image. Even photographs give serious image degradation especially when printed, as in this article.

However, an idea of system performance for the Pyricon may be gathered from the table. These figures are for a 625-line, 50-field-per-second image. The camera had a chopper and a frame store, so the image was in a fixed field of view and flicker-free. Slightly better performance can be obtained with panning—if the panning speed is carefully adapted to the target's characteristics. But such a technique is obviously too tedious for everyday operation, and of course it does not provide

a fixed field of view for the observer viewing the image.

The first figure in the table, the scanned target area, is highly significant. The smaller the target scanned, the less the signal current and resolution.

The irradiation change for which signal current is given typically is equivalent to an object's temperature difference of about 15°C. So signal levels are obviously very low in pyroelectric vidicons when small temperature resolutions are involved. It is for this reason that very careful preamplifier design and noise-elimination techniques such as frame storage are essential.


The two spatial resolutions are given for a minimum resolvable temperature of about 0.3°C. As these two parameters are interrelated, Fig. 5 will give a better idea of the Pyricon's performance. Curve 1 is for the panning mode, and curve 2 is for chopping. The scanned target area was 4.3 square centimeters, and the good-quality coated infrared lens was opened to an F stop of 0.7. The object was an infrared IR test chart with characteristics almost like that of a black body. It consists of a 300-K background with slightly warmer bars superimposed.

The gamma characteristic is the same as that of any optical system. It refers to the slope of the target-irradiance/signal-current curve.

The responsivity figure permits calculating the signal current that will be obtained for a given change in target irradiance. For example, consider the TH 9840, a Pyricon tube with a coated germanium window. If it has an intrinsic responsivity (S) of 4 microamperes per watt, and if it receives radiation in the bandwidth 8 to 14 micrometers, then a change in irradiation ( $\Delta E$ ) of 1 w per square meter will give a signal current ( $i_s$ ):

 $i_s = A \times \Delta E \times S$ 

Scanned target area	4.3 cm <sup>2</sup>
Signal current (change in irradiance of 10 W/m <sup>2</sup>	_ > 17 nA
Resolution at modulation transfer function of 50%, 20 ms after irradiation	> 2 line pairs/mm
Limiting resolution	> 6 line pairs/mm
Average gamma	1
Intrinsic responsivity (8 $\mu$ m < $\lambda$ < $\mu$ m)	$= > 3.5 \mu\text{A/W}.$



**5. Imaging IR chart.** Scanning an 18-by-25-millimeter area of an infrared test chart having characteristics nearly those of a black body shows the minimum resolvable temperature in panning and chopping modes as a function of spatial resolution.

**6. Locating losses.** Ineffective thermal insulation in buildings shows up as white areas in the photograph taken from a Pyricon tube display. On a scale of eight gray tones, the areas of excessive heat losses show up as white; the coolest areas are black.

where A is the 4.3-cm<sup>2</sup> scanned area.

$$i_s = (4.3 \times 10^{-4})(1)(4 \times 10^{-6}) = 17.2 \times 10^{-10} A$$

The overload characteristics of the Pyricon also are good, since signal saturation occurs only with a target radiance exceeding 40 w/m². This corresponds, for example, to a lens opened to an F stop of 1 and an object temperature of 85°C. At higher temperatures, the lens should be stopped down to its lowest value and then opened progressively. If the tube is overloaded, its target will become depoled.

#### **Applications abound**

Pyroelectric vidicons may be used in active or passive environments. In active applications, which are chiefly scientific and industrial, a source of infrared radiation must illuminate the scene of interest.

Passive applications are much more common, because only self-emitted IR radiation (in the 8-to-14- $\mu$ m spectrum) is needed. Such emissions are inherent in human bodies, trees, buildings, etc. Thus the Pyricon thermalimaging tubes are well suited for medical, industrial, and security applications.

The detection of breast cancer is perhaps the most widely known use of thermography, but it is far from being the only medical application. The heat radiated by a given area of skin depends mainly on two factors: the blood flow beneath the surface of the skin and the



condition of the surface of the skin. Medical thermography makes use of the fact that any change in skin texture or any problem that alters the blood flow will cause a change in real or apparent surface temperature.

For example, a severe burn will change the skin texture and therefore its emissivity. Careful use of thermographic equipment can give a rapid assessment of whether a burn is likely to heal or has already started to do so, indicating well in advance whether grafting is needed. Subsequently it can be used to give early evidence concerning the success of grafting operations by indicating if normal blood circulation is returning.

Any anomaly in blood circulation causes a change in the body's surface temperature, and this fact opens up a host of other applications for thermography. Among them are detecting thrombosis and locating partial blockage of arteries, checking the success of surgery, showing the extent of permanent circulatory damage prior to amputation, indicating if and where surgery would be used to remove varicose veins, and determining the efficiency of drugs such as pain killers that affect the blood circulation.

Thermal television systems using the Pyricon tube promise to come into their own for surveillance and inspection chores from a moving vehicle. Because no special cooling is required and because the equipment can operate in any position with no moving parts and with little or no maintenance, the systems are perfect for

long-term surveillance and inspection jobs in a rough mobile environment. An interesting application is in forest fire control, where an airborne camera can "see" through the smoke in order to map out centers of combustion not visible to the human eye.


#### Industrial uses

Thermal imaging cameras are also used to check highvoltage lines, since poor connections and faulty insulators heat up. They can locate leaks in pipelines and gas ducts and heat losses in buildings (Fig. 6).

Another application is checking the homogeneity of cast concrete. Density changes or microcracks cause uneven surface temperatures (Fig. 7). Thermal imaging can also locate discontinuities when concrete is heated by such sources as the sun. What's more, these camera systems can locate overheating in electrical and electronic circuits and can check aerodynamic heating of test objects in a wind tunnel.

In general, surveillance and industrial inspection applications are similar to those of mobile inspection. But they are less physically demanding because the equipment is mounted in a fixed location and is buffered from bad weather, shock, and vibration.

In industrial applications, fixed Pyricon cameras can be used to control the quality of plastics and other materials. Sections containing bubbles or cracks can be weeded out and the surface finish checked.



7. Heat stopper. Real-time thermal imaging pinpoints microcracks in structures. Here, heat applied to the left of the test sample diffuses through it until it meets with a microcrack that otherwise would not be visible to the naked eye.



# Two formats go head to head in consumer VTR confrontation

Sony's Beta Format and Victor Co. of Japan's Video Home System, vying for position in the U. S. and Japanese consumer markets, differ significantly in physical layout and signal-processing methods

by Charles L. Cohen, Tokyo bureau manager



☐ To bring video tape recording to the point where it stands on the threshold of a potentially huge consumer market, Japanese engineers—primarily at Sony Corp. and Victor Co. of Japan—have had to steer an ingenious and inventive course between the complex NTSC color standards, the state of the magnetic-recording art, and the price the consumer is willing to pay.

Poised at the \$1,000 price barrier and sure to duck under it in the coming year, home video cassette recorders should become one of the hottest high-ticket consumer products since the introduction of color TV receivers some 20 years ago. In the forefront are two similar but nonetheless incompatible systems—Sony's Beta Format and Victor's Video Home System (VHS). The major American and Japanese television makers are now aligned with one or the other of these (Fig. 1), even though there are a couple of other VTR systems available (see "The other two VTR entries," p. 113).

Tape economy is the name of the game in consumer VTRS. While video tape technology has been around for decades, and audio tape technology for even longer, the breakthrough represented in these newer formats is in high-density data recording rivaling that of the most sophisticated computer storage systems, yet at a price consumers can afford. Compared with the commercial

machines standardized in 1969 by the Electronic Industries Association of Japan, the present VTRs use almost 80% less tape per hour in their standard-play modes. For one thing, these machines have exceptionally narrow video tracks; for another, unlike previous tape recorders, they lack guard bands between adjacent tracks (Fig. 2). Other means are used to avoid crosstalk between tracks, and the two systems embody slightly different solutions to the problem.

Recording and playing time, however, is the major difference apparent to the consumer between the Sony and Jvc formats. Sony initially aimed for one hour, which had been more or less the expected playing time for consumer vtrs. But Jvc went after two hours, the duration of the longest programs broadcast on Japanese tv. Both have since developed extended-play vtrs: Sony a two-hour model, and Matsushita Electrical Industrial Corp. a four-hour version being produced in Victor's vhs format for American companies.

Between the two ½-inch-wide-tape formats there are of course a number of basic similarities dictated by the fundamental nature of magnetic-tape recorders (see "What makes consumer VTRs run," p. 108). Both use what they call a two-headed helical scan to increase relative speed between recording heads and tape. The

#### What makes consumer VTRs run

Video tape recorders use the same laws of physics as audio tape recorders—in fact, a narrow track along one edge of the video tape operates in exactly the same manner as conventional audio tape recorders, but at a slower speed. The big problem for VTRs is that the conventional NTSC video signal includes frequencies above 4 megahertz and below 30 hertz.

To record the high frequencies, the tape must slide over the head at a speed of 6 meters a second or faster. Yet the wavelengths of the magnetic fields recorded on the tape are so short that submicrometer head gaps are required and head-to-tape spacing must be even smaller.

No consumer VTRs have yet been made in which the tape moves at 6 m/s. Rather, all have been of the helical-scan type, which combine slowly moving tape with rapidly moving tape heads. The tape spirals around a revolving drum, generally for exactly half a turn, and the tape heads are attached to the edge of a rotating disk. This setup allows the tape head, traversing a circular path with the same radius as the drum, to scan diagonal tracks on the tape at the high speed required to record the video signal. Tape speed need only be fast enough to provide the desired track pitch and is orders of magnitude slower than recording speed.

Consumer VTRs are not capable of directly recording

the composite NTSC video signal and color subcarrier, which therefore is disassembled into baseband luminance and subcarrier chrominance signals before being recorded. Even so, the almost-17-octave frequency range of the luminance signal is too much for normal recording techniques, and a narrow-band frequency modulation technique is used to decrease it.

The chroma subcarrier signal is translated into the frequency range below 1 megahertz and recorded as an amplitude-modulated signal. The fm video signal in the 3-to-5 MHz band also serves as the ac bias for the chroma subcarrier.

Along one edge of the tape is a single or a dual (stereo) audio channel. Audio recording is completely conventional. Often, a separate erase head is mounted just before the audio head to facilitate dubbing a new audio signal alongside the video signal.

Along the other edge of the tape is the control track—normally a 30-hertz square-wave signal—which synchronizes playback with recording on the tape.

The normal sequence of recording includes a full-track erase head before the drum. Video signals are recorded as tape passes over the drum, and soon after it leaves the drum, the audio and control track signals are recorded simultaneously.

tape slips along a track that runs spirally around half the periphery of a drum. This drum consists of a concentric stationary layer or layers and a spinning section that makes 30 revolutions per second. Attached to the edge of this spinning disk are two heads that record successive diagonal tracks of video information across the tape. The heads and the tape travel in the same direction.

Like other color VTRs that preceded them, these two systems have to cope with video frequencies ranging from 30 hertz to more than 3 megahertz. So they record the luminance signal as a frequency-modulated signal in the 3-to-5-MHz band and translate the chroma signal into an amplitude-modulated signal below 1 MHz. The use of narrow-band fm makes it feasible to record the luminance signal, which spans a frequency range of almost 17 octaves and, in addition, provides low-noise playback. The chroma signal is translated into the unused frequencies below the lower sideband of the fm signal, which in turn provides the high-frequency bias required for recording the chroma signal.

#### Rejecting the crosstalk

As mentioned earlier, these are the first color video tape recorders to eliminate the guard bands between adjacent tape tracks. Their absence increases interference between tracks, which is further magnified because the individual tracks are slightly less than 60 micrometers wide, narrower than in previous VTRs.

Worse yet, the video-head width is greater than the track width, which makes crosstalk inevitable in the playback signal. During recording of a single track, the full width of the head writes on the tape. But when the next track is recorded, the excess width of the preceding track is wiped off and recorded as part of the next track,

so that tracks are recorded to full width with absolutely no space in between. Thus, it is necessary to provide a high level of crosstalk rejection to maintain clean recording and playback signals.

Interference between fm luminance signals on adjacent tracks is avoided by shifting the azimuth of the two heads in opposite directions from the perpendicular to the track. For the very short wavelengths at which the luminance signals are recorded, variation in azimuth between recording and playback heads causes high loss and, as a result, rejection of adjacent track signals.

However, azimuth shift does not work for the lower-frequency chroma signal because this misalignment causes very little loss at the longer wavelengths involved. Instead, the Sony and Victor recorders use different phase-shift or phase-inversion schemes. In essence, the phase of the chroma subcarrier is so manipulated during recording and playback that the chroma signal of one track cancels out any noise it may cause in the playback of the following track.

The final problem to be solved is interference between the second harmonic of the chroma signal and the luminance signal on the same track. Since the second harmonic of the chroma signal is recovered from the demodulated luminance signal, it can cause moiré patterns on the picture tube. This problem is eliminated by selecting a subcarrier such that the phase of its second harmonic differs by 180° on successive horizontal lines of the picture, making the pattern barely visible. (The same technique is used to reduce the visibility of the 3.58-MHz subcarrier in television broadcasts.) Both VTR systems therefore had to be designed in such a way that the chroma subcarriers simultaneously satisfy conditions for rejecting adjacent-track interference and

		COMPA	FICATIONS			
	EIA-J Type 1	U-matic	V-cord II (Long Play)	Betamax (Beta Format)	Matsushita 1 head, α wrap	VHS 2-hr (4-hr)
Tape type	γ-Fe <sub>2</sub> O <sub>3 3</sub>	CrO <sub>2</sub>	Co γ-Fe <sub>2</sub> O <sub>3</sub>	CrO <sub>2</sub>	γ-F <sub>2</sub> O <sub>3</sub>	Co γ
Tape width (mm)	12.65	19.0	12.65	12.65	12.65	12.65
Tape thickness (μm)	30	27	20	20	26	20
Tape coercivity (Oe)	300	500	550	600	300	550
Video-track width (μm)	110	85	60	58.5 (29.2)	48	58
Video-head gap (μm)	0.7 ~ 1	0.7 ~ 0.8	0.5 ~ 0.6	0.45	0.6	0.35
Tape speed (cm/s)	19.05	9.53	7.387 (3.694)	4.0 (2.0)	5.21	3.34
Head-drum diameter (mm)	115.8	110	81.3	74.5	48	62
Relative speed (m/s)	11.1	10.4	7.73	6.9	9.09	5.8
Audio-track width (mm)	1.0	0.8	1.0	1.05	0.4	1.0
Control-track width (mm)	0.8	0.6	0.8	0.6	0.7	0.75
Playing time (min)	60	60	60/120	60/120	100	120
Tape area (m <sup>2</sup> /hr)	8.68	6.5	3.38/1.69	1.83 (0.9)	2.38	1.52 (0.76)
Luminance signal (MHz)	fm 3.1 ~ 4.5	f m 3.8 ~ 5.4	fm 3.1 ~ 4.3	f m 3.5 ~ 4.8	f m 3.1 ~ 4.6	f m 3.4 ~ 4
Chroma subcarrier (kHz)	767	688	688	688	688	629
Head configuration	2-headed helical	2-headed helical	2-headed helical plus 3rd head	2-headed helical	1-headed helical	2-headed helical
Used by	All mfrs. (commercial)	Sony plus others under license	Sanyo Toshiba	Sony Sanyo Toshiba Zenith (U.S.) Sears/Sanyo (U.S.)	Matsushita Quasar (U.S.)	Victor Co. of Japa Matsushita Hitachi Sharp Mitsubishi RCA (U.S.) Magnavox (U.S.) Sylvania (U.S.)

conditions for rejecting luminance-signal interference within the same track.

Both the extended-play version of the Sony Beta Format, also available from Sanyo Electric Co. and Tokyo Shibaura Electric Co. (Toshiba), and the extended-play version of the vhs, being produced by Matsushita Electrical Industrial Co. for RCA Corp., Magnavox Consumer Electronics Co., and GTE-Sylvania Inc. in this country, use similar techniques to double playing time by halving tape speed. This halves track width with negligible effect on writing speed.

#### Narrowing the tape head

Consequently, the head width must be cut in half, although the gap distance can remain the same. Since tape-head width of both standard- and extended-play versions of the two types is somewhat greater than track width, reduction in width is actually somewhat less than half—from about  $60~\mu m$  to about  $35~\mu m$ .


The major effect of the narrower head is that the signal is 6 decibels lower, with a signal-to-noise ratio that is about 3 dB poorer than that of a standard-play unit. Halving tape speed has much more significant consequences, though. The horizontal sync pulses, which are neatly aligned on the original formats, are no longer aligned on the extended-play formats and generate increased crosstalk along two vertical bands about a quarter of the way from each side.

In these extended-play VTRs, rejection of interference from the adjacent track is augmented by offsetting the entire fm signal by half the horizontal frequency on alternate tracks. This arrangement interleaves the frequency spectrum of the track being played back and that of adjacent tracks and greatly reduces the visibility of any interference.

Both the Beta Format and the VHS extended-play versions improve s/n ratio by including in the luminance channel nonlinear preemphasis—de-emphasis noise-reduction systems resembling those used in audio tape disks. Preemphasis is increased beyond the usual value for high frequencies, but the nonlinear circuit prevents overmodulation when the high-frequency part of the signal also has high amplitude.

On the playback, a de-emphasis nonlinear circuit restores the signal to its original form while reducing noise. Sony claims that its noise-reduction circuit provides 6-dB improvement in s/n ratio, so that even after subtracting the 3-dB loss created by the narrower tracks, the ratio comes out ahead by 3 dB.

Although head widths of normal- and extended-play machines differ, there is no problem in trying to play a tape recorded at normal speed on an extended-play machine, provided, of course, the machines are in the same VTR format and the machine incorporates normal speed. The narrower heads scan the center portion of the recorded tracks, resulting in a signal output drop of 3 dB



2. Dropping the guard. Major advance in tape-saving technique for consumer video recorders required narrowing tape and eliminating guard bands between tracks (a). New format (b) also features skewed azimuth of alternate tracks for interference-rejection.

compared with output on a normal play, while interference from adjacent tracks falls considerably.


Neither is there any problem playing a tape recorded on an extended-play machine at normal speed on a normal-play machine, again provided that the machines are in the same VTR format. As before, the major effect is a 3-dB reduction in signal output compared with the output from a tape recorded on a normal-play machine. Interference from adjacent tracks is reduced because there is an unrecorded band between the tracks left by the smaller head on the extended-play machine.

However, tapes recorded on an extended-play machine at extended-play speed can only be played back on another extended-play machine of the same format.

#### Beta Format and VHS compared

While the two Japanese VTRs have achieved the same basic goals—a means for shifting the time of TV programs and storing broadcasts the consumer wants to retain—there are important differences between them. The differences are in choice of basic dimensions, tape speed, tape-loading mechanism, rotating-drum operation, cassette size, and signal-processing design. It is these factors that make the two systems incompatible.

Sony's Betamax VTR set a new standard for consumer color video cassette recorders when the company started sales in May 1975. Tape consumption was by far the lowest of any recorder on the market, cassettes were the smallest, and the price was the lowest. Betamax had one-hour playing time, and this led to the development of an extended-play version called Beta Format that has a



**3. Loaded for Beta.** The cassette-loading scheme for the Beta Format recorder is an adaptation of the U-loading arrangement developed for commercial VTRs. Each loading pole is a pair of rods, one parallel to the drum, one not.


two-hour recording and playing time. (Sony has stated that a cassette with 50% thinner tape giving three hours of playing time will be forthcoming.) Some extended-play machines can also play back tapes made on earlier one-hour machines, but most of them will probably be extended-play only.

The Beta Format was developed by the company in cooperation with Toshiba and Sanyo. Sony is now also producing units for Zenith Radio for sale in this country on a private-label basis.

In developing its VHS cassette recorder, Victor Co. of Japan aimed for a small and light machine with two hours of recording and playing time. Use of state-of-the-art, high-density recording and a simplified mechanism that would be easy to manufacture were also important design goals. Besides Matsushita, a number of other Japanese companies have joined the VHS camp, including Hitachi Ltd., Sharp Corp., and Mitsubishi Electric Corp, as well as RCA, Sylvania, and Magnavox in the U.S., the last three going with the four-hour extended-play units produced by Matsushita.

Basic choices in the Betamax system are a tape speed of 40 millimeters per second and a head-drum diameter of 74.49 mm. Track width is  $58.5 \mu m$ . Writing speed on the Beta VTRs is 6.9 meters per second.

Victor, on the other hand, has a tape speed of 33.4 mm/s and a head-drum diameter of 62 mm that makes it the smallest yet for a two-headed color VTR. Video track width is 58  $\mu$ m. The low tape speed and small drum make it possible to fit enough 20- $\mu$ m-thick tape for two hours of playing time into a cassette



**4. Simple loading.** Victor's VHS cassette-loading configuration is new for VTRs. Its advantage is that it produces a somewhat simpler tape path with a correspondingly simpler arrangement of mechanical parts, so that cartridge insertion easily positions the tape.

measuring only 188 by 104 by 25 mm. Sony's cassette measures 156 by 96 by 25 mm (see table).


The disadvantage of the small drum is a reduction in the relative speed between the heads and the tape that slows writing speed to only 5.8 m/s. Such slowness decreases the minimum recordable wavelength of the highest fm frequencies to only 1.1  $\mu$ m, which tightens the requirements on the heads, tape, and circuits.

#### **Tape-loading differences**

The tape-loading mechanism on the Beta VTR is a modification of that pioneered by Sony for use on its earlier U-matic recorders. Most of the components associated with loading and controlling tension of the tape are mounted on the so-called U-loading ring, which is parallel with the baseplate and surrounds the rotating-drum assembly.

However, the ring is made highly eccentric with respect to the drum in order to leave space within it for the erase, control, and audio heads, and the capstan. During loading, the U-loading ring rotates about 270°. A rotating guide and a pinch roller, which enters the cassette when it is inserted into the VTR, travel with the loading ring and pull the tape around the drum and against the audio and control heads (Fig. 3a). A tape tension regulator not on the U-loading ring pulls the tape coming directly off the supply reel so that it runs over the full-track erase head and also makes contact with the drum over a full 180°.

Unlike the U-matic approach, the tape-loading system used in the VHS recorder differs entirely from that used



**5. Japanese guide.** Sony's wide tape-guide is designed to keep the thin tape accurately in position and facilitate the use of narrow audio and control tracks. The guide also makes it possible to interchange cassettes made for Beta Format machines.

in previous cassette recorders. A parallel loading method is used, in which two so-called loading poles with a short stroke of only 80 mm rapidly load the tape. Two stoppers with V-shaped notches hold the loading poles in the desired position, ensuring high stability. Since the loading pole stroke is short, the amount of tape pulled from the cassette is small, eliminating the danger of applying excessive force to the tape.


As shown in Fig. 4, in the play mode the tape path is very simple. Insertion of the cartridge positions the tape between the capstan shaft and the pinch roller, so that a minimum of motion suffices to bring the pinch roller to bear against tape and capstan.

The rotating drum on Beta Format VTRs is a threepiece sandwich, with a wheel carrying two heads rotating between two stationary drums. An air film between the wheel and the tape helps decrease friction between the tape and the drum. The lower drum has a precise ridge to guide the tape helically around the drum assembly.

#### **Rotating-drum operation**

Attached to the upper drum is a guide that rests very gently—with a 1- or 2-gram force—on the upper edge of the tape in order to keep the lower edge in contact with the lower guide. This arrangement not only prevents the tape from meandering but also compensates for variations in its width.

The tape passes over a full-width erase head before passing over the drum, then runs over control and audio heads on leaving the drum. Wide tape-guides (Fig. 5) accurately maintain the position of the thin tape and



**6. Canceling.** Crosstalk elimination techniques counterbalance phase shifts in the chroma signal. In Sony's method (a), phase of alternate horizontal lines on B track is inverted. Victor's (b) involves 90° phase shifts for each successive horizontal line.

facilitate the use of the narrow audio and control tracks.

The Victor vHS drum is divided into a lower and an upper section. The lower section has a ridge for guiding the tape, and since the edge of the tape follows this ridge obliquely along the drum, it must be a precision fabrication. The upper section of the drum carries two video heads attached diametrically opposite each other. The rotating upper section of the Victor drum is wider than the rotating portion of the Sony drum and thus provides a wider air film that reduces friction more than in the Sony design.

Tension on the tape at the capstan is less than 100 grams, compared with the 300 to 500 grams recommended in the EIA-J Type 1 vTR standard for ½-in. tape players. Thus, there is a generous margin for tape protection even for the very thin, 20-µm tape used. Overall, the Victor deck was designed to be as compact as possible.

#### Differences in signal processing

Both the Beta Format and VHS video cassette machines record TV luminance and chrominance signals in the same, standard fashion. They differ on the method of eliminating chroma crosstalk from track to track on the tape.

Sony developed what it calls a phase-inversion recording method to eliminate crosstalk between chroma signals on adjacent tracks by interleaving their frequency spectrums (Fig. 6). This method entails dividing alternate tracks on the tape into A and B groups and

processing them in a manner that rejects interference between them.

The chroma signal for the first track, which is an A track, is recorded without changing phase relationships for the individual horizontal lines in the field. The chroma signal for the next track, which is a B track, is processed so that the phase of alternate horizontal lines is inverted before recording (see Fig. 6). It is implemented by a simple circuit that switches between two ends of a transformer secondary whose center tap is grounded. Because the phase is reversed for alternate lines, switching frequency is exactly half the horizontal frequency. During playback, the phase of the chroma signal is further processed to restore the original phase relationships.

Then, to make it possible to reject adjacent-track interference, the signal being reproduced is added to the signal from the previous line delayed by one horizontal period in the delay line. To repeat, because the A track signal received no phase processing during recording, it requires none during playback. The B track signal for alternate horizontal lines was inverted during recording and so requires inversion again during playback—processing that of course also inverts associated interfering signals picked up from the A track.

Thus, the sum of the interfering unprocessed B signal from the A track and the signal from the previous unprocessed B line delayed by the horizontal period is zero. The output of the B track, though, is the sum of the signal being played back and the signal from the

#### The other two VTR entries

Two other color video tape recorders for consumers are made in Japan and sold in the U.S. Both also use half-inch tape. The V-Cord II, developed by Sanyo Electric Co., is produced by it and Tokyo Shibaura Electric Co. The VX-2000 is available only from Matsushita Electric Industrial Co. and is sold in America by Quasar Electronics, a Matsushita subsidiary.

In configuration, the V-Cord II is quite like Sony's Betamax, except for a larger head-drum diameter. It is basically a one-hour machine. Track width is 61 micrometers, but the need for guard bands increases track pitch to 97.2  $\mu m$ . Tape speed is 73.872 millimeters per second, making for somewhat more than twice the tape consumption of the standard-play Victor VTR and slightly less than twice that of the standard-play Sony VTR.

To get two-hour operation, the V-Cord II halves tape speed by skipping every other video field during recording. But this method of course halves vertical resolution and so can give a jerking motion to any images moving rapidly up and down.

In order to provide both one-hour and two-hour operation, the V-Cord II has three heads. The two heads for one-hour record and playback are on diametrically opposite sides of the drum, much as in other two-head recorders. For two-hour operation, one of these heads records every other field and the second is inactive. During playback, the same first head reads the field it recorded, but then a third head, slightly offset from the second one, reaches forward and plays back the same field a second time for display on the picture tube, instead of catching the missing second field. It is necessary to reach forward because of the tape's motion during the 1/60-second interval between

adjacent fields of the NTSC video transmissions.

Matsushita's VX-2000 differs from the other three in that it has only one head—a scheme originally developed by Toshiba more than 20 years ago. This arrangement also makes for a smaller drum because the tape is wrapped spirally around its entire periphery—called alpha wrap, from its resemblance to the Greek letter alpha. In the two-and three-headed recorders, the tape goes only halfway around.

Inclusion of a plastic cylinder that is slightly larger than the recorder head drum in the VX-2000 cassette permits great simplification by almost totally eliminating the tape loading mechanism. The cassette differs, too. It has a tape loop and tape reels stacked one above the other, rather than side by side as in two-headed designs. But as a result it is much larger than the cassettes in other recorders, measuring 44 by 146 by 213 mm.

Also contributing to the comparative largeness of the cassette is a tape speed of 52.133 mm/s—faster than that used by Victor to achieve the same two-hour playing time and therefore requiring more tape. Track width is only 48  $\mu$ m, less than in the normal-play Victor and Sony VTRs. Track pitch, though, is increased to 73  $\mu$ m by the guard band, so that, like the V-Cord II, this recorder does not utilize magnetic tape efficiently. The guard band is necessary because the azimuth of the head cannot be changed for successive tracks, as can be done with two heads.

The 52.13-mm drum of the VX-2000 is the smallest used on any Japanese helical-scan color recorder. But the geometry differs from that of two-headed machines, and track width for a given tape speed is comparable to that of two-headed machines having twice the drum diameter.

previous horizontal line, according to the company.

In the new Victor method of eliminating crosstalk between adjacent tracks, the phase of the chroma signal along a given track, which is equivalent to a full TV field, is shifted 90° for each successive horizontal line in the field. Direction of the 90° phase shift is reversed for successive tracks. This recording scheme also produces a chroma signal whose second harmonic component appearing in the luminance signal is barely visible.

In Fig. 6a, the phase of the first horizontal line signal on the M track, line  $M_1$ , is indicated by an arrow. The phase of the second horizontal line,  $M_2$ , is 90° ahead of  $M_1$ , and the phase of  $M_3$  is another 90° ahead of  $M_2$ . However, the phase of successive horizontal lines on the adjacent A track rotates 90° in the opposite, or counterclockwise, direction.

During playback, the signal phase of each successive horizontal line is rotated 90° in the direction opposite that during recording to restore it to the same phase as in the original signal. This successive phase shift during recording and playback permits rejection of crosstalk during playback.

Two aspects of signal processing in the Victor VHS differ from that in other VTRS. First, double limiting is used during playback to prevent the effects of overmodulation, which show up as high-amplitude black-level noise for 3 to 5 microseconds following a sharp transition from black to white. Second, Victor enhances the ampli-

tude of the color carrier reference burst before recording to increase its s/n ratio during playback.

During playback, the high-frequency components of the fm luminance signal are normally smaller in amplitude than the low-frequency components. Usually the amplitude of all components is leveled to the same value in the limiter, but at an abrupt black-to-white transition the fm signal consists of large-amplitude, low-frequency components with small-amplitude, high-frequency components superimposed on them. These last, under certain conditions, may become lost during limiting, making it impossible to demodulate them and leading to a reversal of signal polarity.

Victor's solution is to use a double limiter circuit. High- and low-frequency portions of the fm signal are separated by high- and low-pass filters with gentle slopes. Then, the high-frequency portions only are amplified and limited at a higher level. Limited high-frequency portions are recombined with the low-frequency portions, and the reconstituted signal is limited, thus preventing loss of the high-frequency components.

In the VHS, the color burst is enhanced 6 dB at playback. This procedure provides a 6-dB improvement in burst s/n ratio. Since noise in the color burst is translated into phase jitter in the color-processing circuits, the improvement in s/n ratio goes a long way toward eliminating color errors.


#### Designer's casebook.

### Adjustable limiter controls telephone-line signal power

by Tom Hilleary
HMS Corp., Shawnee Mission, Kansas

To minimize crosstalk and other unwanted line radiation on telephone lines, it is often necessary to limit the input power of the data or voice signals, and to do so without amplitude distortion. This circuit does so by using two shift registers to monitor the relation of a set reference to the input signal amplitude (which is directly proportional to power at constant line impedance) and then divert some input current from the line transformer's primary winding whenever necessary. The limiter is effective when used with any constant-current data source. It provides 0 to -12 dBm of limiting and is accurately adjustable to 1 dB.

As shown in the figure, data or voice signals having a maximum amplitude of 1.4 volts at 0 dBm are applied to operational amplifier  $A_1$ . The output of  $A_1$  in turn feeds



**Digital limiter.** Circuit provides 0 to -12 dBm of signal attenuation. Relative amplitude of constant-current data signal to set reference determines number of logic 1s generated by  $A_2$  into 4015 registers over a given time. Signal above threshold loads more 1s into register, turning on more transmission gates as register is clocked and thus diverting the input current away from the primary winding.

the noninverting input of comparator  $A_2$ . The desired limiting (reference) level is set by five switches, operated in accordance with the table.  $A_3$  is a voltage follower and passes the reference voltage to the inverting input of  $A_2$ .

A<sub>2</sub> compares the peak value of the input signal to the reference and when the reference voltage is exceeded generates a logic 1 for the data input of two 8-bit 4015 shift registers. The 4015s are configured as a single 16-bit device that is clocked at an arbitrary 8-hertz rate. If the input signal is mostly larger in amplitude than the reference, the shift register is periodically loaded with more 1s. Conversely, low-amplitude signals introduce more logic 0 signals into the register.

Thus, as the signal power rises above the value desired, more register outputs are activated and themselves activate more of the 14066 transmission gates, each of which when switched on places approximately 100 ohms across the transformer winding. As a result, more of the input current is diverted through these shunt paths, limiting the current though the transformer's primary and the induced voltage in its secondary. If the signal power drops, the shunts are in essence removed, allowing more of the signal to pass. Either way, the current output is constant, so that the effective line

DIGITAL LIMITER					
D⊤ PEAK LEVEL (dBm)	А	CL(	OSE SWITCI C	HES D	E
0					
-1					
-2					3
-3					
-4	3.7				DER CO
-5					-
-6					
-7					
-8					
-9	10.00				
-10					
-11					
-12					


impedance as seen by the data source does not change.

The sampling rate and the RC integrator following  $A_2$  between them control the circuit's response time. Either or both may be altered for a specific application.

## Synchronous timing loop controls windshield wiper delay

by John Okolowicz Honeywell Inc., Fort Washington, Pa. A 555 timer can control an auto's windshield-wiping rate by providing a selectable delay time between wipes. The timer uses a feedback signal from the cam-operated switch within the wiper motor to synchronize the delay time to the position of the wiper blades, as measured from their starting point.

With synchronization, the minimum delay time can still be reliably kept to nearly zero (normal delay for



1. Wipe-rate selection. Control over the time between sweeps in negative-ground windshield wiper systems is done by the 555 and a synchronous feedback loop. Delay time can be varied from 0 to 22 seconds. Synchronizing the feedback to the wiper blades' position ensures that sweep rate will be independent of variations in wiper speed. Terminal block notations are for Volkswagen Rabbit.

# Head of the class

United Systems' Datalogger 1000 leads the industry in data acquisition. Its versatility delivers more performance per dollar than any other logger in its class. Check its report card. The "grade A" features speak for themselves.


You can easily afford the best ... call now for a demonstration.





918 Woodley Road, Dayton, Ohio 45403 (513) 254-6251, TWX (810) 459-1728

United Systems Corp.:
Precision measurements to count on



**2. Positive-ground system.** Suggested modification for many General Motors vehicles and other autos with positive-ground system uses same number of components as standard system. Wiper motor is energized by completing ground connection. Note that diodes  $D_1$ ,  $D_3$ , and  $D_4$  are reversed with respect to the polarities shown in Fig. 1 and that pulse-train polarity from 555 output is inverted.

standard systems), which is best for heavy rain. In addition, it ensures that the delay time is independent of the wiper speed across the windshield. Further, the maximum delay time in this circuit can be set to about 22 seconds, which is suitable for mist or light drizzle, or to any value desired, by suitable selection of the 555's timing components. This circuit offers a better approach to synchronous-delay wipers than those that use silicon controlled rectifiers in parallel with the cam switch, because cam-switch voltage is affected by dirt and grease.

The circuit shown in Fig. 1 is for a Volkswagen Rabbit, but it can be used in any car that has one end of the wiper motor always grounded (which requires a positive energizing voltage). As shown, the 555 assumes the high state on power-up ( $S_1$  initialized), driving the MJ1000 Darlington amplifier, which in turn energizes the wiper motor. As the blades traverse through an angle of approximately 5°, the cam switch is engaged to the 12-volt ignition-line voltage. Thus a feedback voltage is presented to the trigger threshold port of the 555 through  $D_1$ . This voltage exceeds two thirds of the supply voltage on the 555; as a result, the output voltage at pin 3 falls at time  $t_1$ , which is less than the normal pulse width time usually controlled by the 20-kilohm resistor and  $C_1$ .

Normally, C<sub>1</sub> would now begin to charge, but because the voltage supplied to the cam switch remains high, the

555 simply sits in the low state. Meanwhile, both wiper blades reach the far end of their sweep and begin to move back toward their starting position.

As the blades approach within  $5^{\circ}$  of their starting point, the cam switch disengages from the ignition voltage and moves back to ground. Now  $C_1$  begins its slow discharge through the 300-k $\Omega$  potentiometer. Note that  $t_2$ , the delay, is measured from the time the wiper moves within  $5^{\circ}$  to the time the 555 fires again. Triggering occurs once  $C_1$  discharges to less than one third of the supply voltage.

 $D_1$  prevents  $C_1$  from discharging through the cam switch, and  $D_2$  allows independent selection of times  $t_1$  and  $t_2$ .  $D_3$  provides suppression of the back voltage produced when the MJ1000 turns off; without the diode, the 555 will be retriggered falsely.  $D_4$  allows normal operation when the circuit is not activated and also prevents the MJ1000 from shorting to ground through the cam switch.

Some cars have a reversed wiper-motor configuration. Thus one end of the wiper motor is always connected to the positive ignition-line voltage and so requires a connection to ground to energize it. Figure 2 shows a suggested modification of the wiper-delay circuit to handle such cases.

Designer's casebook is a regular feature in *Electronics*. We invite readers to submit original and unpublished circuit ideas and solutions to design problems. Explain briefly but thoroughly the circuit's operating principle and purpose. We'll pay \$50 for each item published.

# Calculator programs simplify design of cascaded tuned circuits

Part 1 of two-part article sets forth procedures for single and synchronous tuned networks


by Albert E. Hayes Jr., Fullerton, Calif.

☐ Engineers charged with the task of designing cascaded tuned circuits with specific characteristics have traditionally faced a series of complex and tedious calculations involving trial-and-error procedures and the juggling of many variables, such as Q, inductance and capacitance, frequency, bandwidth, and so on. With the advent of the programmable calculator, however, much of the time and tedium can now be eliminated.

This two-part article describes a family of programs for the HP-67/97 scientific calculator that simplify the task of designing cascaded tuned LC circuits of the synchronous, Butterworth, and Chebyshev types. Essentially, the design for each kind of circuit is reduced to a simple step-by-step procedure.

#### Single tuned-circuit calculation

The cascaded tuned-circuit equations are derived from an extended analysis of the single tuned circuit, which will therefore be discussed first. Design is simple,



**1. Single tuned circuit.** Single-stage (n=1) LC circuit is easily analyzed for  $R_{\rm eff}$ , L or C (a). Frequency response is characterized by the ultimate slope of circuit (6 dB per octave) and the amplitude of the relative-voltage peak, which is a function of circuit Q (b).

TABLE 1: HP-97 PRINTER LISTING OF SINGLE TUNED-CIRCUIT PROGRAM							
001 002 003 004 005 * 006 007 008 009 010 011 012 * 013 014 015 * 016 017 018 019 020 021 * 022 023 024	CF1 CF0 CLX R/S LBLA Pi X 2 X ST01 RTN LBLB ST02 RTN LBLC SF1 F0? GT01 ST03 RTN LBLD SF0 F1? GT02	030 031 032 033 034 035 036 037 038 039 040 041 042 043 044 045 046 047 048 049 050 051 052 053	RTN *LBLE RCL1 X² RCL4 X 1/X EEX 3 X DSP3 R/S EEX 3 X DSP1 R/S *LBL0 R/S GT00 *LBL1 RCL2 RCL1 ÷	059 060 061 062 063 064 065 066 067 068 069 070 071 072 073 074 075 076 077 078 079 080 081	RTN *LBL2 RCL1 ÷ RCL3 ÷ STO4 DSP4 EEX 6 X R/S EEX 6 X DSP1 R/S GTO0 R/S *LBLd EEX 6 CHS		
025 8 026 8 027 0 028 3	EEX 6 CHS × STO4	054 055 056 057 058	RCL4 ÷ FIX DSP1 STO3	083 084 085	X GTOD R/S		

#### INSTRUCTIONS

- Key in program
- Initialize
- Enter resonant frequency (KHz) and quality factor (f<sub>o</sub>), A, (Q), B
- Enter either effective shunt resistance (ohms) or tuning capacitance (microfarads) (R<sub>eff</sub>), C or (C), D

To enter capacitance in picofarads: (C), f, D

- Press C to find the effective shunt resistance (ohms), or press D to find the tuning capacitance (microfarads)
   If the result is desired in picofarads, press R/S after D
- Press E to find the inductance, L (millihenries)
   If the answer is desired in microhenries, press R/S after E

because single tuned-circuit analysis is based upon only two equations:

$$Q = 2\pi f R_{\text{eff}} C \tag{1}$$


$$L = 1/(4\pi^2 f^2 C)$$
 (2)

where:

Q = loaded quality factor

f = resonant frequency

R<sub>eff</sub> = parallel impedance of the source, resonant-



2. Synchronously tuned circuits. When several tuned circuits are joined by means of isolating amplifiers (a), they yield an overall response characteristic equal to the product of the responses of the component circuits (b). Ultimate slope is 6n dB per octave. Program makes it easy to design a synchronously tuned array.

circuit, and load resistance (effective shunting resistance)

C = tuning capacitance

L = inductance (in millihenries if C is in microfarads or in microhenries if C is in picofarads).

For a specific frequency (f<sub>o</sub>), the program for the single tuned circuit finds R<sub>eff</sub> and L when Q and C are known; when Q and R<sub>eff</sub> are known, it finds L and C. Although the calculation is simple, the program is important because it is needed for the design problems that will be introduced in subsequent sections. Table 1 shows the program as generated by the HP-97 printer.

A representative problem is the calculation of the L and C components in a tuned circuit that has a resonant frequency of 459.62 kilohertz and a Q of 118.83. This resonant circuit is used in an intermediate amplifier developed from Butterworth design formulas, which will be discussed in Part 2. From any of several tuned-circuit

#### **TABLE 2: CASCADED CIRCUIT NOTATION** = attenuation, in dB Ai = attenuation, from peak value, at BWi, in dB = attenuation, from peak value, at BWi, in dB Ai = attenuation, from peak value, at BW<sub>x</sub>, in dB Ax (A<sub>x</sub> and BW<sub>x</sub> are unknowns) BW; = bandwidth between the -A; (dB) points on a = bandwidth between the -A; (dB) points on a BW<sub>i</sub> response curve $BW_{x}$ = bandwidth between the $-A_x$ (dB) points on a response curve (A<sub>v</sub> and BW<sub>v</sub> are unknowns) = voltage measured at peak of response curve $V_i$ , $V_i$ = voltage measured at the $-A_i$ , $-A_i$ (dB) points on a response curve $(A_i = 20 \log_{10} V/V_i)$ = center frequency (nominal frequency of passband) (f<sub>a</sub>)<sub>m</sub> = resonant frequency of higher-tuned circuit of mth pair (f<sub>b</sub>)<sub>m</sub> = resonant frequency of lower-tuned circuit of mth pair = number of tuned circuits in system m<sub>max</sub> = number of pairs of tuned circuits in system if n is even, $m_{max} = n/2$ if n is odd, $m_{max} = (n + 1)/2$ = Q of mth pair of tuned circuits Qm

charts and nomograms found in numerous engineering handbooks, it may be determined that a tuning capacitance on the order of 500 pF is reasonable at this frequency.

The program is started by pressing the RTN and R/S keys, followed by 459.62, EEX, 3, A, then 118.83, B. The value of the capacitor is then entered as 500, f, D. Pressing C yields an R<sub>eff</sub> of 82,295.7 ohms, but it may be that this value is too high for the particular application. In this case, therefore, a value of 5 kilohms is assumed, and C and L are recalculated.

The program is restarted by pressing RTN, R/S, followed by 459.62, EEX, 3, A, 118.83, B, 5000, C. The capacitance is found by pressing D. Its value this time is 0.0082 microfarad, not an unreasonable number. Pressing R/S yields a more exact value expressed in picofarads (8,229.6). Pressing E yields an inductance of 0.015 mH; pressing R/S, 14.6  $\mu$ H. With the procedure having been gone through twice, the most practical values for R, L, and C have now been found.

Single tuned circuits will have a frequency response as shown in Fig. lb, where the region designated "ultimate slope" will be 6 decibels per octave of frequency change, and where the height of the peak is a function of the Q.

Having reviewed the single tuned circuit, now consider a string of such circuits. Synchronously tuned, n-stage circuits produce a peaked frequency-amplitude response. Consequently, their applications are largely confined to narrow-band communications circuits and some types of control systems requiring a very narrow bandwidth without stringent requirements for off-frequency signal rejection.

#### Synchronously tuned cascades

The most primitive arrangement is two or more parallel resonant circuits separated from each other by isolating stages, driven from a source having a resistance  $R_{\rm gen}$ , as shown in Fig. 2a. The terminating impedance of the tuned-circuit array is assumed to be resistive. If all the tuned circuits are resonant at the same frequency, they are said to be synchronously tuned.

The amplifier stages serve to eliminate interaction between adjacent tuned circuits, allowing each circuit to act as an isolated entity, with an overall response characteristic equal to the product of the responses of each stage. To accurately predict this new circuit response, a brand-new set of equations, necessarily more complex than for a single tuned circuit, must be solved.

The frequency response of the n-stage array shown in Fig. 2b has a shape similar to that shown in Fig. 1b, except that its ultimate slope is approximately 6n dB per octave and the height of the Q peak varies in proportion to the average Q of the several circuits. Generally, it is most convenient and practical to design a synchronously tuned array so that all tuned circuits have the same Q.

In the mathematical derivations in this and subsequent sections, the notation in Table 2 is used throughout. For an n-stage, synchronously tuned circuit, the classical equations are:

$$x = (BW_i/f_o) Q (3)$$

$$V/V_i = (1+x^2)^{n/2} (4)$$

$$\Theta = \tan^{-1}(\mathbf{BW_i}/f_o) \mathbf{Q} = \tan^{-1}\mathbf{x} \tag{5}$$

where  $V/V_i$  is the attenuation ratio at the bandwidth  $(BW_i)$  end points, and  $\theta$  is the phase shift between the current at  $f_o$  and the current at the bandwidth end points.

Using Eq. 3 through Eq. 5, the program, shown in Table 3:

- Finds the value of n (the number of tuned circuits—often determined to be a noninteger) for a given  $f_o$ ,  $V/V_i$ , and  $BW_i$ , at an estimated value of  $Q(Q_{est})$ .  $Q_{est}$  is a realistic (attainable) value of loaded Q.
- Rounds off n to the next highest integer (if initially a noninteger), then calculates the  $V/V_i$  for that n.
- Proceeds to calculate the new circuit Qs required to find the originally specified value of  $V/V_i$  at the new value of n.
- $\blacksquare$  Calculates the phase shift,  $\Theta$ .

The program first finds x from Eq. 3. The entered value of Q must be selected on the basis of knowledge of the tuned circuits at the  $f_o$  in question. The number of tuned circuits is then found by manipulation of Eq. 4. This equation becomes:

$$(V/V_i)^2 = (1+x^2)^n$$

Taking the logarithm of the equation:

$$n \log(1 + x^2) = 2 \log(V/V_i)$$

TABLE 3: HP-97 PRINTER LISTING OF SYNCHRONOUS PROGRAM							
001 002	*LBLA STO3	037 038	*LBLD RCL5	073 074	R/S		
002	RTN	039	RCL6	074	GTOO *LBLa		
004	*LBLB	040	2	075	RCL3		
005	2	040	÷	076	÷		
006	0	042	YX	077	RCL8		
007	÷	043	LOG	079	X		
008	10×	044	2	080	X <sup>2</sup>		
009	STO1	045	0	081	1		
010	R.	046	×	082	+		
011	STO4	047	DSP1	083	$\sqrt{X}$		
012	RTN	048	RTN	084	RCL6		
013	*LBLC	049	*LBLE	085	YX		
014	STO2	050	RCL1	086	LOG		
015	RCL4	051	2	087	2		
016	RCL3	052	ENT †	088	0		
017	÷	053	RCL6	089	X		
018	X	054	÷	090	R/S		
019	STO7	055	YX	091	*LBLb		
020	ENT +	056	1	092	2		
021	×	057	_	093	0		
022	1	058	$\sqrt{X}$	094	÷		
023	+	059	RCL3	095	10 <sup>X</sup>		
024	STO5	060	X	096	2		
025	LOG	061	RCL4	097	RCL6		
026	RCL1	062	÷	098	÷		
027	LOG	063	STO8	099	YX		
028	2	064	R/S	100	1		
029	×	065	RCL4	101	-		
030	XZY	066	×	102	$\sqrt{X}$		
031	÷	067	RCL3	103	RCL3		
032	INT	068	÷	104	X		
033	1	069	$TAN^{-1}$	105	RCL8		
034	+	070	R/S	106	÷		
035	STO6	071	*LBLO	107	R/S		
036	RTN	072	0				

INSTRUCTIONS

- Key in program
- Enter design parameters: resonant frequency, bandwidth, attenuation (dB), and estimated Q (f<sub>o</sub>), A, (BW<sub>1</sub>), ENTER, (A<sub>i</sub>), B, (Q<sub>est</sub>), C

The number of tuned circuits required (n) is displayed

- Press D to find actual attenuation (A)
- Press E to find the Q required to attain the original design value of attenuation
- Press R/S to calculate phase shift (θ)
- Enter arbitrary bandwidth and find attenuation at that bandwidth, or enter arbitrary attenuation ratio and read the bandwidth for that attenuation ratio:

$$(BW_x)$$
, f,  $A --- \rightarrow (A)$  displayed  
or  $(A_x)$ , f,  $B --- \rightarrow (BW_x)$  displayed

- Repeat preceding step as necessary to generate response plot
- Units of f and BW are arbitrary, but must be consistent throughout run

or, after division by  $log(1 + x^2)$ :

$$n = \frac{2\log(V/V_i)}{\log(1+x^2)} \tag{6}$$

Substituting Eq. 3 into Eq. 6 yields:

$$n = \frac{2 \log(V/V_i)}{\log[1 + (BW_iQ_{est}/f_o)^2]}$$
 (7)

This equation is evaluated by the calculator. The attenuation is then found by evaluating Eq. 4 in its initial form. The new circuit Qs are calculated by combining Eqs. 3 and 4:

$$Q_{req} = xf_o/BW_i = \frac{[(V/V_i)^{(2/n)-1} - 1]^{1/2}f_o}{BW_i}$$
 (8)

Finally, the phase shift is determined using Eq. 5.

In accordance with conventional engineering practice, this program, as well as those to follow, characterizes the attenuation in decibels  $(A_x)$ , rather than as a voltage ratio  $(V/V_x)$ . In every case, the program computes  $V/V_x$  from  $A_x$ :

$$V/V_{x} = 10^{A_{x}/20}$$
 (9)

With the array of tuned circuits defined by the synchronous program, either the attenuation at an arbitrary bandwidth (BW<sub>x</sub>), or vice versa, can be computed from:

$$A_x (dB) = 20 \log\{[1 + (QBW_x)^2/f_o]^{-1/2}\}^n$$
 (10)

or:

$$BW_x = (f_0/Q)[(V/V_x)^{2/n} - 1]^{1/2}$$
(11)

These two equations are also evaluated by the program.

Assume a requirement for a tuned cascaded circuit to provide a 2-megahertz bandwidth at the 3-dB points, at a center frequency of 140 MHz. From experience, it is known that a Q of 25 is easily attained at 140 MHz.

Enter the synchronous program into the HP-67 and key in 140, A, 2, ENTER, 3, B, 25, C. The calculator will indicate that six tuned stages are needed. A calculation of the actual attenuation with n=6 is performed by pressing the D key. This yields an answer of 3.1 dB, certainly close enough to the original 3-dB requirement. If, however, greater accuracy is desired, pressing the E key will yield a value of 24.5, the precise value of Q needed for the required 3-dB attenuation. Pressing R/S will initiate the phase shift calculation, which gives an answer of 19.3°.

More information can be obtained—for example, the attenuation at the 3-MHz band edges or the bandwidth at the -60-dB points. For the former, it is necessary only to key in 3, f, A, giving an answer of 6.3 dB; for the latter, keying in 60, f, B, gives a bandwidth of 17.2 MHz. By repeating these last two steps, a complete response curve can be developed.

For applications where the sharp crest of the synchronously tuned response is not desirable, a wider, flattopped response may be attained by tuning each circuit of a casade to one of several frequencies above and below the nominal center frequency. A discussion of the procedures used to attain these flat characteristics requires examination of the Butterworth and Chebyshev responses and will appear in Part 2, in the next issue.

# "Siliconix VMOS are down. Bipolars'

"VMOS power FETs, introduced by Siliconix in 1975, have always been better than bipolars—more rugged, more reliable, faster and simpler. Today, we're lowering our prices as we move further along the learning curve, and our economical plastic package brings superior VMOS technology within reach of all designers. At 96¢ apiece,\* the new TO-202s will replace bipolars in a broad range of power applications, particularly in interfacing with

\*VN46AF in quantities of 100-999

computers and in

telecommunications."



# power FET prices time is up."

Siliconix VMOS power FETs in plastic: TO-202 package	10	Maximum Safe Operating Region		MOS pov			duced by
VDS(on) Part # BVDSS (ID=1 Amp) Price:1-29 31-99 100-999	MPS)		Part #	Package	PDISS	BVDSS	VDS(on) (ID=1.0 Amps
VN46AF 40 3.0V \$1.33 \$1.12 \$0.96	DRAIN CURRENT (AMPS)		2N6656	TO-3	25W	35	1.8V
VN66AF 60 3.0V \$1.39 \$1.16 \$1.00	CURRI		2N6657	TO-3	25W	60	3.0V
VN88AF 80 4.0V \$1.54 \$1.29 \$1.10	N BAIN		2N6658	TO-3	25W	90	4.0V
All three devices are guaranteed over the	ا، ا	4 4 4	2N6659	TO-39	6.25W	35	1.8V
temperature range of $-55^{\circ}$ C to $150^{\circ}$ C; their maximum power dissipation is 12.5		VN46	2N6660	TO-39	6.25W	60	3.0V
watts, and their current rating is 2.0 amperes.	.01	10 100  V <sub>os</sub> —DRAIN-TO-SOURCE VOLTAGE (VOLTS)  No secondary breakdown voltage derating.	2N6661	TO-39	6.25W	90	4.0V

"Until 1975, MOS field-effect transistors (FETs) were restricted to small-signal, low-power applications. To control high currents, designers used bipolar devices. Then Siliconix, using Vertical MOS technology, introduced the VMOS power FET—combining the reliability of FETs with the power of bipolars.

"Today, Siliconix' new plastic TO-202 package means that VMOS power FETs are not only superior to bipolars in performance, but also competitive with them in price. They'll simplify designs and reduce component count in most systems because they eliminate pre-amplifiers, driver transistors, and external protective circuitry required for bipolars. And they can be inserted by machine, a time- and cost-saving advantage in high volume production.

"Anyone who has designed with bipolars knows the failures that can result from thermal runaway, secondary breakdown and current hogging. You don't have to worry about these problems with VMOS power FETs; their positive temperature coefficient eliminates hot-spotting and provides uniform current density, making them fail-safe. Consider how this inherent reliability will reduce your system interruptions and maintenance costs. And VMOS power FETs are faster than bipolars in switching operations—as much as 100 times faster. With all these advantages packed into the low-cost TO-202, you'll be able to eliminate bipolars' problems completely from many system designs.

"The high input impedance of VMOS and its threshold voltage range allow it to interface directly with CMOS, MOS and TTL logic families. And the VMOS power FET is the only interface device with a switching time comparable to that of ECL, so it will interface with a simple

level shift—without losing speed. These features make the TO-202s ideal for data processing applications: computer peripherals, micro- and minicomputer systems, and process control equipment. They're also ideal for use in telecommunications: as telephone relay replacements, Touch-Tone muting switches, audio amplifiers, central office systems and analog switches.

"Our new line of VMOS power FETs in plastic may mean the end of the line for bipolars. We want you to discover for yourself how they can improve system design, so use the coupon to send for our detailed brochure. To order parts, contact any of our franchised distributors: Alliance, Century, Components Plus, Future, Hamilton/Avnet, Industrial Components Inc., Pioneer Standard, Pioneer Washington, Quality Components, Semiconductor Specialists, Wilshire, Wyle/Elmar, Wyle/Liberty, or RAE."

Yes, I want to find out for myself h put bipolars on the list of endar Please send me your brochur	ngered species.
Name/title	
Siliconix Incorporated, 2201 Laurelwood Road, Santa Clara, CA 9 (408) 246-8000.	5054, EL 11/24/77



# Five people and a million bucks in equipment. And they're waiting for a replacement

Call Profit By Air.

Profit By Air will ship anything from a disc drive to a solenoid to a modem. And we'll do the job quickly, safely and efficiently. Because we specialize in transporting electronic components.

We tailor-make programs for individual customers. We'll even create a program for you. And base it on your specifications and requirements.

We know the cost of down time—and how urgent it is to replace a "tired" part. We give special care to shipments marked "fragile" since we realize how delicate electronic components can be. And we're reliable. Short of a disaster—and sometimes despite it—we'll deliver your package when promised. After all, if we didn't keep our word we wouldn't be where we are today.

Profit By Air—founded in 1968—has grown to become one of America's ten largest air freight forwarders.

We offer personalized service—you deal with the same well-trained people all the time. We ship all over the country—and the world. We have a global communications system that keeps us zeroed in on the location of any shipment from pick-up to delivery.



Profit By Air. Remember our name when you need the air freight specialist in electronic components. Understanding your business is part of ours.

To find out how you can have an air freight program custom-made for your company, call our electronic specialists at this toll-free number: 800-241-8328.

## PROFIT BY AIR The air freight specialist

in electronic components

© 1977 Profit By Air

### **MICPOPPOCESSOPS** in action ...............

#### Monitoring system optimizes apple-tree spray cycle

by P. David Fisher and Sigurd L. Lillevik. Michigan State University, East Lansing, Mich.

☐ Growers of apples, the second most popular fruit in the U.S., have an enemy in apple scab, a fungus that attacks the leaves of apple trees every spring. To combat it, growers apply fungicide sprays or dusts regularly 12 to 15 times a year. But now they may have found a friend in the microprocessor: an alternative approach to apple scab control, using a microprocessor-based system, is being tested that will likely mean fewer but more effective fungicide applications—which should, in turn, mean reduced costs and environmental damage.


The system comprises a small special-purpose computer, built around a microprocessor, and field sensors that measure and record three environmental variables, plus allied signal conditioners. Using a program stored in its memory, the computer predicts the severity of apple scab attacks so that the grower can apply fungicide when it is most effective. The program consists of a table of fungus severity versus the three environmental variablesaverage air temperature, hours of leaf wetness, and relative humidity (which, when high, extends the hours of leaf wetness).

Manual use of the table—the work of D. W. Mills of Cornell University—was tried, but it proved too slow and cumbersome because of the considerable amount of data gathering and calculation needed. A microprocessor-based system, on the other hand, can collect the data




1. Apple protector. This movable, microprocessor-controlled instrument, shown in an orchard, predicts severity of fungus attacks on apple trees. Manual instruments for measuring temperature and humidity are grouped about the new unit, which replaces them.

automatically and be interrogated on the spot for an instant prediction—and it requires less than one hour of training to operate properly. Further, it can be moved easily. Because of these advantages, as well as the fact that the projected unit cost of about \$500 can readily be recovered in a single growing season, most growers



2. Busing data. Simplified diagram of microprocessor-controlled predictor of apple scab fungus shows all major system blocks linked by a 44line common bus. Most of the bus is taken up by an Intersil IM6100 single-chip C-MOS microprocessor.



3. Apple PIE. System clock, environmental sensors and signal conditioners, and operator console are tied to the system bus through peripheral interface elements. These devices provide addressing interrupts and controls for peripheral functions.

should quickly adopt it. In addition, the system can be modified for use against other crop diseases, making it an even more attractive solution to the problem of apple scab infestation.

To test the feasibility of using microprocessors to predict attacks of apple scab, as well as other crop diseases, a prototype system has been designed, built, and installed in an orchard. The self-contained special-purpose computer, connected to field sensors, resides for the entire growing season in a relatively open frame, mounted on a pole (Fig. 1). As depicted in Fig. 2, five major sections constitute the basic instrument; a sixth is optional. Since each section uses complementary-metal-oxide-semiconductor logic, the entire instrument consumes very little power—60 milliwatts—and therefore operates easily from a battery for prolonged periods.

A bus shared by 44 lines links the sections and the sensors. It makes the system both expandable and flexible, since memory, input and output lines, and so on, can be freely added or deleted. Also, the bus helps isolate failures, thus simplifying maintenance.

The microprocessor is Intersil Inc.'s single-chip IM6100. It has all the advantages of C-MOS (low power consumption, wide voltage supply range, low temperature sensitivity, and so on), and it executes Digital Equipment Corp.'s PDP-8/E instruction set as well. With resident machines and operating systems available, the latter feature eliminates the need for a cross assembler. Moreover, much application software already exists for the PDP-8/E.


Furthermore, the IM6100's 40 pins can act as a subset of DEC's omnibus, allowing the direct use of many peripherals. In addition, a PDP-8/E can be used as an IM6100 emulator, greatly speeding up prototype development for other applications. These reasons, together with Intersil's complete line of support chips for its central processing unit, led to the selection of the IM6100.

#### Peripheral interfacing

To minimize external logic for the microprocessor, three programmable interface devices (Intersil's IM6101) are used to address, interrupt, and control the peripherals, like the operator console and the optional control panel, as well as the sensors. (These devices, of course, can do the same for peripherals added for other applications, like universal asynchronous receiver/transmitters and first-in, first-out registers.) Because the properties of these chips are programmable—that is, polarity assignment, vectored interrupt addresses, and so on—input/output implementation is greatly simplified.

The real-time clock in Fig. 3 uses a single chip (IM7213) having a 4.193404-megahertz crystal oscillator and count-down circuitry with both 1-hertz and 1/60-Hz outputs. Each output triggers a vectored interrupt, by means of a peripheral interface element, to routines that control data acquisition and scab-prediction updates.

The environmental sensors record ambient and wetbulb (for relative humidity) temperatures along with



**4. External control.** Optional external control panel can be used both in maintenance work on the instrument and in development for other applications. The control panel can load in new programs from an external computer or minicomputer, or supply diagnostic tests.

degree of leaf wetness, and the signal conditioners translate the data into digital signals. Both temperature sensors use linear thermistors to vary the frequency of individual RC astable pulse oscillators as the air temperature varies, and the oscillators trigger vectored interrupts to the appropriate counting software. A look-up table in the software correlates wet- and dry-bulb temperatures with the relative humidity. As for leaf wetness, the appropriate sensor biases a comparator on or off, and the computer uses the signal from the comparator, together with its real-time clock, to determine the hours of leaf wetness. Hence the signal conditioners replace the traditional scheme of analog multiplexer and analog-to-digital converter.

The operator console section includes a 25-station keyboard and a four-digit, alphanumeric, liquid-crystal display. A single-chip encoder (74C923) debounces switch closures, provides two-key roll-over protection, and maintains a last-key register. Its data-available signal triggers another vectored interrupt, via a peripheral interface element, to a routine that reads the keyboard and services the command. For example, an operator may use the keyboard and display to inspect or change the date or time, as well as to interrogate the data base or obtain a forecast and a histogram.

Lastly, the semiconductor memory contains read-only memories in its higher addresses and random-access memories in its lower addresses. The application program (Mills's table) resides in roughly 1,096 bits of ROM. Additionally, a battery-backed 1-k RAM provides portable, permanent storage for histograms of the scab forecasts. Growers may then remove the memory card from the computer and later receive a hard copy of the histogram.

The external control panel, the optional sixth section of the instrument, aids both development for other appli-

cations and maintenance. The IM6100 has a dedicated control panel interrupt request and a control panel memory-select line. Therefore control panel programs reside in their own unique memory, separate from main memory. Furthermore, control panel routines may access main memory through indirect reads and writes. Thus an external control panel can display all IM6100 registers, alter them, and read or write into main memory.

#### **External control**

The panel, shown in Fig. 4, includes a high-speed paper-tape reader and interface, a 25-station keyboard and encoder, a latch with light-emitting-diode indicators, and its separate solid-state memory. The control panel program performs three functions: it accesses IM6100 registers and main memory; it deciphers binary paper tapes by means of a loader program; and it performs a set of diagnostic tests for maintenance.

During development, battery-backed RAMS, instead of ROMS, can make up the program memory. A PDP-8/E with an operating system can assemble the application program, which would then be loaded through the control panel into memory. After the normal debugging period, the application would be programmed into the ROMS, and the control panel would be removed until needed for diagnostic testing.

The application program executes three independent, real-time tasks under priority interrupt scheduling. The real-time clock task has the highest priority. It maintains the date and time and initiates the apple scab prediction updates. Data acquisition is second. Lowest in priority is servicing an operator. When the grower uses the keyboard, this task decodes the request and executes the command—change time, display data, predict scab status, etc. The tasks operate independently, and the peripheral interface devices coordinate their scheduling.

#### **Engineer's notebook**


### LED bar-segment array forms low-cost scope display

by Vernon Boyd
The Welding Institute, Abington, Cambridge, England


Building a small, low-powered, and low-cost oscilloscope for simple monitoring applications is easy, especially if light-emitting diodes are used in place of the cathode-ray tube. This circuit uses 10 bar displays, each containing 10 LEDS, to form a 100-dot viewing matrix. With this configuration, of course, resolution is only 10% in both the X and Y axes, but it can be improved by adding additional displays and expanding the driving circuitry.

As shown in Fig. 1, the signal-processing and logic circuits for the scope are straightforward. The signal-path circuit is extremely simple and has all of the options usually expected—ac and dc input coupling, variable Y-axis gain, and offset control. The signals to be observed pass through amplifier  $A_1$ , are amplified up to 100 times by  $A_2$  and are inverted by  $A_3$ , and then pass through to the display comparator.

The trigger and timing circuits are not complicated,



1. Signal, timing, and logic. Driver circuits for scope's LED bar displays are straightforward. Input circuit can process ac or dc signals and has variable Y-axis gain control.  $A_1 - A_3$  is input-signal path.  $A_4$ ,  $B_1$ , and  $B_2$  provide sync for 555 clock generator and 4017 counter, which strobes bar displays. Circuit has internal, free-run, or power-line triggering option. Maximum sweep rate with 555 is 10 kHz.




counter's location to the sweep rate.

A<sub>4</sub> is triggered either by the signal (internal mode) or by the 60-cycle power-line input. In the free-run mode, A<sub>4</sub> is not required. These three modes are selected through S<sub>1a</sub>, which is ganged to S<sub>1b</sub>. The trigger level can be set by the 10-turn potentiometer at A<sub>4</sub>'s input.

A<sub>4</sub> drives the 4013 D-type flip-flop circuit, composed of B<sub>1</sub> and B<sub>2</sub>, through a transistor buffer. The 4013 ensures that triggering on repetitive waveforms will be reliable, for it is reset at the end of any display sweep by the final stage (C<sub>0</sub>) of the 4017. This event causes B<sub>2</sub> to reset B<sub>1</sub>, which in turn resets the 4017.

As shown in Fig. 2, the bar displays are driven by ten LM324 comparators and a ten-gate NAND decoder. The chain of reference voltages, each separated by 1 volt, are generated by a string of 10 resistors and a 10-kilohm calibration potentiometer. These resistance values must be changed to accommodate the Y-axis resolution required. For example, if there are 20 elements in the Y



2. Display. Comparators, NAND gates, and transistors drive bar displays as each is strobed in succession (a). Amplitude of Y-axis signal determines which of 10 LEDs in each display is illuminated during sweep. Typical sine wave is displayed on 100-dot matrix (b).

axis (two 10-bar displays vertically mounted one above the other), the resistances must be selected to provide 0.5-v increments. Also, the Y-axis expansion must be implemented with additional comparators and gates. The NAND gates ensure that only one LED can be activated at any given time.

Expansion of the X axis is a bit more elaborate, but

not overly difficult. Simply cascading additional 4017s will not do, however, as two output states will occur, one for each driver. Consequently, these states must be decoded using NAND gates.

The 555 clock generator will sweep at a maximum rate of 10 kilohertz. For faster sweeps, a different clock circuit is needed. The comparators' frequency limits must also be well above the sweep rate.

## Variable oscillator reacts to magnetic flux changes

by V. Vijayakumaran Nair Vikram Sarabhai Space Center, Trivandrum, India

An oscillator employing a saturable-core reactor can detect small changes in the intensity of any magnetic field that cuts through the reactor's windings. The oscillator utilizes core hysteresis in order to generate a frequency that is directly proportional to the magnetic field component along the inductor's longitudinal axis.

As shown in (a), two 2N3020 transistors form a simple astable multivibrator that oscillates at a frequency of 11 kilohertz in the absence of an external magnetic field. The inductor, L, in the collector lead of  $Q_1$  has a core made from  $\mu$  metal, a commonly available, high-permeability magnetic alloy with the characteristics shown in (b). The  $\mu$  metal consists of nickel, iron, copper, and manganese. Placed around it is an insulating layer of phenolic resin impregnated with paper or cloth, of a kind frequently used in coil forms. As shown in (c), 800 turns of AWG 36 wire, wound over the insulator, gives L a value of a few millihenries.

Circuit operation may be understood from (d). Disregarding any external field for the moment, and assuming an arbitrary start time of  $t_1$ , at which point  $Q_1$  is on and  $Q_2$  is off, current will build through L at the rate of i=(V/L)t, where V is the supply voltage and t is the time. Generated in the coil is a magnetic field of intensity  $H_s$ , in a direction determined by the corkscrew rule. As the field increases, the level of flux density also increases. As  $t_2$  approaches, the current rises to a value sufficient to saturate the  $\mu$  metal ( $H_{sat}$ ). The flux density reaches  $B_{sat}$  and remains at that value.

As a result, the inductance drops to that of an air-core inductor, because the core permeability is proportional to  $\Delta B/\Delta H$ . Thus, at  $t_2$ , the current increases almost instantaneously towards an infinite value, and as  $Q_1$ 's base current is about  $V/(R_1+R_3)$ , too little to keep the transistor in conduction,  $Q_1$  is eventually cut off.


The base current into  $Q_2$ , which is approximately equal to  $V/R_2$ , is not quite enough to turn this transistor on, however. But as  $Q_1$  turns off, an induced electromotive force, much greater than V, is produced across the inductor, giving rise to enough additional current to turn  $Q_2$  on and keep it conducting.  $Q_2$  remains on until  $t_3$ , when the induced current, which has been falling from time  $t_2$  with a rate equal to  $-L/R_2$ , finally decreases to near zero. The collector of  $Q_2$  rises, bringing  $Q_1$  into conduction, current builds in L, and the process repeats.

Consider an external field with intensity H<sub>a</sub> along the

axis of the coil such that the actual field causing a flux change is equal to  $H_s \pm H_a$ , depending on the direction of the external field. When  $H_a$  is opposing the field, the current takes longer to bring the total field to a value equal to  $H_{sat}$  between times  $t_1$  and  $t_2$ ; hence the oscillator's frequency will be lower than with no external field present. Similarly, when  $H_a$  is in the same direction as  $H_s$ , the core will reach saturation sooner, and the cycle will be speeded up, causing a rise in frequency.

The frequency will increase from 8 to 14 kHz for an external field change of  $\pm 0.4$  oersted. This change can be obtained merely by rotating the coil in a horizontal plane from the east—west to the north—south direction of the earth's magnetic field.

Engineer's notebook is a regular feature in *Electronics*. We invite readers to submit original design shortcuts, calculation aids, measurement and test techniques, and other ideas for saving engineering time or cost. We'll pay \$50 for each item published.



**Field sensitive.** Saturable core reactor enables oscillator to detect change in any magnetic field whose flux lines cut reactor windings (a). Oscillator frequency is determined by the core saturation time (b). Inductor is made of  $\mu$  metal, insulated core form, and 800 turns of high-gauge wire (c). Timing diagram details operation (d).



# take sides with the leader

Solid State Scientific has over 100 device types for your standard circuit requirements. We are a major supplier of the 4000, 4100, 4400 and 4500 families and our line includes all popular package configurations.

One indication of our commitment to leadership in the B-Series of CMOS circuits is our product development program. Recently, we have upgraded five devices (4016, 4020, 4040, 4060 and 4416) to meet or exceed the full electrical characteristics of the JEDEC Standard Specification. Five additional types (4006, 4017, 4022, 4043 and 4044) are now being upgraded and samples will be available shortly. In addition, eight new circuits (4048B, 4085B, 4086B, 4094B, 4174B, 4192B, 4193B and 4494B) are available for sampling and will shortly be moving into production.

We offer commercial grade devices, 883B Mil-Spec devices and a variety of low cost, industrial high reliability screening programs. Known as Solid Plus, these screening programs can simplify incoming inspection at your plant and reduce problems caused by infant mortalities.

Write today for our new CMOS condensed catalog. In addition to our complete line of B-Series devices. it includes our standard memories and timekeeping circuits, plus details on the Solid Plus program. Solid State Scientific Inc., Montgomeryville, Pa., 18936. Phone: (215) 855-8400. TWX: 510-661-7267.



#### SOLID STATE SCIENTIFIC INC.

All sides of CMOS technology

Circle 131 on reader service card

#### Engineer's newsletter.

#### When to use hardware rather than software

With nearly everyone using microprocessor-based systems to perform virtually every function in software, many designers may overlook the more cost-effective hardware solutions open to them. In fact, it's often better to implement a function in hardware than to be lured by the elegance and novelty of writing your own program.

Remember, software can be extremely expensive, costing as much as \$10 for each fully debugged line of program. Moreover, the microprocessor is relatively slow, so you may actually get better performance out of hardwired circuits because they are able to operate over a wider frequency range than the microcomputer. Also, since the processor is often driven by clocks external to the system and capable of high-frequency operation, there is seldom any need to pay extra for a high-speed clock to drive the hardware.

For example, hardware, rather than software, is generally better able to: synthesize sinusoidal waveforms, implement tapped-stage shift registers and other simple counting circuits, and even set program breakpoints, which permit you to test the program no matter what type of memory the microcomputer uses.

#### Insertion molding a reliable way to join metal and plastic

Most electromechanical components contain both plastic and metal parts with the metal and plastic joined together with a pin or rivet. A new insertion-molding process called Metl-Plas, originated at Capsonic Group Inc., Elgin, Ill., eliminates this costly labor-intensive attachment. During the new process, the metal component is manufactured and then fed into a mold, where plastic is formed directly around it.

For instance, in manufacturing a television circuit breaker, Capsonic's engineers were able to produce a cost saving of 40%—plus a more reliable unit. The new technique has also been applied to such diverse components as television tuner assemblies, load coils for citizens' band antennas, and computer printout heads.

# Learn to design microprocessor-based gear for testability

Along with the benefits of large-scale integration has come one of the most difficult challenges facing today's designers: making the microcomputer-based equipment easy to test. If testability isn't considered during the design phase, there could be a high price to pay in servicing once the equipment gets into the field. To attack these problems, the IEEE Computer Society's Test Technology Committee is forming a subcommittee on "Design for Testability."

If you're interested in participating in the subcommittee's work or in a workshop now being planned for early 1978, write T. M. Williams, Department 23M, Building 910, IBM Corp., P. O. Box 1900, Boulder, Colo. 80302, or phone (303) 447-7752.

## HP gives lowdown on rf power measurement

Hewlett-Packard's done it again—another good application note on measurement techniques. This one's called "Fundamentals of Rf and Microwave Power Measurements," Application Note 64-1. You can get a copy by writing to the Inquiries Manager, Hewlett-Packard Co., 1507 Page Mill Rd., Palo Alto, Calif. 94304.

Lucinda Mattera



Whether your radio tunes to the "sweetest music this side of heaven" on the AM and FM bands, the busiest chatter on the CB band, or the weather report on the public service band; our new Model 103 signal generator meets all your test signal requirements ... and then some.

The generator combines a frequency coverage of 125 kHz to 175 MHz with five IF and RF sweep ranges. It has full external counting capability down to 5 Hz, accurately metered FM and AM

modulation, high RF output to +23 dBm, and phase lock on the 103B version.

The 6 digit readout has selectable resolution to as high as 1 Hz. It can also display the center frequency of each sweep range or the frequency of a built-in variable marker.

Boonton's Model 103 replaces two or more older signal generators, a counter, and a sweeper, giving you cost savings you hadn't thought possible since that other Big Band Era. Don't just take our word for it. Call us or your Boonton rep (you'll find him listed in EEM, ECC, and the Goldbook). We'll arrange a demonstration, and bring along a record album of the top hits by the big bands of that other era. It's yours for allowing us to sound off a bit.

Call or write: Boonton Electronics Corp., Rt. 287 at Smith Rd., Parsippany, New Jersey, 07054, Phone (201) 887-5110.

### **BOONTON**



# Digital Signal Processing?

# 14 new LSIs can give you the answers to hundreds of digital signal processing design problems

Pick out the function that presents you a design problem. Look at the word size. Look at the speed. Then call TRW for all the engineering/application information you need!

All 14 of these new digital-LSI components are designed to reduce your circuit costs, reduce your size and power requirements . . . and to improve system reliability. These are the newest and best

components you can buy!

TRW has been setting new performance standards since we started the TTL business in the early 60s. Our future is committed to setting even higher performance standards . . . at prices you can afford! For complete information, contact your nearest TRW Electronic Components Division Rep directly. Or write us. Or call us at (213) 535-1831.

## CONTACT YOUR NEAREST TRW ELECTRONIC COMPONENTS DIVISION REP NOW!

#### SALES OFFICES

ALABAMA, Huntsville	
CALIFORNIA, Los Angeles	(213) 478-0183
Menlo Park	(415) 321-9050
Tustin	(714) 832-4952
COLORADO, Westminster	(303) 426-0890
CONNECTICUT, Orange	(203) 795-3515
Rowayton	(203) 853-4466
FLORIDA, Ft. Lauderdale	
Orlando	(305) 857-3650

<b>ILLINOIS</b> , Elk Grove Village (312) 593-0200
INDIANA, Fort Wayne(219) 432-5591
Indianapolis(317) 359-9283
Kokomo
IOWA, Cedar Rapids (319) 393-8703
KANSAS, Prairie Village(913) 236-4646
Wichita (316) 686-6685
<b>KENTUCKY</b> , Louisville (502) 897-1569
MARYLAND, Baltimore (301) 254-1736
MASSACHUSETTS, Waltham (617) 890-3232
MICHIGAN, Grand Rapids (616) 942-5420
Southfield
St. Joseph
MINNESOTA, Minneapolis (612) 835-5454
MISSOURI, St. Louis (314) 432-2830
NEBRASKA, Lincoln (402) 474-5151
<b>NEW MEXICO</b> , Albuquerque (505) 265-7759

# We've got the answers!

FUNCTION*	WORD SIZE	SPEED	PART NUMBER	AVAILABILITY
Multipliers	8 x 8	130 ns	MPY-8AJ	Now
	12 x 12	150 ns	MPY-12AJ	Now
	16 x 16	160 ns	MPY-16AJ	Now
	24 x 24	200 ns	MPY-24AJ	3/78 +
Multiplier-	8 x 8	70 ns	TDC1008J	2/78 +
Accumulators	12 x 12	150 ns	TDC1003J	Now
	16 x 16	100 ns	TDC1010J	3/78 +
A/D Converters	8	1000 ns	TDC1002J	Now
	8	400 ns	TDC1001J	Now
	8	80 ns	TDC1007J	4/78 +
	10	1000 ns	TDC1013J	5/78 +
Shift Registers	1 x 256 bit	40 MHz	TDC1005J	Now
	2 x 64 bit	40 MHz	TDC1006J	Now
Correlators	1 x 64 bit	15 MHz	TDC1004J	Now

<sup>\*</sup>All parts are guaranteed 0-70°C in *still* air. MIL temperature versions available.

TRW LSI Products, An Electronic Components Division of TRW Inc. P.O. Box 1125, Redondo Beach, CA 90278

#### **INTERNATIONAL SALES OFFICES:**

NEW YORK, Rochester		AUSTRALIA, Kingsgrove N.S.W.         500111           BELGIUM, Brussels         6600012
OHIO, Cincinnati Columbus Dayton Middleburg Heights OREGON, Beaverton	(614) 888-9396 (513) 298-9546 (216) 826-4424	DENMARK, Bagsvaerd       986333         FINLAND, Helsinki       640641         FRANCE, Paris       7581111         GERMANY, Munich       503007         ISRAEL, Tel Aviv       444572
PENNSYLVANIA, Bala Cynwyd	(215) 667-3400	ITALY, Monza       360021         JAPAN, Tokyo       4615121
TENNESSEE, Greeneville TEXAS, Austin Dallas Houston	(512) 451-2959 (214) 387-3030	NETHERLANDS, Amsterdam       934824         NORWAY, Oslo       157550         SOUTH AFRICA, Capetown       457656         Johannesburg       6181027         SPAIN Modeled       2425204
UTAH, Salt Lake City	(801) 943-5650	SPAIN, Madrid
VIRGINIA, Richmond	(804) 288-8334	<b>SWITZERLAND</b> , Zurich
WASHINGTON, Bellevue		<b>TAIWAN</b> , Taipei

### TRW LSI PRODUCTS

... for Digital Signal Processing

Included to help you with your newest design plans.
 Write or call to receive information when available.

# After you've checked double-sided floppy, the best-designed.

### Introducing the simple, versatile MFE 700/750.

We took a whole new look at floppy disc technology. And came up with a whole new kind of flexible disc drive.

The MFE 700/750 is the smallest full-sized floppy

around, which gives you extra design flexibility.

And because we designed from scratch—not from an existing model—we were able to provide state-of-theart features throughout. For example:

Our floppy uses a fast, precise HELI-BAND™ positioning system instead of the less-accurate lead screw.

In addition to our AC motor, we offer a unique brushless DC motor which cuts power consumption in half and won't add to your heat problem.

Our twin ceramic heads act as nearly frictionless

load pads. They actually help extend media life.

Our IBM compatibility is <u>true</u> compatibility, including track 43 write-current switching, tunnel erase for sharper trim and less fringing, and a data separator that can handle either a missing-clock or a non-missing-clock scheme.

Standard features include data transfer rates of 250/500K bits/sec. and a packing density of 3400/6800bpi. And our standard option list is the longest in the industry. We can tailor a unit to your exact needs.

Naturally, we offer single-sided models, too.


Once you've talked to the company everybody's heard of, talk to us. We'll show you why the best design is more important than the biggest name.

For details, contact MFE, Keewaydin Drive, Salem, New Hampshire 03079, Tel. 603-893-1921/ TWX 710-366-1887/TELEX 94-7477.

Europe: MFE Products SA, Vevey, Switzerland, Tel. 021 52.80.40/TELEX 26238.



# out the best-known check out





# System 6000.

Burn-in is now part of the Ane

process!

A new Microtest System 6000 at the end of your process line will weed out the bad ones by carefully controlled burn-in.

Two years ago we introduced the first Murphy's Ovens. Murphy's Law said that your IC's would fail if they could fail. We set out to find the bad ones and make them fail before they could hurt a system.

You liked the idea. We have since sold lots of our first two systems, the 1,000 and 10,000, which perform burn-in tests on 1,000 and 10,000 circuits respectively.

Now we've leapfrogged the middle-sized system that we had in mind originally, and have developed what looks to us like the standard burn-in system for the next decade.

Our System 6000 is, in one word, adaptable.

It is available, in its simplest configuration, as a stand-alone test-oven shell containing six independent zones, each with six burn-in-tray slots. Base price of the shell is \$15,000. To get into operation, you add clock driver modules, power regulator modules, and burn-in trays—as few or as many as you like. You can then handle burn-in tests for any variety of circuits, in any socket under any stress conditions.

But new advanced microprocessors and three years of software development make it infinitely flexible. It can be configured to handle any burn-in requirement. MOS. Bipolar. I<sup>2</sup>L. Microprocessors and computers. And, it can grow in modular fashion to give even the biggest IC houses the kind of precision screening that saves big money. When you're life testing 10,000 4K or 16K RAMs at once, lack of precision in power supplies or timing can destroy parts that ought to pass. Microtest fails only the failures.

But the details cover page after page of the data sheet. Let us leave something for your reading. Please call or write for information or a demonstration. Microtest Systems, Inc., 1188 Bordeaux Drive, Sunnyvale, CA 94086. (408) 745-7000. TWX: 910-339-9325.

Microtest Variable Power (MVP™) regulators (up to 30 of them) provide stable, precision power to your boards under test. Circuitry is fail-safe throughout. Clocking is programmable and flexible enough to handle any test protocol. This innovative power distribution scheme dramatically cuts the cost of system power

supplies.

Up to 18 Driver Cards set the test conditions for circuits in the zone they are driving. There are three varieties: Basic static burn-in, Condition D burn-in, and sophisticated VLSI burn-in. For the

latter, our basic system includes shell, card cages, feedthrough connectors, power transformer, and programmer-controller.

Programmer-controller, μP-based, houses CRT, tape cassette memory, keyboard input, ambient test console. It will handle programming and monitoring chores for up to 16 systems, each holding 6000 devices. Yet it is simple to program and can even be ordered with pre-programmed cassettes.

Circle 139 on reader service card

## "Until now, we'd been mistaking access to processing for access to answers."

Problem: It takes more than a desktop processor to organize output into its simplest, most usable form.

A personal computer can shave timeshare expenses, but do nothing about trimming the fat off alphanumeric answers. You can give up the power of a mainframe without the promise of more intelligent, instantly visible data.

Solution: Tektronix' 4051 Graphic System. The one desktop unit that shapes information into usable graphics.





From interfaces and firmware to hard copy units, data storage devices, printers, plotters, graphic tablets and proven software, Tektronix provides plug-in capability to customize the 4051 to your special needs.

A graphics answer is the most concise of all possible solutions. The 4051 can eliminate the hand-plotting and mental gymnastics that users of alphanumeric-only systems take for granted. It lets you instantly unscramble data and interactively experiment with graphs, charts, maps and models. With exceptional simplicity. With almost the speed of thought.

You command up to 32K of off-line processing power. With a graphically beefed-up BASIC language. With complete editing and versatile graphic-oriented software.

You can tackle big programs on-line in any language,

store data on built-in mag tape, and generate graphic reports all at your own pace.

The 4051: Its Graphics keep working when other systems quit. Yet it can pay for itself in less than a year in timeshare savings alone. Call your local Tektronix Sales Engineer, or write:

Tektronix, Inc.
Information Display Group
P.O. Box 500
Beaverton, OR 97077
Tektronix Datatek N.V.
P.O. Box 159
Badhoevedorp, The Netherlands

Get the picture. Get straight to the point.



Tektronix®

OEM prices available Copyright © 1977, Tektronix All rights reserved

#### **C-MOS** converters resolve 12 bits


Hybrid digital-to-analog units are the first such equipment to combine direct microprocessor compatibility with the low power dissipation of C-MOS

by Larry Waller, Los Angeles bureau manager

As manufacturers of test instrumentation and process and industrial systems seek better overall performance, more accurate data conversion components-particularly at the 12-bit resolution level—are needed. Furthermore, rapid incorporation of microprocessors make compatibility of these converters without hooking up extra external interfacing components another important objective. To get these features in a pair of new digital-to-analog converters now being offered in prototype, Beckman Instruments, Inc. employs a hybrid approach that uses a thin-film resistor network for current weighting and a separate complementarymetal-oxide-semiconductor chip for low power dissipation. Thus Beckman has the first single-package microprocessor-compatible d-to-a converters that offer 12-bit accuracy and the milliwatt power consumption of C-MOS circuitry.

"The key to this performance is a mature thin-film technology that allows achieving linearity and tracking specifications," says Lyle F. Pittroff, product marketing manager for hybrid microcircuits. "We knew we could combine thin-film on the same substrate with C-MOS without compromising performance of the switches." Beckman developed the converters in an 18-month program, and plans to introduce additional a-d models in January.

In contrast to monolithic converter producers that put the resistor switching ladder on the circuitry chip itself, Beckman felt this design makes laser trimming too difficult. "The ease of trimming the ladder by dividing it from the chip enables us to attain accuracy to within ½ least-



significant bit," says Lerdy Little, senior product engineer responsible for the converter design.


"By working both pieces separately, we're able to keep tighter tolerances," he says. Also, he says, Beckman found that it could "hold the geometry and separate the resistor ladder and C-Mos chip all within a 125-mil-square substrate, above which size costs skyrocket." He believes the converters should attain an operating life of 100,000 hours.

Of the two converters, series 7545 is a multiplying model with a four-quadrant configuration, implemented by bipolar digital proportioning of an ac external reference. It can be used to accommodate tran-

sistor-transistor-logic or C-MOS standard supply levels where digital and analog subsystems operate on different supplies, Pittroff says.

The more complex series 7546 provides complete general-purpose conversion with self-contained 10-volt dc reference and the operational amplifier and feedback circuitry to achieve up to 5 milliamperes of output drive capability. It incorporates preadjusted zero offset for the output buffer amplifier and a biasing amplifier for bipolar operation.

For microprocessor compatibility, both models offer a double buffering input feature with separate input and holding registers. Here, two input registers can accept a 12-bit



# FOR TRULY STATE-OF-ART INDICATOR AND DISPLAY (FULL COLOR) SCREENS —

### **ELMITRONS**

- as bright as 2000 cd/m<sup>2</sup>
- line width to 0.15 mm
- recording/reproduction rate to 2 mm/µsec
- clearly and distinctly broken-down spectrum from red through intermediate colors to green – for dependable performance even in bright sunlight
- a choice of screens: spherical and flat, round and square, 6 to 20 inches, deflection angles 50° to 100°, afterglow from 0.001 s to 10 s

#### Available in a comprehensive range:

single- or double-ray (i.e. with one or two beam systems), with rear screens, with screen grids.

Also available in a **special vibration**- **impact** - **explosion proof make** for the most trying conditions and high altitudes.

#### Exporter:



32/34 Smolenskaya-Sennaya 121200 Moscow USSR Tel. 251-39-46, Telex 7586

#### **New products**



data word in 4-bit and 8-bit form from an 8-bit processor bus.

For TTL-C-MOS compatibility, both input registers have translators which take TTL inputs using a +5-v supply or C-MOS inputs with from +5- to +15-v levels. Separate power supply lines for both holding and input registers allow flexibility without compromising linearity, according to Pittroff. Both series operate in serial or parallel input modes and can be switched from one to the other. The registers are switch updated upon command through enabling lines or for continuous conversion by permanently enabling transfer lines for parallel operation.

Internal configuration of the converters has the thin-film nichrome resistors deposited on an alumina substrate. The separate C-MOS chip contains input level translators and shift registers, the converter-switch holding register, switch drivers, and analog switches. It is silicon nitride passivated for both commercial and military versions. The commercial unit is available in a polymer sealed package, guaranteed over a 0 to 70° C range. Military models have a hermetically sealed package, over -55° C to +125° C.

The two converters will be available in quantities during January. Prices for commercial versions are \$21.90 for the 7545 and \$43 for the 7546, in hundreds.

Beckman Instruments, Inc., Helipot Division, 2500 Harbor Blvd., Fullerton, Calif. 92634. (714) 871-4848, Ext. 1126 (338)

# Signetics Op Amps: Fast Performers Ready For Fast Delivery.

Choose from three new op amps with high slew rates. One specifies the industry's lowest noise: 4nV/ \( \frac{\text{Hz}!}{} \)

The next time you find yourself searching the specification tables for a high-performance op amp, be sure to search ours. You'll find a broad offering—more than 60 models, each with package and temperature options. You'll also discover three new entries, one of which is likely to provide that exceptional spec you need.

Our Quiet Performer: SE/NE5534.

If low noise is critical to your design, then you need our new SE/NE5534. There's not another op amp around with better noise performance. With input noise specified at  $4nV\sqrt{Hz}$  at 1 kHz, this device can drive a 600-ohm load. Great for quality audio equipment and instrumentation/control circuits. Our quiet performer also offers a

generous 10-MHz bandwidth and a respectable 13V, usec slew rate.

When you compare the SE/NE5534 with standards like the  $\mu$ A741 and LM307, you'll find that it offers superior performance—spec for spec. This outstanding op amp is internally compensated for gains equal to, or greater than, 3. And if you want to optimize frequency response for unity gain, capacitive load, low overshoot, etc., you can do so easily with an external capacitor.

Two For High Slew. For those designs demanding high slew rates, you should look into our super-fast performers—the SE/NE530 or SE/NE538. Internally compensated, both of these devices have excellent input characteristics.

The SE/NE530 is a superior rereplacement for any device in the \$\mu A741\$ family. With high slew rates of 18V/\$\mu\$sec (+1 gain) and 25V/\$\mu\$sec (-1 gain)—plus a small-signal bandwidth of 3 MHz—this op amp is a veritable workhorse for numerous applications. Selecting it over a 741-type device translates to improved performance, greater design flexibility and reduced inventory.

With the SE/NE538, you get 40V/µsec slew at a minimum gain of +5/-4. This guaranteed speed comes without power penalty, as the maximum supply current required is just 3 mA. If you're using op amps like the µA741, LM301A or BiFETs, you could be getting better performance with our 530 or 538.

Move up to better op amp performance. Move up to Signetics. For complete details, use the coupon below or contact your local Signetics distributor.



a subsidiary of U.S. Philips Corporation

Signetics Corporation 811 East Arques Avenue Sunnyvale, California 94086 Telephone 408/739-7700

P.O. Box 9052, Sunnyv. Please send technical data following op amp(s):	and sample(s) for the
☐ Low-Noise SE/NE5534 ☐ High Slew SE/NE538 ☐ My need is urgent; hav phone me at once: (	☐ High Slew SE/NE530  we an applications specialist  ext.
Name	Title
Company	Division
Address	MS
City	State Zip
I'm also interested in any of application:	ther op amps you offer for this EM1124

## **Multimeter delivers extra functions**


31/2-digit instrument selling for \$279 offers full capability including direct dBm and true-rms readings and a 10-ampere range in current measurements

by Lawrence Curran, Boston bureau manager

With prices for 4½-digit multimeters in the range from \$200 to \$300, why would a company bring out a 3½-digit instrument selling for \$279? According to Harold Goldberg, president of Data Precision Corp., it is because users are looking for a variety of functions. He calls his company's 1750 a "bells and whistles model—an extra-function instrument that provides just about any measurement anyone using a digital multimeter would want."

Data Precision is probably the leading supplier of 31/2-digit multimeters. "Traditionally, we've emphasized low cost," Goldberg explains, "but here we've gone to the user who wants full capability." Besides the traditional functions in an instrument with dc accuracy to within 0.1% for high-precision applications, the model 1750 offers these extras: direct dBm and true rootmean-square readings, high and low excitation in resistance, and a 10-ampere range in current measurements. Goldberg expects the dBm feature to be especially attractive to users in the audio and telecommunications fields, observing that the latter is growing rapidly as a market for multimeters.

The unit measures dc volts in five ranges from  $\pm 100$  microvolts to  $\pm 1,000$  volts and ac volts in five ranges from  $100~\mu v$  to 1,000~v rms, with a frequency response of 20 hertz to 20 kilohertz. In dc current, (six ranges) the meter covers from  $\pm 100$  nanoamperes to  $\pm 10$  amperes rms; in ac (six ranges), from 100 nA to 2 A, with the same frequency response except for the 10-A range, where the frequency is 20~Hz to 1~kHz. High and low excitation resist-



ance measurements are provided in six ranges from 100 milliohms to 20 ohms, and the direct-reading dBm function is from -60 to plus 20 dBm

The model 1750 also offers a sensitivity of 100 µv, overload protection 100% overrange, and automatic zero. Goldberg says that in addition to the extra functions, the unit "has the one thing that most people working in relatively unknown voltage environments want. It's forgiving; it allows mistakes and won't blow up in your face." Specifically, the instrument will withstand 1,000 v dc or ac rms continuously applied, and the ohms function is protected electronically against 250 v dc or rms ac continuously applied, says Robert Sheinfein, vice president of sales.

Weighing just 3 pounds, including its field-installable batteries and carrying handle, the instrument is fully portable. The drop-in nickel-cadmium battery pack is a \$20 option that provides 8 hours of operation before requiring recharging by the built-in recharger.


The \$279 price covers the basic and extra functions, plus test leads, detachable line cord, spare fuse, instruction manuals, full test data, certificate of conformance, and one-year warranty. Options other than the drop-in battery pack include optically isolated binary-coded-decimal outputs and a high-efficiency extra-bright light-emitting-diode display for high ambient-light environments. Both the standard and extra-bright LEDs are 0.43 inch high.

Summing up, Goldberg says: "We've added a lot of functions at the expense of one digit, but we've found that people are looking for functions. We can't give the da accuracy commensurate with a 4½-digit instrument, but 3½-digit multimeters are the most widely selling ones today."

Delivery is from stock.

Data Precision Corp., Audubon Road, Wakefield, Mass. 01880. Phone Robert Sheinfein at (617) 246-1600 [339]

# THE LARGEST FAMILY OF MOS/LSI DATA COMMUNICATIONS CIRCUITS PROUDLY ANNOUNCES A NEW ADDITION:



# THE COM 1671 ASTRO

We've lead the way in MOS/LSI data communications circuits with proprietary products like our COM 5025 Multi-Protocol Synchronous Receiver/Transmitter and our COM 2017 and COM 2502 Universal Asynchronous Receiver/Transmitter plus others. Now we're second sourcing Western Digital's UC 1671 ASTRO with our new COM 1671.

It's a software responsive device capable of handling complex communications formats in a variety of systems applications.

Like our COM 5025, and our recently announced CRT 5027, the new COM 1671 ASTRO has high speed, and high density n-channel Coplamos® technology in a 40 lead ceramic DIP.

And it carries the Standard Microsystems Corp. name so you know you can count on it for maximum performance and reliability.

#### We make custom LSIs too.

SMC's custom circuit department has helped many medium-volume users with the design and production of custom devices. Applications personnel are available to discuss the tradeoffs involved in custom MOS/LSI design. The solution may include either standard or custom circuits or a combination of both.

For standard or custom LSI come to Standard Microsystems Corp. No one knows more about building data communications circuits than us.



PICTURED ABOVE: VIDEO TIMER/CONTROLLER CRT5027 UNIVERSAL SYNCHRONOUS RECEIVER/TRANSMITTER COM5025 & COM2601 BAUD RATE GENERATOR COM5026 & COM5046 DUAL BAUD RATE GENERATOR COM5036 & COM5016 UNIVERSAL ASYNCHRONOUS RECEIVER/TRANSMITTER COM6402, COM2017 & COM2502 ASYNCHRONOUS/SYNCHRONOUS RECEIVER/TRANSMITTER COM1671

# TERADIFIER LASER TRINGERS. ACUTABOVE THE REST.

If you make film resistors or hybrids, make Teradyne your source for laser trimmers. There are four good reasons why.

#### **EXPERIENCE**

In the past six years Teradyne has established a base of over 200 laser trimming systems. An investment of over \$25,000,000 by the hybrid industry.

That's a lot of experience. Experience you'll see reflected in the systems we build and the services we provide.

#### **TECHNOLOGY**

The series of technological advances that made Teradyne number one are a direct result of your increased requirements. The galvanometer beam positioner. The high-speed bridge. The step-and-repeat handler. Multiplexed trim and test stations. Combined, they give you the highest-throughput trimmers in the business.

#### COMMITMENT

In order to stay number one, we've tripled the size of our laser trimming development staff in just the past year. This makes it the strongest team in the industry. A new, higher-speed beam positioner is the first advance made by this expanded group. It won't be the last.

#### SUPPORT

Teradyne also offers you the most comprehensive after-sale support. Applications and service engineers in the U.S., Europe, and Japan are working to make your laser trimmers the most profitable in the world.

We provide regular software updates, too. Like our menu programming format. Its approach to the programming problem helps you get new parts into production fast.

In addition, we offer the industry's only 10-year circuit module warranty, worldwide parts stocking centers, and a 24-hour telephone troubleshooting service.

The fact is, no company has as many laser trimming resources as Teradyne. Nor can any company give you faster, more substantive support.

Before you invest in something as important as a laser trimmer, investigate the advantages of Teradyne.

For a more detailed account of what makes us a cut above the rest, write Teradyne, 183 Essex Street, Boston, Massachusetts, 02111.





# REpower we've made the we've made the most of it... you can, too!!


All wrapped up in a neat little package, our Model 510L is an ultra-wideband RF power amplifier whose wide range of frequency coverage and power output provide the user with the ultimate in flexibility and versatility in a laboratory instrument. Easily mated with any signal generator, this completely solid state unit amplifies AM, FM, SSB, TV, pulse and other complex modulations with a minimum of distortion.

Constant forward power is continuously available regardless of the output load impedance match making the 510L ideal for driving highly reactive loads.

Unconditional stability and instantaneous fail-safe provisions in the unit provide absolute protection from damage due to transients and overloads.

This outstanding unit covers the frequency range of 1.7 to 500 MHz with a linear power output of more than 9.5 watts and there is no tuning.

For further information or a demonstration, contact ENI, 3000 Winton Road South, Rochester, New York 14623. Call 716-473-6900 or TELEX 97-8283 E N I ROC Or, ENI Power Systems, Ltd., 23 Old Park Rd., Hitchin, Hertfordshire SG5 2JS England. Call Hitchin 51711. TELEX 825153 E N I HITCHIN.



#### **New products**

Microprocessors

# 4-bit slice acts as sequencer

40-pin device controls flow of instructions from stored microprogram

The first in an advanced generation of new 4-bit slice components in its AM2900 family will soon be available from Advanced Micro Devices. Designated the AM2910, the 40-pin device is a 12-bit-wide address sequencer and microprogram controller that is designed to perform the functions of three 4-bit-wide sequencers of the previous generation, the AM2911/12.

According to John Springer, the company's bipolar microprocessor marketing manager, the AM2910 is intended for controlling the sequence of execution of microinstructions stored in microprogram memory. Besides the capability of sequential access, it provides conditional branching to any microinstruction within its 4,096-microword range. A last-in, first-out stack provides microsubroutine return linkage and looping capability. There are five levels of nesting microroutines. Microinstruction loop count control is provided with a count capacity of 4,096.

The controller contains a fourinput multiplexer that is used to select the register/counter, direct input, microprogram counter, or stack as the source of the next microinstruction address. The register/counter consists of 12 D-type edge-triggered flip-flops with a common clock-enable. It contains a microprogram counter that is composed of a 12-bit incrementer followed by a 12-bit register.

Among the features of the AM2910, says Springer, are an internal loop counter with a presettable down counter for repeating instructions and counting loop-interactions and four address sources

from which the microprogram address can be selected: branch address bus, five-level push-pop stack, internal holding register, or microprogram counter. It also boasts outputenable controls for three branch address sources, with a built-in decoder function to enable external devices onto the branch address bus, eliminating an external decoder; positive edge-triggered registers that simplify timing problems and eliminate long set up times; and fast control from condition input, with delays from condition code input to address output of only 35 nanose-


The AM2910 provides 16 instructions that select the address of the next microinstruction to be executed. Four of them are unconditional—their effect depends only on the instruction. The rest have an effect, says Springer, that is controlled partly by an external data-dependent condition and partly by the contents of an internal register/counter.

Available in sample quantities now, the AM2910, hermetically packaged, is priced at \$25.95 each in 100-piece quantities.

Advanced Micro Devices Inc., 901 Thompson Place, Sunnyvale, Calif. 94086 [361]

# One-chip computer has 4-microsecond cycle time

Designed for use in household appliances, telecommunications equipment, automobiles, and other high-volume applications, the S2000



# **SABRE VII**

# makes no compromise with quality and performance... Why should you?

No other IRIG tape recorder/reproducer gives you all these capabilities. System prices from less than \$15,000.


- Two electrically switchable tape speed ranges from 120 to 1% ips or 60 to 15/16 ips
- Direct bandwidths to 2 MHz
- FM bandwidth from DC to 500 kHz
- 10½, 14 and 15-inch reels with 38.4 hours of record time
- IRIG PCM to 600 kb/s serial rate
- HDR to 4 Mb/s serial rate
- 7, 14 or 16 channel capacity
- Low flutter/TBE
- operation available

Now have the full-capability performance you need at the lowest price. All it takes is SABRE VII, the all-band portable recorder/reproducer that handles either 1/2-inch or 1-inch tape . . . records and reproduces Direct, FM, PCM and either serial or parallel high density PCM. Easily switches between IRIG, FM bands by means of a single switch. For even more versatility, you get two bidirectional speed ranges, plus automatically-switched reproduce electronics for up to 7 tape speeds. You get it all, and SABRE VII actually costs less than comparable systems.

Amazing? Yes, and because of the same superior engineering, SABRE VII also controls tape speed accuracy to within ±0.10% and extends tape and head life through enhanced tape handling. Options include FM calibrator, remote control, voice, IRIG tape servo, rack mount kit, shuttle, sequential record and/or reproduce and anti-vibration mounts. SABRE VII doesn't compromise with quality and performance. Why should you!

For complete details, write or call:

Sangamo Weston, Inc. Data Recorder Division P.O. Box 3347 Springfield, IL 62714 TEL: (217) 544-6411



#### **New products**

is a 4-bit microcomputer with a cycle time of 4 microseconds. Included on the chip are 1,024 bytes of read-only memory, 64 4-bit words of readwrite memory, input/output circuitry, and a clock oscillator. The unit's input sensing lines have TouchControl compatibility, which means that they can be easily interfaced to capacitive switch devices. A sevensegment display decoder and lightemitting-diode drivers are also included in the single-chip architecture. A version of the computer that will drive vacuum-fluorescent displays is also available.

The chip's firmware consists of 51 instruction codes, including skips similar to those in the DEC PDP-8 minicomputers instead of conditional branching.

American Microsystems Inc., 3800 Homestead Rd., Santa Clara, Calif. 95051. Phone Tom Edel at (408) 246-0330 [364]

# One-board computer is compatible with F8 systems

Capable of being used as a standalone board for low-volume production, as a low-cost development system, or for real-time emulation of pilot production and field testing, the OCM/1 is a one-card computer for use with F8-based systems. The computer comprises four major sections: processor, memory, input/output, and interrupt. The processor section consists of a 3850 central processing unit, a 3853 static memory interface (SMI), a clock generator, and reset circuitry. The memory section is capable of using several different types of memory chips. The board is supplied with a kilobyte of random-access memory and sockets for various read-only memories.

The I/O portion of the computer is made up of the 3850 and a 3851 program storage unit (PSU), each containing two 8-bit I/O ports. Sockets for additional interface circuitry are provided to allow a maximum of eight I/O ports. An additional port allows the unit to communicate with a teletypewriter.

The standard OCM/1 incorpo-

rates two interrupts and two timers—one in the PSU and one in the SMI. Two additional interrupts and timers may be added. The basic machine, in unit quantity, sells for \$295. It is available from stock.

Fairchild Camera and Instrument Corp., Instruments and Controls Division, 1725 Technology Dr., San Jose, Calif. 95110 [365]

## Z80-based computer works with 8080 support boards

The MM1-ZCPU microcomputer board is built around the Zilog Z-80 microprocessor yet is fully compatible with the MM1 family of support boards originally developed for use with computers built around the Intel 8080A. The new board has space for 4,096 bits of erasable readonly memory and 1,024 bits of readwrite memory. It operates at a clock rate of 2 MHz. Among the support boards available for it are a 16-k erasable PROM board, a 16-k dynamic random-access-memory board, a 4-k nonvolatile RAM board, a 4-k static RAM board, and six analog and digital input/output boards. The MM1-ZCPU sells for \$350 in single quantity and has a delivery time of 30 days.

Control Logic Inc., 9 Tech Circle, Natick, Mass. 01760. Phone (617) 655-1170 [363]

# Disk system for PACE unit speeds software development

A disk-operating system for PACE microprocessor development system substantially reduces the time required to assemble, edit, and execute programs. Designated the IPC-16P/840, the system comprises a dual floppy-disk drive in a standard enclosure, an interface circuit subsystem card, and a read-onlymemory card. The disk-operating system provides comprehensive filemanagement capability, support for assembly programs, editors, linking loaders, utility programs, and diagnostics. It may be installed on any IPC-16P PACE microprocessor devel-

# Monsanto

## Products Are Available from These Distributors:

AVNET ELECTRONICS
CESCO ELECTRONICS
DIPLOMAT/ALTALAND
ELMAR ELECTRONICS
HAMILTON/AVNET
HAMILTON ELECTRO SALES
HAMMOND ELECTRONICS, INC.
HARRISON EQUIPMENT CO.
KIERULFF ELECTRONICS
LIBERTY ELECTRONICS
R.A.E. ELECTRONICS
SCHWEBER ELECTRONICS
SEMICONDUCTOR SPECIALISTS
SHERIDAN SALES

For technical assistance contact our representative in your area:

A.P.J. Associates, Inc. Plymouth, MI. (313) 459-1200

Beacon Electronic Associates Huntsville, AL. (205) 881-5031 Ft. Lauderdale, FL. (305) 971-7320 Maitland, FL. (305) 647-3498 Atlanta, GA. (404) 351-3654 Charlotte, NC. (704) 525-7412 Oak Ridge, TN. (615) 482-2409 Falls Church, VA. (703) 534-7200

Bob Dean, Inc. Ithaca, NY. (607) 272-2187

CMS Marketing Oreland, PA. (215) 885-5106

Cantronics
Downsview, Ont. Canada. (416) 661-2494
Montreal, Que. Canada. (514) 341-5207

Comtronic Associates Melville, L.I., N.Y. (516) 249-0505

CPS, Inc. Orange, CT. (203) 795-3515

Datcom Waltham, MA. (617) 891-4600

Mel Foster & Assoc. Edina, MN. (612) 835-2252

Harvey King, Inc. San Diego, CA. (714) 566-5252

Ed Landa Company Los Angeles, CA. (213) 879-0770

Lorenz Sales Inc. Cedar Rapids, IA. (319) 393-6912

Midwest Marketing Associates Chagrin Falls, OH. (216) 247-6655 Dayton, OH. (513) 433-2511

Mycrosystems Marketing Dallas, TX. (214) 238-7157 Houston, TX. (713) 783-2900

Spectrum Associates Phoenix, AZ. (602) 997-6324

Straube Associates
Denver, CO. (303) 426-0890
Salt Lake City, UT. (801) 943-5650

Sumer, Inc.
Rolling Meadows, IL. (312) 394-4900
Milwaukee, WI. (414) 259-9060

Technical Representatives, Inc. Olathe, KS. (913) 782-1177 Hazelwood, MO. (314) 731-5200

Valentine-Schillinger Greenwood, IN. (317) 888-2260 South Bend, IN. (219) 291-6258

Waggoner-Ver Hill Associates Pittsburgh, PA. (412) 241-5202

Western Technical Sales Portland, OR. (503) 297-1711 Bellevue, WA. (206) 641-3900 No one has ever seen a lamp like this. It's our bright, new, revolutionary rectangular LED

#### OUR "LEGEND LAMP" PUTS LIGHT UP FRONT, WHERE YOU NEED IT.

The MV57124 rectangular LED from Monsanto gathers light from a high brightness chip and focuses it on a flat front surface. The shape of the lamp and the uniform illumination across a large emitting area (.15"x.25") makes the "legend lamp" an exciting, aesthetically pleasing element in your modern industrial panel design. It's available now in high brightness red and will soon be available in other colors.

#### STACKABLE: SIDE-BY-SIDE, OR END-TO-END.

The unique design of the MV57124 utilizes a special plastic to house the LED assembly, so that

no light is emitted from the sides or edges of the unit. All of the light is concentrated on the viewed surface. This means that lamps can be stacked, side-by-side in an X or Y direction, without light interference between units.

#### 4 MCD BRIGHT. UNIFORM.

The MV57124 "legend lamp" uses Monsanto's high efficiency red emitter. The carefully engineered package makes maximum use of that emitted light, minimizing unusable light. Light output is a very bright 4 millicandelas at

20 mA forward current. That's up to 3 times the output of other rectangular lamps. So you can use the MV57124 as a legend backlight, a panel indicator, or a bargraph meter.


### ANOTHER PERFORMANCE PRODUCT FROM MONSANTO.

This unique new product is a development from the technology and experience that is Monsanto. Our history as being one of the first suppliers of LED's has led to the features and characteristics of the "legend lamp."

#### FREE SAMPLE.

Write today, on your company letterhead, for a free sample. We'll also send you full specifications on our new MV57124.

Monsanto Commercial Products Co., Electronics Division, 3400 Hillview Ave., Palo Alto, CA 94304. Telephone: (415) 493-3300.



Monsanto: the science company.

#### **New products**




opment system with 12 kilowords of read-write memory and a heavy-duty power supply. It sells for \$4,500 including the dual-floppy-disk subsystem, a disk interface card, a prom card, and cables. The unit has a delivery time of 30 days.

National Semiconductor Corp., Microcomputer Systems Group, 2900 Semiconductor Dr., Santa Clara, Calif. 95051 [367]

# C-MOS memory module stores 1,024 12-bit words

The latest addition to the LP-12 family of low-power microcomputer boards is a read-write memory module with a capacity of 1,024 12-bit words. Built using complementary-metal-oxide-semiconductor random-access memories, the LP-12D can be strapped for address block recognition and RAM-select signal generation, enabling it to simulate the 6312



read-only memory for prototyping purposes. Other features of the LP-12D include write-protect capability and optional on-board batteries for nonvolatility. In unit quantity, the memory module sells for \$280 without the battery and \$310 with it. Delivery time is four weeks.

Cybertek Inc., 222 150th Ave., Madeira Beach, Fla. 33708 [366]

# Database-management system runs on microcomputers

Micro-Seed, a data-base-management system for the Xitan microcomputer, will support both hierarchical and network data structures. It includes a program that prepares disks for data-base loading.

Technical Design Labs, Research Park, Bldg. H, 1101 State Rd., Princeton, N. J. 08540 [368]

# From our shelf to yours in two weeks.

We can give you immediate delivery on nearly 300 styles and configurations of high carbon steel and aluminum slides. The most popular styles are right on the shelf, ready for immediate delivery. No delays. No excuses.

These narrow profile slides give you maximum room for your slide mounted chassis, so you don't have to compromise your design to get your equipment into the rack. Zero slides range from 3/8" to 7/16" in cross section thickness, permitting full utilization of an EIA standard 17" chassis in a standard 19" rack. Load ratings range from 80 to 275 pounds per pair.

Zero slides are also compatible with all standard enclosures and most custom enclosures. Call today for immediate action. Or write for our new slide catalog.



ZERO
We make you look good.

Zero Corporation · Burbank, CA 213/846-4191 · Monson, MA 413/267-5561

# For lower cost insertion of any components like these ... ask Universal.

Only Universal can supply you with machines for testing, sequencing and inserting axial lead components, plus DIPs, transistors, wire wrap pins and literally any type of electronic hardware. We are the innovators responsible for a majority of the semi-automatic and mechanized equipment used throughout the world for conditioning and assembling components into circuit boards.

Now as many as eight of these machines can be programmed and operated by our new Satellite Controller System. That's up to 144,000 insertions an hour, with each machine handling totally different boards for both short and long runs.


No other system offers anything like the Satellite Controller System's range of management data, on-line diagnostics and program editing. All programs are stored for instant access on a dual drive floppy disk memory, and entered thru a high speed tape reader/punch. Data for continuous production control and executive monitoring can even be called up on remote CRT displays.


Find out what Universal's machines for lower cost insertion . . . and the innovative Satellite Controller System . . . can do for your company's production/profit ratio. Contact your Universal sales office or send for a brochure today.



Universal Instruments Corporation Kirkwood Industrial Park Box 825, Binghamton, New York 13902 Tel: 607/772/7522 TWX: 510/252/1990

Circle 153 on reader service card





# Our incredible shrinking inductors.



You will find one of our tiny space-age wonders inside today's electronic watches and lightweight telephone headsets among others. But you'd have to look closely since it's only .075" by .170". The Cambion inductor line stretches from the minute to standard ceramic coils to completely electromagnetically and electrostatically shielded units. Our catalog is bulging with designs that should induce you. Write to: Cambridge Thermionic Corporation, 445 Concord Avenue, Cambridge, MA 02138. Phone: 617-491-5400. In California: 2733 Pacific Coast Hgwy., Torrance, CA 90505. Phone: 213-326-7822.

Standardize on

CAMBION

The Guaranteed Electronic Components

#### **New products**

Subassemblies

# Smart display offers low drain

Microprocessor-run module for computer systems includes character generator


Vacuum-fluorescent technology appears in a series of smart micro-processor-controlled displays, designed for use with any microcomputer-based system. Digital Electronics Corp. has three models in its DE/200 series of intelligent, random-access displays.


These alphanumeric, single-line display modules offer low power consumption and 14-segment character design that permits clear and readable messages, even under high ambient light conditions. The natural blue-green color of the characters can be filtered to blue, green, or yellow by use of acetate or acrylic filters.

The microdisplay models, DE/210 (10-character positions), DE/220 (20-character positions), and DE/232 (32-character positions) all include an on-board microprocessor that incorporates a character generator, display buffer, and refresh logic. The display incorporates both parallel and serial interfaces, offering universal compatibility with busoriented microprocessor systems and with serial data devices.

Since all character positions are uniquely addressable, the display can be selectively updated in accordance with the host system's requirements. Display changes are instantaneous, with no line-shift effect. Full ASCII character sets are augmented by period-insertion capability (period and comma on the DE/210 and DE/220) in the same character space.

Display evaluation kits (shipped with each initial display module ordered) include a data cable, power connector, and complete documentation. Mounting kits complete with bezel, filter, and hardware are optional. Power supplies are available with either +5 volts ac or





# We don't build a connector for everybody.

#### We build everybody a connector.

More often than not, your problem can't be solved with a substandard connector.

That's why our first concern is quality. You present us with a problem and we're flexible enough to give you back an approved connector that's designed or modified for your application.

We make connectors for PC card to chassis or mother board connections. We make connectors for PC board input-output, cable to panel and cable to chassis connections. We make connectors for inter-

equipment connections like cable to panel, cable to cable and drawer to cabinet. And we make every component that goes into them

It simply comes down to this. You either use a connector that's been stamped out on an assembly line or a connector that's carefully and completely built specifically for your job.

That decision is easy. And that's why we're in the connector business.
If you want the best, call AirBorn.

AirBorn, Inc.

#### **New products**

110/220 v ac input, Digital says.

Interfacing to a computer-based system is simple, requiring a minimum of control and "hand-shaking" in a bus-oriented system. Each microdisplay represents as few as one output address to the host system.

As parallel output devices, each microdisplay is latched, requiring

little, if any, additional circuitry to be connected to the data bus of most 8-bit microcomputer systems. In a bidirectional bus scheme, each microdisplay may be used to return status or data to the host system upon request, as well as receive data codes and control codes.

In serial operation, each microdisplay is an output-only device. All data and control characters are applied to the display in a 10-bit format, having 1 start bit followed by 8 data bits and 1 stop bit.

Each of the DE/200 microdisplays has exactly the same interface configuration, permitting interchangeability of displays with no changes in the interface. In quantities of 100 and up, the displays are priced at \$99, \$140, and \$199 each for the DE/210, DE/220 and DE/232, respectively.

Digital Electronics Corp., 415 Peterson St., Oakland, Calif. 94601 [381]

# Hybrid clock oscillators occupy less than 0.04 in<sup>3</sup>

A line of clock oscillators that operate at frequencies from 1 hertz to 30 megahertz is available in flat packs ranging in size from 0.375 by 0.500 by 0.110 inch up to 0.625 by



0.625 by 0.100 in. The oscillators are thus well suited for use in high-density circuitry such as that built on multilayer boards. In hundreds, the clock oscillators sell for \$38 each. They have a delivery time of six to eight weeks.

Q-Tech Corp., 2201 Carmelina Ave., Los Angeles, Calif. 90064. Phone (213) 820-4921 [387]

# Fast 8-bit a-d converter has three-state outputs

Designed for interfacing with 8-bit microprocessors, the MN5150 is a complete 8-bit analog-to-digital converter with three-state outputs. The unit contains a built-in reference

# Beauty comes in different shapes and sizes.



These smart looking Optima Accent Cases bring you a wide choice of standard sizes, colors and finishes. But in case you want to bring the world something different, you're not boxed in. We'll cut these special beauties to your own specs. With solid walnut or metal sides, sloped or vertical front panels or whatever. We ship knockeddown to save you money.

Send for our catalog. For freedom of design, we give you freedom of choice.

We make you look better

# OPTIMA® Scientific-Atlanta

2166 Mountain Industrial Blvd.. Tucker, Ga. 30084 • Tel: (404) 939-6340 Europe: McKettrick-Agnew, Macmerry, East Lothian, Scotland, EH33 1EX • Telex: 72623.

Citals 156 on reader convice pard

# The Complete Solution to your F3870 and F8 Design-In Problems

#### The Formulator Development System



Formulator family is designed to allow easy, efficient software development and real time hardware simulation of F8 or F3870 based systems. It is supported by a complete line of functional modules including memory, I/O and simulation cards that plug directly into

the Formulator cardframe.

The Formulator can, itself, be used as the system breadboard. It provides microprocessor hardware, plus card slots for breadboarding your system. Thus the entire system may reside within the Formulator or in a combination of external and internal configurations.

#### **In-Circuit Emulation**

To develop, test and debug F8 and F3870 based products, Fairchild offers simulation options that extend the functional features of the micro-



processor from the Formulator to the 40-pin socket on your breadboard. This allows complete ROM firmware development, real-time symbolic debugging of your breadboard and freezing of ROM codes during the breadboard stage.

#### PROM Prototypes

The 3870 Emulator is a PROM-based substitute for the F3870 microprocessor. The Emulator measures 5" x 7" and contains two 2708 or 2716 EROMs in place of the F3870 so ROM codes can be verified and easily changed



Emulator plugs directly into the F3870 40-pin socket in the production prototype via a short cable.

#### Powerful and Complete Software

The software consists of an operating system, utility programs and diagnostic routines; a monitor, text editor, assembler and debug package. It includes linking loader and relocating assembler and will operate in interactive or batch mode. The result is an easy to use, reliable, fast and extremely efficient capability for microprocessor based system development.

The Formulator-Floppy Disk Marriage

An inexpensive plug-in module interfaces the Formulator with up to four plug-compatible ICOM Floppy Disc Drives, providing over one megabyte of storage. If you prefer other Floppies an application note provides the information necessary to modify Drivers for your system.

#### And That Isn't All

There is a lot more to Fairchild's line of design aids: PCB modules, memory options, PROM programmer, application and peripheral options, design kits, one card microcomputers, software, user's guides and training courses.



extensive F8 and F3870 support that you can get from Fairchild. Just ask us about it.

Fairchild Instrumentation and Controls, a division of Fairchild Camera and Instrument Corp., 1725 Technology Drive, San Jose, California 95110 (408) 998-0123, Ext. 220.

FAIRCHILD

# When the heat's on for Regal, Plenco phenolics help deal with it.

Example: this giant-capacity Poly Pop<sup>TM</sup> "Buttercup" Automatic Electric Corn Popper. A product of Regal Ware, Inc., Kewaskum, WI, the popper's base and the terminal board and pin assembly are both molded of Plenco heat-resistant phenolic compounds.

Here's what the molder of the terminal board, Boerger Molding & Manufacturing Co., Racine, WI, has to say about the use of our Plenco 349:

"Along with good heat resistance your 349 compound provides us with ease of moldability, excellent finish, and material consistency plus the ability to injectionmold the part . . . a winning combination for processing quality molded parts at a cost savings."



More than likely Plenco can provide a thermoset compound to suit your particular application or molding problem. Call us and we'll try to help.


Just dial (414) 458-2121.



PLASTICS ENGINEERING COMPANY Sheboygan, WI 53081

Through Plenco research...a wide range of ready-made or custom-formulated phenolic, melamine-phenolic and alkyd thermoset molding compounds, and industrial resins.

#### **New products**



source and features a conversion time of 2.5 microseconds. It is housed in a 24-pin hermetic dual inline package for easy mounting on the same board as its controlling microprocessor.

Seven user-selectable input ranges are provided:  $\pm 2.5$ ,  $\pm 5.0$ ,  $\pm 10.0$ , 0 to 5, 0 to 10, 0 to -5, and 0 to -10 v. Regardless of which range is selected (by the appropriate strapping of various pins), the converter is guaranteed to have no missing codes over its operating temperature range. For the standard \$75 MN5150, this range is from 0°C to 70°C. For the MN5150H, which costs \$149, the range is -55°C to 125°C. Delivery of all units is from stock to four weeks.

Micro Networks Corp., 324 Clark St., Worcester, Mass. 01606. Phone John F. Munn at (617) 852-5400 [383]

# 12-bit d-a converter runs off ± 12-V supplies

The DAC80Z digital-to-analog converter is similar to other units in the DAC80 family, except that it allows operation from ±12-volt supplies, the company says. The other models





# DOES DATA I/O KEEP

We allow you complete design flexibility. Data I/O programmers are capable of programming all of the more than 200 PROMs currently available.

You'll always be programming to PROM manufacturers' approved specifications.

Data I/O Program Card Sets are tested and certified by the PROM manufacturers themselves before we approve them for manufacturing and distribution to our customers.

If manufacturers change specifications, we

keep our customers updated on how to make proper adjustments to the card sets.

To help you reduce programming costs and reach maximum yields and reliability, we also offer a universal calibrator so that you can conduct your own periodic calibration tests.

We're there when you need us. Data I/O is a worldwide organization. Our field sales and service offices are staffed by Data I/O personnel. Our customers have direct access to us through people who understand the products.

We'd like to tell you more. This fact filled tabloid gives you valuable information about PROM programming technology. To get your copy, circle reader service number or contact Data I/O Corporation, P.O. Box 308, Issaguah, WA 98027. Phone 206/455-3990.



THE PROM PROGRAMMER PEOPLE.



#### 55% efficiency in a 25 watt DC to DC Converter

Why pay for useless heat when you want power? That's the philosophy behind the new high efficiency 1200 Series 25 volt regulated converter from Tecnetics.

With efficiency as high as 55% at full load under normal conditions, an integral heat sink, improved circuitry and a black anodized aluminum case, this converter operates within a range of -20°C ambient to +100°C case temperature.

Available with a single output, this series features full input-output isolation to 500VDC allowing the user to change polarity and prevent ground loops. Compact size and sturdy barrier strip terminals make this the perfect converter for a wide

variety of military, industrial, aerospace and telecommunication applications.

For more information on the 1200, and hundreds of other power supplies, write for our 26 page catalog.

#### SPECIFICATIONS: 1200 Series 25 watt DC to DC converter

Inputs: 12 ±2VDC to 48 ±6VDC Outputs: 12, 24, 28 and 48VDC Dimensions: 5" x 4.1" x 1.25" (typ)

Weight: 16 oz.

Price: Single Output - \$198.00

**TECNETICS** The Power Conversion Specialists P.O. Box 910, 1625 Range Street, Boulder, Colorado 80302 (303) 442-3837 TWX 910-940-3246

Circle 160 on reader service card

# If this magazine is worth your time, it's worth 54¢.

Drop off the routing list. Avoid the Perils of Passalong. Get your own fresh, unclipped copy mailed to your home or office. \$14 (54¢ per issue) for a one-year U.S. subscription. (\$16 in Canada.) Turn to the subscription card in the back of the magazine. If somebody beat you to it, write: Electronics, P.O. Box 430, Hightstown, N.J. 08520.

#### **New products**

require ±15 v. The new 12-bit converter will settle to within 0.01% of final value in 300 nanoseconds (in its current-output mode) and meets all its specifications with power-supply voltages from ±11.4 to ±16.0 v. Housed in a ceramic dual in-line package, the DAC80Z sells for \$19.50. Delivery of the converter is from stock.


Burr-Brown Research Corp., P. O. Box 11400, Tucson, Ariz. 85734. Phone Joe Santen at (602) 294-1431 [385]

## 20-bit synchro-to-digital converter fits in one module

A two-speed, 20-bit synchro-to-digital converter with a maximum error of 0.001° at a speed ratio of 36:1 occupies only one standard module measuring 2.6 by 3.6 by 0.8 inches. Competitive units require two or even three modules to do the same job, according to the manufacturer. The model 2SD412 requires two power supplies—5 v and 15 v. Total power consumption is 3.5 watts for the version with standard transistor-transistor-logic outputs and 2 w for the unit with low-power TTL outputs.

The 2SD412 accepts pairs of either three-wire synchro or four-wire resolver signals plus a reference input. The reference frequency is 400 hertz; for 60-Hz operation, a separate transformer module is available. Standard inputs are 11.8, 26, and 90 v root mean square, and the reference can be either 26 or 115 v rms.

The standard unit sells for \$1,195





#### It's amazing how an easy mind cements relationships.

We're the easy mind people. TRW Capacitors.

We can solve your problems connected with reliability in ultra-miniature capacitors. Our X463UW metallized polycarbonates are designed to do just that.

The X463UW gives you "Space Age" performance in circuits demanding the smallest possible size. Capacitances range from .001 to 10 mfd, at 50,100, 200 and 400 vdc—with less than 1.5% capacitance change from —55°C through 125°C. IR is 60,000 megohm x mfd minimum at 25°C. DF is less than 0.3% at 25°C and 1 KHz. And stability? In humidity and shelf life tests the stability of the X463UW is actually two to three times better than polysulfone.

You get all that because we've applied the latest in component technology to combine the improved electrical performance of polycarbonate with dramatic size and weight reductions made possible by the use of our exceptionally reliable metallized dielectric.

We also put the same kind of effort into our engineering services and our field support. Try us. We can help reduce the tension. Give us a call, or write: TRW capacitors. An

Electronic Components Division of TRW, Inc., 301 West "O" St., Ogallala, Nebraska 69153. Tel: (308) 284-3611.







#### **New products**

in small quantities and is available from stock to 45 days. Special units, with extended temperature range and high-reliability components, are also available. A 16-bit converter is offered for applications that do not need the resolution of the 20-bit device.

Natel Engineering Co., 8954 Mason Ave., Canoga Park, Calif. 91306. Phone (213) 882-9620 [386]

# Gould introduces 18 switching power supplies

Gould Inc. is introducing 18 switching power supplies, including 12 5-volt models designed for the telecommunications and data-processing areas. The SMG series includes units with power ratings from 8 to 2,250 watts. In addition to the 5-v models, which are available with current ratings from 1.6 to 450 amperes, there are three 12-v supplies and three 24-v units.

Gould Inc., Electronic Components Division, 4601 North Arden Dr., El Monte, Calif. 91731. Phone (213) 442-7755 [384]

#### **TOPICS**

#### **Subassemblies**

The Singer Co's. Kearfott Division, Little Falls, N. J., has improved its Trigac VI C70 4773 digital-to-synchro/resolver converters in several ways. Among the improvements are protection from static electricity and transformation ratio as a function of angle constant to within 0.25%.

...Burr-Brown Research Corp., Tucson, Ariz., is now selling its popular ADC82 8-bit analog-to-digital converter in a Q-screened version. Q-screening is Burr-Brown's stressing and testing sequence, which is appropriate when extremely high product reliability is needed. ...Micro Networks Corp., Worcester, Mass., has slashed the prices of its MN2000 series voltage references by 20 to 36%. Prices now go as low as \$28 each in hundreds.

# New Giant in optoelectronics

Affiliation with Siemens gives Litronix all you could want from an optoelectronics source.

#### On OCTOBER 18,

**19775** Siemens A.G., an \$8 billion per year firm, acquired an 80% interest in Litronix through a wholly-owned subsidiary — bringing financial stability, new technologies and dozens of new products to the American firm.

Foremost among the new technologies and products are LCD displays, high-power infra-red emitters, green, yellow and red GaP LEDs, and a full line of photo detectors. Nearly all types of optoelectronic products will now be available from Litronix.

Litronix will operate under its own name and market all products in the U.S. and abroad through the same distributors and sales representatives as before.

# All resources devoted to components

Litronix ceased manufacture of calculators and digital watches in January 1977. All the design and production capability once devoted to these products is now directed entirely to components. The component portion of the company's business has always been highly successful. Now, operating from a strong financial position, Litronix will resume its place as

the leading source of advanced, cost-effective optoelectronic components.

# New, advanced products coming fast

Already in 1977 Litronix has developed 21 new products. With the recent affiliation, new product development is being further accelerated. The company's line of displays, lamps and other opto devices is being broadened and upgraded. Special emphasis is being placed on "intelligent" displays and indicators — devices which incorporate a display and integrated logic in the same package.

The recently introduced DL-1416 alphanumeric display, which interfaces exactly like a RAM, is an apt example. Such devices eliminate need for much associated interface and logic circuitry — simplifying design and producing a sizable net saving in the production cost of customers' products. Litronix is the uncontestable leader in this promising extension of optoelectronic integration.

When you have need for virtually anything in optoelectronics, contact Litronix at 19000 Homestead Road, Cupertino, California 95014. Phone (408) 257-7910.



# **The Threat**

Japanese trade and technology

# **The Opportunity**

Today's microprocessor explosion

# **The Conference**

Learn how to cope with the threat and make the most of the opportunity.

# 1977 Electronics Conference

December 7-8 Washington D.C.

Send in the registration form today



# How to cope with the Japanese trade and technology threat.

The gathering wave of Japanese technology: What will the impact be? Japan's share of the semiconductor market is still small and its share of the computer market is even smaller. But the Japanese have set their sights on these targets and their progress in the past couple of years has been startling. Wilfred J. Corrigan, Chairman and President, Fairchild Camera and Instrument Corp. Other speakers to be announced.

What must American companies do to keep their technological edge? In the past the U.S. electronics industries have been the world's unquestioned technological leaders. A serious challenge is developing now in semiconductors, computers, fiber optics, and other areas. In the past couple of years, Japanese research and development programs have begun to close the gap, and it is the Japanese government that is financing much of the R & D. J. Fred Bucy, President, Texas Instruments Incorporated.

The Labor Department's Response to the Japanese Challenge: Greater Japanese penetration in the market means fewer jobs for U.S. workers. Deputy Under Secretary of Labor for International Affairs will give the Labor Department's plans for action. *Howard D. Samuel*, Deputy Under Secretary for International Affairs, U.S. Department of Labor, Washington, D.C.

How to succeed in business with the Japanese: Experts will outline some of the different ways of doing business with the Japanese, listing the advantages and potential pitfalls of each. Bernard V. Vonderschmitt, Vice President and General Manager, Solid State Division, RCA Corporation. Terry Wong, Director, Business Development, Microelectronic Devices, Rockwell International Corporation.

How American electronic companies can win the battle for foreign markets: Some portions of the Japanese marketing effort—financing terms, for example—are tough to counter, but other tools are available to U.S. companies. *Richard Hodgson*, Senior Vice President, International Telephone and Telegraph Corporation.

Japan versus the U.S.: The government response: Richard Heimlich will discuss the Carter Administration's response to the question of Japanese competition and describe what steps the Office of Special Trade Negotiations is taking. *Richard W. Heimlich*, Assistant Special Trade Representative for Industrial Trade Policy, Office of the Representative for Trade Negotiations, Washington, D.C.

How can domestic electronics firms respond to the Japanese marketing threat in the U.S.? Leading experts from the U.S. industries will give their insights into steps U.S. firms can take to cope with the Japanese challenge. L. J. Sevin, Chairman of the Board, Mostek Corporation.

# 2 The potential of microprocessors: What is going to happen?

The outlook in microprocessors: Where are they going next? Microprocessor development is far from complete. One of the leading microprocessor experts will tell you how he sees microprocessors developing. Leslie L. Vadasz, Vice President and Assistant General Manager, Microcomputer Division, Intel Corporation.

The microprocessor universe: What's out there? What are the advantages of choosing a one-chip microprocessor? What are the advantages and disadvantages of 8-bit and 16-bit systems? What are the cost-performance tradeoffs of chips versus boards? Colin Crook, Group Opera-

tions Manager, Microproducts, Semiconductor Group, Motorola, Inc. Andrew C. Knowles, Vice President/Group Manager, Digital Equipment Corporation. Malcolm B. Northrup, Vice President, Microelectronic Devices, Electronic Devices Division, Rockwell International Corporation. James Van Tassel, Manager, MOS Microprocessor, Texas Instruments Incorporated.

**How to get started in microprocessors:** What can a microprocessor do for your company? What will be the likely effect of microprocessors on your industry? *Eric Garen*, Vice President, Integrated Computer Systems.

## 3 The economy and the markets: Where are they going?

Electronics markets in the coming year: A preview. Electronics publisher Dan McMillan and Executive Editor Samuel Weber will give a special preview of the annual Electronics market forecast, looking at worldwide market prospects. Dan McMillan, Publisher, Electronics. Samuel Weber, Executive Editor, Electronics.

Where is the economy going and what does it mean for you? Will the economy lose steam by mid-1978? What does future economic growth rate mean for the inventory levels electronics firms should maintain? If capital spending takes off, what should that mean for your business? Douglas Greenwald, Vice President—Economics, McGraw-Hill Publications Company.

			77 • New York, N.Y. • (212) 997-4930 ges, sponsored by <b>Electronics.</b>	
Name			Check one:	
Ttame			☐ Payment enclosed COM	
Company	Title		☐ Please bill me directly	
			☐ Please bill company	
Street			Hotel reservations: The Shorehan	
		7:-	Hotel is holding a block of rooms for	
City	State	ZIP	this conference. For reservations, con tact the Shoreham directly. Be sure to	
Business Phone			identify the title of the conference.	
			Cancellation policy: No refunds will be mad seven days prior to the Conference. You may	
Applicant's signature	Date		if you wish, send a substitute.	



#### **New products**

Industrial

# 10-channel RTD scanner sells for \$595

Getting temperature data from an array of resistance temperature detectors into a computer is not as simple as it might at first appear. First the RTDs must be excited, then their outputs must be amplified and linearized, and finally they must be converted to digital form and fed into the computer. Also, unless users want to use one computer per RTD, some form of multiplexing must be used at some stage or other in the proceedings.

The model SL115 RTD scanner is designed to perform all of the analog functions mentioned above, with a few extras thrown in for good measure. It will scan up to 10 detectors, thus performing the multiplexing function. It checks all of them for continuity and warns if a line is broken. It excites the devices, compensates for lead resistance, linearizes and amplifies the outputs, and


provides filtering to reduce noise. All this it does for a 10-piece price of \$595, or less than \$60 per channel.

Other key features of the SL115 are output sensitivities adjustable from 1 mv/°C to 100 mv/°C, individual zero-trim potentiometers for each channel, compatibility with transistor-transistor-logic voltage levels, and scan rates up to 20 channels per second. The board can accommodate two-, three-, and four-wire hookups while providing active common-mode-noise rejection. It plugs into a standard 6.25-inch card slot on 1-in, centers.


San Diego Instrument Laboratory, 7969 Engineer Rd., San Diego, Calif. 92111. Phone (714) 292-0646 [371]

# Matched thermistors work well in gas chromatographs

Suitable for use in gas-chromatographic equipment and other thermal-conductivity instrumentation, a series of matched thermistors is designed to operate in the self-heat mode. Typical units in the series are the G112, G126, and G128, with



# iCOM's Intelligent Floppy."



Controller/Formatter built-in. Packaging problems designed out.

When designing a floppy disk into a compact microcomputer-based system, engineers have been plagued with the problem of where to mount the controller/formatter cards and associated cables.

Our new FD5200 Intelligent Floppy™ solves this packaging dilemma by mounting all circuitry, including the single chip LSI controller/formatter, as an integral part of the disk drive chassis. A neat idea!

The 8 bit bi-directional bus makes it simple to integrate the iCOM® FD5200 into any system. Accrued benefits include: reduced hardware costs, smaller size, shorter assembly time, easier software development, improved reliability and lower maintenance. A mighty impressive list!

#### Compatibility to IBM 3740 Format... and Others

The special LSI controller/formatter chip provides the complex logic needed to write data on the diskette in IBM 3740 format — or other user selected formats as well. Another big plus is a phase-locked-loop for data and clock bit separation, and address word detection, which maximizes data reliability.

#### Pertec Makes the Driving Easy...

Since a floppy disk drive system is only as good as the mechanics, we use our field proven Pertec drive with three stepper-track head positioning for better accuracy and the unique head retract system for longer media life.

#### Why iCOM®?

iCOM, part of Pertec Computer Corporation, is one of the world's largest manufacturers of Microperipherals. Thousands of our floppy disk systems are operating reliably in the field. And many major computer manufacturers have incorporated iCOM floppies into their systems. Which means we deliver—and will be around to give you service whenever and wherever you may need it.

#### Speaking of Delivery...and Price

Our new FD5200 Intelligent Floppy™ is available now at a unit price of just \$795. Naturally, OEM discounts are available.

So phone us today. Or send for our brochure.

# **ICOM MICROPERIPHERALS**

Products of Pertec Computer Corporation


Microsystems Division

6741 Variel Ave., Canoga Park, CA 91303 U.S.A. Tel: (213) 348-1391 TWX: 910-494-2788


#### **VECTORBORD® TENTH/TENTH HOLES MOUNT:**

DIPS, SIPS, KLIPS, CHIPS PINS, POSTS, POTS, PADS RCs, ICs, PCs, SCs

Save Work — Time — Money



#### 8800V MICROPROCESSOR PLUGBORD



(Component Side with Added Sockets)

Has 100 contacts on .125" centers, is 10" wide by 5.313" high. Has heavy tinned back-to-back buses, overall 0.1" spaced 0.042" hole pattern. Socketed models available.

#### WIDE SELECTION OF SIZES AND MATERIALS

MICRO-VECTORBORD® "P" – 0.042" holes match DIP leads. Epoxy glass, or glass composite, paper, copper clad. Also 1/64" to 1/16" thick and 10" max. width.

VECTORBORD "H" — For larger terminals, leads. Available in epoxy glass sheets 4.8" to 8.5" wide and 8.5" to 17" long. 1/32" and 1/16" thick.

TERMINALS — Complete selection of wire wrappable and solderable push-in terminals for 0.042" and 0.062" dia. holes — plus wiring tools available.

PLUGBORDS — For solder or wrap wire construction 2.73" to 10" wide and 4.5" to 9,6" long. With holes .1"x .1", .1"x .2", .2"x .2", or loaded with IC sockets.

Vector

Send for complete literature

#### ELECTRONIC COMPANY, INC.


12460 Gladstone Ave., Sylmar CA 91342 (213) 365-9661 — TWX (910) 496-1539



Circle 168 on reader service card



#### **New products**



resistance values at 25°C of 8,000, 2,000, and 100,000 ohms, respectively. The thermistor beads are mounted on hermetic stems and are available with standard or custom housings.

Fenwal Electronics, 63 Fountain St., Framingham, Mass. 01701. Phone Nicholas Spiro at (617) 872-8841 [373]

# Sealed load cell operates in tension and compression


A sealed load cell in the shape of an S beam is available in models that can handle both tensile and compressive loads from  $\pm 100$  to  $\pm 1,000$  pounds full scale. Maximum nonlinearity is 0.05% of full scale, and unidirectional hysteresis is 0.03% of full scale. Zero balance is within 1% of full scale, and the maximum temperature effect on the zero balance is 0.0008% of full scale per  $^{\circ}$ F. Because they are sealed, units in the SSB301 family are unaffected by humidity, sand, or dust.

Celesco Transducer Products Inc., 7800 Deering Ave., Canoga Park, Calif. 91304. Phone Philip Gindes at (213) 884-6860 [375]

## Pressure transducer has sensitivity of 25 mV/psi

EPG-400 series low-range pressure transducers are high-sensitivity devices that provide outputs as high as 25 millivolts per pound per square inch. Available with full-scale ranges from 2 to 50 psi, the transducers are hermetically sealed and are constructed of stainless steel. They can

# How fast can you measure rise time, fall time and pulse width?





# Your way.

(About 5 minutes.)

- 1. Connect signal to scope.
- 2. Adjust trace intensity.
- 3. Adjust focus. 4. Select VOLTS/DIV range.
- 5. Select TIME/DIV
- range. 6. Adjust vertical gain to fill screen for location of 10% & 90%

points. 7. Locate 10%

point. 8. Locate 90%

point. 9. Determine horizontal displacement

between 10% & 90% points.

10. Multiply displacement by horizontal scale factor.

That's RISE TIME. Only 9 more steps and you've got PULSE WIDTH and FALL TIME.



# Our way.

(About 5 seconds.)

- 1. Connect signal.
- 2. Push button for RISE TIME. 3. Push button for PULSE

WIDTH. 4. Push ~ button for FALL TIME.

The rest is automatic.

#### Your move.

Give us a call and we'll tell you how the Dana 9000 Microprocessing Timer/Counter can solve your measurement problem the easy way.



Others measure by us.

Dana Laboratories, Inc., 2401 Campus Drive, Irvine, CA 92715 Phone: 714/833-1234

> Circle 264 for Product Demonstration Circle 169 for Literature Only


### MCC builds custom ICs using I<sup>2</sup>L to provide Consumer Product Prices

With I<sup>2</sup>L designs both linear and digital functions can be combined in a single chip. This means fewer external components, lower costs and improved reliability. Also, they permit interface power output capability not available with CMOS. Micro Components Corporation is ready to discuss your requirements for custom ICs demanding high performance and consumer product pricing.

Call us at: (401) 463-6000

Successfully being used in:

- Peripheral Microprocessor ICs
- Electronics in Cameras
- Electronic Photo-Flash
- Smoke Detectors
- Ground Fault Interrupters
- Motor Speed Control
- Mobile Communications
- Dynamic Microphones
- Toys & Games
- Automotive Systems
- Opto-Electronic Interface
- Dust & Particle Detection
- Security & Intrusion Alarm Systems
- Electromagnetics
- Timers for Appliances




#### MICRO COMPONENTS CORPORATION

99 Bald Hill Road • Cranston, R.I. 02920

Circle 170 on reader service card

#### From Electronics Magazine Book Series. Zero-risk trial offer. **Electronics Book Series Applyina** P.O. Box 669, Hightstown, N.J. 08520 Microprocessors Send me copies of "Applying Micro-2nd and 3rd generation processors" at \$9.95 per copy. technology. 26 detailed Discounts of 40% on orders of 10 or more copies. applications from I must be fully satisfied or you will refund data networks full payment if the book is returned after tento video games. \$9.95 day trial examination. ☐ Bill firm ☐ Bill me □ Payment enclosed Name Charge to my credit card: ☐ American Express ☐ Diners Club☐ BankAmericard ☐ Master Charge Company Street Acc't No City State Zip Date exp. On Master Charge only, Signature first numbers above name.

#### **New products**



therefore be used in some corrosive media.

The standard units are thermally compensated over the range of  $-40^{\circ}$ C to  $121^{\circ}$ C and have nominal resonant frequencies of 10 kilohertz and above. Units with accuracies to within 0.25% and 0.50% of full scale are available. In small quantities, EPG-400 devices sell for \$395 each. Availability is from stock to four weeks.

Entran Devices Inc., 145 Paterson Ave., Little Falls, N. J. 07424. Phone (201) 785-4060 [374]

# Bidirectional counter runs at 60,000 counts/minute

The model 7903 Countroller is a solid-state, bidirectional, predetermining counter that can handle rates up to 60,000 counts per minute. Fast, automatic reset is a standard feature, making the counter suitable for the control of machinery with fast recycle operations. Models with four or five digits are available. They use light-emitting-diode readouts 0.375 inch high for easy readability





Under the cover, we kept hardware and moving parts to a minimum for maximum reliability. Solidstate circuitry and only five modular componentsplus a built-in test capability-mean service is not


multiple copies.

unsurpassed price/performance value. Plus it's compatible with systems incorporating model 33 terminals.

The Teletype model 43. No TELETYP matter how you look at it, nothing even comes close.



## Testing low ESR Capacitors at 10 kHz/20 kHz



### assures low"switching"power.

Due to its remarkable versatility, ESI's Model 296 Automatic LRC Meter now measures capacitors at 10 kHz or 20 kHz. You can quickly and accurately verify ESR to assure low power switching regulator power supplies. (As a dual frequency instrument the Model 296 is available with either of those higher frequencies, plus 1 kHz or 120 Hz as the second frequency.)

ESI's premier LRC tester gives you everything you could want—for now or the forseeable future: Wide ranges, choice of any loss parameters—R, G, D or Q—with either L or C, direct reading or deviation display and field installable options. Options include dc resistance measurements and interfaces for GPIB, 11-bit serial bus, card readers and automatic handlers. Basic price (in the U.S.A. only) is \$5700.

- · L,R,C,G + D&Q.
- % and units deviation.
- · multiple limits.
- · 2 farad range.
- · dual frequencies.
- · dual displays.
- dual voltages.
- · active guard.
- 6 terminal connections.
- high accuracy.
- high speed measure- ment.
- programmable settling time.
- digital averaging.
- interface options.

Another ESI "easy weeder"



Electro Scientific Industries 13900 N.W. Science Park Drive Portland, Oregon 97229 Phone: 503/641-4141



Circle 172 on reader service card

Name


Street

City

Company

# 1977 Answer Book. It makes your job easier. \$25.

Who makes what? Over 4000 products, more than 5000 manufacturers with their local contracts and distributors, directory of trade names and catalogs, post-paid inquiry cards for 5-second ordering of current catalogs.



State

Zip

#### **New products**

at distances up to 25 feet.

Most standard types of bidirectional input signal will be acepted by the 7903. Among them: 90° quadrature signals from rotary or linear encoders, two-line add/subtract signals, and two-line count/direction signals. Both reset-to-zero and reset-to-preset models are available from stock. A prewarning signal output is available as an option for such applications as the control of high-speed machines that must be slowed down before final shutoff.

Veeder-Root, 70 Sargeant St., Hartford, Conn. 06102. Phone (203) 527-7201, Ext. 422 [377]

# Temperature controllers offer three types of output

Three new models of Pyromatic II temperature controllers provide three types of output, allowing them to cover many industrial heating and cooling requirements. The three types are dual-setpoint, dual-mode, and current-proportioning.

The dual-setpoint unit is designed for processes requiring primary and secondary levels of activation or for those in which a single instrument is required to control both heating and cooling in the same zone. The controller has two relay outputs—one for each setpoint.

The dual-mode controller is intended for applications in which the temperature must be tightly controlled within a narrow range. It offers proportional control within a tight band and full-on or full-off control outside it.

For processes in which the Pyromatic II must operate valve actuators or SCR power controllers, the current-proportioning device delivers a 0-to-20-ma or 0-to-5-v output.

All of the new Pyromatic II controllers are solid-state devices, housed in DIN standard cases, and designed to work with thermocouples. They are priced from \$187 to \$264 each, depending upon model and quantity.

Alnor Instrument Co., 7301 N. Caldwell Ave., Niles, III. 60648 [378]

## OUR ICE-FLOE MAPS KEEP SHIPS OUT OF A JAM.



Ships threading their way through hazardous ice floes need all the help they can get. So aircraft equipped with infrared sensors and Honeywell 1856A Line Scan Recorders now patrol northern shipping lanes. Changes in thermal patterns detected by the sensors are converted by an 1856A into maps showing the current location of the floes.

The maps transmitted to ships provide a detailed look at ice conditions. And it is this ability to capture fine detail that explains the popularity of the 1856A. You can count on


it for resolution greater than 100 line pairs per inch, scan rates up to 18,000 per second and high-performance 4-axis recording with a fiber-optic CRT. And that's just the beginning.

If your recording applications include sonar, IR or radar mapping and you need hard-copy readouts with exceptionally good contrast, don't overlook the 1856A. For complete details on this and other Honeywell instrumentation recorders, call or write: Bob Shipman, Honeywell Test Instruments Division, Box 5227, Denver, CO 80217. (303) 771-4700.

### **WE'LL SHOW YOU A BETTER WAY.**

Honeywell

# About the only No Touch Controls we don't make you haven't asked for. Yet.



#### are the ones

For years, MICRO SWITCH has been the leading maker of No Touch Controls.

That's because we're also leaders when it comes to listening to switching problems where mechanical devices just don't fill the bill. And then solving them with industry's broadest line of photoelectric and proximity controls.

For example, the ferroussensitive XK can detect metal targets of any thickness, either moving or stationary. There's also the vane-operated AV and the magnetically operated SR, both featuring dependable Hall-effect technology and high speed operation unaffected by dust and dirt.

You can also choose from a wide selection of solid state FY proximity sensors designed to be directly compatible with programmable controllers and solid state logic. These self-contained controls have models ranging from 14 mm in diameter to 76 mm.

For materials other than metals or where distances are too great for proximity switches, MICRO SWITCH offers a complete line of photoelectric controls.

At shorter distances, choose from MLS4A controls with a range of 8 feet or MLS7A controls that scan up to 10 feet. Both are DC powered and use advanced integrated circuitry to increase reliability.

There are also models with much greater scanning ranges, like the high intensity MLS5A that sees up to 250 feet in clean air and through dust, smog, steam and other pollutants at shorter distances.

Another model provides a scanning range up to 700 feet.

And whether you need proximity or photoelectric controls, you'll be getting solid state design that delivers long life. Which is what you've come to expect from the leading maker of No Touch Controls.

MICRO SWITCH will provide you with field engineers for application assistance and a network of authorized distributors for local availability. Write us for details or call 815/235-6600.

#### **MICRO SWITCH**

FREEPORT, ILLINOIS 61032

A DIVISION OF HONEYWELL

MICRO SWITCH products are available worldwide through Honeywell International.

#### **New products**

Packaging & production

# Software aids pc-board design

Program reduces
design cycle, cuts errors
and documentation cost

Traditionally, the most time-consuming portion of integrated-circuit-based product development has been the design cycle—specifically, the packaging of the functions, their placement on a printed-circuit board, and the routing of interconnections. In recent years, in attempts to shorten the cycle, various portions of the cycle have been automated and brought under computer control.

Now, a new software package completes a minicomputer-based stand-alone system that is capable of automating all three elements together and reducing design cycles by as much as 50% has been developed by Calma Co.

Called Tridesign, the computer software package operates on Calma's interactive graphics systems to perform the packaging, placement, and routing of component pin assignments and circuit traces, according to E. W. Emmerich, a vice president for marketing. The software, used with a Calma interactive graphic system, produces the artwork that is needed for complex two-sided and multilayer boards.

Until now a large part of the pc-board design process had to be done manually, Emmerich says. Using a large central computer, much of the preliminary artwork drafting and all of the design and logic testing remained a manual task. Even with an interactive graphics system such as Calma's, circuit routing and device placement and layout, as well as design checking, still had to be done by hand.

With Tridesign software installed in a graphic data system, the only manual task is data entry. After that, Tridesign provides computer support for design review, component packaging and placement, iterative design improvement, device and terminal pin assignments, subgrid optimization, placement analysis, strategy routing, and exhaustive search-routing.

Initial data entry is also greatly simplified with Tridesign, according to Emmerich. Input required is just the logic diagram for the circuit, the geometry and dimensions of the board itself, and a list of devices to be mounted. If the devices are preentered, they can be recalled by part number; if not, device specifications can be used as the entry data.


After data is entered, Tridesign allows the operator to review and verify the data and to check the circuit rule violations, such as pin numbers used twice, pins missing, too many or too few connections, and the like.

The packaging cycle automatically assigns logic blocks to one or more component packages that perform the logic function. Placement of the packaged components is then done according to parameters that the user can adjust to suit circuit requirements. After automatic placement is completed, the operator can use the software to examine the layout and experiment with swapping parts to shorten net lengths.

The strategy-router program in Tridesign includes an algorithm that gives fast routing of most connections, using a strategy that minimizes circuit congestion on the board. The exhaustive search-router uses another algorithm to complete the routing of signal and power nets on the pc board.

The overall effect of using Tridesign, according to Emmerich, is a significant reduction in design time, documentation costs, and processing errors. A primary benefit, however, is the improved accuracy and efficiency of the resulting pc-board design brought about by the error-checking and optimization techniques available in Tridesign that are generally not feasible with other systems, Emmerich says.

Available now, the Tridesign software package ranges in price from



The Continental concept of sales and service has grown to a team of more than 150 "Professionals" in 10 nation-wide offices.

More plant More experience

Rental inventory, offices, service and calibration labs exceed 60,000 square feet of floor space.

In-house service, experienced personnel and four hundred thousand dollars/month in new equipment purchases keep us #1.

# Rent with Confidence

Call Get our FREE Catalog Continental Rental

Div. Continental Resources, Inc. 175 Middlesex Turnpike, Bedford, MA 01730 (617) 275-0850

FOR IMMEDIATE RESPONSE CALL: N.E. (617) 275-0850; L.I. (516) 752-1622; NY, NJ (201) 654-6900;

Florida (800) 638-4050; Gtr. Phila. (609) 234-5100; Wash., D.C. area (301) 948-4310; Mid West (312) 439-4700; So. Central (800) 323-9656; Costa Mesa, CA (714) 540-6566; L.A., CA (213) 638-0454; Santa Clara, CA (408) 735-8300.


#### **New products**

\$75,000 to \$100,000, depending on configuration.

Calma Co., 707 Kifen Rd., Sunnyvale, Calif. 94086 [391]

# Zero-force connector for pc boards needs no gold

Called the Clam connector, a zeroinsertion-force unit for use at the edges of printed-circuit boards is snapped closed after insertion to develop from three to four times the loading force of standard connectors. The higher loading permits reliable connection to be made to solderplated edge contacts, making gold plating unnecessary.



Contacts on the Clam are tinplated brass on 0.100-inch centers. The standard insulator material is 94V2 nylon, but a material that conforms to 94V0 is also available. Methode Electronics Inc., Dept. PR, 1700 Hicks Rd., Rolling Meadows, III. 60008. Phone (312) 392-3500 [393]

## IC failure analyzer uses laser to cut conductors

The model LFA destructive-failureanalysis system is designed to aid in the study of failure modes of small-

## Make us your headquarters for

# EMI/RFI FILTERS




#### Passive Filter Headquarters:

Centralab Los Angeles is a one-stop source for reliable miniature ceramic low pass Feed Thru's/Filters. They're cost effective from 30 KHz to beyond 1 GHz. Threaded or solder mount for easy installation. Proven in AC as well as DC applications. Monolithic and multi-element. Standard products or computerized custom designs, including multi-circuit custom packages. Call Rich Colburn at (213) 240-4880.

#### **Active Filter Headquarters:**

That's Centralab Milwaukee. Solve design problems and cut costs with our thick film hybrids. Band pass, low pass, high pass and band reject. Cost effective for low to medium frequencies. Let us put our design and manufacturing expertise to work for you.

Call Don Weiland at (414) 228-2872.





4561 Colorado Blvd., Los Angeles, California 90039 5757 North Green Bay Ave., Milwaukee, Wisconsin 53201

CERAMIC CAPACITORS • FILTERS • POTENTIOMETERS • SWITCHES
THICK FILM CIRCUITS • TRIMMER RESISTORS

# More

Introducing the 920-D logic analyzer. Nine channels, 20 MHz and much, much more.



Don't let the low price mislead you. Biomation's new 920-D stands up to logic analyzers costing twice, even three times as much. It includes the features engineers ask for most. And combines them with  $9\frac{1}{2}$  pound portability, making the 920-D an ideal field troubleshooting tool.

ortability, making the 920-D an ideal field troubleshooting tool. Nine channels—not just eight—give you added capability for more



applications. Use the extra channel for recording data, or to mark a trigger location. And select between trigger or clock qualifier. Attach the optional Biomation 10-TC probe pod and you can select up to a 19-bit combinational trigger word.

The 920-D enables you to set a precise interval between the actual trigger and the start of recording, using either clock periods or number of trigger events. Or the pre-

trigger recording mode can be selected to capture data from before the actual trigger. The logic threshold level is selectable—TTL, ECL or variable. And you can record at rates from DC to 20 MHz.

Captured data, at 256 bits per channel, can then be displayed on any single channel scope or CRT display in timing diagram format.

What more can we tell you? Plenty. Ask for the 920-D product sheet. Or give us a call to arrange a demonstration. Ask for Ed Jacklitch

(408) 255-9500. Or write Biomation, 10411 Bubb Road, Cupertino, CA 95014.

biomation

Circle No. 177 for information.
Circle No. 178 for information and demonstration.

#### **New products**




geometry, high-density integrated circuits. It uses a pulsed xenon laser to sever the aluminum conductors on silicon wafers or chips where mechanical cutters would be too crude. It thus allows parts of the circuit to be isolated from each other until the faulty part has been determined.

The complete LFA system includes the pulsed xenon laser, a Leitz Dialux microscope head, a TV viewing system, and a probe station. It sells for \$39,000.


Florod Corp., 3341 West El Segundo Blvd., Hawthorne, Calif. 90250. Phone Marty Compton at (213) 679-8201 [392]

# Laser system examines wafers for surface defects


An automatic surface-inspection system designed primarily for use in the semiconductor industry employs a laser to monitor wafer surface quality before and after critical processing steps. The system makes a quantitative determination of the defect level by measuring the amount of laser light scattered by scratches, hillocks, spikes, fingerprints, foreign particles, and other imperfections. During inspection, the laser beam traverses the wafer surface in an Archimedes spiral. This allows it to cover the entire surface of a 5-inch wafer in 4 seconds. To check







this is what you're missing




The AO® DICV Differential Interference Contrast Microscope makes the big difference.

With a standard brightfield microscope you see only what is shown in the top sample.

Now look at the bottom sample. The AO DICV Microscope can help you see surface irregularities, inclusions and faults long before final testing. Long before you have invested more production time and money in a circuit or component that is defective.

By using incident light, after Nomarski, the AO DICV Microscope reveals significant detail in outstanding relief through vivid contrast enhancement.

So, if missing detail is costing you money, you can't afford to overlook the AO DICV Microscope. For details or a demonstration see your AO Dealer or write American Optical, Scientific Instrument Division, Buffalo, NY 14215.



### High Voltage Products



- Custom design
- "In-house" capability
- MIL approved facilities
- Hi reliability

### TYPICAL APPLICATIONS

- Military Industrial
- Commercial
- CRTs
   PMTs
   SITs
- I-SITs LLLTV Lasers
- Image Intensifiers
- Detectors
- Electrostatic Applications



ERIE TECHNOLOGICAL PRODUCTS, INC. ERIE, PENNSYLVANIA 16501 (613) 392-2581 **New products** 

patterned wafers at any stage up to metalization, the system has a memory that stores data on standard clean wafers and compares this data with that generated by the wafer under test. The system has a delivery time of 12 to 14 weeks.

Advanced Semiconductor Materials/America, 4302 E. Broadway, Phoenix, Ariz. 85040. Phone (602) 894-1274 [394]

Low-profile heat sinks provide extra surface area

A series of low-profile heat sinks have wing-like radiators that increase their total surface area and thus their cooling ability. The units are particularly well suited for mounting on circuit boards where high-density placement of plastic-packaged power devices makes cooling a critical problem.



For applications requiring even more cooling, the 5071 unit may be stacked for multiside cooling of devices mounted in TO-220 cases. A sample assortment of the four heat sinks in the new line is available for prototyping and evaluation.

Aavid Engineering Inc., 30 Cook Ct., Laconia, N. H. 03246. Phone (603) 524-4443 [395]

Taping machine makes axiallead components from radial

A fast axial-lead taping machine for disk capacitors and other radial-lead devices automatically removes the radial-lead components from Die Craft or other types of strips on which they are shipped, straightens and trims the leads, forms them into

### STANDARD ELECTRONIC MODULES

Call Ed Gray (714) 759-2411

Or send for new brochure: 500 Superior Ave., Newport Beach, CA 92663

HUGHES

MICROELECTRONIC PRODUCTS DIVISION
Circle 269 on reader service card

CUSTOM CRYSTAL OSCILLATORS

Call Vic Gill (714) 759-2411

Or send for new brochure: 500 Superior Ave., Newport Beach, CA 92663

HUGHES

MICROELECTRONIC PRODUCTS DIVISION
Circle 265 on reader service card

The 1977 Answer Book. It makes your job easier. \$25

- Over 4000 products.
- More than 5000 manufacturers with local sales offices, reps/and distributors.
- Directory of Catalogs with postpaid inquiry cards for 5-second ordering of current catalogs.

Electronics Buyers' Guide 1221 Ave. of the Americas New York, N Y. 10020



Yes, send me a copy of The Answer Book. I've enclosed \$25 (USA and Canada only, elsewhere send \$35). Full money back guarantee if returned within 10 days.

Name					
Company					
Street					
City	State	Zin			

# HERE'S YOUR CHANCE TO TRY FIBEROPTICS.



reasonably priced, off-the-shelf fiberoptic engineering kit with all the electronic and mechanical components necessary for use in TTL systems up to 5 mbps.

Augat developed it to give engineers a quick and easy way of evaluating the exciting new technique of fiberoptic interconnection in their existing or prototype systems. The price

to use it... even assuming no prior experience in fiberoptics.

The kit contains a 5-meter length of Hytrelt-jacketed cable terminated with ferrules that have precision ground and polished ends. All connector

range of 0 to 55°C without drifts or inadvertent comparator switching usually associated with non-temperature referenced pre-amps.



Detector Assembly With Bracket

Cable Assembly

is right.\* And the kits are in stock at Augat's nearly 200 worldwide integrity of shielded enclosures. distributor locations.

The combination of the kit's driver, emitter, cable assembly, pre-amp, and detector provide the necessary elements for a complete TL-compatible digital fiberoptic system. We've even included mounting brackets and sockets for convenience. And its comprehensive instruction manual will

\*Complete Kit (No. 698-OK-002): \$190. Kit less driver and pre-amp (No. 698-OK-001): \$99.50.

elements feature gold-plated brass construction to ensure the

The temperature referenced pre-amp operates from dc to



†Dupont trademark

All components of the kit are available separately. Standard accessories include butt splices, o-ring seals, and cables of other lengths. For more details and a list of Augat distributors, write Augat, Inc., 33 Perry Avenue, P.O. Box 779, Attleboro, Mass. 02703.

Augat interconnection products. Isotronics microcircuit packaging, and Alco subminiature switches.



where you need them, when you need them.

Specify Delevan inductors and transformers and relax. Our coast-to-coast distribution network guarantees reliable, on-time delivery, no matter where you are. In Europe, too, our distributors have coils in stock for immediate, off-the-shelf service. Components are also available direct from the factory for OEM production or prototype design evaluation.

Our no-fault production record, plus sophisticated quality control and testing, have made Delevan components the standard of excellence throughout industry. In the long run, Delevan subassemblies can cost you less than "cheaper" ones. Delevan's proven dependability is your assurance of avoiding premature malfunction . . . a major cost to pay for a few cents' savings in parts.

Our lineup of RF inductors and transformers have been developed to keep pace with the growing needs of the electronics industry. So we're not going to let you down when you need them, wherever you need them. When your reputation is on the line, Delevan delivers.



270 QUAKER RD./EAST AURORA, N.Y. 14052 TELEPHONE 716/652-3600 TELEX 91-293 OTHER DIVISIONS INCLUDE: BASCO, DUSTEX, AMERICAN PRECISION INDUSTRIES (U.K.) LTD., DUSTEX OF CANADA INC.

### **New products**


an axial configuration, and applies them to double lead tape on 0.2- or 0.4-inch spacing. The result is components ready for use in conventional sequencing and inserting machines.

The Discap Taper is a self-contained floor-mounted unit. It can handle disk capacitors with head diameters from 0.25 to 0.375 in. and lead spacings from 0.25 to 0.375 in. Continuous-feed reels are available as an option. The standard machine sells for \$24,475.

Cambridge Automatic Division, Eyelet Tool Co., 15 Erie Dr., Natick, Mass. 01760. Phone Dave Spencer at (617) 653-9002 [396]

### Analyzer checks continuity on bare or loaded boards

A circuit analyzer and test fixture combined in one package can check bare or loaded circuit boards, wired backplanes, and cable harnesses for shorts and opens. The analyzer, which programs itself from a knowngood unit, can handle products up to 24 by 26 inches with up to 10,240



test points. Designated the CA-1000 circuit analyzer, it displays all its activity to the operator in real time.

Options for the tester include a printer that shows errors by printing out the opens in black and the shorts in red and a cassette deck for program storage.

Program Data Inc., 16752 Hale Ave., Irvine, Calif. 92714. Phone (714) 549-0335 [397]

### Impedance tester sorts components automatically

The GR 1658 Digibridge is an automatic, microprocessor-based, key-

# BergLance Wire-Wrapping Posts give a classic performance on the Lowrey Organ.

The BergLance System assures rapid staking of miniature thru-lugs for solid or stranded wire terminations. It's an approach that offers high quality and reliability . . . and is economical, too.


Lowrey likes it, and has used millions of BergLance posts throughout the past decade. Lowrey has found it can rely on Berg Electronics...to supply the product and the application machines that precisely meet its interconnection needs.

Berg is experienced. We read interconnection needs like Lowrey reads music. We have the products, the background and the back-up to do the job. Your job. Let's work on it, together. Berg Electronics, Division, E. I. du Pont de Nemours & Co., New Cumberland, Pa. 17070—Phone (717) 938-6711.




Circle 183 on reader service card

We serve special interests—yours!



### KEYBOARDS BY THE MILE



These one piece units provide circuit coding, board edge connections, springs for your keytops and contact

closures for 10M cycles. You provide the top

and bottom, we'll supply the action!

**CHOMERICS** 8

Write 77 Dragon Court Woburn, Ma. 01801 (617) 935-4850

### **New products**



board-controlled, impedance-measuring component tester that measures the resistance, capacitance, inductance, dissipation factor, and Q factor of various components at selectable frequencies of 120 Hz and 1 kHz. No calibration is normally required to keep the instrument within its basic maximum-error specification of 0.1%.

A novel feature of the 1658 is its provision for 10 limit-comparison bins for sorting. Both symmetrical and asymmetrical limits can be entered through the keyboard.

The machine can run in three test modes: continuous, single, and average. The average mode is useful for unstable components or noisy environments, since it can reduce errors by averaging 10 successive measurements. Three selectable display modes show either the measured values, the bin number, or the programmed limits for any bin. An IEEE 488 bus interface option provides the means for connecting the 1658 to a parts handler, a printer, or a bench-top calculator system. The 1658 sells for \$1,985.

GenRad Inc., 300 Baker Ave., Concord, Mass. 01742. Phone Thomas A. Bergendahl at (617) 369-4400 [398]

### High-barrier terminal strips come in five colors

A selection of thermoplastic high-barrier terminal strips rated to handle 20 A at 600 V is available in five colors: red, green, black, blue, and off-white. The units have a 94V-0 UL listing.

Kulka Electric Corp., 520 S. Fulton Ave., Mount Vernon, N. Y. [399]



### Higher efficiency at lower cost. New VLEDs from Texas Instruments.

			Min. I <sub>v</sub> @		Texas Instruments	Hewlett- Packard
Color	Package	TI P/N	I <sub>F</sub> =10 mA	$I_F = 20 \text{ mA}$	100 pc. price	100 pc. price
Yellow	T-13/4	5082-4550	1.0 mcd		.43	.52
Yellow	T-13/4	5082-4550A	2.6 mcd		.43	_
Red	T-13/4	5082-4650	1.0 mcd		.43	.52
Red	T-13/4	5082-4650A	2.6 mcd		.43	-
Green	T-13/4	5082-4950		1.0 mcd	.43	.52
Green	T-13/4	5082-4950A		2.1 mcd	.43	-
Yellow	T-13/4	5082-4555	2.2 mcd		.77	.85
Yellow	T-13/4	5082-4555A	3.9 mcd		.77	_
Red	T-13/4	5082-4655	3.0 mcd		.77	.85
Red	T-13/4	5082-4655A	3.9 mcd		.77	-
Green	T-13/4	5082-4955		2.2 mcd	.77	.85
Green	T-13/4	5082-4955A	1	6.0 mcd	.77	_

Compare quality. Compare performance. Compare price. Then switch to a leader and pioneer in optoelectronics, Texas Instruments. To make your changeover easier, TI uses the original Hewlett-Packard part designations. And TI offers higher brightness "A" versions.

The new TI high-intensity VLEDs are available as presented in the chart to the left. Higher efficiency at lower cost. Also available are red, yellow and green VLEDs in T-1 and T-134 sizes with wide angle, narrow angle and clear lenses.

### FREE

VLED data sheets for all TI optoelectronics products are available on request.

Applications Notes. A 32-page booklet on VLED applications including such topics as filter selection for VLEDs, display interface with the TMS 8080A system, VSWR indicator using VLEDs.

Texas Instruments In Inquiry Answering Se P. O. Box 5012, M/S 3 Dallas, Texas 75222	vice
☐ Please send me a d	ppy of your new Optoelectronics Applications booklet.
Please send me dat	sheets on the following products:
Please send me dat	sheets on the following products:
Name	

### Our new AMPL Prototyping Lab brings out the best in the 9900 Microprocessor Family.



### VAS INSTRUMENTS.

TI's new AMPL\* Microprocessor Prototyping Lab can help you apply the full potential of the 9900 Microprocessor Family to your design problems.

You can generate stand-alone routines for execution on the TMS 9900 target system. And the AMPL system's modular design means that you can apply its capabilities to the TMS 9900 16-bit microprocessor and the 990 Mini/Microcomputer family now. And, to additional 9900 family microprocessors in the future.

Now, you can move from hardware breadboarding through finished application software with confidence. And with the efficiency possible only with stateof-the-art support. Best of all, you can do it for hundreds or even thousands of dollars less than with other development systems.


The best in hardware design support.

With the AMPL lab you can de-

\*Trademark of Texas Instruments

velop hardware designs that fully The best in software design complement your software needs. This new development system combines the power of the computer with the latest logic-signal analysis techniques.

In-circuit emulation and logicstate trace are controlled by AMPL software. It has an interactive language with designed-in features to simplify orientation of the new user, while providing versatility and support for the more experienced.



### support.

The AMPL Lab is ideal for software development in both FORTRAN and assembly language. FORTRAN provides increased support for your benchmark evaluations, generalpurpose engineering data processing and data reduction. The combined capabilities give you fully integrated software and hardware emulation for straightforward debugging, testing and firmware implementation.

### Ask your TI distributor.

The AMPL Microprocessor Prototyping Lab and the 9900 Microprocessor Family are available at your nearby TI distributor. Call him today. Or write Texas Instruments Incorporated, P.O. Box 1444, M/S 784, Houston, Texas 77001. Or call Computer Systems Marketing at (512) 258-7305.

Copyright® 1977, Texas Instruments Incorporated

### TEXAS INSTRUMENTS

INCORPORATED

# New SUPERIBBON Connector System drastically reduces assembly costs

Mating is instantaneous—without separate hardware. An integral spring clip on the female engages a window in the male and an audible "click" tells you the connector is mated.

Any pointed object inserted in the window at either end of the male depresses the clip and allows fast separation with slight hand pressure.

Plastic hood snaps in place without additional hardware; is separate from the cable clamp and readily removed. Available in six colors.

Termination is Solderless Cinch Ribbon System that terminates 25-pairs of wires in less than two minutes in the plant, less than five minutes in the field. Individual wires are replaced with simple hand tools.

Cable clamp is part of the connector—not the hood. It accommodates wide variations in cable diameter. No other hardware needed—just a pliers.

Everything about the TRW Cinch Connectors' Superibbon System is new—except the industry-proven ribbon contact! Here are some of its other "super" design features:

- Fast panel mounting with clips that eliminate nuts, bolts, tapped holes and special tools.
- Wire restraints replace cable clamps for panel connectorization. They restrain each wire individually, at point of termination.
- Two-piece, center-entry hoods allow assembly after termination. Built-in spacers provide for four sizes of cable openings.
- Dimensions that permit intermating with or replacement of all ribbon connectors now in use.

Superibbon connectors are available in 14, 24, 36, 50 and 64 contact sizes, each with 90° and 180° hoods. Buff gold is standard color for connectors and hoods. Other hood colors are blue, orange, green, brown and slate.

For additional information, contact any TRW Electronic Components sales office or TRW Cinch Connectors, An Electronic Components Division of TRW Inc., 1501 Morse Avenue, Elk Grove Village, III. 60007. Phone 312/439-8800.

TM TRW Inc

TRW CINCH CONNECTORS

ANOTHER PRODUCT OF A COMPANY CALLED TRW



- 4 Bit/50 nSec; Low Cost
- Ideal for Radar Scan Converters
- Holds Absolute Accuracy Over Temperatures
- Tracks a 10 MHz Analog Input



- 9 Bit/200 nSec.
- < 2 Bit Drift Over Temperature</li>
- Insensitive to Clock Frequency

For Further Information Call or Write M.S. Kennedy Corp.

Pickard Drive, Syracuse, New York, 13211 Tel. 315-455-7077

### **New products**

Components

# One-pole, 20-A mercury relay sells for \$6

A single-pole mercury-displacement relay, which sells for less than \$6 in large quantities, is available in models rated at 10, 15, and 20 A. The units are Underwriters Laboratories-tested at 480 v. The AFM relays are general-



purpose devices with lifetimes in excess of 100,000 cycles. They have all-steel hermetic bodies enclosing a high-pressure arc-suppressing gas, which dissipates heat rapidly and eliminates erosion. The units are therefore suitable for use in hot, humid, wet, contaminated, and explosion-prone atmospheres.

The relay is small for its type: it measures 1.25 by 2.375 by 1.313 in. Its silent mercury-to-metal contacts eliminate burning and welding, common causes of contact failure in conventional electromechanical relays.

Delivery of the single-pole unit is from stock. Two- and three-pole versions of the AFM are expected to become available in the near future, according to the company.

Durakool Inc., 1010 N. Main St., Elkhart, Ind. 46514 [341]

### Light-emitting diode has 180° viewing angle

The OSL-1 and OSL-1S gallium-phosphide red light-emitting-diode lamps are extremely small devices with a typical luminous intensity of 1.1 millicandelas at 15 mA and a viewing angle in excess of 180°. Both lamps are packaged in a metal coaxial header; the OSL-1 has one lead, and the OSL-1S has two. The lamps can be driven by transistor-transistor-logic voltage levels. They sell for 90 cents each in hundreds




and 60 cents each in thousands.

Opcoa Division, IDS Inc., 330 Talmadge Rd.,
Edison, N. J. 08817. Phone (201) 287-0355
[344]

### Tiny snap-action switch handles 7 A at 115 V ac

Although it is only 0.5 inch long and 0.2 in. wide, the B2 series snapaction switch is rated at 7 A at either 115 v ac or 28 v dc. Five terminal styles are offered, as is a choice of



Unlike fabricated metal, GE Engineering Structural Foam can show a beautifully simple side plus an incredibly complex side together, in one piece.

Take the outside. In GE Engineering Structural Foam resin, the total effect is a clean, integrated, contemporary look. And it stays that way with excellent impact, heat or chemical resistance. Yet, while the

outside looks like a work of art, the other side works. And works hard.

That's because GE Engineering Structural Foam is so rigid, strong and stable, it supports internal components and assemblies all by itself. Costly secondary parts, materials and operations are eliminated. What's more, GE Engineering Structural Foam is double-insulated and can meet UL 94 V-O\*. Best of all,

its simple one-step molding process eliminates metal's numerous, costly production steps, and its lighter weight reduces shipping costs.

For more information, write Structural Foam Resins Section 300, Plastics Division, General Electric Company, One Plastics Ave., Pittsfield, MA 01201.

Or talk to NCR, TRW and Datapoint.





STYLING FREEDOM OUTSIDE



COSTREDUCTION/NSIDE


This rating is not intended to reflect hazards presented by this or any other material under actual fire conditions.

WHAT THE WORLD IS COMING TO: GE ENGINEERING STRUCTURAL FOAM.

LEXAN\* NORY!\* VALOX\*

GENERAL & ELECTRIC

Circle 189 on reader service card



For further information, please send your name and address with the reference : G.7.30 For U. S. A. rhodia inc

Chemicals Division - P.O. Box 125, Monmouth Junction, NEW JERSEY 08852 (USA), Tel. 201-846-7700, Telex 844527

rhône-poulenc (CF/PSP) 21, rue J. Goujon, F-75 360 PARIS CEDEX 08, Tel. (1) 256-40 00, Telex 640 100 F

rhône-pouler

### **New products**

contact materials. The standard switch comes with silver contacts and sells for \$1.93 when purchased in 100-piece lots. A unit with gold contacts for low-level and dry-circuit switching is also available. Delivery is from stock to six weeks.

Otto Controls Division, Otto Engineering Inc., 36 Main St., Carpentersville, III. 60110. Phone Ronald E. Sparks at (312) 428-7171 [346]


### Modular rotary switches are easily modified

Modular rotary switches that offer the user options of assembling switches from building-block parts or ordering custom-made components can also be easily modified when necessary. Designed to control currents up to 55 A at voltages as high as 750 v, the switches may be assembled with up to six stages. Each of the stages can have multiple contacts actuated by an independent cam.

Cogenel Inc., Entrelec Division, 2 Ram Ridge Rd., Spring Valley, N. Y. 10977. Phone (914) 425-7460 [343]

### Tantalum capacitor has 4-mm diameter, 10-mm length

Type EL solid-tantalum capacitors are very small components for use in hand-held calculators, cameras, and similar miniature commercial



### Their Computer, Our Tape Deck, Your Gain!

Still putting up with year-long delivery waits for tape decks from your minicomputer vendor? Digi-Data's compatible magnetic tape systems are yours in one fourth the time... and for half the price. Whether your minicomputer is the DEC PDP-11, the Data General Nova or Eclipse, or the HP 2100/21 MX, you have a practical alternative... and with extra choices in the bargain!

You can get the tape deck alone, or with formatter and computer interface. Specify 7-in., 8½-in. or 10½-in. reel size. Get different speeds, plus either NRZ or phase-encoded formats and total playback/record interchangeability with any other ANSI-compatible computer tape. Get all these advantages, along with the reliability and ease of maintenance of Digi-Data's complete minicomputer tape system, proven in thousands of installations. Now add our 2:1 price edge and 60-90 day delivery, and it's no wonder Digi-Data tops them all.

For a full product catalog and details on ordering single units or quantities, call or write today.



DIGI-DATA CORPORATION

8580 Dorsey Run Road, Jessup, MD 20794

... First in Value!



Circle 191 on reader service card



KERAMAX high temperature furnaces and LaCrO3 heating elements excel where others pale by delivering higher working temperatures in oxidizing atmospheres with stability, durability, simple operation and a lower cost/service life ratio.

KERAMAX developed by Nippon Kagaku Togyo Co., Ltd. provides a new level of performance at the highest working temperatures, whether for R&D, materials testing or production.

#### **Furnace Applications**

 Growing single crystals of (for example), ferrite for VTR heads
 High temperature properties measuring . Ceramics sintering . Metal and slag heat treatment

KERAMAX LaCrO3 Elements

• Longer service life at higher working temperatures in oxidizing atmospheres . Lower cost/ service life ratio . Near zero resistance temperature coefficients at high temperatures; negligible electric resistance change due to aging • Excellent sensitivity and stability for precise temperature control; easy operation
• Automatc control ease • Allows direct electricity supply at room temperature . Silicon carbide power units applicable for KERAMAX Suitable for use as light source and electrodes

Write or Telex for Complete Details



Nishimura Bldg. 13-11, Nishi-Gotanda 1-Chome, Shinagawa-ku, Tokyo 141, Japan Telex: TOK 2467455 NISMRAJ

### **New products**

products. The smallest unit in the family has a working voltage of 4 v dc and measures only 4 mm in diameter by 10 mm in length. Other voltage ratings include 6.3, 10, 16, 25, 35, and 50 v dc. Available capacitances range from  $0.1 \,\mu\text{F}$  to  $47 \,\mu\text{F}$ .

The resin-dipped, axial-lead components are available either loose or in reels of tape for use with automatic insertion equipment. They are rated for operation from -55°C to 85°C and have a capacitance tolerance of  $\pm 20\%$ .

Panasonic Electronic Components, One Panasonic Way, Secaucus, N. J. 07094. Phone Justin Camerlengo at (201) 348-7182 [345]

### HP expands its line of light-emitting-diode lamps

An expanded line of light-emittingdiode lamps, including a highbrightness T-1 version and an inexpensive rectangular unit, has been announced by Hewlett-Packard Co. The high-brightness lamps are the red HLMP-1302, which has a minimum luminous intensity of 2.0 millicandelas at 10 ma; the yellow HLMP-1402, which is rated at 2.5 mcd at the same current; and the green HLMP-1502, which puts out 2.0 mcd with a 20-ma drive. In hundreds, the high-brightness lamps will sell for 75 cents each. HP will continue to offer its present mediumbrightness lamps (1.0 mcd for red and yellow, 0.8 mcd for green) at 50¢ and some new low-brightness (0.5-mcd) units at 40¢.

The new low-cost rectangular lamps (HLMP-0300/0400/0500 for red, yellow, and green, respectively) are electrically identical to the older high-performance rectangulars, but not as bright. They sell for 60¢ each in hundreds compared to 90¢ for the brighter HLMP-0301/0401/0501. These lamps will be most appropriate for use with relatively high drive current. All are available from stock.

Inquiries Manager, Hewlett-Packard Co., 1507 Page Mill Rd., Palo Alto, Calif. 94304 [347]

Call Frank Albertson (714) 759-2411

Or send for new brochure: 500 Superior Ave., Newport Beach, CA 92663

### HUGHES

HUGHES AIRCRAFT COMPANY MICROELECTRONIC PRODUCTS DIVISION Circle 267 on reader service card

# **CUSTOM**

Call Dennis Olson (714) 759-2411

Or send for new brochure: 500 Superior Ave., Newport Beach, CA 92663

### HUGHES

HUGHES AIRCRAFT COMPANY MICROELECTRONIC PRODUCTS DIVISION Circle 266 on reader service card



### Wide Band, Precision CURRENT MONITOR

With a Pearson current monitor and an oscilloscope, you can measure pulse or ac currents from milliamperes to kiloamperes, in any conductor or beam of charged particles, at any voltage level up to a million volts, at frequences up to 35 MHz or down to 1Hz.


This video monitor is physically isolated from the circuit. It is a current transformer capable of highly precise measurement of pulse amplitude and waveshape.

Whether you wish to measure current in a conductor, a klystron, or a particle accelerator. it is likely that one of our off-the-shelf models (ranging from ½" to 10¾" ID) will do the job. Contact us and we will send you engineering data.

### PEARSON ELECTRONICS, INC.

4007 Transport St., Palo Alto, California 94303, U. S. A. Telephone (415) 494-6444

Circle 268 on reader service card



## Track Down Your Faults With A Bug Hound. The GenRad 2220 Bug Hound will



The GenRad 2220 Bug Hound will track down your shorts, opens, bad ICs, etc. in a fraction of the time it takes you now, **including those hard-to-find shorts between power and ground**.

Even though your automatic board tester may be giving you good diagnostics, it is still only telling you the **electrical** location of the faults. Finding the **physical** location can still be a time-consuming and expensive task. The GenRad 2220 Bug Hound solves this problem by providing the repair technician with a variety of testing techniques in one self-contained little package.

It has a unique new phase-sensitive current-tracing probe\* which makes it easy to trace the correct track even when many narrow tracks are running very close together. In addition, it has a dc tracing capability, a connectivity tester, an ac current source, and a dc current source.

The GenRad 2220 is easy to use and in most applications will pay for itself in just a couple of weeks.

\*Patent Pending

300 BAKER AVENUE, CONCORD, MASSACHUSETTS 01742 ATLANTA 404 394-5380 - BOSTON 617 686-0550 - CHICAGO 312 884-6900 - DALLAS 214 234-3357 DAYTON 512 284-1500 - LOS ANGELES 714-58-0380 - NEW YOPK (N Y) 212 964-2722, (N J) 201 791-8990 SAN FRANCISCO 408 985-0662 - WASHINGTON, DC 301 348-7071 - TORONTO - 416 252-3395 - ZURICH (01) 55 24 20






COE CORNELL-DUBILIER

### electronics firms love New Bedford, Mass.

A significant number of electronics component manufacturers have located in New Bedford, Mass. Among them are Isotronics, Aerovox, and Cornell-Dubilier.

Why? Several good reasons. They're labor-intensive, and New Bedford has an exceptional supply of skilled workers *guaranteed* by our brand-new \$25-million technical - vocational school! We're within easy reach of many high-technology companies, as well as top-notch educational facilities. We've got low-cost industrial park space and inexpensive existing industrial space.

And it's a great area in which to live, halfway between Newport, R.I., and Cape Cod, and just an hour south of Boston.



If your firm is thinking of relocating or expanding, you ought to find out more about New Bedford and its advantages. Just call or write:



1213 Purchase Street New Bedford, Ma. 02740 Telephone (617) 997-6501

### **New products**

Instruments

# Meter resolves 0.1 microhm on 1-m $\Omega$ range

Designed to provide fast and accurate measurements on large transformers, switch gear, circuit breakers, and similar low-resistance devices, the model 4275 digital ohmmeter can resolve 0.1 microhm on its lowest (1-milliohm) range. The 4½-digit instrument has a test current of 10 amperes on its most sensitive range and features a minimum compliance voltage of 10 v dc.

It has six decade ranges, from the low of 1 milliohm up to a high of 100 ohms. Among the options available for the 4275 are automatic temperature compensation, binary-coded-decimal data outputs, and heavy-duty, industrial-grade, gold-plated Kelvin clip cable sets up to 20 feet long. These convenient cable sets easily attach to lugs while providing for accurate and repeatable measurements. The basic instrument sells for \$2,495.

Valhalla Scientific Inc., 7707 Convoy Ct., San Diego, Calif., 92111. Phone (714) 227-2732 [351]

Logic pulser delivers 10 mA in TTL mode


The DP-1 digital pulser is a logic-probe-like device that monitors the node being probed, presets its output circuitry to pulse the node into the opposite state, and delivers the pulse when its pulse button is pushed. The unit delivers 50 mA in its C-MOS mode and 100 mA in its TTL mode, so



it can usually force the node into the desired state without any necessity for the user to desolder, unplug, or otherwise isolate the node.

When the pulse button is given a brief push, the pulser delivers a single pulse. If the button is held down for more than about 1 second.





contacts

70%-90% Reduction in Mating and Unmating Forces

- simpler board support systems
- fewer damaged boards

### **Extended Circuit Count Potential**

• up to 400 Bristle Brush per connector

### **Extensive Product Line**

- mother board, daughter board, input/output, PC receptacle body styles
- 2-, 3-, and 4-row configurations
- 90° and straight PC, solderless wrap, crimp removable, willowy tail terminations

For complete information, contact The Bendix Corporation, Electrical Components Division, Sidney, New York 13838.



# "Quality... I've heard of O&B test fixtures getting knocked on the floor and going on working like nothing happened."

We have a very simple philosophy when it comes to the products we make at Ostby and Barton: Do it right or don't do it at all. The result is test fixtures built to the highest possible standards. That's why many of the top companies here and abroad pick them. They know Ostby and Barton test fixtures won't cause them a lot of downtime. That everything from the hinges to the probes are going to work the way they're intended to. And do it over the long, long haul. If you're tired of test fixtures that don't last or perform the way they should, the solution is as close as the coupon below. Mail it and see what a difference quality makes in manual, vacuum and pneumatic text fixtures. ostby and barton company 487 Jefferson Boulevard, Warwick, R.I. 02886 (401) 739-7310 TELEX-927573 Name Position Company Address City

Circle 196 on reader service card

### NEW & DAZZLING!!! MS-15 Miniscope—\$289.00 from NLS



Al Fasano, Purchasing Manager



Features Include:

- Power consumption: <15 W.
   Battery or line operation with batteries and charger unit included.
   Weighs only 3 lbs & dimensions are 2.7" H x 6.4" W x 7.5" D.
- Options include a 10 to 1, 10 megohm probe and leather carrying case.

### **New products**

the unit delivers a train of pulses at a rate of about 100 per second. The DP-1 can deliver pulses into a dead short for an indefinite period with no danger of damage to itself.

A light-emitting diode on the instrument blinks once whenever a single pulse is delivered and remains on while a pulse train is being put out. The DP-1 is priced at \$74.95. Continental Specialties Corp., 44 Kendall St.,

Continental Specialties Corp., 44 Kendall St., New Haven, Conn. 06509. Phone (203) 624-3103 [353]

### Low-cost synthesizer works up to 16 megahertz

Priced at only \$459, the SI-101 frequency synthesizer provides 4½ digits of resolution over the frequency range from 0.1 Hz to 16 MHz. The instrument has a pulse output whose amplitude can be varied by means of an uncalibrated attenuator. Delivery is from stock to 30 days.

Syntest, 169 Millham St., Marlboro, Mass. 01752. Phone Curtis P. Hoffman at (617) 481-7827 [355]

### 400-MHz sweep generator sells for only \$625


The model 1061 sweep generator covers the range from 1 to 400 megahertz and sells for only \$625. Among its standard features are p-i-n diode leveling to within 0.25 dB and remote programmability of center frequency, sweep width, and amplitude over the 20-dB vernier range. Both harmonic and non-harmonic spurious signals are 30 dB below the output signal level.

The 1061 has provision for up to six crystal-controlled birdy bypass



State

# If you could cut base material cost from \$15 or \$30 down to \$3 per square foot, how much would you save next month?



Maybe \$10,000 per month? More? Less?


Well, Tektronix, Inc. of Beaverton, Oregon thought the savings impressive enough for their high frequency circuit boards to switch from polyphenylene oxide to an extruded polysulfone (UDEL Polysulfone, of course) just 1/16 of an inch thick.

Their processing costs are about the same as for other base materials with similar electrical properties. Even the quality and yields (c. 80%) are close on. But since they stopped using copper clad polyphenylene oxide they also get a use temperature 100 deg. F. above that material.

Polysulfone outperforms other materials at a lower cost in high frequency applications because of its excellent electricals (see graph) plus all these advantages:

(see graph) plus all these advantages **Electronics**/November 24, 1977

- withstands 500 deg. F. wave solder bath for 5 secs.
- · good notched Izod: 1 ft-lb/in.
- · impressive chemical resistance
- ink and adhesive baking at 320 deg. F.
- · good peel strength
- and polysulfone can be molded with stand-offs, holes of all sizes, and any shape, to save machining and finishing time.



How much more can we tell you here? Write for full data using the coupon below or the reader service card.

Maybe I can cut my high frequency circuit boards cost by 90%. Let me look at your data on UDEL Polysulfone

Name	
Title	
Company	
Address	
Phone (	)
City	
State	Zip
Mail to:	

Circle 197 on reader service card

197



### 2-Sided Single/Double Density Floppy Disk Drive Has a Lot Going for It.

We are talking about meaningful advantages. The kind which spells higher profitability for OEM.

Manufactured by Y-E Data, Japan's OEM diskette drive market leader, the low-cost YD-174 provides a storage capacity of 0.56/ 1.2 M bytes. It's compatible with single-sided IBM 3740/System 32 drives, 2sided IBM 3600/4964 drives and 2-sided double density IBM System 34 drive.

The YD-174 features a 2-sided head carriage assembly, standard ceramic R/W/tunnel erase head and flexured mounting arrangement. A simple/precise steel belt drive assures high reliability.

Contact C. Itoh for complete information on the YD-174 and entire Y-E Data product lineup.

#### **Specifications**

Capacity

unformatted 0.8/1.6 M bytes/disk

IBM format 0.56/1.2 M bytes/disk

Recording density 3408/6816 BPI

Track density 48 TPI

250/500K bits/sec Transfer rate

Access time

4 ms track to track settling 20 ms Head Load Time 50 ms

Also available. \* Key to Floppy Data Entry System (IBM 3740 series compatible)

Termi-Pen (Codeless I/O terminal)

\* Program Loader Mini (Digital Signal to/from audio signal, loaded in audio cassette recorder)

### Sole Exporter

System & Business Machine Section (TOKKP)

C. ITOH & CO., LTD.

C.P.O. Box 136 Tokyo 100-91 Japan

Tel: 03-639-2910 / Telex: J22295 J22296

Manufacturer Y-E Data Inc. Japan 1-20-7, Suehiro Build. Kita-otsuka, Toshima-ku Tokyo, Japan

Circle 198 on reader service card

### INTERFERENCE. WE BUILD THE SOPHISTICATED "TROUBLE MAKER?



Our model 510 Surge Transient Generator provides precise standardized repeatable test signals for determining capabilities, of various equipment, components and systems for possible malfunction or damage caused by line transient surges. (Meets and exceeds IEEE Std. 472-1974/ANS C37.90—1974). Check our reader service card.



Santa Clara, Ca. 95050

### **New products**

markers. The markers can be adjusted, by means of front-panel controls, in both bandwidth and amplitude. They are accurate to within 0.005%. Delivery time for the 1061 is 30 days.

Wavetek Indiana Inc., 66 N. First Ave., Beech Grove, Ind. 46107. Phone Mario Vian at (317) 783-3221 [354]

### Digital correlator has 20-MHz sampling rate

The model SAI-48 digital signal analysis correlator and averager is a high-speed instrument that provides real-time processing of signals in three primary modes: correlation, enhancement, and probability. In its correlation mode it can calculate and display both auto- and cross-correlation functions. In its enhancement mode its principal function is to aid in signal recovery. And in its probability mode it computes density and distribution functions.

Key features include a maximum sampling rate of 20 megahertz, 800 points of pre-computation delay, and digital exponential averaging. The SAI-48 can also capture single-shot phenomena and has the capability to post-process computed functions. Unit prices begin at \$12,900.

Honeywell Test Instruments Division, P.O. Box 5227, Denver, Colo. 80217. Phone Frank Kasper at (303) 771-4700 [356]

### 30-kV power supply has reversible polarity

By withdrawing an interlocked plug on its rear panel and replacing it in the alternate position, the user of a 30-kilovolt power supply can reverse the polarity of the output voltage. The Wallis-Ionex S series unit delivers 1 milliampere over its range of 100 v to 30 kv dc. Its line regulation, load regulation, and ripple are all within 0.01%. The unit sells for \$890.

General Ionex Corp., 19 Graf Rd., P. O. Box 3001, Newburyport, Mass. 01950. Phone (617) 462-7147 [357]

# When you need LEDs or more than LEDs...



Dialight is the first place to look. We can help you do more with LEDs...because we've done more with them.

Discrete LEDs come in a variety of sizes, shapes, colors (red, yellow, green in clear or diffused), with or without built-in resistors.

Low cost logic state fault indicators for trouble shooting complex circuits. Designed for close density PC board mounting.

High-brightness bi-color LEDs (red/green) suitable for go/no-go situations. Designed with unique

lenses for the extra visibility you'll want for your most critical applications.

Snap-in mounting LED indicators reduce labor cost. Available in red, yellow or green with or without built-in resistors.

Whatever you need in LEDs, Dialight's probably got it already. For your free 60-page selector guide and listing of our nationwide stocking distributors, contact us today.

| DIALIGHT | A North American Philips Company | A Nort

### Dialight meets your needs.

Dialight, 203 Harrison Place, Brooklyn, N.Y. 11237 (212) 497-7600

Circle 199 on reader service card

# **CUSTOM**

Call Dennis Olson (714) 759-2411

Or send for new brochure: 500 Superior Ave., Newport Beach, CA 92663

### HUGHES

HUGHES AIRCRAFT COMPANY
MICROELECTRONIC PRODUCTS DIVISION Circle 272 on reader service card

# **CUSTOM**

Call Vic Gill (714) 759-2411

Or send for new brochure: 500 Superior Ave., Newport Beach, CA 92663

### HUGHES

HUGHES AIRCRAFT COMPANY
MICROELECTRONIC PRODUCTS DIVISION Circle 200 on reader service card

### From Electronics Magazine Book Series. Zero-risk trial offer.

# TRONICS

#### Circuits for **Electronics** Engineers

Contains 306 circuits arranged by 51 functions from Amplifiers to Voltage Regulating Circuits. Saves design drudgery, \$15.95

Title

Zip

|Electronics Book Series .

IP.O. Box 669, Hightstown, N.J. 08520

\_\_\_ copies of "Circuits for Electronics Engineers" at \$15.95 per copy.

Discounts of 40% on orders of 10 or more copies. I must be fully satisfied or you will refund

Ifull payment if the book is returned after tenday trial examination.

☐ Payment enclosed ☐ Bill firm ☐ Bill me

State

Charge to my credit card:

☐ American Express ☐ Diners Club ☐ BankAmericard ☐ Master Charge

Acc't No.

Date exp.

On Master Charge only, first numbers above name.

Name

Company

Street

City

Signature

### **New products**

Communications

### 3-in-1 modem provides direct phone link

A microprocessor-controlled modem from Vadic Corp. automatically recognizes and communicates with the Vadic VA3400 modems, as well as with the Bell System's 103 and 212 modems. The new three-in-one modem, the model VA3467, also connects directly to switched telephone lines, thus eliminating the need to rent a data-access arrangement from the phone company.

The VA3467 is aimed at timesharing firms and companies that must support 1,200-bit-per-second dial-up operations and have datacommunications networks with different-type modems at remote sites. And since it offers direct connection to a single phone line, split rotors are eliminated.

The VA3467 is compatible with three distinct configurations: Vadic's VA3400 (1,200 b/s full duplex), Bell's 103 (300 b/s full duplex), and Bell's 212 (1,200 b/s full duplex). It

The direct connection. Seven-inch-high chassis houses eight VA3467 modems including built-in data-access arrangements.

has an automatic-recognition sequence that identifies any of those calling modems without disturbing normal connect protocols—terminalinterface operation is completely transparent to the actual modem used. Another feature is the VA4367's ability to continuously test itself by turning on its transmitter, switching its receiver to the same carrier frequency, and sending a scrambled mark into the transmitter.

Other versions are available for those who do not need all three capabilities. The VA3427 combines a VA3400 and a Bell 212; the VA3437 supports a VA3400 and a Bell 103. The VA3467 is priced at \$850, the VA3427 and VA3437 at \$800 and \$700, respectively, in single units, with shipments starting in January 1978. They can be purchased from the company or leased though General Electric's Instrumentation & Communications Equipment Service group.

Vadic Corp., 222 Caspian Dr., Sunnyvale, Calif. 94086 [401]

### 75-ohm delay lines cover 0 to 2,075 nanoseconds

A line of inductance-capacitance video delay lines contains 10 variable-delay units. The 75-ohm devices have delay ranges of 0 to 10.5 nano-





### The General Purpose **EXPLORER II**

New digital oscilloscope for low-frequency, high precision signal measurement.

EXPLORER II is an oscilloscope in every sense of the word—for use in the same way as other oscilloscopes. It has the same sweep controls, trigger controls and amplifier controls.

What makes it different is its precision and enormously improved waveform storage capability. EXPLORER II is a digital oscilloscope. Because of this and careful human engineering, a dozen old operating problems have just disappeared.

Great Storage: Storage occurs at the touch of a button. The captured waveform has the same quality as live waveforms — amazing quality. There is no trace fading or blooming. If you wish, you can tuck the waveform away, out of sight, for later recall and continue to use the oscilloscope for other things in the meantime. Storage at the touch of a button means more than saving operating steps. It means no blank screen before storage.

Automatic Persistence: The EXPLORER always displays the last signal waveform until the next signal occurs, even when signals occur only rarely. There are no adjustments or mode switching.

CRT Independence: No longer is accuracy dependent on the cathode-ray tube. True voltage and time numerics for any selected point end that problem. The numbers can show differences in both times and voltages, for two selected waveform points. Accuracies and resolution are an order of magnitude greater.

Write-through Storage: At the touch of a switch, both live and stored waveforms are shown superimposed. This is far better than split-screen storage, which shows a stored waveform in one area of the screen and live waveforms in another. Write-through storage allows you to see changes as small as 0.025% while they are happening!

**Dual Beam:** EXPLORERS with two-channel plug-ins are "dual beam". Both signals are accepted together. There is no need for alternate sweeps or chopped sweeps.

Cursor Triggering: It used to be that all you could see on a 'scope was the result of an event. With EXPLORER you can see what caused an event to happen. Move the vertical marker line to any desired position. In the cursor trigger mode, this will be time zero, the time the sweep trigger occurs. The trace shows you what happened before and after the trigger.

Easy Operation: It's as difficult to describe the "feel" of EXPLORER II as it is to describe the feel of a great sports car to someone who has only driven "soft" passenger cars. But once you've had an hour or two of familiarization and used this new digital 'scope you'll know. You'll never want to go back to anything else.

#### EXPLORER III

Identical to EXPLORER II, this unit incorporates an added module that contains a magnetic disk memory and a digital input/output port. To document waveforms for future reference, the diskette preserves the accuracy and resolution of the original. There is no compromise as with a photo document. For computation, the digital I/O allows interface to computers and calculators, also IEEE 488 interface.

**See It Demonstrated.**To really appreciate either of these new 'scopes you have to see them in action. For complete details, including descriptive brochures, send the reader service card or call Jim Bartosch at 608/271-3333.





Madison, Wisconsin 53711 Telephone: 608/271-3333

### **New products**



seconds in 0.5-ns steps up to 0 to 2,075 ns in 25-ns steps. The delay lines are available in models that can be controlled by toggle switches, rotary switches, and strappable terminals. They provide essentially flat operation out to 5.5 megahertz. Prices for single units start at \$55.

Allen Avionics Inc., 224 East 2nd St.,

Allen Avionics Inc., 224 East 2nd St., Mineola, N. Y. 11501. Phone (516) 248-8080 [403]

### 520-MHz frequency counter sells for only \$450

The model 1850 frequency counter is a six-digit instrument with a range of 5 hertz to 520 megahertz and a price tag of only \$450. The instrument, which will typically read to 650 MHz, has a period mode for high-resolution measurements in the range from 5 Hz to 1 MHz.



Fully autoranging in both its normal and prescale modes, the counter automatically positions its decimal point and indicates whether the reading is in kilohertz or megahertz. It is built around a temperature-compensated crystal-controlled time base.

B&K-Precision, 6460 W. Cortland Ave., Chicago, III. 60635. Phone (312) 889-9087 [405]



You can count on Ferranti-Packard's electromagnetic 7-Bar display module to give you the electronic compatibility you need plus the reliability and visibility your customers demand.

Only 7 moving parts to each display module — no complex mechanical linkages to wear out, or incandescent lamps and neon tubes to burn out.

Performance-proven for over 5 years, the simple design and construction.

Performance-proven for over 5 years, the simple design and construction, backed by Ferranti-Packard research and engineering, gives you the combination of reliability, visibility and flexibility that no other read-out component can match.

When you design an electronic read-out system, Ferranti-Packard display modules will help you do it better. It's clearly the display module you should consider. See the difference for yourself, write or call us and we'll prove it.

When clear displays count — Specify Ferranti-Packard.

### FERRANTI PACKARD

### **Ferranti-Packard Limited**

Electronics Division, 121 Industry Street, Toronto, Ontario, M6M 4M3, Canada Telephone: (416) 762-3661 Telex: 06-22007

# Announcing the 20th annual world markets forecast by the editors of Electronics


The regular January 5, 1978 issue of Electronics magazine will contain the editor's annual analysis and forecast of the international electronics market. This highly respected report is eagerly awaited each year by senior engineers and engineering management. It has become an indispensable planning tool for decision-makers around the world.

No other publication in the field prepares a world markets forecast. It is read, re-read, routed to others, saved, filed,

and referred to time and again throughout the year. Exposure to advertising is increased, especially among those levels of management which are relatively inaccessible to your salesmen.

Each year, more advertisers become aware of the potential of this issue for increased advertising productivity. The advertisers' index reads like a directory of the companies best known for their marketing acumen. Some manufacturers, in addition to their regular product campaigns, choose this issue very deliberately to carry their corporate messages.

Closing date for the World Markets Forecast issue of Electronics is December 12, 1977. To be sure space is available, please reserve as early as possible.



### PROVEN PERFORMANCE CRYSTAL CLOCK OSCILLATORS



Motorola's K1100A leads the industry with a crystal clock oscillator that has a proven track record of more than two million units. That's right... over two million oscillators are in use by satisfied, repeat customers.


How versatile is the K1100A? With over 1200 frequencies already designed, and same-day shipment for standard stock frequencies of 4, 4.9152, 5, 10, and 20 MHz, you make the decision.

Oscillators are available from 250 kHz to 70 MHz,  $\pm 0.01\%$  stability from 0°C to 70°C, TTL-compatible, and standard +5V dc input.

For full specifications and prices on the oscillator that design engineers trust, write Motorola, Component Products Department, 2553 N. Edgington, Franklin Park, Illinois 60131.

Or call (312) 451-1000, ext. 4183.





You're looking at an X-Y recorder so reliable that manufacturers are building the Spartan Model XY 575 into their own medical, gaging, geophysical and test equipment of all kinds. It could deliver big benefits in your product or lab in a hurry.

Esterline Angus pioneered accountability technology, so it was only logical that this X-Y has  $\frac{3}{2}$  fewer parts ( $\frac{1}{2}$  of them moving parts). Consider:

- 1. Extremely rapid pen response of 45 in/sec.
- 2. Throwaway pen and ink cartridge, mess-free. Users love it.
- 3. Protective features: auto-powerdown on overrange, wearout-proof feedback pot, 200 VDC common mode, and floating guarded input.
- 4. 45 cps pen drop for plotter applications.
- 5. Back-lighted grid for accurate paper alignment.

Esterline provides accountability in recording. The Model XY 575 OEM is only one of *four* great X-Y's including lab models with many ranges, time bases, and options, plus an X-Y-Y' two-pen recorder. Get Bulletin E500. Esterline Angus Instrument Corporation, Box 24000, Indianapolis, IN 46224. Tel. 317-244-7611.

# Designers found the reliable X-Y



Circle 219 on reader service card

# vou're using the most

Out-of-date information could affect your designs adversely and new data on new lamps could lead the way to new ideas. Take a minute to check the dates on these seven catalogs be sure you've got the most up-to-date information at your fingertips, and help you pick the best GE miniature lamps for each of your design needs.

 All catalogs are free.
 Data and information is current. Organized for quick, easy, accurate reference.
 Saves you valuable time.



#3-5257-R #3-525/-H
Halogen-Cycle Lamps
Revised April, 1977. The 12 pages
feature greatly expanded data including lamp specifications, characteristics, design considerations
and selection guide.



#3-7070
Miniature Lamps
Revised April, 1977. Features almost 100 new lamps not previously listed; covers almost 600 lamps,



#3-5259R2 All-Glass Wedge Base Lamps Revised March, 1977. Contains all specifications and data for 11 newest wedge base lamps plus revised drawings and engineering specifications on the full line.



#3-6383 Farm Tractor Sealed Beam Lamps
Revised September, 1976. Four pages feature the expanded line farm equipment, including diagrams of lamp beam patterns



#3-6016 Sub-Miniature Lamps
Revised May, 1976. Includes latest
data on more than 194 lamps of 1/4"
diameter and smaller, 28 pages.



Form 5000
Miniature, Sealed Beam and Glow Lamps
Revised February, 1976. Features
36 pages of technical lamp data covering 950 lamps, both miniature and sealed beam. Lists lamps in numerical order



#3-5211
Sealed Beam Lamps
Revised September, 1975. Lists electrical and physical specifications, applications and numerical index in 16 pages.

### To get your free GE lamp catalogs today.

Call your local GE Miniature Lamp Products Dept. Specialist. Or write: General Electric Miniature Lamp Products Dept. #3382, Nela Park, Cleveland,

GENERAL

### New products/materials

A sealing glass for liquid-crystal displays provides both hermeticity and high strength because of the strong chemical bonds that form between the soda-lime glass plates and the sealing glass when they are heated together. Designated type 410, the sealing glass has relatively low glazing and sealing temperatures-on the order of 500°C. Its



most outstanding characteristic, however, is its printability. The suspended glass particles will not settle out in the jar or on the screen, and screened lines will retain vertical walls. Further, the material will not dry on the screen during coffee breaks or lunch periods.

Qualco, One First St., Los Altos, Calif. 94022. Phone (415) 964-7666 [476]

Ternary thick-film conductor compositions, Conductrox 3535 and 3567, combine many of the features of gold and platinum-gold conductors with the economy of gold-free formulas. In addition to wire-bondability by ultrasonic and thermalcompression methods, the conductors print readily and accept most solders. The resistivity of the compositions is in the range of 8 to 15 milliohms per square—lower than that of most platinum-gold and palladium-silver pastes.

Aged adhesion of soldered wires, a limiting factor with binary conductors, is not a problem with either formula. Peel strength is unchanged after aging for 48 hours at 150°C. In production quantities, 3535 and 3567 sell for 90 cents a gram and \$1.37 a gram, respectively. They are

### Aerospace technology at a down-to-earth price... the \$3 pot.



U.S. price - \$3 in quantity.


### **New Spectrol Model 157 Precision Pot**

Spectrol now introduces the first low-cost, high-quality, 7/8" singleturn conductive plastic pot with features you'd only expect to find in a more expensive aerospace pot. Features like rugged machined-aluminum housing...ground stainless-steel shaft...short length behind panel (.345")...no glued joints...high-current capacity...standard linearity of ±1%. Wirewound and cermet units are also available in this series, and they come in servo or bushing mounts, with a center tap option. For more information, contact your nearest Spectrol factory or authorized representative.



### SPECTROL ELECTRONICS GROUP

UNITED STATES Spectrol Electronics Corporation P.O. Box 1220, City of Industry, Calif. 91745, U.S.A. • (213) 964-6565 • TWX (910) 584-1314 UNITED KINGDOM Spectrol Reliance Ltd. Drakes Way, Swindon, Wiltshire, England • Swindon 21351 • TELEX: 44692 ITALY SP Elettronica spa Via Carlo Piscane 7, 20016 Pero (Milan) Italy • 35 30 241 • TELEX: 36091



Fast TurnAround

25 days from your design to prototype circuits

Low Cost

Save 80% over a fully custom design

• Reduced Circuit Size

Multiple saving by reducing circuit size 90%

Proven Process


Standard CMOS assures high reliability and dependable delivery

### INTERNATIONAL MICROCIRCUITS, INC.

3004 Lawrence Expwy., Santa Clara, Ca. 95050 (408) 735-9370

Circle 274 on reader service card

### CARBON FILM FIXED RESISTORS



1/2 Watt 5% tol. 1/3 Watt 5% tol. 1/4 Wett 5% tol. 1/16 Watt 5% tol.

2%Tolerance is available

### CARBON TRIMMER POTENTIOMETERS





1/10 Watt( 8mm dia) 1/8 Watt(10mm dia)

### BULTRONICS CORP.

P.O.Box 39, Suminoe, Osaka, Japan(559) Telex: 64548

We are looking for agents.

### New products/materials

platinum-palladium-silver formations and are available in jars or in throwaway plastic syringes.


Thick Film Systems Inc., 324 Palm Ave., Santa Barbara, Calif. 93101. Phone (805) 963-7757 [477]

A semiconductor-grade molding compound, Dow Corning 631, is a hybrid product designed to combine some of the best features of silicone and epoxy materials. Among those of its features that are usually associated with silicone are compatibility with semiconductor chips, ease of use, and moisture resistance. Among its epoxy advantages are high strength. good resistance to salt spray, and a strong lead seal.

The material lends itself well to high-volume transfer molding and can realize cycle times of one to two minutes. It uses a cure system that has no need for nitrogen-containing catalysts—a source of contamination in conventional epoxy systems.

Dow Corning Corp., Midland, Mich. 48640


An RTV silicone rubber with a higher thermal conductivity than conventional silicone rubbers is suitable for potting and encapsulating components from which a sub-



stantial amount of heat is to be dissipated. Eccosil 4952 is a red, pourable composition with a thermal conductivity of 7.5 BTU-in./hr-ft2-°F (0.0026 cal-cm/s-cm<sup>2</sup>-°C). The material sells for \$4.35 a pound in 17pound lots and is available from stock.

Emerson & Cuming Inc., Canton, Mass. 02021 [479]

# A Programmable Attenuator that enhances your equipment...



### ...and your bottom line.

Telonic's new 8360 Series Programmable Attenuators have been designed to boost performance of automatic test equipment, without clobbering your manufacturing costs.

If you're an OEM producing instruments or test gear that need an attenuator, you've probably considered a programmable type—or perhaps are already using one. You know the benefits. Now consider the benefits of Telonic's new series.

DIGITALLY PROGRAMMABLE—via an integral 12-pin connector, the 8360 is totally compatible with the IEEE 488 bus (or the H-P bus)—programmed for automatic systems. Solenoid switches are magnetically latched to minimize power consumption and heat dissipation.

THICK FILM CHIPS—they're used in the 8360 to provide highly accurate attenuation. The distributed field concept combined with an "edge line" conductor has been field proven in thousands of attenuators. And the nature of these thick

The lab version of the 8360 includes a base for benchtop use.

film chips allows high R.F. power ratings—3 watts average, 1 kW peak. Frequency range is DC to 4 GHz.

FOUR VERSIONS—covering dB ranges of 0 to 11 in 1 dB steps, 0 to 70, 110, and 130 in 10 dB steps. And each model comes with three standard input/output connector configurations for easy adaptation to your system design. In fact, the output connector, either "N" or "SMA," can be oriented to be the output of your equipment.

AND NOW COMES THE BEST PART—if you're used to paying \$600 or more for a programmable attenuator, the 8360 gives you a lot of breathing room in your parts cost. With OEM discounts, you can cut that price in half—while giving your customer a better package.

CALL TOLL FREE—800-854-2436
(except in California) and we'll send our new attenuator catalog, take your P.O., or answer any questions you have. Telonic/Berkeley, 2825 Laguna Canyon Road, Box 277, Laguna Beach, CA 92652, Tel; (714) 494-9401

TELONIC/BERKELEY

### **EMR**

### **Frequency Response Analyzers For Every Application**

From the viscous elastic properties of films and fibers, to the frequency response of hydraulic actuators . . . for the open loop response of a servo system with the loop closed, or the frequency response of the Brooklyn Bridge . . . EMR has a Frequency Response Analyzer that is just right for your application.

Take the low-cost, easy-to-use Model 1312. It's ideal for production testing and basic measurements of phase and amplitude to 20 kHz. Or choose the Model 1410, the full capability, single-channel instrument that has become the industry's standard for most engineering applications. Then there's the Model 1172, the ultimate Frequency Response Analyzer featuring all-digital signal processing, fully-isolated dual measurement channels and a computer-type keyboard entry. With the Model 1180 Plotter Interface, you can plot Bode, Nyquist, or Nichols diagrams with a conventional analog XY recorder.

Let EMR solve your frequency response problems . . . call or write for details or a demonstration.

Sangamo Weston, EMR Telemetry Division P.O. Box 3041, Sarasota, FL 33578 813-371-0811

SANGAMO WESTON

Schlumberger



Circle 224 on reader service card

### SUPER MINIATURE

Dimension: mm

Ø3.8 mm

NL-8S

6.0 mm

6.0 (mm

22mm

19mm

Neon Glow Lamps

Circuits Volts ..... AC 105-125 Series Resistance····· 150KΩ Nominal Current ..... 0.3mA Total Flux ..... 20mlm MIN. Average Life Hours ··· 30,000

### CLEAR-GREEN

### Fluorescent Glow Lamps

Circuit Volts ..... AC crDC 105-125 Series Resistance···· 33KΩ Nominal Current ..... 1.6mA

Total Flux(MIN.) ..... AC:120mlm, DC:130mlm NL-35/G Avg. Life Hours ..... AC:30,000 DC:40.000

Circuit Volts ..... AC 105-125 Series Resistace ····· 27ΚΩ Nominal Current ..... 1.5 mA Total Flux ..... 90 mlm MIN. Avg. Life Hours ..... 20,000

### MAIN PRODUCT

NEON GLOW LAMP, XENON FLASH LAMP, NL-21/G RARE GAS, DISCHARGE LAMP. MINIATURE: BLACK-LIGHT, UV-LIGHT,


FLUORESCENT COLOR-LIGHT.

### ELEVAM ELECTRONIC TUBE CO., LTD.

NO. 17-8 CHUO 2-CHOME OTA-KU, TOKYO JAPAN TELEPHONE : 03 (774) 1231 $^{\sim}$ 5

EXPORT DIVISION: JAPAN NANOTRONIX CO., LTD. OTA-KU TOKYO, TELEPHONE. (03)775-4811 TELEX 246-6583 JNANOX

Circle 275 on reader service card



You can now dimension, sort and search any array that will fit in your memory. With Infotek's Fast Basic III ROM the 256 row-column limit no longer exists!!!!

Infotek Systems

1400 N. BAXTER STREET . ANAHEIM, CALIF. 92806 (714) 956-9300 • TWX 910-591-2711

# TEAC's Done It Again Open Reel Performance in the Cassette Mode

The TEAC R-81 has all the features you look for in a high quality data recorder, but with a big plus: 4 speeds.

Open reel data recorders offer 4-speed selection as a standard feature, but cassette types have been limited to the single speed mode.

The R-81 changes all that, giving you the convenience and simplicity of a cassette recorder along with all the options of 4-speed variability. High-frequency data can be recorded at high speed and reproduced at low speed—or low-frequency data converted to a higher frequency, for analysis by a general-purpose frequency analyzer.

There are 7 channels, too, one switchable for noise compensation (fourth channel), another for memos (seventh channel)

The R-81 also features the clean, rational styling that TEAC cassette tape decks are famous for. The front-loading configuration, with all the controls on the front panel, is ideally convenient for desk-top use. It also facilitates mounting with other equipment made to professional standards, as does the body size, which meets EIA specifications.

And the R-81 is ready to operate anywhere. In addition to AC (with adapter) and DC power sources, you have the full portable versatility of dry cell battery operation.

TEAC's done it again: advanced the art of data recording. And you're the winner.



### TEAC

TEAC CORPORATION, 3-7-3, Naka-cho, Musashino, Tokyo, Japan

U.S.A.: B.J. Wolfe Enterprises Inc., 10760 Burbank Blvd., North Hollywood, Calif. 91610 England: International Instruments Ltd.,

Cross Lances Rd., Hounslow, Middx W. Germany: nbn Elektronik Starnberg, 813 Starnberg, Max-Emanuel-Str. 8 France: Tekelec Airtronic S.A., Cite des Bruyeres,

Rue Carle-Vernet 92 Sevres Holland: SIMAC Electronics, Veenstraat 20, Veldhoven Italy: A.E.S.S.E. S.R.L., Corso Lodi, 47 20139 Milano Norway: Rodland & Rellsmo A.S.,


Gladengveien 3A,Oslo 6 Sweden: Teleinstrument ab, Maltesholmsvagen 138, Vallingby Switzerland: Wenger Datentechnik, Bruderholzstrasse 45,

4053 Basel Denmark: Danbit, Plantagevej 23, 2680 Scolrod Strand Australia: Jacoby, Mitchell Ltd., P.O. Box 70, Kingsgrove, N.S.W. 2208

### **New literature**

Specialty transformers. The eighth edition of Underwriters Laboratories' "Safety Standard for Specialty Transformers" contains the requirements for air-cooled transformers and reactors for general use; transformers for use with class-2 remotecontrol, low-power, and signal circuits; ignition transformers for gas burners and oil burners; and gastube-sign transformers for inert-gas tubes. Copies may be obtained at \$3.50 each, or \$9.00 for the edition plus any issued revisions. Underwriters Laboratories Inc., Attn: Publications Stock Dept., 333 Pfingsten Rd., Northbrook, Ill. 60062

Instruments. Thousands of instruments for rent, lease, or sale are listed in a 168-page book. All instruments, including analyzers, counters, digital voltmeters, oscilloscopes, recorders, and voltmeters, are listed with ordering and technical information. A separate section is designed



for the engineer who needs to know whether to rent or buy. Metric Resources Corp., 822 Airport Blvd., Burlingame, Calif. 94010. Circle reader service number 422.

Solder masking. A four-page appli-

cation note, "Solder-Masking Solder-Plated Circuits," explains how to solder-mask solder-plated and reflowed circuits. It discusses the problems encountered and the limitations on the effectiveness of this technique and provides some design ideas. Solder-Masking Reprint, The Sibley Co., Bridge Street, Haddam, Conn. 06438 [423]

Oscillators. A 44-page catalog provides information on crystal, temperature-compensated crystal, high-stability, voltage-controlled, and LC oscillators, with specifications for each type. Also discussed is how to select case configurations, input voltages, waveforms, and temperature ranges. Greenray Industries Inc., 840 West Church Rd., Mechanicsburg, Pa. 17055 [429]

Industrial and scientific problems. Ideas for solving a variety of industrial and scientific problems with

### Biggest DVM news of the year

You name it, Systron-Donner has it! Bench, portable and systems models for every conceivable 4½-digit DVM application. Every model is brand new, packed with all the features you could possibly want. Do you need a battery pack or an analog meter? Do you need to make dBm measurements on tones? How about BCD outputs or complete IEEE-488 interface capability? Systron-Donner's new series of 4½-digit DVM's offers all these capabilities and much more.



### Classy new portables.

These rugged performers for field or lab use come with all five functions (DCV, DCI, resistance, and true RMS ACV and ACI) plus autoranging. Choice of DC accuracy of  $\pm 0.05\%$  or  $\pm 0.02\%$ . Also with or without dBm. Options: Battery Pack and analog meter.

	-		
Mode		~ A ~~	uracies
		- A.C.	
			41 40101

7141A ± 0.05%; 7141B ± 0.02% 7142A ± 0.05% with dBm capability 7142B ± 0.02% with dBm capability digital counters are presented in the "Counting Idea Booklet." It contains sketches that illustrate how to solve problems of production-rate control, in-process monitoring, and remote flow monitoring and control. Nationwide Electronic Systems Inc., 1536 Brandy Pkwy., Streamwood, Ill. 60103 [424]

Products and services. A 40-page digest gives information on tapes, resins, flexible insulation and tubing, and equipment. Application information and technical characteristics are provided for each product. A service section describes how to obtain the best performance from the product and how to reduce costs. Industrial Electrical Products Division, P. O. Box 33600, 3M Center, St. Paul, Minn. 55133 [427]

Panel meters. Product descriptions, application information, and prices for more than 12 line- or logic-



powered digital panel meters and instruments are provided in an 80-page booklet. The booklet also offers information on how to select DPMs for a specific application. Analog Devices Inc., P. O. Box 820, Norwood, Mass. 02062 [431]

Materials. A 40-page catalog offering products and services for the semiconductor industry is available from Dyna-Craft Inc., 2919 San Ysidro Way, Santa Clara, Calif. 95051 [426]

Miniature switches. Featured in a 48-page catalog are switches and



# A 4½-digit DVM for every application!



#### Powerful bench instruments.

A workhorse series with all five functions, autoranging and a neat choice of options including BCD output, IEEE-488 bus, and rack mount. DC accuracy: ±0.02%.

#### **Model Features**

7241A 5 functions, 26 ranges 7244A with IEEE-488 capability



### "Thin Line" for GPIB systems—under \$1,000 loaded.

Here's the first 4½-digit DVM designed around the IEEE-488 bus. Model 7344A is a full rack width, but only 1¾" high. Everything comes standard: IEEE-488 interface, DC volts, true RMS AC volts, and rack mount. DC accuracy: ±0.02%. There's nothing like it! Get the full details on S-D's "think ahead" DVM's. Contact Scientific Devices or Systron-Donner at 10 Systron Drive, Concord, CA 94518. Phone (415) 676-5000.

Circle 226 on reader service card



Ours have better specs, because we're system designers, like you, and we understand the need for generous circuit margins, for smaller "error budgets," for greater transient immunity.

Check our tighter static and dynamic regulation, our lower T.C.'s, our lower RMS and p-p ripple (wideband).

Ours use premium components. We don't components. We don't component standards we've always maintained for our function modules. An Intronics \$29 supply uses the same premium components we use in a \$300 CRT correction module.

Ours are designed more conservatively. They have to be, because we back them by the same warranty, and provide the same post-sale service, engineer-to-engineer, that we have always provided in support of our most sophisticated computing modules — and we simply can't afford marginal behavior.

Ours are tested more thoroughly, because we have to be certain they'll support our precision function modules (about 30% of our supplies are bought to power other Intronics modules). So we check every key parameter on 100% of our power-supply production.

Ours meet your EMI/
RFI needs, for virtually
any environment and application . . .
again, because you may be buying
them to power Intronics circuits.
Our modules are well filtered,
and have broadband control of
critical impedances.

Ours have better thermal design. We've minimized hot-spot-to-case gradients, selected case materials and configurations that optimize convection transfer and insure void-free thermal continuity by incorporating the same potting technique as used on our high-rel modules.

We are systems designers, like you . . . and that means we design power supplies the way you would for yourself. Then we build them at high-volume rates, and share the savings with you.

FREE Send for this frank, no-nonsense handbook on power-supply selection and applications engineering. You'll enjoy and profit from its 20 pages of solid technical materials, plus complete

57 Chapel St., Newton, Mass. 02158 U.S.A. Tel: (617) 332-7350. TWX: 710-335-6835.

SELECTION AND APPLICATION OF MODULAR data on all 78
Intronics AC/DC
and DC/DC
modules . . .
the ones that
give you more,
but don't cost
you more.




#### **New literature**

options for a wide range of actuators, bushings, and terminations. Specifications and descriptions are given for a wide variety of subminiature and microminiature switches, including toggle, rocker- and leverhandle, printed-circuit mounting, and snap-action, alternate-action, and momentary push-button. Included are an ordering guide and a list of foreign and domestic distributors. C&K Components Inc., 103 Morse St., Watertown, Mass. 02172 [425]

Crystal testing. A two-page application note that discusses how to characterize a quartz crystal for use in a filter or oscillator by using a spectrum analyzer and tracking generator is being offered by Marconi Instruments, Division of Marconi Electronics Inc., 100 Stonehurst Ct., Northvale, N. J. 07647 [428]

Cables and connectors. Information on connectors and cable assemblies in miniature- and subminiaturecoaxial, and twin-axial, triaxial, and



quadraxial styles is presented in a 40-page catalog. Trompeter Electronics Inc., 8936 Comanche Ave., Chatsworth, Calif. 91311 [430]

Magnetics. A 14-page booklet discusses and illustrates the use of custom magnetics in modern circuits and provides application information

# If you have one of these...



you can start automatic testing with one of these.



Now you can get into automatic testing equipment (ATE) for well under \$10,000, total cost.

All you need is one of the units pictured, the new SPG-800 Synthesized Programmable Generator, and a little do-it-yourself effort. Just use one of the units pictured to store your test procedure program with simple instructions to command the SPG-800 (and any other programmable instruments you use) and you're off and

No more knob spinning. No more hooking up counters and scopes and voltmeters to your signal source. Now automatic testing is within reach of every manufacturer—along with the savings in time and labor it means.

And the Model SPG-800 is a modular instrument. So you can get started with just the basic unit for only \$3195. It is a combination programmable function generator operating in the 0.1Hz to 13MHz range and a programmable DC voltage source.

Now or later, add Interstate's low cost field-installable plug-in cards and you'll have a programmable synthesizer and pulse generator too-four programmable test instruments in one

Interfacing the SPG-800 is easy, too. Use its basic ASCII interface or one of its (optional) plug-in cards for the IEEE bus, the RS-232C or 20 mil loop or parallel interface.

No matter what configuration you order, you'll find the SPG-800 easy to program and reliable in use. And the optional operator control panel-in English-is easily learned by non-technical per-

sonnel, so you can program it directly,

the day you get it.

If you didn't think your company could afford ATE, it's time to re-think... write today for more information Or call us at (714) 772-2811 or (800) 854-3825 toll free.

#### The new SPG-800

Please send me full information Title Name Company Address City State Zip Telephone Number Interstate Electronics Corp. Department 7000

P.O. Box 3117, Anaheim, CA 92803

INTERSTATE **ELECTRONICS** CORPORATIO

**SUBSIDIARY O** 

# Need a second source on photo SCR isolators?

PART

Spectronics SCS11C1-C3 are pin-for-pin replacements for respective GE H11C1-C3 and MCS2 devices.

5000 VDC Isolation!

PART NUMBER	TURN ON CURRENT (MAX) (I <sub>F</sub> )	FORWARD BLOCKING VOLTAGE (V <sub>DM</sub> @ R <sub>GK</sub> = 10 Kohm)
SCS11C1	11mA	200V (Min)
SCS11C3	14mA	200V (Min)

For more details and delivery information, contact Commercial Component Marketing, 830 E. Arapaho Road, Richardson, Texas 75081, (214) 234-4271.



Circle 230 on reader service card

# BRIGHT NEW IDEA IN REMOTE TIME CODE DISPLAYS

(Small and highly visible—even in direct sunlight)



Systron-Donner's time code specialists have made it perfectly clear: you **can** have a highly visible serial remote display in a space-saving package. Check these features of our new Model 8781:

- Occupies less than 20 inches of panel space.
- Easily visible at 25 ft.—uses planar gas discharge tubes.
- Operates from any time code generator supplying IRIG B.
- Only a single signal line needed between displays and the generator.
- Locate up to 1,500 feet from generator.
- Up to 100 displays from one generator.

Price? \$875 (U.S. only). Quantity discounts available. For details, contact Scientific Devices or Systron-Donner, Data Products Division, at 935 Detroit Avenue, Concord, CA 94518. Phone (415) 798-9900.



#### **New literature**


on wide-band, rectifier, and pulse transformers, and inductors. Polyphase Instrument Co., East Fourth St., Bridgeport, Pa. 19045 [432]

Electronic components. A wide variety of control knobs, miniature switches, panel hardware, and optoelectronic devices are described in a 36-page catalog. It gives specifications and dimensional drawings for commercial and MIL-specified control knobs; toggle, rocker, lever, push-button, and slide switches; and optoisolators and photoconductive cells. Selection guides are provided for easy ordering. Raytheon Co., Fourth Avenue, Burlingham, Mass. 01803 [433]

Thick-film materials. A review of thick-film materials designed to aid an engineer select the correct item for his production needs is contained in a six-page catalog. Base metal, gold, platinum-gold, palladium-gold, and silver conductors, and dielectric materials, cover coats, and resistors are listed with specifications, along with a recommended use for each. Plessey EMD, 320 Long Island Expressway South, Melville, N. Y. 11746 [434]

Machine tools. "The 1978 Directory of Machine Tools and Related Products, Motion Pictures, and Educational Materials" is a 220-page book containing information on machine tools manufactured in the U.S. The book lists every type of machine tool and related product along with the companies that manufacture them, as well as a list of trademarks and the companies that use them. In addition, the directory has a 22-page multilingual table of contents to assist users in locating various types of products. National Machine Tool Builders' Association, 7901 Westpark Dr., McLean, Va. 22101 [435]

Industry research. Everything you always wanted to know about information gathering but were afraid to ask about is discussed in "Competitive Intelligence for the Smaller Company." The booklet provides



# Sooner or later it as bound to get ou

Yes, the Dumb Terminal™ really does have two smarter brothers.

At first, they weren't quite as well known, because their Dumb Brother's smashing success was stealing the show. Although they had been selling quite well along, even without getting constant headlines, like their Brother.

Now, however, Dumb Brother has pulled them into the limelight. And ADM-1 and -2 have decided, after all, that perhaps it's time you knew a little more about how smart they really are.

ADM-2 is the more intelligent of the two, providing you with flexibility of format, security, editing, interface, and transmission. You'll find, among a variety of other outstanding features, up to 8 screen status indicators and a numeric key pad. And a detachable keyboard with 16 function keys. Which give you the ability to access your special program, or form, or instruction.

The ADM-2 is also available in a model compatible with your Burroughs TD-800 Series. The ADM-2B. The ADM-2B adheres to the standard Burroughs poll and address line discipline.

On top of all that, we've made the ADM-2 micro-programmable. And taken all the mystery out of the procedure. Which makes user-microprogrammable simple, quick, and cost-effective. The ADM-2's versatility is limited only by your imagination.

you need, and leave the rest of the "bells and whistles" for someone else. That way, it's more systems adaptable. And it's up to you just how smart you want it to be. The Smarter Brothers have it all. Intelligence, appropriate functions, and sensible cost-perperformance.

You could call the other Smarter Brother, ADM-1, the "with-or-without" terminal. Starting with

some pretty smart standard features, like a stan-

dard 24-line display, a field protection feature with dual-intensity and switch-selectable operating

modes - block mode and conversation mode - you

build up from there. With options like a hardcopy

(line insert, line delete, line erase, character insert, and character delete). Just add the options

printer interface, and display editing capabilities

So, you might as well get used to seeing more of the ADM-1 and -2 in the future. Because we suspect they're going to be in the spotlight from now on.

After all, there's really nothing wrong with exposing your Smarts.



#### The dumb terminal's smarter brothers.

Lear Siegler, Inc., E.I.D./Data Products, 714 N. Brookhurst St., Anaheim, CA 92803;

(800) 854-3805. In California (714) 774-1010.

# **OPTO-METERS**

# two proven performers

Name your most important criteria for a general purpose photometer/radiometer. If you need reliability and an excellent price/performance ratio, we've got it.

40X ANALOG OPTO-METER—a high quality, low cost photometer/radiometer. It's a portable instrument with the accuracy, reliability and capability found in higher priced models. Measurement range: 10-2 to 10-9W; 104 to 10-3fc • flat 450 to 950 nm, and CIE response • NBS traceability to ±2% • no measurable drift • fully calibrated.



80X DIGITAL OPTO-METER—one step up from the 40X with an extra decade of measurement (10-2 to 10-10W and 104 to 10-4fc). The 80X is battery and AC powered for both lab and field use.

These are only two of the UDT Performers—light measurement instrumentation to fill a wide range of requirements. Call or write for applications assistance.



# YEARS AHEAD IN LIGHT detection · measurement · application



#### UNITED DETECTOR TECHNOLOGY, INC.

2644 30th Street, Santa Monica, California 90405 Telephone: (213) 396-3175 Telex: 65-2413

Circle 232 on reader service card

# 1977 Answer Book. It makes your job easier. \$25.

Who makes what? Over 4000 products, more than 5000 manufacturers with their local contracts and distributors, directory of trade names and catalogs, post-paid inquiry cards for 5-second ordering of current catalogs.

		Bectronics
Electronics Bu 1221 Ave. of th New York, N.	ne Americas	GUIDE
\$25 (USA and	a copy of The Answer Canada only, elsewhe ck guarantee if return	re send \$35).
Company		
Street		
City	State	Zip

#### **New literature**

helpful hints on finance and on what may or may not be a legal procedure. Brewster Co., P. O. Box 409, Jackson Heights, N. Y. 11372 [436]

Peripheral systems. A 16-page brochure details the electrical and mechanical parameters and programming considerations for Datel's SineTrac 800 series. The description, background, and user benefits of the analog-to-digital and digital-to-analog peripheral systems are discussed. Block diagrams for program interrupt modes for a-d and d-a systems and also for direct memory access modes for a-d systems are provided. Ordering guides are included. Datel Systems Inc., 1020 Turnpike St., Canton, Mass. 02021 [437]

Switches. Over 300 switches with photographs, line drawings, specifications, and ordering information are described in a 24-page catalog. Slide, snap-action, rotary, pushbutton, toggle, lead, rocker, and paddle switches are covered. Chicago Switch Inc., 2035 Wabansia, Chicago, Ill. 60647 [438]

Data conversion. The challenge of interfacing monolithic integrated-circuit converter designs with micro-processors and computers is featured in the "Analog-Digital Conversion Handbook." The handbook discusses a variety of interfacing techniques, including memory-managed and serial interfacing. Also covered are current designs, technologies, and production techniques employed in conversion circuits. The handbook can be obtained at \$5.95 per copy from Analog Devices Inc., P. O. Box 796, Norwood, Mass. 02062.

Converters. An eight-page brochure covers information on isolation voltage-to-frequency converters. It explains their best use and the resulting problem of high common-mode rejection. Absolute maximum ratings for high- and standard-isolation models and typical applications are given. Dynamic Measurements Corp., 6 Lowell Ave., Winchester, Mass. 01890 [440]

# If you spend more than 20 minutes picking a P.C. connector

It's your guide to the broadest line of printed circuit connectors made by any single manufacturer. We have just about everything and in more combinations and more depth than anyone – more types of contact terminations, insulator materials, mounting styles, contact designs, types of plating.

Send for our catalog. Browse through it and you'll discover that picking out the right printed circuit connector for your job is as simple as it should be.

#### Quick delivery.

And you can get your hands on our connectors, too – in a hurry if need be. We keep a large inventory; so do our distributors.

#### Our "Whatever-you-need-we've-got" department.

As you can guess, we have a lot of tooling filed away. Our production engineers have a unique talent at taking an existing bit of tooling, fiddling with it, and turning out a "custom" connector that's exactly what you need. Your extra cost is only a modest set-up charge...a long way from a full retooling cost. Use the coupon.


...you don't have this catalog.

nan	latest printed circuit connector catc ad your nearest rep. I want to talk to I icular problem I have.	alog. nim about a
NAME:		
TITLE:	TELEPHONE:	
COMPANY:	sulf saw street which the	
ADDRESS:		
CITY:	STATE:	ZIP:

CONNECTOR


Chatsworth, CA 91311 U.S.A./(213) 341-4330/ DATACON DIVISION

Viking Industries, Inc./21001 Nordhoff Street



#### **3 POINTS TO REMEMBER**

- 1. 48 hr. shipment
- 2. U.L. recognized
- 3. 1 yr. warranty



MODEL	RATINGS volts/amps	PRICE (\$) 1 100 250			
QD12/15-0.6 QD12/15-1.7 QD12/15-3.0	±12 to ±15/0.6 ±12 to ±15/1.7 ±12 to ±15/3.0	42 62 79	36 54 67	35 49 64	
QT-1	5/3.0 ±12 to ±15/0.5	69	66	65	
QT-2	5/6.0 ±12 to ±15/1.0	89	82	79	
QT-3	5/9.0 ±12 to ±15/1.0	113	104	100	
QT-4	5/12.0 ±12 to ±15/3.0	159	143	133	
MPS-1	5/3.0; 12/0.6 9 to 12/0.6 or 5/0.38	79	78	77	
MPS-2	5/7.0; 12/1.0 9/1.2 or 5/0.75	95	91	88	

# Deltron inc.

Wissahickon Avenue North Wales, PA 19454 Tel: 215/699-9261 Twx: 510/661-8061

#### **New books**

Fuel Cells for Public Utility and Industrial Power, Robert Noyes, ed. Noyes Data Corp. (Park Ridge, N. J.), 322 pp., \$42.00.

Electronic Processes in Unipolar Solid-State Devices, Dan Dascalu, Abacus Press, 624 pp., \$45.50.

Microcomputer Design and Applications, Samuel C. Lee, ed., Academic Press, 346 pp., \$14.50.

Information Mechanics, Frederick W. Kantor, John Wiley & Sons, 397 pp., \$21.95.

Computer-Communication Network Design and Analysis, Mischa Schwartz, Prentice-Hall Inc., 372 pp., \$18.95.

Topics in Applied Physics, Vol. 17: Electroluminescence, J. I. Pankove, ed., Springer-Verlag, Berlin, Heidelberg, and New York, 214 pp., \$30.40.

Microprocessors from Chips to Systems, Rodnay Zaks, Sybex Inc. (Berkeley, Calif.), 415 pp., \$9.95 (paper).

Angle Modulation, The Theory of System Assessment, J. H. Roberts, Peter Peregrinus Ltd. (IEEE), 278 pp., \$27.50.

Logic Designer's Manual, John D. Lenk, Reston Publishing Co. (Prentice-Hall), 504 pp., \$18.95.

Spectrum Management Techniques, Multi-Volume EMC Encyclopedia Series, Vol. 2, Donald M. Jansky, Don White Consultants Inc. (Germantown, Md.), 200 pp., \$25.00

Digital Modulation Techniques in an Interference Environment, Multi-Volume EMC Encyclopedia Series, Vol. 9, Kamilo Feher, Don White Consultants Inc., 200 pp., \$25.00.

Modern Crystal and Mechanical Filters, Desmond F. Sheahan and Robert A. Johnson, eds., IEEE Press (distributed by John Wiley & Sons), 455 pp., \$12.95 (paper).


#### QUESTION:

WHEN IS 3 NOT A CROWD?

#### ANSWER:

IN THICK FILM HYBRID MULTILAYER CIRCUITS USING . . . TFS's COMPATIBLE THREESOME:

- 3017 GOLD
- 1017 RCA DIELECTRICS
- 850-D RESISTORS



# SCREEN PRINTABLE PASTES FOR GROUND FLOOR RESISTORS STABILITY ON TOP OF DIELECTRIC

3017 GOLD

 New • Very Dense • Fine line • High initial and aged bond adhesion

#### 1017 RCA DIELECTRIC

• Low K (6-8) and high I.R. • Glass-ceramic designed for multiple refirings and support of 850-D Series Resistors.

#### 850-D SERIES

 Applications on top of dielectric • Resistors: 1 to 1MΩ/sq. • TCR: 0 to ±100 ppm/° C • Trimable by laser and abrasion.

ALL ON TFS FAST FIRE 25 MIN-UTE FURNACE CYCLE-850° C.




For full information contact THE PASTEMAKER

THICK FILM SYSTEMS, INC.
324 PALM AVENUE, SANTA BARBARA, CALIFORNIA 93101
TEL: (805) 963-7757

# **Pure logic and hard facts**

- 1. In high-frequency power switching, heat is a prime factor in Darlington failure.
- **2.** Turn-off time is the dominant cause of destructive temperature rise.
- **3.** The faster the turn-off, the cooler the Darlington, the greater the reliability.

Take a look at competitive Darlingtons in an actual 20 KHz bridge converter circuit:



# TRW operates at the lowest temperatures for the greatest reliability in high-frequency Darlington off-line switching regulators

And when you're working with high-power, fastswitching Darlingtons that's no small thing. When you need reliability at high frequencies, the best combination of switchtime and energy capability add up to greater efficiency and longer life. And what circuit are you about to design that doesn't deserve the best? Particularly when TRW Darlingtons are not only com-

petitively priced, but are also immediately available in any quantity.


To get all the facts on TRW's high-frequency Darlington, use coupon or phone John Power at (213)679-4561.

An Electronic Comp 14520 Aviation Boule		
☐ Please send me of transistors.		
☐ Please send me s		voltage and
Name		
Name Company Name		
	t.	
Company Name	C.	

# TRW POWER SEMICONDUCTORS

ANOTHER PRODUCT OF A COMPANY CALLED TRW

# WHO NEEDS A VIDEO OP AMP



#### With 1 GHz Gain Bandwidth Product and 70 Nanosecond Settling to 0.01%?

Far more people than you would have imagined! People who require the performance of a true differential input op amp at frequencies from DC to beyond 100 MHz, with the ease of using a 741 at 100 kHz. Those who want a  $\pm 5$  volt output to reach an accuracy of 0.01% in 70 nanoseconds. Others who require this state-of-the-art performance from -55°C to +125°C, and many more who require the high reliability provided by MIL STD 883 processing.

Your application may not need the full temperature range or the hermetically sealed DIP, but for many industrial applications these and other features of the new Video Op Amp offer you vital reliability.

All of this and more is available to you off-the-shelf with the 1435 - The op amp that solves problems you didn't even try to solve before!



Allied Drive at Route 128 Dedham, Massachusetts 02026 Tel: (617) 329-1600

TWX: (710) 348-6726 Telex: 92-4439 Cable: TELEPHIL

Circle 236 on reader service card



A P made the first solderless breadboard way back in 1968, and we still make them best.

Because our experience taught us to avoid the pitfalls that can mean circuit errors. We do it by paying attention to details. Like using non-corrosive nickelsilver in our frankly superior terminals. And like using a vinyl-insulated back that prevents short circuiting. That's why you can count on the reliability of our solderless boards when you specify A P ACE All Circuit Evaluator Boards, Super Strips™, Terminal and Distribution Strips.

Order from your A P distributor today. For the name of the distributor nearest you call Toll-Free 800-321-9668

Faster and easier is what we're all about.

Part No.	ACE Model No.	Tie Points	DIP Capacity	No. Buses.	No. Posts	Board Size (inches)	Price Each
923333	200-K (kit)	728	8 (16's)	2	2	4-9/16x5-9/16	\$18.95
923332	208 (assem.)	872	8 (16's)	8	2	4-9/16x5-9/16	28.95
923334	201-K (kit)	1032	12 (14's)	2	2	4-9/16x7	24.95
923331	212 (assem.)	1224	12 (14's)	8	2	4-9/16x7	34.95
923326	218 (assem.)	1760	18 (14's)	10	2	6-1/2x7-1/8	46.95
923325	227 (assem.)	2712	27 (14's)	28	4	8x9-1/4	59.95
923324	236 (assem.)	3648	36 (14's)	36	4	10-1/4x9-1/4	79.95

Send for our complete A P catalog, The Faster and Easier Book.

## **AP PRODUCTS**

Box 110 • 72 Corwin Drive Painesville, Ohio 44077 216/354-2101 TWX: 810-425-2250



# oes its broad Even though the Centronics 700 series is a continually expanding

printer family - currently 9 models and a range of print speeds from 60 to 180 cps - there's

much more to it than just breadth of line. For example, there's a choice of 6 different types of forms handling capability; choice of uni- and bidirectional operation; and choice of 80 and 132-column formats. Why so much choice? It comes from the simple, highly flexible modular 700 series design that delivers superior reliability, exceptional parts commonality and competitive prices.

And like all Centronics printers, the 700 series is fully supported by the largest worldwide service organization of any printer company. For complete 700 series information write or call today. Centronics Data Computer

Corp., Hudson, NH 03051, Tel. (603) 883-0111.



CENTRONICS PRINTERS **Simply Better** 

## Classified section for engineering/technical employment opportunities

CLASSIFIED SALES REPRESENTATIVES

 Cleveland
 Mac Huestis
 216/781-7000

 Dallas
 Mike Taylor
 214/742-1747

 Denver
 Shirley Klotz
 303/837-1010

 Detroit
 Mac Huestis
 313/873-7410

Houston . . . Mike Taylor Los Angeles . Stan Kassin . New York . . . Larry Kelly Philadephia . . Dan Ferro . . . 713/659-8381 213/487-1160 212/997-3594 215/568-6161 Pittsburgh . . . Dean Genge . . 412/391-1314
San Francisco . M.E. Kenny . . . 415/362-4600
Stamford . . . . Holt Buchanan . 203/359-2860
XEROX 400 TELECOPIER . . 212/997-6800

I'm my own boss.

# I work for Schlumberger.



There's nothing routine about a career with Schlumberger. Just ask Larry Gutman who joined us a year ago.

"Working as a field engineer for Schlumberger is everything I thought it would be," says Larry. "I like to be outdoors. Work with my hands. And keep my own hours.

"I'm responsible for myself, my crew—and everything that happens on the job. It's really exciting to make things work out right.

"Some people aren't cut out for this. It takes a special person. I work long, hard hours—and sometimes it's tough to stay awake.

"But it's worth it. Because I'm satisfied with myself and my work ...and you can't beat the money."

Ready for a challenge? Maybe this is for you. If you're fresh out of school with a degree in electrical engineering—or if you have no more than three years' work experience, let's talk. Just fill out the coupon and we'll tell you all about the career opportunities with Schlumberger.

Or call collect: (713) 928-4218. Openings are available in Louisiana, Texas and Oklahoma.

Schlumberger Well Services P.O. Box 2175 Houston, Texas 77001

N

#### **POSITIONS VACANT**

Georgia Tech Engineering Experiment Station—Needs Electrical Engineers to perform defense systems analysis/operations research in client-oriented environment. Computer Modeling and electronic system simulation experience desired. MSEE/MSIE required. Send resume to Mr. R.P. Zimmer, Engineering Experiment Station, Georgia Institute of Technology, Atlanta, Georgia 30332. An Equal Opportunity Employer.

#### **EMPLOYMENT SERVICE**

"How To Get A Job Overseas" 253 pages! Jam-Packed info. + Directory 300 firms \$5 Transworld, Box 90802-HR Los Angeles 90009.

Engineers/Scientists — Over 800 firms in Eastern U.S. pay our fees to recruit Top-Caliber professionals in all technical areas. Send detailed resume, in confidence. Wallach Associates, Inc., 1010 Rockville Pike, Rockville, MD 20852.

#### **OVERSEAS JOB GUIDE**

Job Hunting Guide + Directory of 650 Firms. Details on job sources, resumes, taxes. US \$6.50—(US & Canada). To foreign address—\$7.50. Friar Books—EL, 8956 E. Ardendale, San Gabriel, CA 91775.

NAME		
ADDRESS		
CITY	STATE	ZIP
SCHOOL		
DEODEE		

Schlumberger ELECTRICAL ENGINEERS

An Equal Opportunity Employer M/F **BUSINESS OPPORTUNITY** 

How To Earn Money As A Consultant (including specimen contracts) \$21 Business Psychology Int'l 890/44 National Press Bldg. Washington, D.C. 20045.

**GRADUATION DATE** 


# Engineers... are you pigeonholed?

We won't keep you pigeonholed in the same old assignment, year after year. After all, variety is the spice of a life's work. And we have a commitment to it. We make our living selling variety: command and control systems, complete air defense systems, radar systems, sonar systems, computer systems and much more. We're part of a company of 36,000 people, active in more than 550 major product areas in 80 technologies. Plenty of room for developing interests, plenty of room for growth.

Our Systems Division engineers enjoy technical diversity because of our program variety, and growth opportunities that we're steadily expanding. They benefit from the technically oriented management which put us on our strong growth curve. And they enjoy a good professional environment, where many of our people wear 10, 15, and 20 year service pins.

Any more good news? Well, yes. We're hiring now. For quick action, reach for your phone instead of your resume...call M. F. Duggins collect (714) 871-4080, Ext. 5410 between 8 A.M. and 4 P.M. Monday through Friday. Or send your resume to: Professional Employment—Ground Systems Group E, 1901 W. Malvern, Fullerton, CA 92634.

U.S. citizenship required • Equal opportunity M/F/HC employer



HUGHES AIRCRAFT COMPANY

**Communications System Engineers.** Must understand hardware/software interaction, signal processing, spread spectrum.

Senior Systems Engineers. Tactical, strategic system application of radar, sonar communications, electro-optical software, data processing and command and control technologies.

**Communication Analysts.** Lead/direct application of systems theory, applied math, estimation, probability to communication system problems.

Data Processing and Software Analysts.

System level data processing architecture analysis, design, performance evaluation for multisensor systems.

**Display System Engineers.** Long term opportunity to lead display product definition/selection for military C&C Systems.

Radar Systems Engineers. Lead/direct radar system conceptual design/analysis. Integration of radar, weapon, command and control systems.

**Senior Air Defense Engineers.** BSEE, Math or Physics, project management experience in real-time hardware software systems.

**Hardware System Engineers.** Large scale data processing, peripheral, display systems design, specification, integration checkout.

**Systems Analysts.** Systems Theory, applied math background. Variety of problems requiring modern analysis techniques.

# PRODUCT ENGINEERS

#### MAGNETIC MEDIA PRODUCTS DEVELOPMENT

#### San Francisco Peninsula

INFORMATION TERMINALS, a leader in the development of removable magnetic storage media for the computer industry is seeking several key individuals to complement our Engineering staff.

If you are degreed in EE, ME, Physics or Chemistry, have a demonstrated track record in magnetic media products development, materials and processes evaluation, magnetic recording performance characteristics or peripheral drive tape systems and are interested in joining a winning team, give us a call—we'd like to talk to you.

Exceptional benefits in a young successful, planned-growth firm. Please send resume or contact Phil Boltinghouse, INFORMATION TERMINALS, 323 Soquel Way, Sunnyvale, CA 94086. Phone (408) 245-4400. An equal opportunity employer.



## **ENGINEERS**

Are You Tired of a No Challenge Job?

We seek top caliber professionals to advance the state-of-the-Art in hybrid and discrete data conversion products.

#### SENIOR ELECTRONICS ENGINEER

Assume project responsibility and provide technical leadership to supporting staff members. Develop state-of-the-Art hybrid and discrete data conversion products. BSEE and minimum 5 years' analog circuit design experience required.

#### CIRCUIT DESIGN ENGINEER

Analyze, design and evaluate new analog and data conversion products under the guidance of senior electronics engineers. BSEE and 2-5 years' related experience required.

#### COMPONENTS ENGINEER

Responsible for evaluation of hybrid and discrete electronic components. Generation of electrical specifications for a wide variety of electronic components. BSEE and 2-5 years' related experience required.

#### **HYBRID PACKAGING ENGINEER**

Responsible for the design and layout of hybrid integrated circuits. Must be familiar with hybrid assembly and processing techniques. BSEE, BSME or equivalent work experience required.

#### SENIOR DESIGNER

Layout and documentation of hybrid and printed circuit electronic products. Must be a self-starter and have ability to work with minimum of supervision. Extensive related work experience required.

Teledyne Philbrick offers excellent salary and fringe benefits. If you qualify for one of the above positions, please submit your resume and salary requirements, in confidence to Robert A. Porter, Personnel Manager.

Allied Drive, Dedham, MA 02026

Teledyne Philbrick is an Affirmative Action and Equal Opportunity Employer

#### \*\*TELEDYNE PHILBRICK

# ELECTRONIC

#### **KEY POSITIONS**

Our Municipal & Utility Division is searching for talented Electronic Systems and Field Test Engineers to live and work in beautiful Dallas, Texas.

In this division, we develop a broad line of flow measurement and energy related equipment. Last year our corporation spent \$85 million in R&D programs with many projects directed toward the solutions to key national challenges in the field of energy. As a result of these programs we are now beginning a new venture in Load Management/Carrier Current Communication Systems.

#### ELECTRONIC SYSTEMS ENGINEER

We prefer an advanced EE degree with several years experience in computer applications. Knowledge of switching and real time systems is preferred.

#### FIELD TEST ENGINEER

Must have a BSEE and several years proven experience in the installation and start up of electronic systems.

If you are interested in these exceptional career growth opportunities, please send resume including salary requirements, in complete confidence to:

**Robert Arrington, Director of Engineering** 

#### **ROCKWELL INTERNATIONAL**

MUNICIPAL & UTILITY DIVISION/PLCS P.O. Box 10462, Dallas, Tex. 75207



Rockwell International

Equal Opportunity Employer M/F

# Data General Needs: Highly Specialized Senior Engineers.

If the time has come for you to put your career on a path with virtually unlimited possibilities for professional development, then your time has come for Data General. Our growth in terms of new product proliferation, revenues, facilities and manpower literally sets the pace in the small computer industry. Our salaries, benefits and advancement opportunities are established industry leaders.

The positions listed below are available in Westboro, one of our R & D centers and our Corporate Headquarters. We are surrounded by forested hillsides, with mountains to the west and north and the sea to the east. Westboro is less than an hour from the educational, religious and cultural capitol of

the U.S. - Boston.

These positions exist in a creative environment where meaningful challenge and reward can be key elements in your future.

#### **Fiber Optics Communications**

This challenging position will involve thorough investigation and evaluation of fiber optics communications technology and state-of-the-art modem technology. Responsibilities will include development of fiber optics communications interfaces; development of product strategy for modems; and assessment of areas of application.

Requires BSEE minimum, with at least four years engineering experience. Prefer extensive familiarity with modems and communications systems.

#### **Process Control**

We are seeking a professional capable of functioning as lead engineer for a group designing a continuing family of analog and digital products for instrumentation interfacing. This individual will be expected to design new products while leading others in designing computer peripherals interfacing with the instrument field. Position will also involve dealings with marketing and manufacturing.

Requires BSEE minimum, with 5-7 years experience including product design, production interface and/or work-

ing with service agencies.

#### **Intelligent Terminals**

This position affords highly desirable participation in the planning and development of a new family of state-of-the-art, on-line terminals. Areas of design responsibility will include hardware, firmware and overall systems.

Requires a BSEE or BSCS with a minimum of 3 years design engineering experience. This position calls for familiarity with microcomputer architecture, MSI/LSI logic design, and microprocessor programming.

#### C.P.U. Logic Design

This is an opportunity to participate in the design of advanced central processors.

Requires a minimum of five years experience in design with bipolar and MOS logic families and microprocessor design.

#### Circuit Design

This design position will involve assisting systems engineers in selecting or generating special circuits for system use. Will involve recommendation of circuit types and families to systems engineers.

Requires BSEE plus 2-5 years circuit design experience, with knowledge of integrated circuit design and manufacturing techniques helpful.

#### Custom I. C. Design

This position calls for a device designer interested in participating in Data General's advanced industry position in design and manufacture of digital and special purpose analog integrated circuits. In addition to custom I. C. design, there will be significant opportunity for implementation of systems employing custom microprocessor circuits.

Requires equivalent of BSES or BSCS with experience in computer logic/system design. Prefer experience implementing microprocessor based systems.

#### **Data Transmission**

This position will involve development of circuit techniques and transmission schemes in digital systems. Requires BSEE with 2-5 years of design experience including knowledge of transmission line theory.

If one of these positions could be a logical next step in your career, send your resume in strict confidence to: Jim Kimbrough, Technical Personnel Representative, Data General Corp., 15 Turnpike Road, Westboro, MA 01581. Or call: (800) 225-7347, ext. 5773 outside Mass.; (617) 485-9202, ext. 5773 in Mass.

An equal opportunity employer M/F.

**Broadcast Products Division** 

#### **NEW PRODUCT DESIGN ELECTRONIC AND** PROJECT ENGINEERS

Commercial broadcast equipment opportunities with an internationally active division of Harris

Our Division is a leader in design, engineering and manufacture of radio and television broadcast and related equipment, used worldwide. We are part of Harris, a strongly growing diversified company in electronics and communications with volume now past the half-billion mark.

Immediate Career Opportunities in New Product Design: SMALL TO MEDIUM SIGNAL CIRCUIT DESIGN ENGINEERS

Familiar with small to medium signal RF, IF, Video and power supply circuitry. BSEE or MSEE, with 0-5 plus years experience (recent graduates considered) and background in product circuit design. This position and the appropriate training we'll supply provides an excellent opportunity for an engineer to enter the commercial broadcasting industry.

#### LARGE SIGNAL CIRCUIT DESIGN ENGINEERS

Interest or desire to learn large signal circuit design or high frequency vacuum tube power amplifiers. BSEE or MSEE with 3 or more years experience in small signal circuit design or related field and/or interested in training for large signal design career.

#### PROJECT ENGINEERS

Offering future management opportunities, this opening requires BSEE or MSEE with 5-10 years experience as Product Circuit Design Engineer in a manufacturing environment. Background as Project Leader in establishing project objectives, manpower needs and budget is desired.

We offer favorable career prospects in a growth environment, competitive salaries and excellent benefits, and relocation assistance to our desirable small, progressive city. Please direct resume giving full pertinent details including salary progression in confidence to: Lawrence E. Carlstone, Professional Employment Supervisor, Harris Corporation, Broadcast Products Division. Quincy, Illinois 62301.



An Equal Opportunity Employer-Male and Female



#### PRODUCT MANAGER PRECISION RESISTOR **NETWORKS**

ELECTRO FILMS is growing geometrically and is in process of expanding its physical plant. To continue this dynamic growth rate in a balanced way we require the services of a design/applications oriented person to oversee and direct progress in our precision packaged and impackaged network packaged and unpackaged network activity

Opportunity offers a capable and energetic individual financial growth and benefits tied directly to contribu-

Electro Films Incorporated

100 MEADOW STREET - WARWICK, R.I. 02886 TEL. (401) 738-9150

Micro Blectronic Components and Services

#### RELIABILITY MAINTAINABILITY

Participate in Shipboard electronic systems acquisition management. Perform engineering evaluations, develop reliability, maintainability and test specifications. BSEE or with 5 years equivalent experience.

Please forward resumes to:

Mr. L. Orlando

#### **General Research** Corporation (SWL DIVISION)

Suite 700 Park Place 7926 Jones Branch Drive McLean, Virginia 22101 Equal Opportunity Employer

design ngineers

#### **Medical Electronics**

Varian's Ultrasound Division, part of our respected Medical Group, has established its headquarters in the Salt Lake City, Utah area.

Opportunities exist at all levels for career-oriented Design Engineers with BSEE/MSEE or equivalent experience. We can offer you challenges in the design and product development of state-ofthe-art medical systems. Your qualifications should include knowledge of analog, digital and video electronics, microprocessorbased technology and familiarity with acoustic components.

There's also the challenge of Utah's great outdoor activities and wide-open spaces. Room for professional growth and personal development. Room to grow at Varian, in Salt Lake City.

In addition, Varian offers competitive compensation and comprehensive benefits, including cash profit sharing and stock purchase programs. For immediate consideration, please send a resume to our Professional Staffing Office, Varian Ultrasound Division. 2341 South 2300 West, Salt Lake City, Utah 84119. We are an equal opportunity employer m/f.

We are creating technology for the benefit of man.

Come help us.



### WHERE DO YOU FIT?



In today's job market, that is. One way to see if you're in demand is to check the employment opportunities contained ELECin TRONICS' Classified Sec-

Another way to get a reading is to place a blind (box number) Position Wanted ad there. The cost is low (only \$1.25 per line) and the results are often rewarding.

For more information call or write:

Post Office Box 900 New York, N.Y. 10020 Phone: 212/997-2556

#### **SWITZERLAND**

#### Tele-control and Industrial Electronics

Increasing automation everywhere is continually opening up new fields of application for tele-control systems and industrial electronics. By expanding our range of products and systems we are aiming at strengthening our position on world markets. To reinforce our team of engineers we are looking for a

#### **Graduate Electrical Engineer**

for the

#### **Development of Digital Equipment and Systems**

#### from the Initial Concept right through to Production

To name but a few typical applications; automation of networks for the distribution of electricity, water, gas and oil, automatic train control, industrial automation and process control.

Close contact with the practical aspects of applications enable our engineers to keep constantly abreast of technical developments, enabling them to gain experience in the use of microprocessors and to broaden their professional horizon by working intimately with software development groups, with the test laboratories, the sales and engineering groups.

Of course, applicants who already possess such experience will find a post offering excellent prospects for the future. But also those who have just graduated will also find an opportunity of working under expert leadership and becoming a member of a team with a varied field of activity. For advanced training it is possible to attend suitable external and internal courses. Applicants must have a good knowledge of German.

Swiss citizens or aliens with a class C permit are asked to submit their applications, quoting cipher 195/11/76, to Mr. Wehrli, Dept. PDE-A, BBC Brown, Boveri & Co., Ltd. CH-5401 Baden, Switzerland.

BBC

BBC Brown, Boveri & Company Ltd., CH-5401 Baden, Switzerland

# Job-seekers... be the first to know with McGraw-Hill's Advance Job Listings

By having our weekly ADVANCE JOB LISTINGS sent to your home every Monday you can be the first to know about openings both in and out of your field. AJL will enable you to contact anxious recruitment managers BEFORE their ads appear in upcoming issues of 21 McGraw-Hill publications. To receive a free sample copy, plus information about our low subscription rates, fill out and return the coupon below.

ADVANCE JOB LISTINGS / P.O. BOX 900 / NY 10020 PLEASE SEND A SAMPLE COPY OF ADVANCE JOB LISTINGS TO

NAME	ADDRESS	
CITY	STATE/ZIP	

LSI

SENIOR LSI DESIGN ENGINEERS
CAD SYSTEMS ANALYSTS & PROGRAMMERS
CIRCUIT DESIGNERS
APPLICATIONS ENGINEERS
TEST ENGINEERS

## Build your future in Connecticut at the ITT LSI Systems Support Center



Newly relocated to Connecticut, the ITT LSI Systems Support Center is planning on further expansion . . . and your career can grow right along with it. Corporate funded, our specialized technology center is charged with providing the means for optimum use of LSI in wide ranging ITT telecommunications, space, defense, automotive and commercial product areas. The increasing demand for LSI technology within the ITT system dictates our continued need to add to our highly qualified professional staff.

Positions are now available with unusual reach into the future, offering excellent "ground floor" opportunities for professional development and career advancement for those who qualify.

#### SENIOR LSI DESIGN ENGINEERS

Responsible for custom LSI design using state-of-the-art MOS and bipolar techniques. Activities include feasibility studies, chip design, characterization and qualification studies. Requires MSEE and 4 years experience using sophisticated computer-aided design layout and analysis techniques.

#### CAD SYSTEMS ANALYSTS & PROGRAMMERS

Responsible for the development and maintenance of software systems for various CAD applications including automatic placement and routing of circuits, checking art work, logic simulation program, and transient analysis for custom LSI chips. Requires BS in Engineering, Mathematics or Computer Science and minimum of 3 years CAD experience.

#### CIRCUIT DESIGNERS

Experienced designer in advanced LSI technologies. Responsible for design of complex LSI circuits in latest bipolar and MOS technologies. Requires BSEE and 2 years design experience using sophisticated computer-aided techniques.

#### LSI APPLICATIONS ENGINEERS

Direct interface with equipment division engineering personnel to identify and promote LSI design and application opportunity. Capable of assessing, analyzing, and coordinating the long range systems concept combining long range technology forecasting. Experience in telecommunications equipment highly desirable.

#### SENIOR TEST ENGINEERS

Interface with ITT equipment and systems divisions in testing philosophy and testability for new applications. Generate and debug test and characterization programs for custom and standard LSI circuits. Requires BSEE and 4 years in product and test engineering. Sentry experience and knowledge of MIL-38510 qualification techniques preferred.

Please send your resume including salary history in full confidence to Mr. M. Starratt.

# LSI SYSTEMS SUPPORT CENTER

1351 Washington Blvd., Stamford, Connecticut 06902

An Equal Opportunity Employer, M/F

# FREE

# Your dream job

We hope you're happy in your current position, but there's always that ideal job you'd prefer if you knew about it.

That's why it makes sense to have your resume on file in the Electronics Manpower Register, a computerized data bank containing the qualifications of career-conscious ELECTRONICS readers just like yourself.

You'll benefit from nation-wide exposure to industry firms privileged to search the system, and since the computer never forgets, if you match up with their job requirements you'll be brought together in confidence.

To take advantage of this free service, mail your resume to the address below. We'll do the rest.

#### ELECTRONICS MANPOWER REGISTER

Post Office Box 900 New York, N.Y. 10020

# for Innovators who are Seeking Horizons in Telecommunications!



Because those horizons have an infinite number of opportunities for technical accomplishment. We are doing research and development for the communications systems of the future.

#### **CALL TOLL FREE (800) 323-1966**

In Illinois (800) 942-0491 • Monday thru Friday from 8 am to 5 pm cst

There probably has never been such a massive new market for computer-controlled systems, GTE Automatic Electric supplies systems for both domestic and foreign customers, and telecommunications is one of the industries that is both basic and vital to every nation in the world. Let us tell you more about the vast growth potential, and of our unique position in the market.

#### SOFTWARE DESIGN ENGINEER

Responsible for the specification, design and testing of telephone systems support software, network and control software, or maintenance and diagnostics software. Prefer a minimum of 3 years' experience in structured design, coding, testing and documentation of programs; development with large data base on multi-file computers and real-time systems, HIPO design documentation. TSO usage and software simulation techniques. Requires a BS or MS in Computer Science or Electrical Engineering and specialized study in the use of PL/1, Fortran, Assembler, Intel 8080 and PDP-11 programming languages.

#### DATA BASE DESIGN

This position requires a minimum of 5 years' experience in the planning development, design and implementation of data base software, including data base management systems administration. Your primary responsibilities will be the development of data base system for a large on-going project including the implementation, support and administration of systems.

#### **TELETRAFFIC & PLANNING ENGINEER**

Responsible for the analysis of teletraffic probability and queuing problems on digital and analog switching systems and the development of computer programs for switching systems. Perform control and route reliability studies, define and analyze problems for future systems features and their applications. Prefer a minimum of 3 years' experience in real-time control systems teletraffic problems, systems equipment quantities specification, and exposure to switching system specifications. Requires a BS or MS in Electrical Engineering, Computer Science or Math and a strong statistical background and experience in PL/1 or Fortran programming and model simulation.

#### MINI-COMPUTER PROGRAMMERS

We have specific assignments available on project development teams responsible for the design implementation of various telecommunication processing systems utilizing mini-computers as the processing element. Responsibilities will include the development of software programs for real-time operating systems as well as unique hardware elements incorporated into the systems.

If unable to call, send resume including recent salary history to

Manager of Technical Employment, Dept. 471 A6

## AUTOMATIC ELECTRIC LABORATORIES

400 N. Wolf Road . Northlake, IL 60164

An Equal Opportunity Employer M/F

## **ENGINEERS**

BURNS and ROE an internationally recognized leader in the engineering and construction of power plants is seeking proven professionals with a minimum of 3 years engineering experience in the following dis-

## MECHANICAL **ELECTRICAL**

Our current projects require the expertise of engineers capable of contributing to our advanced technology while developing personally and professionally.

We offer excellent compensation, including a fully-company paid benefits package.

Forward resume including detailed work history and salary requirement in confidence to: Mr. R. B. TROUT 550 Kinderkamack Road Oradell, N.J. 07649 An Equal Opportunity Employer M/F



SEMTECH CORPORATION

Expanding manufacturer of quality power rectifiers offers excellent opportunity for:

#### MOS PROCESS **ENGINEER PHOTORESIST**

Participates in bringing into production a new generation of field effect power transistors.

Requires BS in Electronics or Physics plus a minimum of 3 years' experience in MOS wafer fabrication.

Salary commensurate with experience and ability. Excellent benefits including profit sharing.

Send resume with complete salary history to:

SEMTECH CORPORATION 652 Mitchell Road Newbury Park, Calif. 91320

Equal Opportunity Employer M/F

#### ENGINEERS

in FEE-PAID positions
THROUGHOUT THE U.S. since
'59. Over 1,000 client companies.
We are graduate engineers working full-time for you. Send resume
& salary history today or request confidential application.
ATOMIC PERSONNEL, INC.
Suite L. 1518 Walnut St., Phila., Pa. 19102
An Employment Agency
For All Technical Fields

#### FOR WESTERN ACTION

Free resume preparation and distribution to exceptional fee opportunities. Send experience and salary history to:

The Wescott Agency Box 4428 Vancouver, WA 98662



#### **Electronics Regional Offices Classified Section Representatives**

#### **ATLANTA 30309**

Jane Core 1175 Peachtree St. NE

404/892-2868

#### **BOSTON 02116**

Holt Buchanan 607 Boylston St. 617/262-1160

#### **CHICAGO 60611 Bill Higgens**

645 N. Michigan Ave. 312/751-3733

#### **CLEVELAND 44113**

**Mac Huestis** 1750 Illuminating Bldg.

216/781-7000

#### **DALLAS 75201** Mike Taylor

2001 Bryan Tower Suite 1070 214/742-1747

#### **DENVER 80203** Shirley Klotz

123 Speer Blvd. Suite 400 303/837-1010

#### **DETROIT 48202**

**Mac Huestis** 1400 Fisher Bldg. 313/873-7410

#### **HOUSTON 77002**

Mike Taylor 375 Dresser Tower 601 Jefferson St. 713/659-8381

#### **LOS ANGELES 90010**

Stan Kassin Ana Maria Galaz 3200 Wilshire Blvd. South Tower 213/487-1160

#### **NEW YORK 10020**

(Sales only) Larry Kelly 212/997-3593 **Marlene Melton** 212/997-2422 McGraw-Hill Bldg. 1221 Avenue of the Americas

#### **PHILADELPHIA 19102**

Dan Ferro Three Parkway 215/568-6161

#### PITTSBURGH 15222

Dean Genge Two Gateway Center 412/391-1314

#### **SAN FRANCISCO 94111**

Mary Ellen Kenny 425 Battery St. 415/362-4600

#### STAMFORD 06901

**Holt Buchanan** 300 Broad St 203/359-2860

#### McGRAW-HILL HOME OFFICE

McGraw-Hill Publications Co. Post Office Box 900 New York, NY 10020

#### MANAGER

Frank Eberle 212/997-2556

#### MAGAZINE SUPERVISOR FOR ELECTRONICS

Carol Allen 212/997-4392

#### COMMUNICATION **FACILITIES**

For a Xerox 400 Telecopier call 212/ 997-6800 between 8:30 a.m.-4:30 p.m. EST. For overnight or West Coast copy. a 24-hour unattended 3M facsimile is available. Phone 212/997-2821, use 6 minute speed. Also, Telex: 12-7960, and TWX: 710-581-4879

	Abbott Transistor Labs	6	•	Electro Scientific Industries	172		M.S. Kennedy Corp.	188
٠	Adret Electronique	64,22E		Elec-Trol, Inc.	91	•	Kepco, Inc.	5
	Advanced Micro Devices	10-11		Elevam Electronic Tube Co., Ltd.,	224		Lambda Electronics	203-216
	Airborn Inc.	155		EMR-Telemetry	224	•	Lear Siegler — Data Products Div.	231
•	Allen-Bradley	34		Electronic Navigation Industries	148		Litronix	163
•	American Optical — Scientific Instr. Div.	179		Elorg Electronorgtechica	142		Magneti Marelli	16E
	Amp, Inc.	28-29		Erie Technological Products	180		Matsuo Electric Co., Ltd.	14E
	Amphenol North America Division, Bunker Ramo Corporation	70-71		Esterline Angus	219		MDB Systems	251
	A P Products, Incorporated	236		Fairchild (Semiconductor Operations Division	on) 7		MFE Corp.	136-137
	Applied Digital Data Systems	51		Fairchild Systems Technology	157		Micro Components Corporation	170
	Augat, Inc.	181		Ferranti-Packard Ltd.	202		Micro Power Systems	77
	AVX Corporation	92	#	Ferroxcube Corp., A Div. of North Amer. Phili	ips 80		Microswitch, Div. of Honeywell	174-175
	The Bendix Corporation, Electrical Comp. D	<b>Div.</b> 195		Figaro Engineering, Inc.	8		Micro Technical Industries	8
	Berg Electronics Div. of Dupont	183		Fujitsu America Inc.	83		Microtest Systems, Inc.	138-139
	Biomation	178		Futek	192		Microwave Power Devices	34E-35E
	Boonton Electronics	133		GEC M-O Valve	61		Mitel Semiconductor, Inc.	54
	Bourns, Inc.	3rd c.		General Electric Miniature Lamp	220		Monolithic Memories	38-39
*	Bud Industries, Inc.	30		GE Plastics	189		Monsento Company	150-151
	Bultronics	250		General Instrument, Microelectronics	27		Motorola Communications & Electronics	218
	Burr Brown	4E			252		Motorola Semiconductor Products	85
	Cambridge Thermionic Corp.	154		General Magnetics	193			30
	Carlo Erba SA	68		GenRad			Murata Mfg. Co., Ltd.	62
	Centralab / USCC	177		Grayhill, Inc.	79	*	National Connector	67
	Centronics	237	*	Grundy International Inc.	17-26	*	NEC Microcomputers NEOHM SPA	69
	Cherry Electrical Products	2		Hewlett-Packard				
	Chomerics Inc.	184	•	Hipotronics	248		New Bedford Ind Devel Commission	194
	Clairex Electronics	4th c.		Honeywell TID	173		Nichicon America Corporation	168
	C.P. Clare International	19E	•		92,200	•	Nicolet Instrument Corp., Oscilloscope Di	
	Communication Associates Inc.	15		Icom, Inc.	167	•	Non-Linear Systems, Inc.	196
	Continental Rentals, Div. Continental	8,176	•	ILC Data Device Corporation	55 224		North Atlantic Industries	82 67
	Resources	00.00		A.L.S. Corporation for Infotek	47		Oscilloquartz	196
*	Cutler-Hammer, Specialty Products Divisio			Instrumentation Engineering	96-97		Ostby & Barton Panasonic, Industrial Div.	68-69
	Dana Labs	169		Intel-Microcomputer Components	222	*	Pearson Electronics	192
	Data I/O Corporation	159		International Microcircuits Inc.	56-57			5E
	Delevan Div., American Precision Ind.	182		Intersil			Philips ELA	6E
	Deltron, Inc.	234		Interstate Electronics	229		Philips Elcoma	20E-21E
•	Dialight	199		Intronics	228		Philips Industries	
	Digi-Data Corp.	191	•		31E,36E	•	Philips TMI	15E
	Digital Equipment Components	1,2nd c.		C. Itoh & Co., Ltd.	198		Plastics Engineering Company	158
*	Eastman Kodak Co., Graphic Markets Divis	sion 15	•	Kennedy Company	93	•	Power One Inc.	32-33

# potronics inc.

Standard supplies from 1 kW to 50 kW



**Power Supplies** 

Complete range of unregulated high voltage dc supplies with voltage outputs from 1 kV to 1000 kV and current outputs from 10 mA to 50 Amps available in standard designs at economical prices. Fully instrumented and protected, these supplies are ideal for:

- Laboratory use
- Capacitor charging
- Laser supplies
- CRT supplies
- Marx generators
- 5, 7.5 & 10 kV @ 5 mA OEM Many more **Power Packs**







#### **Power Packs**

Miniaturized, oil-filled steel cans for OEM use. Voltages from 2.5 kV to 100 kV at 2, 5 & 10 mA. Low cost, high reliability.

#### **Metered Power Packs**

Same miniature power packs available with simplified or deluxe controls for rack-mounting. Short circuit current limit option makes these ideal for cap charging applications.

Write or call for complete details.



P.O. Drawer A. Brewster, NY 10509 (914) 279-8031 Twx 710-574-2420 Amex Symbol: HIP

	Practical Automation	251	
	Precision Monolithics Inc.	72-73	
	Procond S.P.A.	18E	
	Pro-Log	40	
*	Profit by Air Inc.	124	
	Quest Automation	29E	
•	Racal Thermionic Ltd.	2E-3E	
1.	Radiohm S.A.R.L.	23E	
	Ramtek	88-89	
	Raytheon Co. Industrial Components	124	
•	RCA Electro Optics & Devices	8E-9E	•
	RCA Solid State	9,49	
	Rhone Poulenc-Chimie Fine	190	•
	Riken Denski Co., Ltd.	12E	
	Robinson Nugent, Inc.	94-95	
•	Rohde & Schwarz	1E	
	Sangamo Data Recorder Division	149	
•	Hans Schaffer	27E	
	Scientific Atlanta, Optima Div.	156	
•	Sfernice	17E	
•	SGS ATES	11E	
*	Siemens AG Munich	62	
#	Signetics Corporation	37,143	
•	Silec Thomson	25E	
	Siliconix	122-123	
•	Sivers Labs	13E	*
•	Sodeco	33E	
	Solid State Scientific	131	
	Sorenson, Div. of Raytheon	53	-
	Spectrol Electronics	221	F
	Spectronics, Inc.	230	E
	Sperry Univac	87	E E C C C H H H I I I I I I I I I I I I I I
	Sprague Electric	24E 58	-
			li F
	Standard Microsystems  Systron-Donner Concord	145	9
	Systron-Donner, Concord	226-227	Y
_	Systron-Donner, Data Products Div.  Tansitor Electronics	230	
•		166	÷
	TEAC Corporation	225	-

Practical Automation	251	٠	Tecnetics	160
Precision Monolithics Inc.	72-73	•	Tektronix	140, 13, 45
Procond S.P.A.	18E		Teledyne Philbrick	236
Pro-Log	40		Teledyne Relays	31
Profit by Air Inc.	124		Teletype	171
Quest Automation	29E		Telonic Berkeley	223
Racal Thermionic Ltd.	2E-3E		Teradyne, Inc.	74, 146-147
Radiohm S.A.R.L.	23E		TI, Components	185
Ramtek	88-89		TI, Digital Systems Div.	186
Raytheon Co. Industrial Components	124		Textool Products, Inc.	14
RCA Electro Optics & Devices	8E-9E		Theta Instruments	162
RCA Solid State	9,49		Thick Film Systems, Inc.	234
Rhone Poulenc-Chimie Fine	190		TRW Capacitors	161
Riken Denski Co., Ltd.	12E		TRW LSI Products	134-135
Robinson Nugent, Inc.	94-95		TRW Power Semiconductors	235
Rohde & Schwarz	1E		TRW Cinch Connectors	187
Sangamo Data Recorder Division	149		TRW/UTC Transformer	80
Hans Schaffer	27E		Ultra-Violet Products, Inc.	222
Scientific Atlanta, Optima Div.	156		Union Carbide Corp., Parylene	197
Sternice	17E		United Detector Technology	232
SGS ATES	11E		United Systems Corp., Sub. Monsanto	116
Siemens AG Munich	62		Universal Instruments	153
Signetics Corporation	37,143		Vector Electronics	168
Silec Thomson	25E		Velonex, Inc.	198
Siliconix	122-123		Viking Industries	233
Sivers Labs	13E	‡m	Wabash Electronics	61
Sodeco	33E		Wavetek Indiana	37,98
Solid State Scientific	131		Wilhelm Westermann	16
Sorenson, Div. of Raytheon	53	_	Zero Corporation	152
Spectrol Electronics	221	CI	assified and employment adve berle, Manager 212-997-2557	ertising
Spectronics, Inc.	230	Ato	omic Personnel C Brown Boveri & Co., Ltd.	246 243
Sperry Univac	87	Bui	rns & Roe ta General ctro-Films	246 241 242
SPIITT	24E	GT	E Automatic neral Research Corp ghes Aircraft Co.	245 242
Sprague Electric	58	Hai	rris Corporations Systems	239 242 244


246
242
240
238
246
240
240
244
242
239
242
245
242
241
246
243
246
•

- For more information of complete product line see
- advertisement in the latest Electronics Buyers Guide
- Advertisers in Electronics International
- # Advertisers in Electronics domestic edition

# We know your needs. Electronics Magazine Book Series. Zero-risk trial offer.







CIRCUITS CIRCUITS

#### 1. Microprocessors

What you must know about available microprocessor technology, devices, information, 4th printing. \$8.95

### 2. Applying Microprocessors

**Electronics Book Series** 

2nd and 3rd generation technology. 26 detailed applications from data networks to video games. \$9.95

#### 3. Large Scale Integration

Covers the basic technology, new LSI devices, LSI testing procedures, plus system design and applications. \$9.95

#### 4. Basics of Data Communications

Includes 47 articles from Data Communications magazine covering more than 11 key areas. \$12.95

## 5. Circuits for Electronics Engineers

Contains 306 circuits arranged by 51 functions from Amplifiers to Voltage Regulating Circuits. Saves design drudgery. \$15.95

Maidenhead, Berkshire SL62QL, England.	☐ Ame
1. Send me copies of "Microprocessors" at \$8.95 per copy.	Bank
<ol><li>Send me copies of "Applying Microprocessors" at \$9.95 per copy.</li></ol>	Acc't N
3. Send me copies of "Large Scale Integration" at \$9.95 per copy.	On Mas
4. Send me copies of "Basics of Data Communications" at \$12.95 per copy.	Name
5. Send me copies of "Circuits for Electronics Engineers" at \$15.95 per copy.	Compa
Discounts of 40% on orders of 10 or more copies.	Street
I must be fully satisfied or you will refund full payment if the book	City


s returned after ten-day tri	- Charles and the Control of the Con	and the second second second second	

Payment	enclosed	□ Bill firm	□Bill
rayment	enclosed		

McGraw-Hill Publications Company, Shoppenhangers Rd.,

<ul><li>☐ American Exp</li><li>☐ BankAmerica</li></ul>			
Acc't No	Date exp	Interban	k No
	ge only, pove name		"Al-
Name		Т	itle
Company			
Company Street City		State	Zip

# Only ITAC makes 'em all



No one makes a greater variety of LED digital displays than ITAC NSB / NSN series red GaAsP displays: 0.3," 0.5," 0.7" H; dual or quad board-mounted; direct or multiplexed; common anode or cathode. MAN-equivalent series red single or dual-digit displays: 0.3," 0.4," 0.56" H; standard DIP; BIN coded; common anode or cathode. FND series red GaAsP displays: 3/8," 1/2," 8/10" H; standard DIP; BIN coded; reflector/lense system; common anode or cathode. In addition, ITAC offers a variety of standard LED lamps, including MV-equivalent, FLV-equivalent and TIL-equivalent.

What's more, if you're interested in custom digit or lamp arrays and alphanumeric displays, call or write us about your requirements. Standard or custom, take your pick from the only company that makes 'em all.




U.S. Sales 2430 S. 20th St., Phoenix, AZ 85034; (602) 252-3481; TWX (910) 951-1369 International Sales: 2045 Martin Ave., Santa Clara, CA 95050; (408) 985-2290; TLX 357490

Circle 250 on reader service card

#### **New UVS-11E EPROM Erasing System**

## Performance and Reliability



Now available . . . the newest member of UVP's growing family of quality EPROM Erasing Lamps. The UVS-11E Short Wave UV Lamp was designed specifically for the small systems user and computer hobbyist. It's compact, easy-to-use, and will erase up to 4 chips at one time. It even features a special safety interlock system for complete safety.

This is the first UV erasing system to offer simple operation and foolproof safety features at an affordable price. Like all UVP products, the UVS-11E is quality-built and backed by 45 years of UV technology.

Order now from your local authorized UVP stocking dealer. Or write today for more information and name of nearest dealer.

**ULTRA-VIOLET PRODUCTS, INC.** 5100 Walnut Grove Avenue, San Gabriel, CA 91778 U.S.A.

#### **Advertising Sales Staff**

Advertising sales manager: Paul W. Reiss 1221 Avenue of the Americas, New York, N.Y. 10020 [212] 997-4371

Atlanta, Ga. 30309: Glen N. Dougherty 100 Colony Square, 1175 Peachtree St., N.E. [404] 892-2868

Boston, Mass. 02116: Frank Mitchell 607 Boylston S

607 Boylston St. [617] 262-1160 **Chicago, III. 60611** 645 North Michigan Avenue Robert W. Bartlett [312] 751-3739 Robert M. Denmead [312] 751-3738 **Cleveland, Ohio 44113:** William J. Boyle [716] 586-5040

Dallas, Texas 75201: John J. Uphues 2001 Bryant Tower, Suite 1070 [214] 742-1747

Denver, Colo. 80203: Harry B. Doyle, Jr.

123 Speer Blvd. #400 [303] 837-1010 **Detroit, Michigan 48202:** Robert W. Bartlett 1400 Fisher Bldg. [313] 873-7410

Houston, Texas 77002: John J. Uphues 601 Jefferson Street, Dresser Tower [713] 659-8381

Los Angeles, Calif. 90010: Robert J. Rielly Robert E. Boedicker, 3200 Wilshire Blvd., South Tower [213] 487-1160

Minneapolis, Minn. 55435: Robert M. Denmead 4015 W. 65th St. [312] 751-3738

[312] 751-3738 New York, N.Y. 10020 1221 Avenue of the Americas Michael J. Stoller [212] 997-3616 Matthew T. Reseska [212] 997-3617 Philadelphia, Pa. 19102: Matthew T. Reseska

Pittsburgh, Pa. 15222: Matthew T. Reseska 4 Gateway Center [212] 997-3617

Rochester, N.Y. 14534: William J. Boyle 1175 Pittsford-Victor Rd., Pittsford, N.Y. [716] 586-5040

San Francisco, Calif. 94111: Don Farris Robert J. Rielly, 425 Battery Street, [415] 362-4600

Paris: Patrick Mouillard 17 Rue-Georges Bizet, 75116 Paris, France Tel: 720-73-01

United Kingdom & Scandinavia: Robert Ghey 34 Dover Street, London W1 Tel: 01-493-1451 Scandinavia: Andrew Karnig and Assoc.

Kungsholmsgatan 10 112 27 Stockholm, Sweden Tel: 08 51 68 70 Telex: 179 51 Milan: Luigi Rancati

1 via Baracchini, Italy Phone 86-90-656 **Brussels:** 23 Chaussee de Wavre

Brussels 1040, Belgium
Tel: 13-73-95
Frankfurt/Main: Fritz Krusebecker

Liebigstrasse 27c, Germany Phone 72 01 81 Tokyo: Tatsumi Katagiri, McGraw-Hill

Publications Overseas Corporation, Kasumigaseki Building 2-5, 3-chome, Kasumigaseki, Chiyoda-Ku, Tokyo, Japan [581] 9811

#### **Business Department**

Thomas M. Egan Production Manager [212] 997-3140

Carol Gallagher
Production Manager International [212] 997-2045

**Betty Preis** 

Production Manager Domestic [212] 997-2908

Roberta Cummings
Production Assistant [212] 997-2044

**Frances Vallone** Reader Service Manager [212] 997-6057

#### **Electronics Buyers' Guide**

H.T. Howland, General Manager [212] 997-6642

Regina Hera, Directory Manager [212] 997-2544 Roberta Cummings Production Manager [212] 997-2044 Frances Vallone, Reader Service Manager [212] 997-6057

Classified and Employment Advertising

Frank Eberle, Manager [212] 997-2557



and text at a fast 110 cps. Turn out up to four copies at once on regular 8½ inch roll paper, even on fan-fold forms and labels. Not only are all needle drivers and diagnostic routines included with the microprocessor, but you can choose the interface function you want - parallel ASCII, RS-232C/I-Loop, or switch-selectable baud rates from 110 to 1200. You even get the economy of easily-replaceable ink rollers and a self-reversing 10-million character life ribbon. \* \$345 in 100 qts.; single units \$472

All that for \$345\*? It's phenomenal... and it's also very Practical. PRACTICAL AUTOMATION, INC.

Trap Falls Road, Shelton, CT. 06484 Tel: (203) 929-5381

Circle 251 on reader service card


## MDB SYSTEMS presents...The Printer Connection

From DEC's PDP-11 & 8\*, Data General NOVA\*, Interdata and Hewlett Packard 21MX Computers. Plus the DEC LSI-11 Microcomputer to these popular model Line Printers:

DEC LA 180 · Centronics · Data Printer · Data Products · Data 100 · Mohawk · Printronix · Tally New! Diablo 2300 Series

- ☐ Low-cost line printer controllers
- ☐ Completely software transparent to host computers
- ☐ Runs host computer diagnostics

MDB Systems controllers provide user flexibility in line printer selection with no change in host system software. Just plug-in the MDB module and connect your line printer. Each controller is a single printed



circuit board requiring one chassis slot. Fifteen foot cable length standard.

Transparent to the host computer, the controller is completely compatible with diagnostics, drivers and operating systems. Operation and programming considerations are exactly as described by the host computer manufacturer.

More than three dozen computer-to-printer controller combinations are available from MDB Systems as well as modules for other compatible parallel interface printers.

A long-line parallel operation option is available for most printers permitting full speed operation up to 3000 feet.


MDB Systems has an extensive repertoire of general purpose logic modules, device controllers and accessories for the computers listed. Your inquiry will receive a prompt response.

1995 N. Batavia St., Orange, California 92665 714/998-6900 TWX: 910-593-1339 \*TMs Digital Equipment Corp. & Data General Corp.

CIRCLE 211 FOR DEC; 212 FOR NOVA; 213 FOR INTERDATA: 214 FOR LSI-11; 215 FOR HP.

#### SOLID STATE 3 WIRE SYNCHRO TO LINEAR D.C. CONVERTER

### RESPONSE CURVE MAC 1422-1 MAC 1449-1 1458-1 MAC 1459-1 9



MAC 1460-1 MAC 1461-1

#### **FEATURES:**

 Develops a DC output voltage linearly proportional to a synchro angle over a ± 180° range.

Completely solid state with all of the inherent advantages over a mechanical system such as:

High reliability (since there are no moving parts)

Light weight—6 ozs.

Small size

All units hermetically sealed

•	Wide	temperat	ure range	operation

Output short circuit protected

Three wire inputs isolated from ground

Package size may be altered at no extra cost

Units can be altered to accept different line to line voltages or different operating frequencies at no extra cost

Not affected by reference voltage or power supply variations.

UNIT	MAC 1422-1	MAC 1449-1	MAC 1458-1	MAC 1459-1	MAC 1460-1	MAC 1461-1
TRANSFER EQUATION	± IV/18°	± IV/18°	± IV/18°	± IV/18°	+IV/36°	+IV/36°
ACCURACY (+25°C)	1/2%	1/2%	1/2%	1/2%	1/2%	1/2%
ACCURACY (-25°C-+85°C)	1%	1%	1%	1%	1%	1%
L - L SYNCHRO INPUT (VRMS)	11.8	90	11.8	90	11.8	90
FREQUENCY (Hz)	400	400	60	60	400	400
FULL SCALE OUTPUT	±10V	± 10V	± 10V	± 10V	+10V	+10V
OUTPUT IMPEDANCE	<1Ω	<1Ω	<1Ω	<1Ω	<1Ω	<1Ω
L - L INPUT IMPEDANCE	>10K	>30K	>2K	>10K	>10K	>30K
REFERENCE VOLTAGE (VRMS)	26	115	26	115	26	115
OPERATING TEMP. °C	-25 - +85	-25 - +85	-25 - +85	-25 - +85	-25 - +85	-25 - +85
D.C. SUPPLY	± 15V					
D.C. SUPPLY CURRENT	±75MA	±75MA	±75MA	± 75MA	± 75MA	± 75MA
BANDWIDTH	10Hz	10Hz	OPT.	OPT.	10Hz	10Hz
WEIGHT	6 oz.	6 oz.	6 oz.	8 oz.	6 oz.	6 oz.
SIZE	3.6x2.5x0.6	3.6x2.5x0.6	3.6x3.0x0.6	3.6x3.0x1.0	3.6x2.5x0.6	3.6x2.5x0.

#### A.C. LINE REGULATION

A new method has been developed which allows us to provide a low distortion highly regulated AC waveform without using tuned circuits or solid state active filters of any kind.

The result is a frequency independent AC output regulated to 0.1% for line and load with greater than 20% line variations over a wide temperature range.

#### FEATURES:

0.1% total line and load regulation

Independent of ± 20% frequency fluctuation

1 watt output

Extremely small size

Isolation between input and output can be provided

Specifications: Model MLR 1476-1 AC Line Voltage: 26V ±20% @ 400 Hz ± 20%

Output: 26V ± 1% for set point

Load: 0 to 40ma Total Regulation: +0.1% Distortion: 0.5% maximum rms Temperature Range: -55° C to

+125°C

Size: 2.0" x 1.8" x 0.5"

Other units are available at different power and voltage levels as well as wider temperature ranges. Information will be furnished upon request.

#### **High Precision Analog Multipliers**

PRODUCT ACCURACY (MCM 1519-1)  $\pm$  ½% OF ALL THEORETICAL OUTPUT VALUES OVER FULL MILITARY TEMPERATURE RANGE OF -55° C TO +125° C. ZERO POINT ERROR FOR ANY INPUT COM-BINATION IS ± 2MVRMS



- No external trims required
- Distortion free AC output over entire dynamic range
- Linearity, product accuracy and zero point virtually unaffected by temperature
- · All units are hermetically sealed and are not affected by external fields
- High analog product accuracy and wave quality allows dual multiplier assemblies to be matched with 1% of point over the specified temperature range
- Full four quadrant operation Package size, power supply re-
- quirements and other specs. may be altered to your exact requirements at no extra cost.

#### Specifications:

- Transfer equation: Eo=XY/10
- X & Y input signal ranges: 0 to ±10V PK
- Maximum zero point error (X=0; Y=0 or X=±10; Y=0 or X=0; Y=±10): 2MVRMS
- Input impedance: Both inputs 20K min.
- Full scale output: ±10V peak
- Minimum load resistance for full scale output:  $2K\Omega$
- Output impedance:  $1\Omega$
- Short circuit duration: 5 sec.
- Frequency response characteristics (both inputs) 1% amplitude error: DC to 1200 Hz (min.) 0.5 DB Amplitude error: DC to 3500 Hz min. 3 DB point: Approx. 10K hz Roll off rate: 18 DB/octave
- Noise Level: 5MV PK-PK @ 100K Hz approx.
- Operating temp, range: See chart Storage temperature range:
- -55°C to +125°C DC Power: ±15V ±1% @ 30MA
- Dimensions: 2" x 1.5" x .6'

Type No.	Product Accuracy	Operating Temperature Range
MCM 1519-1	± 0.5%	-55°C - +125°C
MCM 1519-2	± 0.5%	-25° C - +85° C
MCM 1519-3	± 0.5%	0°C-+70°C
MCM 1520-1	± 1.0%	-55°C - +125°C
MCM 1520-2	± 1.0%	-25°C - +85°C
MCM 1520-3	± 1.0%	0°C - +70°C

There is No Substitute for Reliability



#### **GENERAL MAGNETICS · INC**

211 Grove St., Bloomfield, New Jersey 07003 - Tel. (201) 743-2700

# Another Colorful Innovation...

# Conductive Plastic Trimmers at Carbon Prices.

Just when you thought "low cost" also meant "low performance", along comes the dazzling new Bourns® Model 3355. Compare it to the CTS 201, Mepco 46X or Piher PT15. Our revolutionary conductive plastic element vs. their carbon . . . fact is we outperform them all. To prove it, we spec important characteristics such as CRV at 1% and a TC of 500 PPM/°C . . . the others don't. And only the 3355 has board-wash capability, a UL-94V-1 flammability rating and an optional choice of nine rotor colors. The standard blue is priced at just 11¢ each (100,000 pieces) . . . about what you'd expect to pay for the lower performance carbon types.

Send today for complete details on a colorful new way to design in superior performance for your cost effective needs — the Model 3355 Trimmer. Direct or through your local distributor.

TRIMPOT PRODUCTS DIVISION, BOURNS, INC., 1200 Columbia Ave., Riverside, CA 92507. Phone: 714 781-5050 — TWX: 910 332-1252.

#### CATALOG SHEET SPECIFICATION COMPARISONS

CHARACTERISTIC	BOURNS 3355	CTS 201*	MEPCO 46X*	PIHER PT15*
Element	Conductive Plastic	Carbon	Carbon	Carbon
Temperature Coefficient	500 PPM/°C	No Spec	No Spec	1000 PPM/°C
Contact Resistance Variation	1.0% max.	No Spec	No Spec	No Spec
Power Rating	.25 W at 70°C	.25 W at 55°C	.25 W at 55°C	.25 W at 40°C
Flammability	UL-94V-1	No Spec	No Spec	UL-94
Board Wash Capability	Yes	No Spec	No Spec	No Spec

\*Source: CTS Series 201 Data Sheet, Mepco Data Sheet ME1004, Piher Data Sheet F-2002 Rev 7/73













nternational Marketing Affiliates: European Headquarters — Switzerland 042/23 22 42 • Belgium 02/218 2005 • France 1/2039633 • Germany 0711/24 29 36 • Italy 02/32 56 88 • Netherlands 70/87 44 00 • United Kingdom 01/572 6531 • orway 2/71 18 72 • Sweden 764/20 110 • Japan 075/921 9111 • Australia 02/55-0411 03/95-9566 • Israel 77 71 15/6/7

For Immediate Application — Circle 120 For Future Application — Circle 220

# **CLAIREX OPTO-ISOLATORS** 5 darlington, 10 transistor, 4 with a-c input

Clairex now offers 19 standard DIP opto-isolators for logic functions. All units feature 2500 PVAC isolation.


Five isolators have Darlington outputs with characterized CTRs @ 1 ma and/or 10 ma with a guaranteed minimum of 100% to 600%.

The 10 transistor output units feature controlled CTRs @ 1 ma and/or 10 ma ranging from 6% to 100% guaranteed minimum.

Four isolators utilize 2 IREDs connected in inverse parallel to permit the input to operate directly from a-c. Two of these have a transistor output while two have a Darlington output with controlled CTRs at 1 ma and 10 ma on all units.

Call (914) 664-6602 or write Clairex®, 560 South Third Avenue, Mount Vernon, New York 10550.

Circle 902 on reader service card



A Division of Clairex Corporation